



MRI4 – IEC60870-5-103
HighPROTEC

Data point list

Manual DOK-TD-MRI4IDE

Table of Contents

PHYSICAL LAYER.....	3
LINK LAYER.....	3
APPLICATION LAYER.....	4
DATA POINTS LIST.....	8
Signals.....	8
Measuring Values.....	25
Commands.....	27
Analog Traces.....	28

This manual applies to devices (version):

Version 2.2.c

Build: 19707

Physical layer

Electrical interface

EIA RS-485

Number of loads for one equipment: 32

Optical interface

Glass fibre

F-SMA type connector

Plastic fibre

BFOC/2,5 type connector

Transmission speed

9600 bit/s

19200 bit/s

38400 bit/s

Link Layer

There are no choices for the link layer

Application layer

Transmission mode for application data Mode 1 (least significant octet first) as defined in 4.10 of IEC 60870-5-4

Common address of ADSU

- One common address of ADSU (identical with station address) More than one common address of ASDU

Selection of standard information numbers in monitor direction

System functions in monitor direction

- 0 = End of general interrogation 0 = Time synchronization
 2 = Reset FCB 3 = Reset CU
 4 = Start/Restart 5 = Power on

Application layer

Measurands in monitor direction

- | | |
|--|--|
| <input type="checkbox"/> 144 Measurand I | <input type="checkbox"/> 145 Measurands I,V |
| <input type="checkbox"/> 146 Measurand I, V,P,Q | <input type="checkbox"/> 147 Measurands I _N , V _{EN} |
| <input checked="" type="checkbox"/> 148 Measurands I _{L1,2,3} , V _{L1,2,3} , P, Q, f | |

Generic functions in monitor direction

- | | |
|---|--|
| <input type="checkbox"/> 240 Read headings of all defined groups | <input type="checkbox"/> 241 Read values of all entries of one group |
| <input type="checkbox"/> 243 Read directory of a single entry | <input type="checkbox"/> 244 Read value of a single entry |
| <input type="checkbox"/> 245 End of general interrogation of generic data | <input type="checkbox"/> 249 Write entry with confirmation |
| <input type="checkbox"/> 250 Write entry with execution | <input type="checkbox"/> 251 Write entry aborted |

Selection of standard information numbers in control direction

System functions in control direction

- | | |
|---|--|
| <input checked="" type="checkbox"/> 0 = Initiation of general interrogation | <input checked="" type="checkbox"/> 0 Time synchronization |
|---|--|

General commands in control direction

- | | |
|--|--|
| <input checked="" type="checkbox"/> 16 Auto-recloser on/off | <input checked="" type="checkbox"/> 17 Teleprotection on/off |
| <input checked="" type="checkbox"/> 18 Protection on/off | <input checked="" type="checkbox"/> 19 LED reset |
| <input checked="" type="checkbox"/> 23 Activate characteristic 1 | <input checked="" type="checkbox"/> 24 Activate characteristic 2 |
| <input checked="" type="checkbox"/> 25 Activate characteristic 3 | <input checked="" type="checkbox"/> 26 Activate characteristic 4 |

Generic functions in control direction

- | | |
|--|--|
| <input type="checkbox"/> 240 Read headings of all defined groups | <input type="checkbox"/> 241 Read values of all entries of one group |
| <input type="checkbox"/> 243 Read directory of a single entry | <input type="checkbox"/> 244 Read value of a single entry |
| <input type="checkbox"/> 245 General interrogation of generic data | <input type="checkbox"/> 248 Write entry |
| <input type="checkbox"/> 249 Write entry with confirmation | <input type="checkbox"/> 250 Write entry with execution |
| <input type="checkbox"/> 251 Write entry abort | |

Basic application functions

- | | |
|--|--|
| <input type="checkbox"/> Test mode | <input type="checkbox"/> Blocking of monitor direction |
| <input checked="" type="checkbox"/> Disturbance data | <input type="checkbox"/> Generic services |
| <input checked="" type="checkbox"/> Private data | |

Miscellaneous

Measurand	max. value = rated value x	
	1.2	2.4
Current L ₁	<input type="checkbox"/>	<input checked="" type="checkbox"/>
Current L ₂	<input type="checkbox"/>	<input checked="" type="checkbox"/>
Current L ₃	<input type="checkbox"/>	<input checked="" type="checkbox"/>
Voltage L _{1-E}	<input type="checkbox"/>	<input checked="" type="checkbox"/>
Voltage L _{2-E}	<input type="checkbox"/>	<input checked="" type="checkbox"/>
Voltage L _{3-E}	<input type="checkbox"/>	<input checked="" type="checkbox"/>
Voltage L ₁ – L ₂	<input type="checkbox"/>	<input checked="" type="checkbox"/>
Active power P	<input type="checkbox"/>	<input checked="" type="checkbox"/>
Reactive power Y	<input type="checkbox"/>	<input checked="" type="checkbox"/>
Frequency f	<input checked="" type="checkbox"/>	<input type="checkbox"/>

Data Points List

Signals

<i>Module</i>	<i>Subgroups Names Functions</i>	<i>Function Type ASDU</i>	<i>Function (FUN)</i>	<i>Information Number (INF)</i>	<i>Device Interrogation</i>	<i>Description</i>
AR	active	1	160	16	GI	Signal: active
Prot	active	1	160	18	GI	Signal: active
PSet-Switch	min 1 param changed	1	160	22	GI	Signal: At least one parameter has been changed
DI Slot X1	DI 1	1	160	27	GI	Signal: Digital Input
DI Slot X1	DI 2	1	160	28	GI	Signal: Digital Input
DI Slot X1	DI 3	1	160	29	GI	Signal: Digital Input
DI Slot X1	DI 4	1	160	30	GI	Signal: Digital Input
CTS	Alarm	1	160	32	GI	Signal: Alarm Current Transformer Measuring Circuit Supervision
Prot	Alarm L1	2	160	64	GI	Signal: General-Alarm L1
Prot	Alarm L2	2	160	65	GI	Signal: General-Alarm L2
Prot	Alarm L3	2	160	66	GI	Signal: General-Alarm L3
Prot	Alarm G	2	160	67	GI	Signal: General-Alarm - Earth fault
Prot	Trip	2	160	68		Signal: General Trip
Prot	Trip L1	2	160	69		Signal: General Trip L1
Prot	Trip L2	2	160	70		Signal: General Trip L2
Prot	Trip L3	2	160	71		Signal: General Trip L3
Prot	Alarm	2	160	84	GI	Signal: General Alarm

Data Points List

Module	Subgroups Names Functions	Function Type ASDU	Function (FUN)	Information Number (INF)	Device Interrogation	Description
CBF	Alarm	2	160	85		Signal: Circuit Breaker Failure
I[1]	TripCmd	2	160	90		Signal: Trip Command
I[2]	TripCmd	2	160	91		Signal: Trip Command
IG[1]	TripCmd	2	160	92		Signal: Trip Command
IG[2]	TripCmd	2	160	93		Signal: Trip Command
AR	CB ON Cmd	1	160	128		Signal: CB switch ON Command
AR	Blo	1	160	130	GI	Signal: Auto Reclosure is blocked
Ctrl	Local	1	160	160	GI	Switching Authority: Local
AR	Ready	1	34	124	GI	Signal: Ready to shoot
AR	running	1	34	125	GI	Signal: Auto Reclosing running
AR	successful	1	34	128	GI	Signal: Auto Reclosing successful
AR	failed	1	34	129	GI	Signal: Auto Reclosing failure
AR	Shot 1	1	34	139	GI	Shot Control
AR	Shot 2	1	34	140	GI	Shot Control
AR	Shot 3	1	34	141	GI	Shot Control
AR	Shot 4	1	34	142	GI	Shot Control
AR	Shot 5	1	34	143	GI	Shot Control
AR	Shot 6	1	34	144	GI	Shot Control
AR	ARRecCState	1	34	145	GI	Signal: AutoReclosing states defined by IEC61850:1=Ready/2=In Progress/3=Successful
IEC 103	Failure Event lost	1	100	100		Failure event lost
I[1]	active	1	101	50	GI	Signal: active

Data Points List

Module	Subgroups Names Functions	Function Type ASDU	Function (FUN)	Information Number (INF)	Device Interrogation	Description
I[2]	active	1	101	51	GI	Signal: active
I[3]	active	1	101	52	GI	Signal: active
I[4]	active	1	101	53	GI	Signal: active
I[5]	active	1	101	54	GI	Signal: active
I[6]	active	1	101	55	GI	Signal: active
IG[1]	active	1	101	56	GI	Signal: active
IG[2]	active	1	101	57	GI	Signal: active
IG[3]	active	1	101	58	GI	Signal: active
IG[4]	active	1	101	59	GI	Signal: active
I[1]	Blo TripCmd	1	101	60	GI	Signal: Trip Command blocked
I[2]	Blo TripCmd	1	101	61	GI	Signal: Trip Command blocked
I[3]	Blo TripCmd	1	101	62	GI	Signal: Trip Command blocked
I[4]	Blo TripCmd	1	101	63	GI	Signal: Trip Command blocked
I[5]	Blo TripCmd	1	101	64	GI	Signal: Trip Command blocked
I[6]	Blo TripCmd	1	101	65	GI	Signal: Trip Command blocked
IG[1]	Blo TripCmd	1	101	66	GI	Signal: Trip Command blocked
IG[2]	Blo TripCmd	1	101	67	GI	Signal: Trip Command blocked
IG[3]	Blo TripCmd	1	101	68	GI	Signal: Trip Command blocked
IG[4]	Blo TripCmd	1	101	69	GI	Signal: Trip Command blocked
I[3]	TripCmd	2	101	92		Signal: Trip Command
I[4]	TripCmd	2	101	93		Signal: Trip Command
I[5]	TripCmd	2	101	94		Signal: Trip Command
I[6]	TripCmd	2	101	95		Signal: Trip Command

Data Points List

Module	Subgroups Names Functions	Function Type ASDU	Function (FUN)	Information Number (INF)	Device Interrogation	Description
IG[3]	TripCmd	2	101	98		Signal: Trip Command
IG[4]	TripCmd	2	101	99		Signal: Trip Command
I[1]	Alarm	2	101	100	GI	Signal: Alarm
I[2]	Alarm	2	101	101	GI	Signal: Alarm
I[3]	Alarm	2	101	102	GI	Signal: Alarm
I[4]	Alarm	2	101	103	GI	Signal: Alarm
I[5]	Alarm	2	101	104	GI	Signal: Alarm
I[6]	Alarm	2	101	105	GI	Signal: Alarm
IG[1]	Alarm	2	101	106	GI	Signal: Alarm IG
IG[2]	Alarm	2	101	107	GI	Signal: Alarm IG
IG[3]	Alarm	2	101	108	GI	Signal: Alarm IG
IG[4]	Alarm	2	101	109	GI	Signal: Alarm IG
ThR	active	1	102	50	GI	Signal: active
ThR	Blo TripCmd	1	102	60	GI	Signal: Trip Command blocked
ThR	TripCmd	2	102	90		Signal: Trip Command
ThR	Alarm	2	102	100	GI	Signal: Alarm Thermal Overload
I2>[1]	active	1	103	56	GI	Signal: active
I2>[2]	active	1	103	57	GI	Signal: active
I2>[1]	Blo TripCmd	1	103	66	GI	Signal: Trip Command blocked
I2>[2]	Blo TripCmd	1	103	67	GI	Signal: Trip Command blocked
I2>[1]	TripCmd	2	103	90		Signal: Trip Command
I2>[2]	TripCmd	2	103	91		Signal: Trip Command
I2>[1]	Alarm	2	103	100	GI	Signal: Alarm Negative Sequence

Data Points List

Module	Subgroups Names Functions	Function Type ASDU	Function (FUN)	Information Number (INF)	Device Interrogation	Description
I2>[2]	Alarm	2	103	101	GI	Signal: Alarm Negative Sequence
CBF	active	1	108	50	GI	Signal: active
CBF	running	1	108	60	GI	Signal: CBF-Module started
CBF	Trigger1	1	108	100	GI	Module Input: Trigger that will start the CBF
CBF	Trigger2	1	108	101	GI	Module Input: Trigger that will start the CBF
CBF	Trigger3	1	108	102	GI	Module Input: Trigger that will start the CBF
CBF	Lockout	1	108	106	GI	Signal: Lockout
CBF	Waiting for Trigger	1	108	107	GI	Waiting for Trigger
Exp[1]	active	1	114	50	GI	Signal: active
Exp[2]	active	1	114	51	GI	Signal: active
Exp[3]	active	1	114	52	GI	Signal: active
Exp[4]	active	1	114	53	GI	Signal: active
Exp[1]	Blo TripCmd	1	114	60	GI	Signal: Trip Command blocked
Exp[2]	Blo TripCmd	1	114	61	GI	Signal: Trip Command blocked
Exp[3]	Blo TripCmd	1	114	62	GI	Signal: Trip Command blocked
Exp[4]	Blo TripCmd	1	114	63	GI	Signal: Trip Command blocked
Exp[1]	TripCmd	2	114	90		Signal: Trip Command
Exp[2]	TripCmd	2	114	91		Signal: Trip Command
Exp[3]	TripCmd	2	114	92		Signal: Trip Command
Exp[4]	TripCmd	2	114	93		Signal: Trip Command

Data Points List

Module	Subgroups Names Functions	Function Type ASDU	Function (FUN)	Information Number (INF)	Device Interrogation	Description
Exp[1]	Alarm	2	114	100	GI	Signal: Alarm
Exp[2]	Alarm	2	114	101	GI	Signal: Alarm
Exp[3]	Alarm	2	114	102	GI	Signal: Alarm
Exp[4]	Alarm	2	114	103	GI	Signal: Alarm
SOTF	active	1	115	50	GI	Signal: active
CLPU	active	1	115	51	GI	Signal: active
CLPU	enabled	2	115	91		Signal: Cold Load enabled
SOTF	AR Blo	2	115	100	GI	Signal: Blocked by AR
DI Slot X1	DI 5	1	121	27	GI	Signal: Digital Input
DI Slot X1	DI 6	1	121	28	GI	Signal: Digital Input
DI Slot X1	DI 7	1	121	29	GI	Signal: Digital Input
DI Slot X1	DI 8	1	121	30	GI	Signal: Digital Input
BO Slot X2	BO 1	1	123	160	GI	Signal: Binary Output Relay
BO Slot X2	BO 2	1	123	161	GI	Signal: Binary Output Relay
BO Slot X2	BO 3	1	123	162	GI	Signal: Binary Output Relay
BO Slot X2	BO 4	1	123	163	GI	Signal: Binary Output Relay
BO Slot X2	BO 5	1	123	164	GI	Signal: Binary Output Relay
Logics	LE1.Gate Out	1	162	160	GI	Signal: Output of the logic gate
Logics	LE1.Timer Out	1	162	161	GI	Signal: Timer Output
Logics	LE1.Out	1	162	162	GI	Signal: Latched Output (Q)
Logics	LE1.Gate In1-I	1	162	163	GI	State of the module input: Assignment of the Input Signal
Logics	LE1.Gate In2-I	1	162	164	GI	State of the module input: Assignment of the Input Signal

Data Points List

Module	Subgroups Names Functions	Function Type ASDU	Function (FUN)	Information Number (INF)	Device Interrogation	Description
Logics	LE1.Gate In3-I	1	162	165	GI	State of the module input: Assignment of the Input Signal
Logics	LE1.Gate In4-I	1	162	166	GI	State of the module input: Assignment of the Input Signal
Logics	LE2.Gate Out	1	162	167	GI	Signal: Output of the logic gate
Logics	LE2.Timer Out	1	162	168	GI	Signal: Timer Output
Logics	LE2.Out	1	162	169	GI	Signal: Latched Output (Q)
Logics	LE2.Gate In1-I	1	162	170	GI	State of the module input: Assignment of the Input Signal
Logics	LE2.Gate In2-I	1	162	171	GI	State of the module input: Assignment of the Input Signal
Logics	LE2.Gate In3-I	1	162	172	GI	State of the module input: Assignment of the Input Signal
Logics	LE2.Gate In4-I	1	162	173	GI	State of the module input: Assignment of the Input Signal
Logics	LE3.Gate Out	1	162	174	GI	Signal: Output of the logic gate
Logics	LE3.Timer Out	1	162	175	GI	Signal: Timer Output
Logics	LE3.Out	1	162	176	GI	Signal: Latched Output (Q)
Logics	LE3.Gate In1-I	1	162	177	GI	State of the module input: Assignment of the Input Signal
Logics	LE3.Gate In2-I	1	162	178	GI	State of the module input: Assignment of the Input Signal
Logics	LE3.Gate In3-I	1	162	179	GI	State of the module input: Assignment of the Input Signal
Logics	LE3.Gate In4-I	1	162	180	GI	State of the module input: Assignment of the Input Signal

Data Points List

Module	Subgroups Names Functions	Function Type ASDU	Function (FUN)	Information Number (INF)	Device Interrogation	Description
Logics	LE4.Gate Out	1	162	181	GI	Signal: Output of the logic gate
Logics	LE4.Timer Out	1	162	182	GI	Signal: Timer Output
Logics	LE4.Out	1	162	183	GI	Signal: Latched Output (Q)
Logics	LE4.Gate In1-I	1	162	184	GI	State of the module input: Assignment of the Input Signal
Logics	LE4.Gate In2-I	1	162	185	GI	State of the module input: Assignment of the Input Signal
Logics	LE4.Gate In3-I	1	162	186	GI	State of the module input: Assignment of the Input Signal
Logics	LE4.Gate In4-I	1	162	187	GI	State of the module input: Assignment of the Input Signal
Logics	LE5.Gate Out	1	162	188	GI	Signal: Output of the logic gate
Logics	LE5.Timer Out	1	162	189	GI	Signal: Timer Output
Logics	LE5.Out	1	162	190	GI	Signal: Latched Output (Q)
Logics	LE5.Gate In1-I	1	162	191	GI	State of the module input: Assignment of the Input Signal
Logics	LE5.Gate In2-I	1	162	192	GI	State of the module input: Assignment of the Input Signal
Logics	LE5.Gate In3-I	1	162	193	GI	State of the module input: Assignment of the Input Signal
Logics	LE5.Gate In4-I	1	162	194	GI	State of the module input: Assignment of the Input Signal
Logics	LE6.Gate Out	1	162	195	GI	Signal: Output of the logic gate
Logics	LE6.Timer Out	1	162	196	GI	Signal: Timer Output
Logics	LE6.Out	1	162	197	GI	Signal: Latched Output (Q)

Data Points List

Module	Subgroups Names Functions	Function Type ASDU	Function (FUN)	Information Number (INF)	Device Interrogation	Description
Logics	LE6.Gate In1-I	1	162	198	GI	State of the module input: Assignment of the Input Signal
Logics	LE6.Gate In2-I	1	162	199	GI	State of the module input: Assignment of the Input Signal
Logics	LE6.Gate In3-I	1	162	200	GI	State of the module input: Assignment of the Input Signal
Logics	LE6.Gate In4-I	1	162	201	GI	State of the module input: Assignment of the Input Signal
Logics	LE7.Gate Out	1	162	202	GI	Signal: Output of the logic gate
Logics	LE7.Timer Out	1	162	203	GI	Signal: Timer Output
Logics	LE7.Out	1	162	204	GI	Signal: Latched Output (Q)
Logics	LE7.Gate In1-I	1	162	205	GI	State of the module input: Assignment of the Input Signal
Logics	LE7.Gate In2-I	1	162	206	GI	State of the module input: Assignment of the Input Signal
Logics	LE7.Gate In3-I	1	162	207	GI	State of the module input: Assignment of the Input Signal
Logics	LE7.Gate In4-I	1	162	208	GI	State of the module input: Assignment of the Input Signal
Logics	LE8.Gate Out	1	162	209	GI	Signal: Output of the logic gate
Logics	LE8.Timer Out	1	162	210	GI	Signal: Timer Output
Logics	LE8.Out	1	162	211	GI	Signal: Latched Output (Q)
Logics	LE8.Gate In1-I	1	162	212	GI	State of the module input: Assignment of the Input Signal
Logics	LE8.Gate In2-I	1	162	213	GI	State of the module input: Assignment of the Input Signal

Data Points List

Module	Subgroups Names Functions	Function Type ASDU	Function (FUN)	Information Number (INF)	Device Interrogation	Description
Logics	LE8.Gate In3-I	1	162	214	GI	State of the module input: Assignment of the Input Signal
Logics	LE8.Gate In4-I	1	162	215	GI	State of the module input: Assignment of the Input Signal
Logics	LE9.Gate Out	1	162	216	GI	Signal: Output of the logic gate
Logics	LE9.Timer Out	1	162	217	GI	Signal: Timer Output
Logics	LE9.Out	1	162	218	GI	Signal: Latched Output (Q)
Logics	LE9.Gate In1-I	1	162	219	GI	State of the module input: Assignment of the Input Signal
Logics	LE9.Gate In2-I	1	162	220	GI	State of the module input: Assignment of the Input Signal
Logics	LE9.Gate In3-I	1	162	221	GI	State of the module input: Assignment of the Input Signal
Logics	LE9.Gate In4-I	1	162	222	GI	State of the module input: Assignment of the Input Signal
Logics	LE10.Gate Out	1	162	223	GI	Signal: Output of the logic gate
Logics	LE10.Timer Out	1	162	224	GI	Signal: Timer Output
Logics	LE10.Out	1	162	225	GI	Signal: Latched Output (Q)
Logics	LE10.Gate In1-I	1	162	226	GI	State of the module input: Assignment of the Input Signal
Logics	LE10.Gate In2-I	1	162	227	GI	State of the module input: Assignment of the Input Signal
Logics	LE10.Gate In3-I	1	162	228	GI	State of the module input: Assignment of the Input Signal
Logics	LE10.Gate In4-I	1	162	229	GI	State of the module input: Assignment of the Input Signal

Data Points List

Module	Subgroups Names Functions	Function Type ASDU	Function (FUN)	Information Number (INF)	Device Interrogation	Description
Logics	LE11.Gate Out	1	163	160	GI	Signal: Output of the logic gate
Logics	LE11.Timer Out	1	163	161	GI	Signal: Timer Output
Logics	LE11.Out	1	163	162	GI	Signal: Latched Output (Q)
Logics	LE11.Gate In1-I	1	163	163	GI	State of the module input: Assignment of the Input Signal
Logics	LE11.Gate In2-I	1	163	164	GI	State of the module input: Assignment of the Input Signal
Logics	LE11.Gate In3-I	1	163	165	GI	State of the module input: Assignment of the Input Signal
Logics	LE11.Gate In4-I	1	163	166	GI	State of the module input: Assignment of the Input Signal
Logics	LE12.Gate Out	1	163	167	GI	Signal: Output of the logic gate
Logics	LE12.Timer Out	1	163	168	GI	Signal: Timer Output
Logics	LE12.Out	1	163	169	GI	Signal: Latched Output (Q)
Logics	LE12.Gate In1-I	1	163	170	GI	State of the module input: Assignment of the Input Signal
Logics	LE12.Gate In2-I	1	163	171	GI	State of the module input: Assignment of the Input Signal
Logics	LE12.Gate In3-I	1	163	172	GI	State of the module input: Assignment of the Input Signal
Logics	LE12.Gate In4-I	1	163	173	GI	State of the module input: Assignment of the Input Signal
Logics	LE13.Gate Out	1	163	174	GI	Signal: Output of the logic gate
Logics	LE13.Timer Out	1	163	175	GI	Signal: Timer Output
Logics	LE13.Out	1	163	176	GI	Signal: Latched Output (Q)

Data Points List

Module	Subgroups Names Functions	Function Type ASDU	Function (FUN)	Information Number (INF)	Device Interrogation	Description
Logics	LE13.Gate In1-I	1	163	177	GI	State of the module input: Assignment of the Input Signal
Logics	LE13.Gate In2-I	1	163	178	GI	State of the module input: Assignment of the Input Signal
Logics	LE13.Gate In3-I	1	163	179	GI	State of the module input: Assignment of the Input Signal
Logics	LE13.Gate In4-I	1	163	180	GI	State of the module input: Assignment of the Input Signal
Logics	LE14.Gate Out	1	163	181	GI	Signal: Output of the logic gate
Logics	LE14.Timer Out	1	163	182	GI	Signal: Timer Output
Logics	LE14.Out	1	163	183	GI	Signal: Latched Output (Q)
Logics	LE14.Gate In1-I	1	163	184	GI	State of the module input: Assignment of the Input Signal
Logics	LE14.Gate In2-I	1	163	185	GI	State of the module input: Assignment of the Input Signal
Logics	LE14.Gate In3-I	1	163	186	GI	State of the module input: Assignment of the Input Signal
Logics	LE14.Gate In4-I	1	163	187	GI	State of the module input: Assignment of the Input Signal
Logics	LE15.Gate Out	1	163	188	GI	Signal: Output of the logic gate
Logics	LE15.Timer Out	1	163	189	GI	Signal: Timer Output
Logics	LE15.Out	1	163	190	GI	Signal: Latched Output (Q)
Logics	LE15.Gate In1-I	1	163	191	GI	State of the module input: Assignment of the Input Signal
Logics	LE15.Gate In2-I	1	163	192	GI	State of the module input: Assignment of the Input Signal

Data Points List

Module	Subgroups Names Functions	Function Type ASDU	Function (FUN)	Information Number (INF)	Device Interrogation	Description
Logics	LE15.Gate In3-I	1	163	193	GI	State of the module input: Assignment of the Input Signal
Logics	LE15.Gate In4-I	1	163	194	GI	State of the module input: Assignment of the Input Signal
Logics	LE16.Gate Out	1	163	195	GI	Signal: Output of the logic gate
Logics	LE16.Timer Out	1	163	196	GI	Signal: Timer Output
Logics	LE16.Out	1	163	197	GI	Signal: Latched Output (Q)
Logics	LE16.Gate In1-I	1	163	198	GI	State of the module input: Assignment of the Input Signal
Logics	LE16.Gate In2-I	1	163	199	GI	State of the module input: Assignment of the Input Signal
Logics	LE16.Gate In3-I	1	163	200	GI	State of the module input: Assignment of the Input Signal
Logics	LE16.Gate In4-I	1	163	201	GI	State of the module input: Assignment of the Input Signal
Logics	LE17.Gate Out	1	163	202	GI	Signal: Output of the logic gate
Logics	LE17.Timer Out	1	163	203	GI	Signal: Timer Output
Logics	LE17.Out	1	163	204	GI	Signal: Latched Output (Q)
Logics	LE17.Gate In1-I	1	163	205	GI	State of the module input: Assignment of the Input Signal
Logics	LE17.Gate In2-I	1	163	206	GI	State of the module input: Assignment of the Input Signal
Logics	LE17.Gate In3-I	1	163	207	GI	State of the module input: Assignment of the Input Signal
Logics	LE17.Gate In4-I	1	163	208	GI	State of the module input: Assignment of the Input Signal

Data Points List

Module	Subgroups Names Functions	Function Type ASDU	Function (FUN)	Information Number (INF)	Device Interrogation	Description
Logics	LE18.Gate Out	1	163	209	GI	Signal: Output of the logic gate
Logics	LE18.Timer Out	1	163	210	GI	Signal: Timer Output
Logics	LE18.Out	1	163	211	GI	Signal: Latched Output (Q)
Logics	LE18.Gate In1-I	1	163	212	GI	State of the module input: Assignment of the Input Signal
Logics	LE18.Gate In2-I	1	163	213	GI	State of the module input: Assignment of the Input Signal
Logics	LE18.Gate In3-I	1	163	214	GI	State of the module input: Assignment of the Input Signal
Logics	LE18.Gate In4-I	1	163	215	GI	State of the module input: Assignment of the Input Signal
Logics	LE19.Gate Out	1	163	216	GI	Signal: Output of the logic gate
Logics	LE19.Timer Out	1	163	217	GI	Signal: Timer Output
Logics	LE19.Out	1	163	218	GI	Signal: Latched Output (Q)
Logics	LE19.Gate In1-I	1	163	219	GI	State of the module input: Assignment of the Input Signal
Logics	LE19.Gate In2-I	1	163	220	GI	State of the module input: Assignment of the Input Signal
Logics	LE19.Gate In3-I	1	163	221	GI	State of the module input: Assignment of the Input Signal
Logics	LE19.Gate In4-I	1	163	222	GI	State of the module input: Assignment of the Input Signal
Logics	LE20.Gate Out	1	163	223	GI	Signal: Output of the logic gate
Logics	LE20.Timer Out	1	163	224	GI	Signal: Timer Output
Logics	LE20.Out	1	163	225	GI	Signal: Latched Output (Q)

Data Points List

Module	Subgroups Names Functions	Function Type ASDU	Function (FUN)	Information Number (INF)	Device Interrogation	Description
Logics	LE20.Gate In1-I	1	163	226	GI	State of the module input: Assignment of the Input Signal
Logics	LE20.Gate In2-I	1	163	227	GI	State of the module input: Assignment of the Input Signal
Logics	LE20.Gate In3-I	1	163	228	GI	State of the module input: Assignment of the Input Signal
Logics	LE20.Gate In4-I	1	163	229	GI	State of the module input: Assignment of the Input Signal
TCS	active	1	241	50	GI	Signal: active
TCS	ExBlo	1	241	80		Signal: External Blocking
TCS	Alarm	1	241	100	GI	Signal: Alarm Trip Circuit Supervision
TCS	Not Possible	1	241	110	GI	Not possible because no state indicator assigned to the breaker.
SG[1]	Operations Alarm	1	242	104	GI	Signal: Service Alarm, too many Operations
SG[1]	WearLevel Alarm	1	242	130	GI	Signal: Threshold for the Alarm
SG[1]	WearLevel Lockout	1	242	131	GI	Signal: Threshold for the Lockout Level
Sgen	Ex ForcePost-I	1	245	110	GI	State of the module input:Force Post state. Abort simulation.
Sgen	Running	1	245	111	GI	Signal; Measuring value simulation is running
Ctrl	SG Disturb	1	246	32	GI	Minimum one Switchgear is disturbed.
Ctrl	SG Indeterm	1	246	33	GI	Minimum one Switchgear is moving (Position cannot be determined).

Data Points List

Module	Subgroups Names Functions	Function Type ASDU	Function (FUN)	Information Number (INF)	Device Interrogation	Description
SG[1]	Removed-I	1	246	34	GI	State of the module input: The withdrawable circuit breaker is Removed
SG[1]	CES SG removed	1	246	35	GI	Signal: Command Execution Supervision: Switching Command unsuccessful, Switchgear removed.
SG[1]	Removed	1	246	36	GI	Signal: The withdrawable circuit breaker is Removed
SG[1]	SCmd OFF-I	1	246	110	GI	State of the module input: Switching OFF Command, e.g. the state of the Logics or the state of the digital input
SG[1]	SCmd ON-I	1	246	111	GI	State of the module input: Switching ON Command, e.g. the state of the Logics or the state of the digital input
SG[1]	Position Ind manipul	1	246	112	GI	Signal: Position Indicators faked
SG[1]	Prot ON	1	246	113	GI	Signal: ON Command issued by the Prot module
SG[1]	TripCmd	2	246	114		Signal: Trip Command
SG[1]	OFF Cmd	1	246	115		Signal: OFF Command issued to the switchgear. Depending on the setting the signal may include the OFF command of the Prot module.
SG[1]	ON Cmd	1	246	116		Signal: ON Command issued to the switchgear. Depending on the setting the signal may include the ON command of the Prot module.

Data Points List

Module	Subgroups Names Functions	Function Type ASDU	Function (FUN)	Information Number (INF)	Device Interrogation	Description
SG[1]	CES succesf	1	246	117	GI	Signal: Command Execution Supervision: Switching command executed successfully.
SG[1]	Interl OFF	1	246	118	GI	Signal: One or more IL_Off inputs are active.
SG[1]	Interl ON	1	246	119	GI	Signal: One or more IL_On inputs are active.
SG[1]	Ready	1	246	120	GI	Signal: Circuit breaker is ready for operation.

Measuring Values

Module	Subgroup Names Functions	Function type ASDU	Function code (FUN)	Information Number (INF)	Factor	Position	Description
Measured values	IL1 [%]	9	160	148	2.4	0	Measured value: Phase current (fundamental)
Measured values	IL2 [%]	9	160	148	2.4	1	Measured value: Phase current (fundamental)
Measured values	IL3 [%]	9	160	148	2.4	2	Measured value: Phase current (fundamental)
Measured values	IL1 [%]	9	150	148	2.4	0	Measured value: Phase current (fundamental)
Measured values	IL2 [%]	9	150	148	2.4	1	Measured value: Phase current (fundamental)
Measured values	IL3 [%]	9	150	148	2.4	2	Measured value: Phase current (fundamental)
Measured values	IG meas [%]	9	150	148	2.4	3	Measured value (measured): IG (fundamental)
Measured values	IG calc [%]	9	150	148	2.4	4	Measured value (calculated): IG (fundamental)

Data Points List

Module	Subgroups Names Functions	Function Type ASDU	Function (FUN)	Information Number (INF)	Device Interrogation	Description
Fault measurement	IL1	4	92	150		Measured value: Phase current (fundamental)
Fault measurement	IL2	4	92	151		Measured value: Phase current (fundamental)
Fault measurement	IL3	4	92	152		Measured value: Phase current (fundamental)
Fault measurement	IG meas	4	92	186		Measured value (measured): IG (fundamental)

Commands

Module	Subgroups Names Functions	Function Type ASDU	Function (FUN)	Information Number (INF)	Device Interrogation	Description
Scada Cmd	Ack LED	20	160	19		Signal: LEDs acknowledgement
Scada Cmd	PS 1	20	160	23	GI	Signal: Parameter Set 1
Scada Cmd	PS 2	20	160	24	GI	Signal: Parameter Set 2
Scada Cmd	PS 3	20	160	25	GI	Signal: Parameter Set 3
Scada Cmd	PS 4	20	160	26	GI	Signal: Parameter Set 4
Scada Cmd	Scada Cmd 1	20	130	15		Scada Command
Scada Cmd	Scada Cmd 2	20	130	16		Scada Command
Scada Cmd	Scada Cmd 3	20	130	17		Scada Command
Scada Cmd	Scada Cmd 4	20	130	18		Scada Command
Scada Cmd	Scada Cmd 5	20	130	19		Scada Command
Scada Cmd	Scada Cmd 6	20	130	20		Scada Command
Scada Cmd	Scada Cmd 7	20	130	21		Scada Command
Scada Cmd	Scada Cmd 8	20	130	22		Scada Command
Scada Cmd	Scada Cmd 9	20	130	23		Scada Command
Scada Cmd	Scada Cmd 10	20	130	24		Scada Command
Scada Cmd	Ack BO	20	130	40		Signal: Acknowledgement of the Binary Outputs
Scada Cmd	Ack TripCmd	20	130	41		Signal: Reset Trip Command
SG[1]	Control/Position of circuit breaker	20	131	32	GI	Control respectively Position of circuit breaker (1 = OFF, 2 = On).

Analog Traces

<i>Module</i>	<i>IEC60870-5-103 Channel Number</i>	<i>Desc</i>
I L1	1	Analog trace I L1
I L2	2	Analog trace I L2
I L3	3	Analog trace I L3
IG	4	Analog trace IG

We appreciate your comments about the content of our publications.

Please send comments to: kemp.doc@woodward.com

Please include the manual number from the front cover of this publication.

Woodward Kempen GmbH reserves the right to update any portion of this publication at any time. Information provided by Woodward Kempen GmbH is believed to be correct and reliable. However, Woodward Kempen GmbH assumes no responsibility unless otherwise expressly undertaken.
© Woodward Kempen GmbH, all rights reserved



Woodward Kempen GmbH

Krefelder Weg 47 · D – 47906 Kempen (Germany)
Postfach 10 07 55 (P.O.Box) · D – 47884 Kempen (Germany)
Phone: +49 (0) 21 52 145 1

Internet

www.woodward.com

Sales

Phone: +49 (0) 21 52 145 216 or 342
Fax: +49 (0) 21 52 145 354
e-mail: salesEMEA_PGD@woodward.com

Service

Phone: +49 (0) 21 52 145 614
Fax: +49 (0) 21 52 145 455
e-mail: supportEMEA_PGD@woodward.com