

High **PROTEC**

MCA4

IEC 61850 Edition 2 – PICS

**Protocol Implementation Conformance Statement
for the IEC 61850 Edition 2 interface in MCA4**

Build 61991

Revision A

Version: 3.10

Date: 2024-03-16

Original document English

Based Upon UCAlug PICS Template version 3.0

© 2024 SEG Electronics GmbH. All rights reserved.

SEG Electronics GmbH

Krefelder Weg 47 • D-47906 Kempen (Germany)

Telephone: +49 (0) 21 52 145 0

Internet: www.SEGelectronics.de

Sales

Telephone: +49 (0) 21 52 145 331

Fax: +49 (0) 21 52 145 354

E-mail: sales@SEGelectronics.de

Service

Telephone: +49 (0) 21 52 145 600

Fax: +49 (0) 21 52 145 354

E-mail: support@SEGelectronics.de

SEG Electronics GmbH reserves the right to update any portion of this publication at any time.

Information provided by SEG Electronics GmbH is believed to be correct and reliable.

However, no responsibility is assumed by SEG Electronics GmbH unless otherwise expressly undertaken.

Complete address / phone / fax / email information for all locations is available on our website.

Table of Contents

1	General	4
2	ASCI basic conformance statement	5
3	ACSI models conformance statement	6
4	ACSI service conformance statement	8

1 General

This document is applicable for MCA4 Version 3.10.

- [ASCI basic conformance statement](#)
- [ACSI models conformance statement](#)
- [ACSI service conformance statement](#)

The statements specify the communication features mapped to IEC 61850-8-1 and IEC 61850-9-2.

2 ASCI basic conformance statement

The basic conformance statement is defined in the table below.

		Client / Subscriber	Server / Publisher	Value / Comments
Client-Server roles				
B11	Server side (of TWO-PARTY-APPLICATION-ASSOCIATION)	n/a	Y	
B12	Client side of (TWO-PARTY-APPLICATION-ASSOCIATION)	N	n/a	
SCSMs supported				
B21	SCSM: IEC 61850-8-1 used	-	Y	
B22	SCSM: IEC 61850-9-1 used	n/a	n/a	deprecated as of Ed. 2
B23	SCSM: IEC 61850-9-2 used	-	N	
B24	SCSM: other	-	N	
Generic substation event model (GSE)				
B31	Publisher side	n/a	Y	
B32	Subscriber side	Y	n/a	
Transmission of sampled value model (SVC)				
B41	Publisher side	n/a	N	
B42	Subscriber side	-	n/a	
-				
Y = supported				
N or empty = not supported				

3 ACSI models conformance statement

The ACSI models conformance statement is defined in the table below.

		Client / Subscriber	Server / Publisher	Value / Comments
If Server side (B11) or or Client side (B12) supported				
M1	Logical device	-	Y	
M2	Logical node	-	Y	
M3	Data	-	Y	
M4	Data set	-	Y	
M5	Substitution	-	N	
M6	Setting group control	-	Y	
Reporting				
M7	Buffered report control	-	Y	
M7-1	sequence-number	-	Y	
M7-2	report-time-stamp	-	Y	
M7-3	reason-for-inclusion	-	Y	
M7-4	data-set-name	-	Y	
M7-5	data-reference	-	Y	
M7-6	buffer-overflow	-	Y	
M7-7	entryID	-	Y	
M7-8	BufTim	-	Y	
M7-9	IntgPd	-	Y	
M7-10	GI	-	Y	
M7-11	conf-revision	-	Y	
M8	Unbuffered report control	-	Y	
M8-1	sequence-number	-	Y	
M8-2	report-time-stamp	-	Y	
M8-3	reason-for-inclusion	-	Y	
M8-4	data-set-name	-	Y	
M8-5	data-reference	-	Y	
M8-6	BufTim	-	Y	
M8-7	IntgPd	-	Y	

		Client / Subscriber	Server / Publisher	Value / Comments
M8-8	GI	-	Y	
M8-9	conf-revision	-	Y	
	Logging	-	N	
M9	Log control	-	N	
M9-1	IntgPd	-	N	
M10	Log	-	N	
M11	Control	-	Y	
M17	File Transfer	N	Y	
M18	Application association	-	Y	
M19	GOOSE Control Block	-	Y	
M20	Sampled Value Control Block	-	Y	
If GSE (B31/32) is supported				
M12	GOOSE	Y	Y	
M13	GSSE	N	N	deprecated as of Ed. 2
If SVC (B41/42) is supported				
M14	Multicast SVC	-	N	
M15	Unicast SVC	-	N	
For all IEDs				
M16	Time	Y	N	Time source with required accuracy shall be available. Only Time Master are SNTP (Mode 4 response) time server. All other Client / Server devices are SNTP (Mode 3 request) clients.

Y = service is supported

N or empty = service is not supported

4 ACSI service conformance statement

The ACSI service conformance statement is defined in the table below (depending on the statements in the tables in [↔2 ACSI basic conformance statement](#) and in [↔3 ACSI models conformance statement](#)).

	Services	AA: TP/MC	Client (C)	Server (S)	Comments
Server					
S1	GetServerDirectory (LOGICAL-DEVICE)	TP	-	Y	
Application association					
S2-1	Associate_Request	TP	-	Y	
S2-2	Associate_Response		-	Y	
S3-1	Abort_Request	TP	-	Y	
S3-2	Abort_Processing		-	Y	
S4-1	Release_Request		-	Y	
S4-2	Release_Response	TP	-	Y	
Logical device					
S5	GetLogicalDeviceDirectory	TP	-	Y	
Logical node					
S6	GetLogicalNodeDirectory	TP	-	Y	
S7	GetAllDataValues	TP	-	Y	
Data					
S8	GetDataValues	TP	-	Y	
S9	SetDataValues	TP	-	Y	
S10	GetDataDirectory	TP	-	Y	
S11	GetDataDefinition	TP	-	Y	
Data set					
S12	GetDataSetValues	TP	-	Y	
S13	SetDataSetValues	TP	-	Y	
S14	CreateDataSet	TP	-	Y	
S15	DeleteDataSet	TP	-	Y	
S16	GetDataSetDirectory	TP	-	Y	
Substitution					
S17	SetDataValues	TP	-	N	
Setting group control					
S18	SelectActiveSG	TP	-	Y	
S19	SelectEditSG	TP	-	N	
S20	SetEditSGValues	TP	-	N	
S21	ConfirmEditSGValues	TP	-	N	
S22	GetEditSGValues	TP	-	N	

	Services	AA: TP/MC	Client (C)	Server (S)	Comments
S23	GetSGCBValues	TP	-	Y	
Reporting					
Buffered report control block (BRCB)					
S24	Report	TP	-	Y	
S24-1	data-change (dchg)		-	Y	
S24-2	qchg-change (qchg)		-	Y	
S24-3	data-update (dupd)		-	Y	
S25	GetBRCBValues	TP	-	Y	
S26	SetBRCBValues	TP	-	Y	
Unbuffered report control block (URCB)					
S27	Report	TP	-	Y	
S27-1	data-change (dchg)		-	Y	
S27-2	qchg-change (qchg)		-	Y	
S27-3	data-update (dupd)		-	Y	
S28	GetURCBValues	TP	-	Y	
S29	SetURCBValues	TP	-	Y	
Logging					
Log control block					
S30	GetLCBValues	TP	-	N	
S31	SetLCBValues	TP	-	N	
Log					
S32	QueryLogByTime	TP	-	N	
S33	QueryLogAfter	TP	-	N	
S34	GetLogStatusValues	TP	-	N	
Generic substation event model (GSE)					
GOOSE-CONTROL-BLOCK					
S35	SendGOOSEMessage	MC	-	Y	
S36	GetGoReference	TP	-	Y	
S37	GetGOOSEElementNumber	TP	-	Y	
S38	GetGoCBValues	TP	-	Y	
S39	SetGoCBValues	TP	-	Y	
GSSE-CONTROL-BLOCK					
S40	SendGSSEMessage	MC	n.a.	n.a.	deprecated as of Ed. 2
S41	GetReference	TP	n.a.	n.a.	deprecated as of Ed. 2
S42	GetGSSEElementNumber	TP	n.a.	n.a.	deprecated as of Ed. 2
S43	GetGsCBValues	TP	n.a.	n.a.	deprecated as of Ed. 2
S44	SetGsCBValues	TP	n.a.	n.a.	deprecated as of Ed. 2


	Services	AA: TP/MC	Client (C)	Server (S)	Comments
Transmission of sampled value model (SVC)					
Multicast SV					
S45	SendMSVMessage	MC	-	N	
Multicast Sampled Value Control Block					
S46	GetMSVCBValues	TP	-	N	
S47	SetMSVCBValues	TP	-	N	
Unicast SV					
S48	SendUSVMessage	TP	-	N	
Unicast Sampled Value Control Block					
S49	GetUSVCBValues	TP	-	N	
S50	SetUSVCBValues	TP	-	N	
Control					
S51	Select		-	N	
S52	SelectWithValue	TP	-	Y	
S53	Cancel	TP	-	Y	
S54	Operate	TP	-	Y	
S55	CommandTermination	TP	-	Y	
S56	TimeActivatedOperate	TP	-	N	
File transfer					
S57	GetFile	TP	-	Y	
S58	SetFile	TP	-	N	
S59	DeleteFile	TP	-	Y	
S60	GetFileAttributeValues	TP	-	Y	
S61	GetServerDirectory (FILE-SYSTEM)	TP	-	Y	
Time					
T1	Time resolution of internal clock		24	-	Nearest negative power of 2^{-n} in seconds (number 0 ... 24)
T2	Time accuracy of internal clock		T1	T1	TL (ms) (low accuracy), $T3 < 7$ (only Ed2) T0 (ms) (≤ 10 ms), $7 \leq T3 < 10$ T1 (μ s) (≤ 1 ms), $10 \leq T3 < 13$ T2 (μ s) (≤ 100 μ s), $13 \leq T3 < 15$ T3 (μ s) (≤ 25 μ s), $15 \leq T3 < 18$ T4 (μ s) (≤ 25 μ s), $18 \leq T3 < 19$ T5 (μ s) (≤ 1 μ s), $T3 \geq 20$
T3	Supported TimeStamp resolution		10	xx	Nearest value n of 2^{-n} in seconds (number 0 ... 24)

High **PROTEC**

MCA4

IEC 61850 Edition 2 — PICS

docs.SEGelectronics.de/HighPROTEC



SEG Electronics GmbH reserves the right to update any portion of this publication at any time.
Information provided by SEG Electronics GmbH is believed to be correct and reliable.
However, SEG Electronics GmbH assumes no responsibility
unless otherwise expressly undertaken.



SEG Electronics GmbH
Krefelder Weg 47 • D-47906 Kempen (Germany)
Telephone: +49 (0) 21 52 145 0

Internet: www.SEGelectronics.de

Sales
Telephone: +49 (0) 21 52 145 331
Fax: +49 (0) 21 52 145 354
E-mail: sales@SEGelectronics.de

Service
Telephone: +49 (0) 21 52 145 600
Fax: +49 (0) 21 52 145 354
E-mail: support@SEGelectronics.de