

# IEC 61850 – MICS

High **PROTEC** | PROTECTION TECHNOLOGY  
MADE SIMPLE

MCDGV4 | GENERATOR PROTECTION

Model Implementation Conformance Statement (MICS)

UCA International Users Group Testing Sub Committee

Version: 3.7

Original document

English

Original reference manual

**SEG Electronics GmbH**

Krefelder Weg 47 • D-47906 Kempen (Germany)

Postfach 10 07 55 (P.O.Box) • D-47884 Kempen (Germany)

Telephone: +49 (0) 21 52 145 1

Internet: [www.SEGelectronics.de](http://www.SEGelectronics.de)

Sales

Telephone: +49 (0) 21 52 145 331

Fax: +49 (0) 21 52 145 354

E-mail: [SalesPGD\\_EMEA@SEGelectronics.de](mailto:SalesPGD_EMEA@SEGelectronics.de)

Service

Telephone: +49 (0) 21 52 145 614

Fax: +49 (0) 21 52 145 354

E-mail: [industrial.support@SEGelectronics.de](mailto:industrial.support@SEGelectronics.de)

© 2020 SEG Electronics GmbH. All rights reserved.

# Table of Contents

<b>1</b>	<b>Introduction</b>	<b>7</b>
<b>2</b>	<b>Logical Nodes</b>	<b>8</b>
2.1	Logical Nodes List	8
2.2	Logical Node Definitions	10
2.3	WW_CILO1	12
2.4	WW_CSWI1	12
2.5	WW_GAPC1	12
2.6	WW_GGIO4	13
2.7	WW_GGIO10	14
2.8	WW_GGIO11	15
2.9	WW_GGIO14	17
2.10	WW_IHMI1	18
2.11	WW_LLNOCON	18
2.12	WW_LLNOMEA	19
2.13	WW_LLNOPRO	19
2.14	WW_LLNOREC	20
2.15	WW_LLNOSYS	20
2.16	WW_LPHDCON	20
2.17	WW_LPHDMEA	21
2.18	WW_LPHDPRO	21
2.19	WW_LPHDREC	21
2.20	WW_LPHDSYS	22
2.21	WW_MMTR1	22
2.22	WW_MMXU3	22
2.23	WW_MMXU6	23
2.24	WW_MMXU7	23
2.25	WW_MSTA1	24
2.26	WW_MSTA2	25
2.27	WW_MSTA3	25
2.28	WW_PDIF1	26

Table of Contents

2.29	WW_PDIF2	27
2.30	WW_PDIF3	27
2.31	WW_PDIF4	27
2.32	WW_PDIS1	28
2.33	WW_PDOP1	28
2.34	WW_PDUP1	29
2.35	WW_PDUP2	29
2.36	WW_PFRC1	30
2.37	WW_PHAR1	30
2.38	WW_PIOC1	31
2.39	WW_PPAM1	31
2.40	WW_PPAM2	31
2.41	WW_PSOFF1	32
2.42	WW_PTOC1	32
2.43	WW_PTOC3	33
2.44	WW_PTOC4	33
2.45	WW_PTOF1	34
2.46	WW_PTOV1	34
2.47	WW_PTOV2	35
2.48	WW_PTOV3	35
2.49	WW_PTTR3	35
2.50	WW_PTTR4	36
2.51	WW_PTUF1	36
2.52	WW_PTUV1	37
2.53	WW_PTUV2	37
2.54	WW_PTUV3	38
2.55	WW_PTUV5	38
2.56	WW_PUPF1	39
2.57	WW_PVPH1	39
2.58	WW_PSDE1	39
2.59	WW_PSDE2	40
2.60	WW_RBRF1	40

2.61	WW_RDRE1	41
2.62	WW_RPSB1	41
2.63	WW_RSYN2	42
2.64	WW_SCBR1	42
2.65	WW_XCBR2	43
2.66	WW_XSWI1	43
<b>3</b>	<b>Common Data Class</b>	<b>45</b>
3.1	Common Data Class Definitions	45
3.1.1	WW_ACD1	46
3.1.2	WW_ACT1	46
3.1.3	WW_BCR1	46
3.1.4	WW_CMV2	46
3.1.5	WW_DEL2	47
3.1.6	WW_DPC1	47
3.1.7	WW_DPC2	47
3.1.8	WW_DPL1	48
3.1.9	WW_INC1	48
3.1.10	WW_INS1	48
3.1.11	WW_INS2	49
3.1.12	WW_INS3	49
3.1.13	WW_INS5	49
3.1.14	WW_LPL1	49
3.1.15	WW_LPL2	50
3.1.16	WW_LPL3	50
3.1.17	WW_MV1	50
3.1.18	WW_SPC1	50
3.1.19	WW_SPC2	51
3.1.20	WW_SPS1	51
3.1.21	WW_WYE2	51
3.2	Common Data Attributes Type Definitions	52
3.2.1	WW_analogValue1	52
3.2.2	WW_Cancel1	52

3.2.3	WW_Oper1 .....	52
3.2.4	WW_origin1 .....	52
3.2.5	WW_units1 .....	53
3.2.6	WW_vector1 .....	53
3.3	Enumerated type definitions .....	54
3.3.1	AutoRecSt .....	54
3.3.2	Beh .....	54
3.3.3	CBOpCap .....	54
3.3.4	ctlModel .....	54
3.3.5	Dbpos .....	55
3.3.6	ACDdir .....	55
3.3.7	Health .....	55
3.3.8	Mod .....	55
3.3.9	MotorCycle .....	56
3.3.10	multiplier .....	56
3.3.11	orCategory .....	57
3.3.12	sboClass .....	57
3.3.13	SIUnit .....	57
<b>4</b>	<b>Appendix .....</b>	<b>60</b>
4.1	Register Maps .....	60
4.2	Device Planning Dependencies .....	112

# 1 Introduction

This model implementation conformance statement is applicable to the MCDGV4 version 3.7.

This MICS document specifies the modelling extensions compared to IEC 61850 edition 1.

Clause 2 contains the list of implemented logical nodes.

Clause 3 describes the new and extended logical nodes.

Clause 4 describes the existing common data classes.

Clause 5 describes the existing enum types.

## 2 Logical Nodes

### 2.1 Logical Nodes List

The following table contains the list of logical nodes implemented in the device:

<b>L: System Logical Nodes</b>
<b>LLNO</b> (Logical Node device)
<b>LPHD</b> (Physical device)
<b>P: Logical Nodes for protection functions</b>
<b>PDIF</b> (Differential)
<b>PDIS</b> (Phase Distance)
<b>PDOP</b> (Directional overpower)
<b>PDUP</b> (Directional underpower)
<b>PFRC</b> (Rate of change of frequency)
<b>PHAR</b> (Harmonic restraint)
<b>PIOC</b> (Instantaneous overcurrent)
<b>PPAM</b> (Phase angle or out-of-step protection)
<b>PSDE</b> (Sensitive directional earthfault)
<b>PSOF</b> (Switch Onto Fault)
<b>PTOC</b> (Time overcurrent)
<b>PTOF</b> (Overfrequency)
<b>PTOV</b> (Overvoltage)
<b>PTTR</b> (Thermal overload protection)
<b>PTUF</b> (Underfrequency)
<b>PTUV</b> (Undervoltage)
<b>PUPF</b> (Underpower factor)
<b>VVPH</b> (Volts per Hz)
<b>R: Logical Nodes for protection related functions</b>
<b>RBRF</b> (Breaker failure)
<b>RDRE</b> (Disturbance recorder function)
<b>RPSB</b> (Power swing detection/blocking)
<b>RSYN</b> (Synchronism-check or synchronising)
<b>G: Logical Nodes for generic references</b>
<b>GAPC</b> (Generic automatic process control)
<b>GGIO</b> (Generic process I/O)



**M: Logical Nodes for metering and measurement**

**MMTR** (Metering)

**MMXU** (Measurement)

**MSTA** (Metering Statistics)

**X: Logical Nodes for switchgear**

**XCBR** (Circuit Breaker)

**XSWI** (Circuit Switch)

**C: Logical Nodes for control**

**CILO** (Interlocking)

**CSWI** (Switch controller)

**I: Logical Nodes for interfacing and archiving**

**IHMI** (Human machine interface)

**S: Logical Nodes for sensors and monitoring**

**SCBR** (Circuit breaker monitoring)

## 2.2 Logical Node Definitions

Abbreviations used in the following table:

- **M**: Data is mandatory in the IEC 61850-7-4.
- **O**: Data is optional in the IEC 61850-7-4 and is used in the device.
- **E**: Data is an extension to the IEC 61850-7-4.

LN Type	LN Class	Description
WW_CILO1	CILO	Interlocking
WW_CSWI1	CSWI	Switch controller
WW_GAPC1	GAPC	Generic automatic process control
WW_GGIO10	GGIO	Generic process I/O
WW_GGIO11	GGIO	Generic process I/O
WW_GGIO14	GGIO	Generic process I/O
WW_GGIO4	GGIO	Generic process I/O
WW_IHMI1	IHMI	Human machine interface
WW_LLNOCON	LLNO	Logical Node device
WW_LLNOMEA	LLNO	Logical Node device
WW_LLNOPRO	LLNO	Logical Node device
WW_LLNOREC	LLNO	Logical Node device
WW_LLNOSYS	LLNO	Logical Node device
WW_LPHDCON	LPHD	Physical device
WW_LPHDMEA	LPHD	Physical device
WW_LPHDPRO	LPHD	Physical device
WW_LPHDREC	LPHD	Physical device
WW_LPHDSYS	LPHD	Physical device
WW_MMTR1	MMTR	Metering
WW_MMXU3	MMXU	Measurement
WW_MMXU6	MMXU	Measurement
WW_MMXU7	MMXU	Measurement
WW_MSTA1	MSTA	Metering Statistics
WW_MSTA2	MSTA	Metering Statistics
WW_MSTA3	MSTA	Metering Statistics
WW_PDIF1	PDIF	Differential
WW_PDIF2	PDIF	Differential
WW_PDIF3	PDIF	Differential
WW_PDIF4	PDIF	Differential
WW_PDIS1	PDIS	Phase Distance
WW_PDOP1	PDOP	Directional overpower

LN Type	LN Class	Description
WW_PDUP1	PDUP	Directional underpower
WW_PDUP2	PDUP	Directional underpower
WW_PFRC1	PFRC	Rate of change of frequency
WW_PHAR1	PHAR	Harmonic restraint
WW_PIOC1	PIOC	Instantaneous overcurrent
WW_PPAM1	PPAM	Phase angle or out-of-step protection
WW_PPAM2	PPAM	Phase angle or out-of-step protection
WW_PSDE1	PSDE	Sensitive directional earthfault
WW_PSDE2	PSDE	Sensitive directional earthfault
WW_PSO1	PSOF	Switch Onto Fault
WW_PTOC1	PTOC	Time overcurrent
WW_PTOC3	PTOC	Time overcurrent
WW_PTOC4	PTOC	Time overcurrent
WW_PTOF1	PTOF	Overfrequency
WW_PTOV1	PTOV	Overvoltage
WW_PTOV2	PTOV	Overvoltage
WW_PTOV3	PTOV	Overvoltage
WW_PTTR3	PTTR	Thermal overload protection
WW_PTTR4	PTTR	Thermal overload protection
WW_PTUF1	PTUF	Underfrequency
WW_PTUV1	PTUV	Undervoltage
WW_PTUV2	PTUV	Undervoltage
WW_PTUV3	PTUV	Undervoltage
WW_PTUV5	PTUV	Undervoltage
WW_PUPF1	PUPF	Underpower factor
WW_PVPH1	PVPH	Volts per Hz
WW_RBRF1	RBRF	Breaker failure
WW_RDRE1	RDRE	Disturbance recorder function
WW_RPSB1	RPSB	Power swing detection/blocking
WW_RSYN2	RSYN	Synchronism-check or synchronising
WW_SCBR1	SCBR	Circuit breaker monitoring
WW_XCBR2	XCBR	Circuit Breaker
WW_XSWI1	XSWI	Circuit Switch

## 2.3 WW\_CILO1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>CILO class</b>				
CILO	WW_CILO1	Interlocking		
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behavior	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
EnaOpn	WW_SPS1	Enable Open	M	
EnaCls	WW_SPS1	Enable Close	M	

## 2.4 WW\_CSWI1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>CSWI class</b>				
CSWI	WW_CSWI1	Switch Controller		
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
Loc	WW_SPS1	Local operation	O	
<i>Controls</i>				
Pos	WW_DPC2	Switch position	M	

## 2.5 WW\_GAPC1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>GAPC class</b>				
GAPC	WW_GAPC1	Generic automatic process control		

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
Loc	WW_SPS1	Local operation	O	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

## 2.6 WW\_GGIO4

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>GGIO class</b>				
GGIO	WW_GGIO4	Generic process I/O		
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Ind1	WW_SPS1	General indication (binary input)	O	
Ind2	WW_SPS1	General indication (binary input)	O	
Ind3	WW_SPS1	General indication (binary input)	O	
Ind4	WW_SPS1	General indication (binary input)	O	
Ind5	WW_SPS1	General indication (binary input)	O	
Ind6	WW_SPS1	General indication (binary input)	O	
Ind7	WW_SPS1	General indication (binary input)	O	
Ind8	WW_SPS1	General indication (binary input)	O	
Ind9	WW_SPS1	General indication (binary input)	O	
Ind10	WW_SPS1	General indication (binary input)	O	
Ind11	WW_SPS1	General indication (binary input)	O	
Ind12	WW_SPS1	General indication (binary input)	O	

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
Ind13	WW_SPS1	General indication (binary input)	O	
Ind14	WW_SPS1	General indication (binary input)	O	
Ind15	WW_SPS1	General indication (binary input)	O	
Ind16	WW_SPS1	General indication (binary input)	O	
Ind17	WW_SPS1	General indication (binary input)	O	
Ind18	WW_SPS1	General indication (binary input)	O	
Ind19	WW_SPS1	General indication (binary input)	O	
Ind20	WW_SPS1	General indication (binary input)	O	
Ind21	WW_SPS1	General indication (binary input)	O	
Ind22	WW_SPS1	General indication (binary input)	O	
Ind23	WW_SPS1	General indication (binary input)	O	
Ind24	WW_SPS1	General indication (binary input)	O	
Ind25	WW_SPS1	General indication (binary input)	O	
Ind26	WW_SPS1	General indication (binary input)	O	
Ind27	WW_SPS1	General indication (binary input)	O	
Ind28	WW_SPS1	General indication (binary input)	O	
Ind29	WW_SPS1	General indication (binary input)	O	
Ind30	WW_SPS1	General indication (binary input)	O	
Ind31	WW_SPS1	General indication (binary input)	O	
Ind32	WW_SPS1	General indication (binary input)	O	

## 2.7 WW\_GGIO10

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>GGIO class</b>				
GGIO	WW_GGI10	Generic process I/O		
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Ind1	WW_SPS1	General indication (binary input)	O	
Ind2	WW_SPS1	General indication (binary input)	O	

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
Ind3	WW_SPS1	General indication (binary input)	0	
Ind4	WW_SPS1	General indication (binary input)	0	
Ind5	WW_SPS1	General indication (binary input)	0	
Ind6	WW_SPS1	General indication (binary input)	0	
Ind7	WW_SPS1	General indication (binary input)	0	
Ind8	WW_SPS1	General indication (binary input)	0	
Ind9	WW_SPS1	General indication (binary input)	0	
Ind10	WW_SPS1	General indication (binary input)	0	
Ind11	WW_SPS1	General indication (binary input)	0	
Ind12	WW_SPS1	General indication (binary input)	0	
Ind13	WW_SPS1	General indication (binary input)	0	
Ind14	WW_SPS1	General indication (binary input)	0	
Ind15	WW_SPS1	General indication (binary input)	0	
Ind16	WW_SPS1	General indication (binary input)	0	
Ind17	WW_SPS1	General indication (binary input)	0	
Ind18	WW_SPS1	General indication (binary input)	0	
Ind19	WW_SPS1	General indication (binary input)	0	
Ind20	WW_SPS1	General indication (binary input)	0	
Ind21	WW_SPS1	General indication (binary input)	0	
Ind22	WW_SPS1	General indication (binary input)	0	
Ind23	WW_SPS1	General indication (binary input)	0	
Ind24	WW_SPS1	General indication (binary input)	0	
Ind25	WW_SPS1	General indication (binary input)	0	
Ind26	WW_SPS1	General indication (binary input)	0	
Ind27	WW_SPS1	General indication (binary input)	0	
Ind28	WW_SPS1	General indication (binary input)	0	
Ind29	WW_SPS1	General indication (binary input)	0	
Ind30	WW_SPS1	General indication (binary input)	0	
Ind31	WW_SPS1	General indication (binary input)	0	
Ind32	WW_SPS1	General indication (binary input)	0	

## 2.8 WW\_GGIO11

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>GGIO class</b>				

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
GGIO	WW_GGI11	Generic process I/O		
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Ind1	WW_SPS1	General indication (binary input)	O	
Ind2	WW_SPS1	General indication (binary input)	O	
Ind3	WW_SPS1	General indication (binary input)	O	
Ind4	WW_SPS1	General indication (binary input)	O	
Ind5	WW_SPS1	General indication (binary input)	O	
Ind6	WW_SPS1	General indication (binary input)	O	
Ind7	WW_SPS1	General indication (binary input)	O	
Ind8	WW_SPS1	General indication (binary input)	O	
Ind9	WW_SPS1	General indication (binary input)	O	
Ind10	WW_SPS1	General indication (binary input)	O	
Ind11	WW_SPS1	General indication (binary input)	O	
Ind12	WW_SPS1	General indication (binary input)	O	
Ind13	WW_SPS1	General indication (binary input)	O	
Ind14	WW_SPS1	General indication (binary input)	O	
Ind15	WW_SPS1	General indication (binary input)	O	
Ind16	WW_SPS1	General indication (binary input)	O	
Ind17	WW_SPS1	General indication (binary input)	O	
Ind18	WW_SPS1	General indication (binary input)	O	
Ind19	WW_SPS1	General indication (binary input)	O	
Ind20	WW_SPS1	General indication (binary input)	O	
Ind21	WW_SPS1	General indication (binary input)	O	
Ind22	WW_SPS1	General indication (binary input)	O	
Ind23	WW_SPS1	General indication (binary input)	O	
Ind24	WW_SPS1	General indication (binary input)	O	
Ind25	WW_SPS1	General indication (binary input)	O	
Ind26	WW_SPS1	General indication (binary input)	O	
Ind27	WW_SPS1	General indication (binary input)	O	
Ind28	WW_SPS1	General indication (binary input)	O	



Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
Ind29	WW_SPS1	General indication (binary input)	O	
Ind30	WW_SPS1	General indication (binary input)	O	
Ind31	WW_SPS1	General indication (binary input)	O	
Ind32	WW_SPS1	General indication (binary input)	O	

## 2.9 WW\_GGIO14

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>GGIO class</b>				
GGIO	WW_GGI14	Generic process I/O		
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
SPCSO1	WW_SPC2	Single point controllable status output	O	
SPCSO2	WW_SPC2	Single point controllable status output	O	
SPCSO3	WW_SPC2	Single point controllable status output	O	
SPCSO4	WW_SPC2	Single point controllable status output	O	
SPCSO5	WW_SPC2	Single point controllable status output	O	
SPCSO6	WW_SPC2	Single point controllable status output	O	
SPCSO7	WW_SPC2	Single point controllable status output	O	
SPCSO8	WW_SPC2	Single point controllable status output	O	
SPCSO9	WW_SPC2	Single point controllable status output	O	
SPCSO10	WW_SPC2	Single point controllable status output	O	
SPCSO11	WW_SPC2	Single point controllable status output	O	
SPCSO12	WW_SPC2	Single point controllable status output	O	
SPCSO13	WW_SPC2	Single point controllable status output	O	
SPCSO14	WW_SPC2	Single point controllable status output	O	
SPCSO15	WW_SPC2	Single point controllable status output	O	
SPCSO16	WW_SPC2	Single point controllable status output	O	
SPCSO17	WW_SPC2	Single point controllable status output	O	
SPCSO18	WW_SPC2	Single point controllable status output	O	

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
SPCSO19	WW_SPC2	Single point controllable status output	O	
SPCSO20	WW_SPC2	Single point controllable status output	O	
SPCSO21	WW_SPC2	Single point controllable status output	O	
SPCSO22	WW_SPC2	Single point controllable status output	O	
SPCSO23	WW_SPC2	Single point controllable status output	O	
SPCSO24	WW_SPC2	Single point controllable status output	O	
SPCSO25	WW_SPC2	Single point controllable status output	O	
SPCSO26	WW_SPC2	Single point controllable status output	O	
SPCSO27	WW_SPC2	Single point controllable status output	O	
SPCSO28	WW_SPC2	Single point controllable status output	O	
SPCSO29	WW_SPC2	Single point controllable status output	O	
SPCSO30	WW_SPC2	Single point controllable status output	O	
SPCSO31	WW_SPC2	Single point controllable status output	O	
SPCSO32	WW_SPC2	Single point controllable status output	O	

## 2.10 WW\_IHMI1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>IHMI class</b>				
IHMI	WW_IHMI1	Human machine interface		
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	

## 2.11 WW\_LLNOCON

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>LLNO class</b>				
LLNO	WW_LLNOCON	Logical Node device		
<b>Data</b>				
<i>Common Logical Node Information</i>				

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL2	Name plate	M	

## 2.12 WW\_LLNOMEA

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>LLNO class</b>				
LLNO	WW_LLNOMEA	Logical Node device		
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL2	Name plate	M	

## 2.13 WW\_LLNOPRO

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>LLNO class</b>				
LLNO	WW_LLNOPRO	Logical Node device		
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL2	Name plate	M	

## 2.14 WW\_LLNOREC

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>LLNO class</b>				
LLNO	WW_LLNOREC	Logical Node device		
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL2	Name plate	M	

## 2.15 WW\_LLNO5SYS

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>LLNO class</b>				
LLNO	WW_LLNO5SYS	Logical Node device		
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL2	Name plate	M	

## 2.16 WW\_LPHDCON

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>LPHD class</b>				
LPHD	WW_LPHDCON	Physical device information		
<b>Data</b>				
<i>Common Logical Node Information</i>				
PhyNam	WW_DPL1	Physical device name plate	M	
PhyHealth	WW_INS3	Physical Device Health	M	
Proxy	WW_SPS1	Indicates if this LN is a proxy	M	

## 2.17 WW\_LPHDMEA

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>LPHD class</b>				
LPHD	WW_LPHDMEA	Physical device information		
<b>Data</b>				
<i>Common Logical Node Information</i>				
PhyNam	WW_DPL1	Physical device name plate	M	
PhyHealth	WW_INS3	Physical Device Health	M	
Proxy	WW_SPS1	Indicates if this LN is a proxy	M	

## 2.18 WW\_LPHDPRO

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>LPHD class</b>				
LPHD	WW_LPHDPRO	Physical device information		
<b>Data</b>				
<i>Common Logical Node Information</i>				
PhyNam	WW_DPL1	Physical device name plate	M	
PhyHealth	WW_INS3	Physical Device Health	M	
Proxy	WW_SPS1	Indicates if this LN is a proxy	M	

## 2.19 WW\_LPHDREC

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>LPHD class</b>				
LPHD	WW_LPHDREC	Physical device information		
<b>Data</b>				
<i>Common Logical Node Information</i>				
PhyNam	WW_DPL1	Physical device name plate	M	
PhyHealth	WW_INS3	Physical Device Health	M	
Proxy	WW_SPS1	Indicates if this LN is a proxy	M	

## 2.20 WW\_LPHDSYS

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>LPHD class</b>				
LPHD	WW_LPHDSYS	Physical device information		
<b>Data</b>				
<i>Common Logical Node Information</i>				
PhyNam	WW_DPL1	Physical device name plate	M	
PhyHealth	WW_INS3	Physical Device Health	M	
Proxy	WW_SPS1	Indicates if this LN is a proxy	M	

## 2.21 WW\_MMTR1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>MSTA class</b>				
MMTR1	WW_MMTR1	Metering		
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Metered values</i>				
TotVAh	WW_BCR1	Absolute Apparent Power Hours	O	
TotWh	WW_BCR1	Absolute Active Power Hours	O	
TotVARh	WW_BCR1	Absolute Reactive Power Hours	O	
SupWh	WW_BCR1	Consumed Active Energy	O	
SupVARh	WW_BCR1	Consumed Reactive Energy	O	
DmdWh	WW_BCR1	Fed Active Energy	O	
DmdVARh	WW_BCR1	Fed Reactive Energy	O	

## 2.22 WW\_MMXU3

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>MMXU class</b>				

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
MMXU	WW_MMXU3	Measurement		
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Measured values</i>				
TotW	WW_MV1	Total Active Power (Total P)	O	
TotVAr	WW_MV1	Total Reactive Power (Total Q)	O	
TotVA	WW_MV1	Total Apparent Power (Total S)	O	
TotPF	WW_MV1	Total Power factor (Total PF)	O	

## 2.23 WW\_MMXU6

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>MMXU class</b>				
MMXU	WW_MMXU6	Measurement		
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Measured values</i>				
PPV	WW_DEL2	Phase to phase voltages (VL12, VL23, VL31)	O	
PhV	WW_WYE2	Phase to ground voltages (VL1, VL2, VL3)	O	
Hz	WW_MV1	Frequency	O	

## 2.24 WW\_MMXU7

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>MMXU class</b>				
MMXU	WW_MMXU7	Measurement		

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Measured values</i>				
A	WW_WYE2	Phase currents (IL1, IL2, IL3)	O	

## 2.25 WW\_MSTA1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>MSTA class</b>				
MSTA	WW_MSTA1	Metering Statistics		
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Metered values</i>				
AvAPhA	WW_MV1	Average current IL1	E	
AvAPhB	WW_MV1	Average current IL2	E	
AvAPhC	WW_MV1	Average current IL3	E	
MaxAPhA	WW_MV1	Maximum current IL1	E	
MaxAPhB	WW_MV1	Maximum current IL2	E	
MaxAPhC	WW_MV1	Maximum current IL3	E	
MinAPhA	WW_MV1	Minimum current IL1	E	
MinAPhB	WW_MV1	Minimum current IL2	E	
MinAPhC	WW_MV1	Minimum current IL3	E	



## 2.26 WW\_MSTA2

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>MSTA class</b>				
MSTA	WW_MSTA2	Metering Statistics		
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Metered values</i>				
AvVPhAB	WW_MV1	Average voltage VL12	E	
AvVPhBC	WW_MV1	Average voltage VL23	E	
AvVPhCA	WW_MV1	Average voltage VL31	E	
MaxVPhAB	WW_MV1	Maximum voltage VL12	E	
MaxVPhBC	WW_MV1	Maximum voltage VL23	E	
MaxVPhCA	WW_MV1	Maximum voltage VL31	E	
MinVPhAB	WW_MV1	Minimum voltage VL12	E	
MinVPhBC	WW_MV1	Minimum voltage VL23	E	
MinVPhCA	WW_MV1	Minimum voltage VL31	E	
AvVPhA	WW_MV1	Average voltage VL1	E	
AvVPhB	WW_MV1	Average voltage VL2	E	
AvVPhC	WW_MV1	Average voltage VL3	E	
MaxVPhA	WW_MV1	Maximum voltage VL1	E	
MaxVPhB	WW_MV1	Maximum voltage VL2	E	
MaxVPhC	WW_MV1	Maximum voltage VL3	E	
MinVPhA	WW_MV1	Minimum voltage VL1	E	
MinVPhB	WW_MV1	Minimum voltage VL2	E	
MinVPhC	WW_MV1	Minimum voltage VL3	E	

## 2.27 WW\_MSTA3

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>MSTA class</b>				
MSTA	WW_MSTA3	Metering Statistics		

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Metered values</i>				
AvVA	WW_MV1	Average apparent power	O	
MaxVA	WW_MV1	Maximum apparent power	O	
MinVA	WW_MV1	Minimum apparent power	O	
Avw	WW_MV1	Average real power	O	
MaxW	WW_MV1	Maximum real power	O	
MinW	WW_MV1	Minimum real power	O	
AvVAr	WW_MV1	Average reactive power	O	
MaxVAr	WW_MV1	Maximum reactive power	O	
MinVAr	WW_MV1	Minimum reactive power	O	

## 2.28 WW\_PDIF1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>PDIF class</b>				
PDIF	WW_PDIF1	Differential		
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

## 2.29 WW\_PDIF2

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>PDIF class</b>				
PDIF	WW_PDIF2	Differential		
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

## 2.30 WW\_PDIF3

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>PDIF class</b>				
PDIF	WW_PDIF3	Differential		
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

## 2.31 WW\_PDIF4

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>PDIF class</b>				
PDIF	WW_PDIF4	Differential		

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

## 2.32 WW\_PDIS1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>PDIS class</b>				
PDIS	WW_PDIS1	Phase Distance Protection		
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

## 2.33 WW\_PDOP1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>PDOP class</b>				
PDOP	WW_PDOP1	Directional overpower		
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

## 2.34 WW\_PDUP1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>PDUP class</b>				
PDUP	WW_PDUP1	Directional underpower		
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

## 2.35 WW\_PDUP2

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>PDUP class</b>				
PDUP	WW_PDUP2	Directional underpower		
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
Op	WW_ACT1	Operate	M	

## 2.36 WW\_PFRC1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>PFRC class</b>				
PFRC	WW_PFRC1	Rate of change of frequency		
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

## 2.37 WW\_PHAR1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>PHAR class</b>				
PHAR	WW_PHAR1	Harmonic restraint		
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	

## 2.38 WW\_PIOC1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>PIOC class</b>				
PIOC	WW_PIOC1	Instantaneous overcurrent		
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

## 2.39 WW\_PPAM1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>PPAM class</b>				
PPAM	WW_PPAM1	Phase angle measuring		
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

## 2.40 WW\_PPAM2

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>PPAM class</b>				
PPAM	WW_PPAM2	Phase angle measuring		

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

## 2.41 WW\_PSOFF1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>PSOF class</b>				
PSOF	WW_PSOFF1	Protection Switch Onto fault		
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL3	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	

## 2.42 WW\_PTOC1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>PTOC class</b>				
PTOC	WW_PTOC1	Time overcurrent		
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	



Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

## 2.43 WW\_PTOC3

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>PTOC class</b>				
PTOC	WW_PTOC3	Time overcurrent		
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

## 2.44 WW\_PTOC4

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>PTOC class</b>				
PTOC	WW_PTOC4	Time overcurrent		
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
Op	WW_ACT1	Operate	M	

## 2.45 WW\_PTOF1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>PTOF class</b>				
PTOF	WW_PTOF1	Overfrequency		
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

## 2.46 WW\_PTOV1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>PTOV class</b>				
PTOV	WW_PTOV1	Overvoltage		
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

## 2.47 WW\_PTOV2

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>PTOV class</b>				
PTOV	WW_PTOV2	Overvoltage		
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

## 2.48 WW\_PTOV3

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>PTOV class</b>				
PTOV	WW_PTOV3	Overvoltage		
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

## 2.49 WW\_PTTR3

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>PTTR class</b>				
PTTR	WW_PTTR3	Thermal overload		

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Op	WW_ACT1	Operate	M	

## 2.50 WW\_PTTR4

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>PTTR class</b>				
PTTR	WW_PTTR4	Thermal overload		
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Op	WW_ACT1	Operate	M	

## 2.51 WW\_PTUF1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>PTUF class</b>				
PTUF	WW_PTUF1	Underfrequency		
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

## 2.52 WW\_PTUV1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>PTUV class</b>				
PTUV	WW_PTUV1	Undervoltage		
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

## 2.53 WW\_PTUV2

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>PTUV class</b>				
PTUV	WW_PTUV2	Undervoltage		
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
Op	WW_ACT1	Operate	M	

## 2.54 WW\_PTUV3

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>PTUV class</b>				
PTUV	WW_PTUV3	Undervoltage		
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

## 2.55 WW\_PTUV5

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>PTUV class</b>				
PTUV	WW_PTUV5	Undervoltage		
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

## 2.56 WW\_PUPF1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>PUPF class</b>				
PUPF	WW_PUPF1	Underpower factor		
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

## 2.57 WW\_PVPH1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>PVPH class</b>				
PVPH	WW_PVPH1	Volts per Hz		
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

## 2.58 WW\_PSDE1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>PSDE class</b>				
PSDE	WW_PSDE1	Wattmetric directional earthfault (IG meas dir)		

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	

## 2.59 WW\_PSDE2

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>PSDE class</b>				
PSDE	WW_PSDE2	Wattmetric directional earthfault (IG meas dir)		
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	

## 2.60 WW\_RBRF1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>RBRF class</b>				
RBRF	WW_RBRF1	Breaker failure		
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	



Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
OpEx	WW_ACT1	Breaker failure trip	M	

## 2.61 WW\_RDRE1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>RDRE class</b>				
RDRE	WW_RDRE1	Disturbance recorder function		
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
RcdMade	WW_SPS1	Recording made	M	
FltNum	WW_INS2	Fault Number	M	
GriFltNum	WW_INS2	Grid Fault Number	O	
RcdStr	WW_SPS1	Recording started	O	

## 2.62 WW\_RPSB1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>RPSB class</b>				
RPSB	WW_RPSB1	Power Swing Blocking		
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start (Power Swing Detected)	M	

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
BlkZn	WW_SPS1	Blocking of correlated PDIS zone	M	

## 2.63 WW\_RSYN2

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>RSYN class</b>				
RSYN	WW_RSYN2	Synchronism-check or synchronising		
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Rel	WW_SPS1	Release	M	
AngInd	WW_SPS1	Phase Angle difference to high	E	
HzInd	WW_SPS1	Frequency difference to high	E	
VInd	WW_SPS1	Voltage difference to high	E	
<i>Measured Values</i>				
DifAngClc	WW_MV1	Phase Angle difference value	E	
DifHzClc	WW_MV1	Frequency difference value	E	
DifVClc	WW_MV1	Voltage difference value	E	

## 2.64 WW\_SCBR1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>RBRF class</b>				
SCBR	WW_SCBR1	Circuit breaker monitoring		
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<i>Status Information</i>				
TrCctAlm	WW_ACD1	Alarm signal	E	

## 2.65 WW\_XCBR2

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>XCBR class</b>				
XCBR	WW_XCBR2	Circuit Breaker		
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
Loc	WW_SPS1	Local operation	M	
OpCnt	WW_INS2	Operation counter	M	
<i>Status Information</i>				
CBOpCap	WW_INS5	Circuit breaker operating capability	M	
<i>Controls</i>				
Pos	WW_DPC1	Switch position	M	
BlkOpn	WW_SPC1	Block opening	M	
BlkCls	WW_SPC1	Block closing	M	

## 2.66 WW\_XSWI1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<b>XSWI class</b>				
XSWI	WW_XSWI1	Circuit switch		
<b>Data</b>				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	

2 Logical Nodes  
 2.66 WW\_XSWI1

<b>Attribute Name</b>	<b>Attribute Type</b>	<b>Explanation</b>	<b>M/O/E</b>	<b>Remarks</b>
Loc	WW_SPS1	Local operation	M	
OpCnt	WW_INS2	Operation counter	M	
<i>Status Information</i>				
SwTyp	WW_INS5	Switch type	M	
SwOpCap	WW_INS5	Switch operating capability	M	
<i>Controls</i>				
Pos	WW_DPC1	Switch position	M	
BlkOpn	WW_SPC1	Block opening	M	
BlkCls	WW_SPC1	Block closing	M	

## 3 Common Data Class

### 3.1 Common Data Class Definitions

The following table contains the list of Common Data Classes implemented in the device:

CDC Type	CDC Class	Description
WW_ACD1	ACD	Directional Protection activation information
WW_ACT1	ACT	Protection Activation Information
WW_analogValue1	analogValue	Analogue value
WW_BCR1	BCR	Binary Counter Reading
WW_Cancel1	Cancel	Cancel operating
WW_CMV2	CMV	Complex measured value
WW_DEL2	DEL	Delta
WW_DPC1	DPC	Controllable Double Point
WW_DPC2	DPC	Controllable Double Point
WW_DPL1	DPL	Device name plate
WW_INC1	INC	Controllable Integer Status
WW_INS1	INS	Integer Status
WW_INS2	INS	Integer Status
WW_INS3	INS	Integer Status
WW_INS5	INS	Integer Status
WW_LPL1	LPL	Logical node name plate
WW_LPL2	LPL	Logical node name plate
WW_LPL3	LPL	Logical node name plate
WW_MV1	MV	Measured Value
WW_Oper1	Oper	Start/Select operating
WW_origin1	origin	Originator
WW_SPC1	SPC	Controllable Single Point
WW_SPC2	SPC	Controllable Single Point
WW_SPS1	SPS	Single Point Status
WW_units1	units	Unit definition
WW_vector1	vector	Vector definition
WW_WYE2	WYE	Phase to ground related measured values of a three phase system

**3.1.1 WW\_ACD1**

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
<b>ACD class</b>						
General	BOOLEAN	ST	dchg		M	
dirGeneral	Enum	ST	dchg	ACDdir	M	
q	Quality	ST	qchg		M	
t	Timestamp	ST			M	

**3.1.2 WW\_ACT1**

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
<b>ACT class</b>						
General	BOOLEAN	ST	dchg		M	
q	Quality	ST	qchg		M	
t	Timestamp	ST			M	

**3.1.3 WW\_BCR1**

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
<b>BCR class</b>						
actVal	INT32	ST	dchg		M	
q	Quality	ST	qchg		M	
t	Timestamp	ST			M	
pulsQty	FLOAT32	CF			M	
units	Struct	CF			O	

**3.1.4 WW\_CMV2**

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
<b>CMV class</b>						
cVal	Struct	MX		WW_vector1	M	
q	Quality	ST	qchg		M	
t	Timestamp	ST			M	

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
instCVal	Struct	MX		WW_vector1	O	
units	Struct	CF		WW_units1	O	
db	INT32U	CF			O	
dbAng	INT32U	CF			E	

### 3.1.5 WW\_DEL2

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
<b>DEL class</b>						
phsAB	WW_CMV2					
phsBC	WW_CMV2					
phsCA	WW_CMV2					

### 3.1.6 WW\_DPC1

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
<b>DPC class</b>						
stVal	Dbpos	ST	dchg	Dbpos	M	
q	Quality	ST	qchg		M	
t	Timestamp	ST			M	
ctlModel	Enum	CF		ctlModel	M	

### 3.1.7 WW\_DPC2

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
<b>DPC class</b>						
origin	Struct	ST		WW_origin1	O	
ctlNum	INT8U	ST			O	
stVal	Dbpos	ST	dchg	Dbpos	M	
q	Quality	ST	qchg		M	
t	Timestamp	ST			M	
stSeld	BOOLEAN	ST	dchg		O	

### 3 Common Data Class

#### 3.1.8 WW\_DPL1

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
ctlModel	Enum	CF		ctlModel	M	
sboTimeout	INT32U	CF			O	
sboClass	Enum	CF		sboClass	O	
cdcNs	VisString255	EX			O	
Oper	Struct	CO		WW_Oper1		
SBOw	Struct	CO		WW_Oper1		
Cancel	Struct	CO		WW_Cancel1		

#### 3.1.8 WW\_DPL1

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
<b>DPL class</b>						
vendor	VisString255	DC			M	

#### 3.1.9 WW\_INC1

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
<b>INC class</b>						
stVal	Enum	ST	dchg	Mode	M	
q	Quality	ST	qchg		M	
t	Timestamp	ST			M	
ctlModel	Enum	CF		ctlModel	M	

#### 3.1.10 WW\_INS1

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
<b>INS class</b>						
stVal	Enum	ST	dchg	Behaviour	M	
q	Quality	ST	qchg		M	
t	Timestamp	ST			M	



**3.1.11 WW\_INS2**

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
<b>INS class</b>						
stVal	INT32	ST	dchg		M	
q	Quality	ST	qchg		M	
t	Timestamp	ST			M	

**3.1.12 WW\_INS3**

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
<b>INS class</b>						
stVal	Enum	ST	dchg	AutoRecSt	M	
q	Quality	ST	qchg		M	
t	Timestamp	ST			M	

**3.1.13 WW\_INS5**

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
<b>INS class</b>						
stVal	Enum	ST	dchg	CBOpCap	M	
q	Quality	ST	qchg		M	
t	Timestamp	ST			M	

**3.1.14 WW\_LPL1**

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
<b>LPL class</b>						
vendor	visString255	DC			M	
swRev	visString255	DC			M	
d	visString255	DC			M	

### 3.1.15 WW\_LPL2

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
<b>LPL class</b>						
vendor	visString255	DC			M	
swRev	visString255	DC			M	
d	visString255	DC			M	
ldNs	visString255	EX				

### 3.1.16 WW\_LPL3

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
<b>LPL class</b>						
vendor	visString255	DC			M	
swRev	visString255	DC			M	
d	visString255	DC			M	
LnNS	visString255	EX				

### 3.1.17 WW\_MV1

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
<b>MV class</b>						
mag	Struct	MX		WW_analogValue1	M	
q	Quality	ST	qchg		M	
t	Timestamp	ST			M	
units	Struct	CF		WW_units1	O	
db	INT32U	CF			O	
d	visString255	DC			O	
dataNs	visString255	DC			O	

### 3.1.18 WW\_SPC1

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
<b>SPC class</b>						

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
stVal	BOOLEAN	ST	dchg		M	
q	Quality	ST	dchg		M	
t	Timestamp	ST			M	
ctlModel	Enum	CF		ctlModel	M	

### 3.1.19 WW\_SPC2

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
<b>SPC class</b>						
Oper	Struct	CO		WW_Oper1		
stVal	BOOLEAN	ST	dchg		M	
q	Quality	ST	dchg		M	
t	Timestamp	ST			M	
ctlModel	Enum	CF		ctlModel	M	

### 3.1.20 WW\_SPS1

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
<b>SPS class</b>						
stVal	BOOLEAN	ST	dchg		M	
q	Quality	ST	qchg		M	
t	Timestamp	ST			M	

### 3.1.21 WW\_WYE2

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
<b>WYE class</b>						
phsAB	WW_CMV2					
phsBC	WW_CMV2					
phsCA	WW_CMV2					
neut	WW_CMV2					

## 3.2 Common Data Attributes Type Definitions

### 3.2.1 WW\_analogValue1

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
<b>analogValue class</b>						
f	FLOAT32	MX			M	

### 3.2.2 WW\_Cancel1

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
<b>Cancel class</b>						
ctlval	BOOLEAN	CO			M	
origin	Struct	ST		WW_origin1	O	
ctlNum	INT8U	ST			O	
T	Timestamp	CO			O	
Test	BOOLEAN	CO			O	

### 3.2.3 WW\_Oper1

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
<b>Oper class</b>						
ctlval	BOOLEAN	CO			M	
origin	Struct	ST		WW_origin1	O	
ctlNum	INT8U	ST			O	
T	Timestamp	CO			O	
Test	BOOLEAN	CO			O	
Check	Check	CO			O	

### 3.2.4 WW\_origin1

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
<b>origin class</b>						
orCat	Enum	ST		orCategory	M	

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
orIdent	Octet64	ST			M	

### 3.2.5 WW\_units1

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
<b>unit class</b>						
SIUnit	Enum			SIUnit	M	
multiplier	Enum			multiplier	O	

### 3.2.6 WW\_vector1

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
<b>vector class</b>						
mag	Struct			WW_analogValue1	M	
ang	Struct			WW_analogValue1	O	

### 3.3 Enumerated type definitions

#### 3.3.1 AutoRecSt

Ordinal	Semantic
1	Ready
2	InProgress
3	Successful

#### 3.3.2 Beh

Ordinal	Semantic
1	on
2	blocked
3	test
4	test/blocked
5	off

#### 3.3.3 CBOpCap

Ordinal	Semantic
1	None
2	Open
3	Close-Open
4	Open-Close-Open
5	Close-Open-Close-Open

#### 3.3.4 ctIModel

Ordinal	Semantic
1	status-only
2	direct-with-normal-security
3	sbo-with-normal-security
4	direct-with-enhanced-security

Ordinal	Semantic
5	sbo-with-enhanced-security

### 3.3.5 Dbpos

Ordinal	Semantic
1	intermediate
2	off
3	on
4	bad

### 3.3.6 ACDDir

Ordinal	Semantic
0	unknown
1	forward
2	backward
3	both

### 3.3.7 Health

Ordinal	Semantic
1	Ok
2	Warning
3	Alarm

### 3.3.8 Mod

Ordinal	Semantic
1	on
2	blocked
3	test
4	test/block

Ordinal	Semantic
5	off

### 3.3.9 MotorCycle

Ordinal	Semantic
0	Trip/Off
1	Stop
2	Start
3	Run

### 3.3.10 multiplier

Ordinal	Semantic
-24	y
-21	z
-18	a
-15	f
-12	p
-9	n
-6	μ
-3	m
-2	c
-1	d
0	
1	da
2	h
3	k
6	M
9	G
12	T
15	P
18	E



Ordinal	Semantic
21	Z
24	Y

### 3.3.11 orCategory

Ordinal	Semantic
0	not-supported
1	bay-control
2	station-control
3	remote-control
4	automatic-bay
5	automatic-station
6	automatic-remote
7	maintenance
8	process

### 3.3.12 sboClass

Ordinal	Semantic
0	operate-once
1	operate-many

### 3.3.13 SIUnit

Ordinal	Semantic
1	none
2	m
3	kg
4	s
5	A
6	K
7	mol
8	cd

Ordinal	Semantic
9	deg
10	rad
11	sr
21	Gy
22	q
23	°C
24	Sv
25	F
26	C
27	S
28	H
29	V
30	ohm
31	J
32	N
33	Hz
34	lx
35	Lm
36	Wb
37	T
38	W
39	Pa
41	m <sup>2</sup>
42	m <sup>3</sup>
43	m/s
44	m/s <sup>2</sup>
45	m <sup>3</sup> /s
46	m/m <sup>3</sup>
47	M
48	kg/m <sup>3</sup>
49	m <sup>2</sup> /s
50	W/m K

Ordinal	Semantic
51	J/K
52	ppm
53	1/s
54	rad/s
61	VA
62	Watts
63	VAr
64	phi
65	cos(phi)
66	Vs
67	V <sup>2</sup>
68	As
69	A <sup>2</sup>
70	A <sup>2</sup> t
71	VAh
72	Wh
73	VArh
74	V/Hz

## 4 Appendix

### 4.1 Register Maps

Legend: \* The Logical Node is dependent on the settings in the “Device planning”. (See [↪ “4.2 Device Planning Dependencies”](#)).

***LDevice::CTRL***

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>CILO1* (WW_CILO1)</b>		
	Mod	
	Beh	
	Health	
	NamPlt	
	EnaOpn	SG[1] . Interl OFF
	EnaCls	SG[1] . Interl ON

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>CILO2* (WW_CILO1)</b>		
	Mod	
	Beh	
	Health	
	NamPlt	
	EnaOpn	SG[2] . Interl OFF
	EnaCls	SG[2] . Interl ON

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>CILO3* (WW_CILO1)</b>		
	Mod	
	Beh	
	Health	
	NamPlt	
	EnaOpn	SG[3] . Interl OFF
	EnaCls	SG[3] . Interl ON

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>CILO4* (WW_CILO1)</b>		
	Mod	
	Beh	
	Health	

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>CILO4* (WW_CILO1)</b>		
	NamPlt	
	EnaOpn	SG[4] . Interl OFF
	EnaCls	SG[4] . Interl ON

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>CILO5* (WW_CILO1)</b>		
	Mod	
	Beh	
	Health	
	NamPlt	
	EnaOpn	SG[5] . Interl OFF
	EnaCls	SG[5] . Interl ON

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>CILO6* (WW_CILO1)</b>		
	Mod	
	Beh	
	Health	
	NamPlt	
	EnaOpn	SG[6] . Interl OFF
	EnaCls	SG[6] . Interl ON

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>CSWI1* (WW_CSWI1)</b>		
	Mod	
	Beh	
	Health	
	NamPlt	
	Loc	
	Pos	SG[1] . Pos

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>CSWI2* (WW_CSWI1)</b>		
	Mod	
	Beh	
	Health	
	NamPlt	

4 Appendix  
 4.1 Register Maps

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>CSWI2* (WW_CSWI1)</b>		
	Loc	
	Pos	SG[2] . Pos

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>CSWI3* (WW_CSWI1)</b>		
	Mod	
	Beh	
	Health	
	NamPlt	
	Loc	
	Pos	SG[3] . Pos

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>CSWI4* (WW_CSWI1)</b>		
	Mod	
	Beh	
	Health	
	NamPlt	
	Loc	
	Pos	SG[4] . Pos

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>CSWI5* (WW_CSWI1)</b>		
	Mod	
	Beh	
	Health	
	NamPlt	
	Loc	
	Pos	SG[5] . Pos

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>CSWI6* (WW_CSWI1)</b>		
	Mod	
	Beh	
	Health	
	NamPlt	
	Loc	

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>CSWI6* (WW_CSWI1)</b>		
	Pos	SG[6] . Pos

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>LLN0 (WW_LLNOCON)</b>		
	Mod	
	Beh	
	Health	
	NamPlt	

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>LPHD1 (WW_LPHDCON)</b>		
	PhyNam	
	PhyHealth	
	Proxy	

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>TCSSCBR1 (WW_SCBR1)</b>		
	Mod	TCS - 74TC . active
	Beh	
	Health	
	NamPlt	
	TrCctAlm	TCS - 74TC . Alarm

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>XCBR1* (WW_XCBR2)</b>		
	Mod	
	Beh	
	Health	
	NamPlt	
	Loc	
	OpCnt	
	Pos	SG[1] . Pos
	BlkOpn	
	BlkCls	
	CBOPCap	

4 Appendix  
4.1 Register Maps

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>XCBR2* (WW_XCBR2)</b>		
	Mod	
	Beh	
	Health	
	NamPlt	
	Loc	
	OpCnt	
	Pos	SG[2] . Pos
	BlkOpn	
	BlkCls	
	CBOpCap	

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>XCBR3* (WW_XCBR2)</b>		
	Mod	
	Beh	
	Health	
	NamPlt	
	Loc	
	OpCnt	
	Pos	SG[3] . Pos
	BlkOpn	
	BlkCls	
	CBOpCap	

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>XCBR4* (WW_XCBR2)</b>		
	Mod	
	Beh	
	Health	
	NamPlt	
	Loc	
	OpCnt	
	Pos	SG[4] . Pos
	BlkOpn	
	BlkCls	
	CBOpCap	



Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>XCBR5* (WW_XCBR2)</b>		
	Mod	
	Beh	
	Health	
	NamPlt	
	Loc	
	OpCnt	
	Pos	SG[5] . Pos
	BlkOpn	
	BlkCls	
	CBOpCap	

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>XCBR6* (WW_XCBR2)</b>		
	Mod	
	Beh	
	Health	
	NamPlt	
	Loc	
	OpCnt	
	Pos	SG[6] . Pos
	BlkOpn	
	BlkCls	
	CBOpCap	

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>XSWI1* (WW_XSWI1)</b>		
	Mod	
	Beh	
	Health	
	NamPlt	
	Loc	
	OpCnt	
	Pos	SG[1] . Pos
	BlkOpn	
	BlkCls	
	SwTyp	
	SwOpCap	

4 Appendix  
4.1 Register Maps

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>XSWI2* (WW_XSWI1)</b>		
	Mod	
	Beh	
	Health	
	NamPlt	
	Loc	
	OpCnt	
	Pos	SG[2] . Pos
	BlkOpn	
	BlkCls	
	SwTyp	
	SwOpCap	

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>XSWI3* (WW_XSWI1)</b>		
	Mod	
	Beh	
	Health	
	NamPlt	
	Loc	
	OpCnt	
	Pos	SG[3] . Pos
	BlkOpn	
	BlkCls	
	SwTyp	
	SwOpCap	

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>XSWI4* (WW_XSWI1)</b>		
	Mod	
	Beh	
	Health	
	NamPlt	
	Loc	
	OpCnt	
	Pos	SG[4] . Pos
	BlkOpn	
	BlkCls	

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>XSWI4* (WW_XSWI1)</b>		
	SwTyp	
	SwOpCap	

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>XSWI5* (WW_XSWI1)</b>		
	Mod	
	Beh	
	Health	
	NamPlt	
	Loc	
	OpCnt	
	Pos	SG[5] . Pos
	BlkOpn	
	BlkCls	
	SwTyp	
	SwOpCap	

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>XSWI6* (WW_XSWI1)</b>		
	Mod	
	Beh	
	Health	
	NamPlt	
	Loc	
	OpCnt	
	Pos	SG[6] . Pos
	BlkOpn	
	BlkCls	
	SwTyp	
	SwOpCap	

***LDevice::DR***

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>LLN0 (WW_LLNOREC)</b>		
	Mod	
	Beh	
	Health	

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>LLN0 (WW_LLNOREC)</b>		
	NamPlt	

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>LPHD1 (WW_LPHDREC)</b>		
	PhyNam	
	PhyHealth	
	Proxy	

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>RDRE1 (WW_RDRE1)</b>		
	Mod	
	Beh	
	Health	
	NamPlt	
	RcdMade	Disturb rec . recording
	FltNum	
	GriFltNum	
	RcdStr	Disturb rec . recording

***LDevice::EXT***

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>COU GGIO1 (WW_GGIO4)</b>		
	Mod	
	Beh	
	Health	
	NamPlt	
	Ind1	IEC 61850 . COUTGGIO1.Ind1.stVal-I
	Ind2	IEC 61850 . COUTGGIO1.Ind2.stVal-I
	Ind3	IEC 61850 . COUTGGIO1.Ind3.stVal-I
	Ind4	IEC 61850 . COUTGGIO1.Ind4.stVal-I
	Ind5	IEC 61850 . COUTGGIO1.Ind5.stVal-I
	Ind6	IEC 61850 . COUTGGIO1.Ind6.stVal-I
	Ind7	IEC 61850 . COUTGGIO1.Ind7.stVal-I
	Ind8	IEC 61850 . COUTGGIO1.Ind8.stVal-I
	Ind9	IEC 61850 . COUTGGIO1.Ind9.stVal-I
	Ind10	IEC 61850 . COUTGGIO1.Ind10.stVal-I
	Ind11	IEC 61850 . COUTGGIO1.Ind11.stVal-I

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>COUFGGIO1 (WW_GGIO4)</b>		
	Ind12	IEC 61850 . COUFGGIO1.Ind12.stVal-I
	Ind13	IEC 61850 . COUFGGIO1.Ind13.stVal-I
	Ind14	IEC 61850 . COUFGGIO1.Ind14.stVal-I
	Ind15	IEC 61850 . COUFGGIO1.Ind15.stVal-I
	Ind16	IEC 61850 . COUFGGIO1.Ind16.stVal-I
	Ind17	IEC 61850 . COUFGGIO1.Ind17.stVal-I
	Ind18	IEC 61850 . COUFGGIO1.Ind18.stVal-I
	Ind19	IEC 61850 . COUFGGIO1.Ind19.stVal-I
	Ind20	IEC 61850 . COUFGGIO1.Ind20.stVal-I
	Ind21	IEC 61850 . COUFGGIO1.Ind21.stVal-I
	Ind22	IEC 61850 . COUFGGIO1.Ind22.stVal-I
	Ind23	IEC 61850 . COUFGGIO1.Ind23.stVal-I
	Ind24	IEC 61850 . COUFGGIO1.Ind24.stVal-I
	Ind25	IEC 61850 . COUFGGIO1.Ind25.stVal-I
	Ind26	IEC 61850 . COUFGGIO1.Ind26.stVal-I
	Ind27	IEC 61850 . COUFGGIO1.Ind27.stVal-I
	Ind28	IEC 61850 . COUFGGIO1.Ind28.stVal-I
	Ind29	IEC 61850 . COUFGGIO1.Ind29.stVal-I
	Ind30	IEC 61850 . COUFGGIO1.Ind30.stVal-I
	Ind31	IEC 61850 . COUFGGIO1.Ind31.stVal-I
	Ind32	IEC 61850 . COUFGGIO1.Ind32.stVal-I

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>COUFGGIO2 (WW_GGIO4)</b>		
	Mod	
	Beh	
	Health	
	NamPlt	
	Ind1	IEC 61850 . COUFGGIO2.Ind1.stVal-I
	Ind2	IEC 61850 . COUFGGIO2.Ind2.stVal-I
	Ind3	IEC 61850 . COUFGGIO2.Ind3.stVal-I
	Ind4	IEC 61850 . COUFGGIO2.Ind4.stVal-I
	Ind5	IEC 61850 . COUFGGIO2.Ind5.stVal-I
	Ind6	IEC 61850 . COUFGGIO2.Ind6.stVal-I
	Ind7	IEC 61850 . COUFGGIO2.Ind7.stVal-I
	Ind8	IEC 61850 . COUFGGIO2.Ind8.stVal-I
	Ind9	IEC 61850 . COUFGGIO2.Ind9.stVal-I

4 Appendix  
 4.1 Register Maps

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>COUFGGIO2 (WW_GGIO4)</b>		
	Ind10	IEC 61850 . COUFGGIO2.Ind10.stVal-I
	Ind11	IEC 61850 . COUFGGIO2.Ind11.stVal-I
	Ind12	IEC 61850 . COUFGGIO2.Ind12.stVal-I
	Ind13	IEC 61850 . COUFGGIO2.Ind13.stVal-I
	Ind14	IEC 61850 . COUFGGIO2.Ind14.stVal-I
	Ind15	IEC 61850 . COUFGGIO2.Ind15.stVal-I
	Ind16	IEC 61850 . COUFGGIO2.Ind16.stVal-I
	Ind17	IEC 61850 . COUFGGIO2.Ind17.stVal-I
	Ind18	IEC 61850 . COUFGGIO2.Ind18.stVal-I
	Ind19	IEC 61850 . COUFGGIO2.Ind19.stVal-I
	Ind20	IEC 61850 . COUFGGIO2.Ind20.stVal-I
	Ind21	IEC 61850 . COUFGGIO2.Ind21.stVal-I
	Ind22	IEC 61850 . COUFGGIO2.Ind22.stVal-I
	Ind23	IEC 61850 . COUFGGIO2.Ind23.stVal-I
	Ind24	IEC 61850 . COUFGGIO2.Ind24.stVal-I
	Ind25	IEC 61850 . COUFGGIO2.Ind25.stVal-I
	Ind26	IEC 61850 . COUFGGIO2.Ind26.stVal-I
	Ind27	IEC 61850 . COUFGGIO2.Ind27.stVal-I
	Ind28	IEC 61850 . COUFGGIO2.Ind28.stVal-I
	Ind29	IEC 61850 . COUFGGIO2.Ind29.stVal-I
	Ind30	IEC 61850 . COUFGGIO2.Ind30.stVal-I
	Ind31	IEC 61850 . COUFGGIO2.Ind31.stVal-I
	Ind32	IEC 61850 . COUFGGIO2.Ind32.stVal-I

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>CTLGGIO1 (WW_GGIO14)</b>		
	Mod	
	Beh	
	Health	
	NamPlt	
	SPCSO1	
	SPCSO2	
	SPCSO3	
	SPCSO4	
	SPCSO5	
	SPCSO6	
	SPCSO7	

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>CTLGGIO1 (WW_GGIO14)</b>		
	SPCSO8	
	SPCSO9	
	SPCSO10	
	SPCSO11	
	SPCSO12	
	SPCSO13	
	SPCSO14	
	SPCSO15	
	SPCSO16	
	SPCSO17	
	SPCSO18	
	SPCSO19	
	SPCSO20	
	SPCSO21	
	SPCSO22	
	SPCSO23	
	SPCSO24	
	SPCSO25	
	SPCSO26	
	SPCSO27	
	SPCSO28	
	SPCSO29	
	SPCSO30	
	SPCSO31	
	SPCSO32	

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>EPGAPC1 (WW_GAPC1)</b>		
	Mod	Intertripping . active Intertripping . Blo TripCmd Intertripping . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	Intertripping . Alarm
	Op	Intertripping . Trip

4 Appendix  
4.1 Register Maps

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>EPGAPC10 (WW_GAPC1)</b>		
	Mod	Ext Temp Superv[3] . active Ext Temp Superv[3] . Blo TripCmd Ext Temp Superv[3] . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	Ext Temp Superv[3] . Alarm
	Op	Ext Temp Superv[3] . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>EPGAPC2 (WW_GAPC1)</b>		
	Mod	Exp[1] . active Exp[1] . Blo TripCmd Exp[1] . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	Exp[1] . Alarm
	Op	Exp[1] . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>EPGAPC3 (WW_GAPC1)</b>		
	Mod	Exp[2] . active Exp[2] . Blo TripCmd Exp[2] . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	Exp[2] . Alarm
	Op	Exp[2] . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>EPGAPC4 (WW_GAPC1)</b>		
	Mod	Exp[3] . active Exp[3] . Blo TripCmd Exp[3] . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	Exp[3] . Alarm
	Op	Exp[3] . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>EPGAPC5 (WW_GAPC1)</b>		
	Mod	Exp[4] . active Exp[4] . Blo TripCmd Exp[4] . ExBlo TripCmd



Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>EPGAPC5 (WW_GAPC1)</b>		
	Beh	
	Health	
	NamPlt	
	Str	ExpP[4] . Alarm
	Op	ExpP[4] . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>EPGAPC6 (WW_GAPC1)</b>		
	Mod	Ext Sudd Press . active Ext Sudd Press . Blo TripCmd Ext Sudd Press . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	Ext Sudd Press . Alarm
	Op	Ext Sudd Press . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>EPGAPC7 (WW_GAPC1)</b>		
	Mod	Ext Oil Temp . active Ext Oil Temp . Blo TripCmd Ext Oil Temp . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	Ext Oil Temp . Alarm
	Op	Ext Oil Temp . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>EPGAPC8 (WW_GAPC1)</b>		
	Mod	Ext Temp Superv[1] . active Ext Temp Superv[1] . Blo TripCmd Ext Temp Superv[1] . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	Ext Temp Superv[1] . Alarm
	Op	Ext Temp Superv[1] . Trip

4 Appendix  
 4.1 Register Maps

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>EPGAPC9 (WW_GAPC1)</b>		
	Mod	Ext Temp Superv[2] . active Ext Temp Superv[2] . Blo TripCmd Ext Temp Superv[2] . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	Ext Temp Superv[2] . Alarm
	Op	Ext Temp Superv[2] . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>GOSINGGIO1 (WW_GGIO11)</b>		
	Mod	
	Beh	
	Health	
	NamPlt	
	Ind1	
	Ind2	
	Ind3	
	Ind4	
	Ind5	
	Ind6	
	Ind7	
	Ind8	
	Ind9	
	Ind10	
	Ind11	
	Ind12	
	Ind13	
	Ind14	
	Ind15	
	Ind16	
	Ind17	
	Ind18	
	Ind19	
	Ind20	
	Ind21	
	Ind22	
	Ind23	

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>GOSINGGIO1 (WW_GGIO11)</b>		
	Ind24	
	Ind25	
	Ind26	
	Ind27	
	Ind28	
	Ind29	
	Ind30	
	Ind31	
	Ind32	

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>GOSINGGIO2 (WW_GGIO10)</b>		
	Mod	
	Beh	
	Health	
	NamPlt	
	Ind1	
	Ind2	
	Ind3	
	Ind4	
	Ind5	
	Ind6	
	Ind7	
	Ind8	
	Ind9	
	Ind10	
	Ind11	
	Ind12	
	Ind13	
	Ind14	
	Ind15	
	Ind16	
	Ind17	
	Ind18	
	Ind19	
	Ind20	
	Ind21	

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>GOSINGGIO2 (WW_GGIO10)</b>		
	Ind22	
	Ind23	
	Ind24	
	Ind25	
	Ind26	
	Ind27	
	Ind28	
	Ind29	
	Ind30	
	Ind31	
	Ind32	

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>LLN0 (WW_LLNSYS)</b>		
	Mod	
	Beh	
	Health	
	NamPlt	

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>LPHD1 (WW_LPHDSYS)</b>		
	PhyNam	
	PhyHealth	
	Proxy	

***LDevice::MEAS***

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>CMMXU1 (WW_MMXU7)</b>		
	Mod	
	Beh	
	Health	
	NamPlt	
	A	CT Ntrl . IL1 RMS CT Ntrl . phi IL1 CT Ntrl . IL2 RMS CT Ntrl . phi IL2 CT Ntrl . IL3 RMS CT Ntrl . phi IL3 CT Ntrl . IG meas RMS CT Ntrl . phi IG meas CT Ntrl . IG calc RMS CT Ntrl . phi IG calc

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>CMMXU2 (WW_MMXU7)</b>		
	Mod	
	Beh	
	Health	
	NamPlt	
	A	CT Mains . IL1 RMS CT Mains . phi IL1 CT Mains . IL2 RMS CT Mains . phi IL2 CT Mains . IL3 RMS CT Mains . phi IL3 CT Mains . IG meas RMS CT Mains . phi IG meas CT Mains . IG calc RMS CT Mains . phi IG calc

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>CMSTA1 (WW_MSTA1)</b>		
	Mod	
	Beh	
	Health	
	NamPlt	
	AvAPhsA	CT Ntrl . IL1 avg
	AvAPhsB	CT Ntrl . IL2 avg
	AvAPhsC	CT Ntrl . IL3 avg
	MaxAPhsA	CT Ntrl . IL1 max
	MaxAPhsB	CT Ntrl . IL2 max
	MaxAPhsC	CT Ntrl . IL3 max
	MinAPhsA	CT Ntrl . IL1 min
	MinAPhsB	CT Ntrl . IL2 min
	MinAPhsC	CT Ntrl . IL3 min

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>CMSTA2 (WW_MSTA1)</b>		
	Mod	
	Beh	
	Health	
	NamPlt	
	AvAPhsA	CT Mains . IL1 avg
	AvAPhsB	CT Mains . IL2 avg
	AvAPhsC	CT Mains . IL3 avg
	MaxAPhsA	CT Mains . IL1 max
	MaxAPhsB	CT Mains . IL2 max
	MaxAPhsC	CT Mains . IL3 max
	MinAPhsA	CT Mains . IL1 min

4 Appendix  
4.1 Register Maps

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>CMSTA2 (WW_MSTA1)</b>		
	MinAPhSB	CT Mains . IL2 min
	MinAPhSC	CT Mains . IL3 min

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>ECMMTR1 (WW_MMTR1)</b>		
	Mod	
	Beh	
	Health	
	NamPlt	
	SupWh	PQSCr . Wp+
	DmdWh	PQSCr . Wp-
	SupVARh	PQSCr . Wq+
	DmdVARh	PQSCr . Wq-
	TotWh	PQSCr . Wp Net
	TotVARh	PQSCr . Wq Net
	TotVAh	PQSCr . Ws Net

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>LLNO (WW_LLNO MEA)</b>		
	Mod	
	Beh	
	Health	
	NamPlt	

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>LPHD1 (WW_LPHD MEA)</b>		
	PhyNam	
	PhyHealth	
	Proxy	

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PMMXU1 (WW_MMXU3)</b>		
	Mod	
	Beh	
	Health	
	NamPlt	
	TotW	PQSCr . P RMS

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PMMXU1 (WW_MMXU3)</b>		
	TotVAr	PQSCr . Q
	TotVA	PQSCr . S RMS
	TotPF	PQSCr . cos phi RMS

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PMSTA1 (WW_MSTA3)</b>		
	Mod	
	Beh	
	Health	
	NamPlt	
	AvVA	PQSCr . S avg (Demand)
	MaxVA	PQSCr . S max
	MinVA	PQSCr . S min
	AvW	PQSCr . P avg
	MaxW	PQSCr . P max
	MinW	PQSCr . P min
	AvVAr	PQSCr . Q avg (Demand)
	MaxVAr	PQSCr . Q max
	MinVAr	PQSCr . Q min

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>VMMXU1 (WW_MMXU6)</b>		
	Mod	
	Beh	
	Health	
	NamPlt	
	PPV	VT . VL12 RMS VT . phi VL12 VT . VL23 RMS VT . phi VL23 VT . VL31 RMS VT . phi VL31
	PhV	VT . VL1 RMS VT . phi VL1 VT . VL2 RMS VT . phi VL2 VT . VL3 RMS VT . phi VL3 VT . VX meas RMS VT . phi VX meas VT . VG calc RMS VT . phi VG calc
	Hz	VT . f

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>VMSTA1 (WW_MSTA2)</b>		
	Mod	
	Beh	
	Health	
	NamPlt	

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>VMSTA1 (WW_MSTA2)</b>		
	AvVPhsAB	VT . VL12 avg
	AvVPhsBC	VT . VL23 avg
	AvVPhsCA	VT . VL31 avg
	MaxVPhsAB	VT . VL12 max
	MaxVPhsBC	VT . VL23 max
	MaxVPhsCA	VT . VL31 max
	MinVPhsAB	VT . VL12 min
	MinVPhsBC	VT . VL23 min
	MinVPhsCA	VT . VL31 min
	AvVPhsA	VT . VL1 avg
	AvVPhsB	VT . VL2 avg
	AvVPhsC	VT . VL3 avg
	MaxVPhsA	VT . VL1 max
	MaxVPhsB	VT . VL2 max
	MaxVPhsC	VT . VL3 max
	MinVPhsA	VT . VL1 min
	MinVPhsB	VT . VL2 min
	MinVPhsC	VT . VL3 min

***LDevice::PROT***

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>BPDIS1 (WW_PD1S1)</b>		
	Mod	Z[1] - 21P . active Z[1] - 21P . ExBlo Z[1] - 21P . Blo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	Z[1] - 21P . Alarm
	Op	Z[1] - 21P . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>BPDIS2 (WW_PD1S1)</b>		
	Mod	Z[2] - 21P . active Z[2] - 21P . ExBlo Z[2] - 21P . Blo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	Z[2] - 21P . Alarm



Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>BPDIS2 (WW_PDIS1)</b>		
	Op	Z[2] - 21P . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>GFPTOC1 (WW_PTOC3)</b>		
	Mod	IG[1] - 50N, 51N . active IG[1] - 50N, 51N . Blo TripCmd IG[1] - 50N, 51N . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	IG[1] - 50N, 51N . Alarm
	Op	IG[1] - 50N, 51N . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>GFPTOC2 (WW_PTOC3)</b>		
	Mod	IG[2] - 50N, 51N . active IG[2] - 50N, 51N . Blo TripCmd IG[2] - 50N, 51N . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	IG[2] - 50N, 51N . Alarm
	Op	IG[2] - 50N, 51N . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>GFPTOC3 (WW_PTOC3)</b>		
	Mod	IG[3] - 50N, 51N . active IG[3] - 50N, 51N . Blo TripCmd IG[3] - 50N, 51N . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	IG[3] - 50N, 51N . Alarm
	Op	IG[3] - 50N, 51N . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>GFPTOC4 (WW_PTOC3)</b>		
	Mod	IG[4] - 50N, 51N . active IG[4] - 50N, 51N . Blo TripCmd IG[4] - 50N, 51N . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	

4 Appendix  
4.1 Register Maps

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>GFPTOC4 (WW_PTOC3)</b>		
	Str	IG[4] - 50N, 51N . Alarm
	Op	IG[4] - 50N, 51N . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>GPDIF1 (WW_PDIF3)</b>		
	Mod	IdGH[1] - 87N . active IdGH[1] - 87N . Blo TripCmd IdGH[1] - 87N . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	IdGH[1] - 87N . Alarm
	Op	IdGH[1] - 87N . TripCmd

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>GPDIF2 (WW_PDIF3)</b>		
	Mod	IdGH[2] - 87N . active IdGH[2] - 87N . Blo TripCmd IdGH[2] - 87N . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	IdGH[2] - 87N . Alarm
	Op	IdGH[2] - 87N . TripCmd

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>HRGPDIF1 (WW_PDIF4)</b>		
	Mod	IdH - 87 . active IdH - 87 . Blo TripCmd IdH - 87 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	IdH - 87 . Alarm
	Op	IdH - 87 . TripCmd

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>HSPPDIF1 (WW_PDIF2)</b>		
	Mod	IdG[1] - 87N . active IdG[1] - 87N . Blo TripCmd IdG[1] - 87N . ExBlo TripCmd
	Beh	
	Health	

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>HSPPDIF1 (WW_PDIF2)</b>		
	NamPlt	
	Str	IdG[1] - 87N . Alarm
	Op	IdG[1] - 87N . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>HSPPDIF2 (WW_PDIF2)</b>		
	Mod	IdG[2] - 87N . active IdG[2] - 87N . Blo TripCmd IdG[2] - 87N . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	IdG[2] - 87N . Alarm
	Op	IdG[2] - 87N . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>IE5027PIOC1 (WW_PIOC1)</b>		
	Mod	InEn - 50/27 . active InEn - 50/27 . Blo TripCmd InEn - 50/27 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	InEn - 50/27 . Alarm
	Op	InEn - 50/27 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>IHMI1 (WW_IHMI1)</b>		
	Mod	
	Beh	
	Health	
	NamPlt	

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>INRPHAR1 (WW_PHAR1)</b>		
	Mod	IH2 . active
	Beh	
	Health	
	NamPlt	
	Str	IH2 . 3-ph Blo

4 Appendix  
4.1 Register Maps

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>LLNO (WW_LLNOPRO)</b>		
	Mod	
	Beh	
	Health	
	NamPlt	

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>LPHD1 (WW_LPHDPRO)</b>		
	PhyNam	
	PhyHealth	
	Proxy	

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>LoEPDUP1* (WW_PDUP2)</b>		
	Mod	LoE-Z1[1] - 40 . active LoE-Z1[1] - 40 . Blo TripCmd LoE-Z1[1] - 40 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	LoE-Z1[1] - 40 . Alarm
	Op	LoE-Z1[1] - 40 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>LoEPDUP2* (WW_PDUP2)</b>		
	Mod	LoE-Z2[1] - 40 . active LoE-Z2[1] - 40 . Blo TripCmd LoE-Z2[1] - 40 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	LoE-Z2[1] - 40 . Alarm
	Op	LoE-Z2[1] - 40 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>LoEPDUP3* (WW_PDUP2)</b>		
	Mod	LoE-Z1[2] - 40 . active LoE-Z1[2] - 40 . Blo TripCmd LoE-Z1[2] - 40 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	LoE-Z1[2] - 40 . Alarm

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>LoEPDUP3* (WW_PDUP2)</b>		
	Op	LoE-Z1[2] - 40 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>LoEPDUP4* (WW_PDUP2)</b>		
	Mod	LoE-Z2[2] - 40 . active LoE-Z2[2] - 40 . Blo TripCmd LoE-Z2[2] - 40 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	LoE-Z2[2] - 40 . Alarm
	Op	LoE-Z2[2] - 40 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>OEPVPH1* (WW_PVPH1)</b>		
	Mod	V/f>[1] - 24 . active V/f>[1] - 24 . Blo TripCmd V/f>[1] - 24 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V/f>[1] - 24 . Alarm
	Op	V/f>[1] - 24 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>OEPVPH2* (WW_PVPH1)</b>		
	Mod	V/f>[2] - 24 . active V/f>[2] - 24 . Blo TripCmd V/f>[2] - 24 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V/f>[2] - 24 . Alarm
	Op	V/f>[2] - 24 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>OSTPPAM1* (WW_PPAM2)</b>		
	Mod	OST - 78 . active OST - 78 . ExBlo OST - 78 . Int.blocked
	Beh	
	Health	
	NamPlt	
	Str	OST - 78 . Start

4 Appendix  
4.1 Register Maps

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>OSTPPAM1* (WW_PPAM2)</b>		
	Op	OST - 78 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>OSTPPAM2* (WW_PPAM2)</b>		
	Mod	PSB - 68 . active PSB - 68 . ExBlo PSB - 68 . Int.blocked
	Beh	
	Health	
	NamPlt	
	Str	PSB - 68 . Start
	Op	PSB - 68 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PDOP1* (WW_PDOP1)</b>		
	Mod	P[1] - 32R . active P[1] - 32R . Blo TripCmd P[1] - 32R . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	P[1] - 32R . Alarm
	Op	P[1] - 32R . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PDOP2* (WW_PDOP1)</b>		
	Mod	Q - 32 . active Q - 32 . Blo TripCmd Q - 32 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	Q - 32 . Alarm
	Op	Q - 32 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PDOP3* (WW_PDOP1)</b>		
	Mod	PQS[1] - 32, 37 . active PQS[1] - 32, 37 . Blo TripCmd PQS[1] - 32, 37 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	PQS[1] - 32, 37 . Alarm

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PDOP3* (WW_PDOP1)</b>		
	Op	PQS[1] - 32, 37 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PDOP4* (WW_PDOP1)</b>		
	Mod	PQS[2] - 32, 37 . active PQS[2] - 32, 37 . Blo TripCmd PQS[2] - 32, 37 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	PQS[2] - 32, 37 . Alarm
	Op	PQS[2] - 32, 37 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PDOP5* (WW_PDOP1)</b>		
	Mod	PQS[3] - 32, 37 . active PQS[3] - 32, 37 . Blo TripCmd PQS[3] - 32, 37 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	PQS[3] - 32, 37 . Alarm
	Op	PQS[3] - 32, 37 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PDOP6* (WW_PDOP1)</b>		
	Mod	PQS[4] - 32, 37 . active PQS[4] - 32, 37 . Blo TripCmd PQS[4] - 32, 37 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	PQS[4] - 32, 37 . Alarm
	Op	PQS[4] - 32, 37 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PDOP7* (WW_PDOP1)</b>		
	Mod	PQS[5] - 32, 37 . active PQS[5] - 32, 37 . Blo TripCmd PQS[5] - 32, 37 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	

4 Appendix  
4.1 Register Maps

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PDOP7* (WW_PDOP1)</b>		
	Str	PQS[5] - 32, 37 . Alarm
	Op	PQS[5] - 32, 37 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PDOP8* (WW_PDOP1)</b>		
	Mod	PQS[6] - 32, 37 . active PQS[6] - 32, 37 . Blo TripCmd PQS[6] - 32, 37 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	PQS[6] - 32, 37 . Alarm
	Op	PQS[6] - 32, 37 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PDUP1* (WW_PDUP1)</b>		
	Mod	P[1] - 32R . active P[1] - 32R . Blo TripCmd P[1] - 32R . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	P[1] - 32R . Alarm
	Op	P[1] - 32R . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PDUP2* (WW_PDUP1)</b>		
	Mod	Q - 32 . active Q - 32 . Blo TripCmd Q - 32 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	Q - 32 . Alarm
	Op	Q - 32 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PDUP3* (WW_PDUP1)</b>		
	Mod	PQS[1] - 32, 37 . active PQS[1] - 32, 37 . Blo TripCmd PQS[1] - 32, 37 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	



Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PDUP3* (WW_PDUP1)</b>		
	Str	PQS[1] - 32, 37 . Alarm
	Op	PQS[1] - 32, 37 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PDUP4* (WW_PDUP1)</b>		
	Mod	PQS[2] - 32, 37 . active PQS[2] - 32, 37 . Blo TripCmd PQS[2] - 32, 37 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	PQS[2] - 32, 37 . Alarm
	Op	PQS[2] - 32, 37 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PDUP5* (WW_PDUP1)</b>		
	Mod	PQS[3] - 32, 37 . active PQS[3] - 32, 37 . Blo TripCmd PQS[3] - 32, 37 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	PQS[3] - 32, 37 . Alarm
	Op	PQS[3] - 32, 37 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PDUP6* (WW_PDUP1)</b>		
	Mod	PQS[4] - 32, 37 . active PQS[4] - 32, 37 . Blo TripCmd PQS[4] - 32, 37 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	PQS[4] - 32, 37 . Alarm
	Op	PQS[4] - 32, 37 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PDUP7* (WW_PDUP1)</b>		
	Mod	PQS[5] - 32, 37 . active PQS[5] - 32, 37 . Blo TripCmd PQS[5] - 32, 37 . ExBlo TripCmd
	Beh	
	Health	

4 Appendix  
4.1 Register Maps

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PDUP7* (WW_PDUP1)</b>		
	NamPlt	
	Str	PQS[5] - 32, 37 . Alarm
	Op	PQS[5] - 32, 37 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PDUP8* (WW_PDUP1)</b>		
	Mod	PQS[6] - 32, 37 . active PQS[6] - 32, 37 . Blo TripCmd PQS[6] - 32, 37 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	PQS[6] - 32, 37 . Alarm
	Op	PQS[6] - 32, 37 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PFRC1* (WW_PFRC1)</b>		
	Mod	df/dt - 81R . active df/dt - 81R . Blo TripCmd df/dt - 81R . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	df/dt - 81R . Alarm
	Op	df/dt - 81R . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PFRC2* (WW_PFRC1)</b>		
	Mod	delta phi - 78V . active delta phi - 78V . Blo TripCmd delta phi - 78V . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	delta phi - 78V . Alarm
	Op	delta phi - 78V . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PFRC3* (WW_PFRC1)</b>		
	Mod	f[1] - 81 . active f[1] - 81 . Blo TripCmd f[1] - 81 . ExBlo TripCmd
	Beh	

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PFRC3* (WW_PFRC1)</b>		
	Health	
	NamPlt	
	Str	f[1] - 81 . Alarm
	Op	f[1] - 81 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PFRC4* (WW_PFRC1)</b>		
	Mod	f[2] - 81 . active f[2] - 81 . Blo TripCmd f[2] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[2] - 81 . Alarm
	Op	f[2] - 81 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PFRC5* (WW_PFRC1)</b>		
	Mod	f[3] - 81 . active f[3] - 81 . Blo TripCmd f[3] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[3] - 81 . Alarm
	Op	f[3] - 81 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PFRC6* (WW_PFRC1)</b>		
	Mod	f[4] - 81 . active f[4] - 81 . Blo TripCmd f[4] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[4] - 81 . Alarm
	Op	f[4] - 81 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PFRC7* (WW_PFRC1)</b>		
	Mod	f[5] - 81 . active f[5] - 81 . Blo TripCmd f[5] - 81 . ExBlo TripCmd

4 Appendix  
4.1 Register Maps

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PFRC7* (WW_PFRC1)</b>		
	Beh	
	Health	
	NamPlt	
	Str	f[5] - 81 . Alarm
	Op	f[5] - 81 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PFRC8* (WW_PFRC1)</b>		
	Mod	f[6] - 81 . active f[6] - 81 . Blo TripCmd f[6] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[6] - 81 . Alarm
	Op	f[6] - 81 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PPAM1* (WW_PPAM1)</b>		
	Mod	df/dt - 81R . active df/dt - 81R . Blo TripCmd df/dt - 81R . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	df/dt - 81R . Alarm
	Op	df/dt - 81R . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PPAM2* (WW_PPAM1)</b>		
	Mod	delta phi - 78V . active delta phi - 78V . Blo TripCmd delta phi - 78V . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	delta phi - 78V . Alarm
	Op	delta phi - 78V . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PPAM3* (WW_PPAM1)</b>		
	Mod	f[1] - 81 . active f[1] - 81 . Blo TripCmd f[1] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[1] - 81 . Alarm
	Op	f[1] - 81 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PPAM4* (WW_PPAM1)</b>		
	Mod	f[2] - 81 . active f[2] - 81 . Blo TripCmd f[2] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[2] - 81 . Alarm
	Op	f[2] - 81 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PPAM5* (WW_PPAM1)</b>		
	Mod	f[3] - 81 . active f[3] - 81 . Blo TripCmd f[3] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[3] - 81 . Alarm
	Op	f[3] - 81 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PPAM6* (WW_PPAM1)</b>		
	Mod	f[4] - 81 . active f[4] - 81 . Blo TripCmd f[4] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[4] - 81 . Alarm
	Op	f[4] - 81 . Trip

4 Appendix  
4.1 Register Maps

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PPAM7* (WW_PPAM1)</b>		
	Mod	f[5] - 81 . active f[5] - 81 . Blo TripCmd f[5] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[5] - 81 . Alarm
	Op	f[5] - 81 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PPAM8* (WW_PPAM1)</b>		
	Mod	f[6] - 81 . active f[6] - 81 . Blo TripCmd f[6] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[6] - 81 . Alarm
	Op	f[6] - 81 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PPDIF1 (WW_PDIF1)</b>		
	Mod	Id - 87 . active Id - 87 . Blo TripCmd Id - 87 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	Id - 87 . Alarm
	Op	Id - 87 . TripCmd

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PSBRPSB1* (WW_RPSB1)</b>		
	Mod	OST - 78 . active OST - 78 . ExBlo OST - 78 . Int.blocked
	Beh	
	Health	
	NamPlt	
	Str	OST - 78 . Swinging
	BlkZn	OST - 78 . Start

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PSBRPSB2* (WW_RPSB1)</b>		
	Mod	PSB - 68 . active PSB - 68 . ExBlo PSB - 68 . Int.blocked
	Beh	
	Health	
	NamPlt	
	Str	PSB - 68 . Swinging
	BlkZn	PSB - 68 . Start

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PSDE1 (WW_PSDE1)</b>		
	Mod	VT . IG meas dir wattm
	Beh	
	Health	
	NamPlt	
	Str	

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PSDE2 (WW_PSDE2)</b>		
	Mod	VT . IG calc dir wattm
	Beh	
	Health	
	NamPlt	
	Str	

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PSOF1 (WW_PSOF1)</b>		
	Mod	SOTF . active SOTF . ExBlo SOTF . Ex rev Interl
	Beh	
	Health	
	NamPlt	
	Str	SOTF . enabled

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PTOC1 (WW_PTOC1)</b>		
	Mod	I[1] - 50, 51 . active I[1] - 50, 51 . Blo TripCmd I[1] - 50, 51 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	

4 Appendix  
4.1 Register Maps

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PTOC1 (WW_PTOC1)</b>		
	Str	I[1] - 50, 51 . Alarm
	Op	I[1] - 50, 51 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PTOC2 (WW_PTOC1)</b>		
	Mod	I[2] - 50, 51 . active I[2] - 50, 51 . Blo TripCmd I[2] - 50, 51 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	I[2] - 50, 51 . Alarm
	Op	I[2] - 50, 51 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PTOC3 (WW_PTOC1)</b>		
	Mod	I[3] - 50, 51 . active I[3] - 50, 51 . Blo TripCmd I[3] - 50, 51 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	I[3] - 50, 51 . Alarm
	Op	I[3] - 50, 51 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PTOC4 (WW_PTOC1)</b>		
	Mod	I[4] - 50, 51 . active I[4] - 50, 51 . Blo TripCmd I[4] - 50, 51 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	I[4] - 50, 51 . Alarm
	Op	I[4] - 50, 51 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PTOC5 (WW_PTOC1)</b>		
	Mod	I[5] - 50, 51 . active I[5] - 50, 51 . Blo TripCmd I[5] - 50, 51 . ExBlo TripCmd
	Beh	
	Health	



Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PTOC5 (WW_PTOC1)</b>		
	NamPlt	
	Str	I[5] - 50, 51 . Alarm
	Op	I[5] - 50, 51 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PTOC6 (WW_PTOC1)</b>		
	Mod	I[6] - 50, 51 . active I[6] - 50, 51 . Blo TripCmd I[6] - 50, 51 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	I[6] - 50, 51 . Alarm
	Op	I[6] - 50, 51 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PTOF1* (WW_PTOF1)</b>		
	Mod	df/dt - 81R . active df/dt - 81R . Blo TripCmd df/dt - 81R . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	df/dt - 81R . Alarm
	Op	df/dt - 81R . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PTOF2* (WW_PTOF1)</b>		
	Mod	delta phi - 78V . active delta phi - 78V . Blo TripCmd delta phi - 78V . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	delta phi - 78V . Alarm
	Op	delta phi - 78V . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PTOF3* (WW_PTOF1)</b>		
	Mod	f[1] - 81 . active f[1] - 81 . Blo TripCmd f[1] - 81 . ExBlo TripCmd
	Beh	

4 Appendix  
4.1 Register Maps

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PTOF3* (WW_PTOF1)</b>		
	Health	
	NamPlt	
	Str	f[1] - 81 . Alarm
	Op	f[1] - 81 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PTOF4* (WW_PTOF1)</b>		
	Mod	f[2] - 81 . active f[2] - 81 . Blo TripCmd f[2] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[2] - 81 . Alarm
	Op	f[2] - 81 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PTOF5* (WW_PTOF1)</b>		
	Mod	f[3] - 81 . active f[3] - 81 . Blo TripCmd f[3] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[3] - 81 . Alarm
	Op	f[3] - 81 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PTOF6* (WW_PTOF1)</b>		
	Mod	f[4] - 81 . active f[4] - 81 . Blo TripCmd f[4] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[4] - 81 . Alarm
	Op	f[4] - 81 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PTOF7* (WW_PTOF1)</b>		
	Mod	f[5] - 81 . active f[5] - 81 . Blo TripCmd f[5] - 81 . ExBlo TripCmd

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PTOF7* (WW_PTOF1)</b>		
	Beh	
	Health	
	NamPlt	
	Str	f[5] - 81 . Alarm
	Op	f[5] - 81 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PTOF8* (WW_PTOF1)</b>		
	Mod	f[6] - 81 . active f[6] - 81 . Blo TripCmd f[6] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[6] - 81 . Alarm
	Op	f[6] - 81 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PTOV1* (WW_PTOV2)</b>		
	Mod	V[1] - 27, 59 . active V[1] - 27, 59 . Blo TripCmd V[1] - 27, 59 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V[1] - 27, 59 . Alarm
	Op	V[1] - 27, 59 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PTOV2* (WW_PTOV2)</b>		
	Mod	V[2] - 27, 59 . active V[2] - 27, 59 . Blo TripCmd V[2] - 27, 59 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V[2] - 27, 59 . Alarm
	Op	V[2] - 27, 59 . Trip

4 Appendix  
4.1 Register Maps

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PTOV3* (WW_PTOV2)</b>		
	Mod	V[3] - 27, 59 . active V[3] - 27, 59 . Blo TripCmd V[3] - 27, 59 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V[3] - 27, 59 . Alarm
	Op	V[3] - 27, 59 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PTOV4* (WW_PTOV2)</b>		
	Mod	V[4] - 27, 59 . active V[4] - 27, 59 . Blo TripCmd V[4] - 27, 59 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V[4] - 27, 59 . Alarm
	Op	V[4] - 27, 59 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PTOV5* (WW_PTOV2)</b>		
	Mod	V[5] - 27, 59 . active V[5] - 27, 59 . Blo TripCmd V[5] - 27, 59 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V[5] - 27, 59 . Alarm
	Op	V[5] - 27, 59 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PTOV6* (WW_PTOV2)</b>		
	Mod	V[6] - 27, 59 . active V[6] - 27, 59 . Blo TripCmd V[6] - 27, 59 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V[6] - 27, 59 . Alarm
	Op	V[6] - 27, 59 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PTUF1* (WW_PTUF1)</b>		
	Mod	df/dt - 81R . active df/dt - 81R . Blo TripCmd df/dt - 81R . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	df/dt - 81R . Alarm
	Op	df/dt - 81R . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PTUF2* (WW_PTUF1)</b>		
	Mod	delta phi - 78V . active delta phi - 78V . Blo TripCmd delta phi - 78V . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	delta phi - 78V . Alarm
	Op	delta phi - 78V . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PTUF3* (WW_PTUF1)</b>		
	Mod	f[1] - 81 . active f[1] - 81 . Blo TripCmd f[1] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[1] - 81 . Alarm
	Op	f[1] - 81 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PTUF4* (WW_PTUF1)</b>		
	Mod	f[2] - 81 . active f[2] - 81 . Blo TripCmd f[2] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[2] - 81 . Alarm
	Op	f[2] - 81 . Trip

4 Appendix  
 4.1 Register Maps

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PTUF5* (WW_PTUF1)</b>		
	Mod	f[3] - 81 . active f[3] - 81 . Blo TripCmd f[3] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[3] - 81 . Alarm
	Op	f[3] - 81 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PTUF6* (WW_PTUF1)</b>		
	Mod	f[4] - 81 . active f[4] - 81 . Blo TripCmd f[4] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[4] - 81 . Alarm
	Op	f[4] - 81 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PTUF7* (WW_PTUF1)</b>		
	Mod	f[5] - 81 . active f[5] - 81 . Blo TripCmd f[5] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[5] - 81 . Alarm
	Op	f[5] - 81 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PTUF8* (WW_PTUF1)</b>		
	Mod	f[6] - 81 . active f[6] - 81 . Blo TripCmd f[6] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[6] - 81 . Alarm
	Op	f[6] - 81 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PTUV1* (WW_PTUV2)</b>		
	Mod	V[1] - 27, 59 . active V[1] - 27, 59 . Blo TripCmd V[1] - 27, 59 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V[1] - 27, 59 . Alarm
	Op	V[1] - 27, 59 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PTUV2* (WW_PTUV2)</b>		
	Mod	V[2] - 27, 59 . active V[2] - 27, 59 . Blo TripCmd V[2] - 27, 59 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V[2] - 27, 59 . Alarm
	Op	V[2] - 27, 59 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PTUV3* (WW_PTUV2)</b>		
	Mod	V[3] - 27, 59 . active V[3] - 27, 59 . Blo TripCmd V[3] - 27, 59 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V[3] - 27, 59 . Alarm
	Op	V[3] - 27, 59 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PTUV4* (WW_PTUV2)</b>		
	Mod	V[4] - 27, 59 . active V[4] - 27, 59 . Blo TripCmd V[4] - 27, 59 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V[4] - 27, 59 . Alarm
	Op	V[4] - 27, 59 . Trip

4 Appendix  
4.1 Register Maps

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PTUV5* (WW_PTUV2)</b>		
	Mod	V[5] - 27, 59 . active V[5] - 27, 59 . Blo TripCmd V[5] - 27, 59 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V[5] - 27, 59 . Alarm
	Op	V[5] - 27, 59 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PTUV6* (WW_PTUV2)</b>		
	Mod	V[6] - 27, 59 . active V[6] - 27, 59 . Blo TripCmd V[6] - 27, 59 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V[6] - 27, 59 . Alarm
	Op	V[6] - 27, 59 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PUPF1 (WW_PUPF1)</b>		
	Mod	PF[1] - 55 . active PF[1] - 55 . Blo TripCmd PF[1] - 55 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	PF[1] - 55 . Alarm
	Op	PF[1] - 55 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>PUPF2 (WW_PUPF1)</b>		
	Mod	PF[2] - 55 . active PF[2] - 55 . Blo TripCmd PF[2] - 55 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	PF[2] - 55 . Alarm
	Op	PF[2] - 55 . Trip



Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>QVPTUV1 (WW_PTUV5)</b>		
	Mod	Q->&V< . active Q->&V< . ExBlo Q->&V< . Fuse Fail VT Blo
	Beh	
	Health	
	NamPlt	
	Str	Q->&V< . Alarm
	Op	Q->&V< . Decoupling Distr. Generator

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>RBRF1 (WW_RBRF1)</b>		
	Mod	CBF - 50BF, 62BF . active CBF - 50BF, 62BF . ExBlo CBF - 50BF, 62BF . ExBlo
	Beh	
	Health	
	NamPlt	
	Str	CBF - 50BF, 62BF . running
	OpEx	CBF - 50BF, 62BF . Alarm

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>RSYN1 (WW_RSYN2)</b>		
	Mod	Sync - 25 . active Sync - 25 . ExBlo Sync - 25 . ExBlo
	Beh	
	Health	
	NamPlt	
	Rel	Sync - 25 . Ready to Close
	AngInd	Sync - 25 . AngleDiffTooHigh
	HZInd	Sync - 25 . SlipTooHigh
	VInd	Sync - 25 . VDiffTooHigh
	DifAngClc	Sync - 25 . Angle Diff
	DifHzClc	Sync - 25 . Slip Freq
	DifVClc	Sync - 25 . Volt Diff

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>RTDPTTR1 (WW_PTTR4)</b>		
	Mod	RTD . active RTD . Blo TripCmd RTD . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Op	RTD . Trip

4 Appendix  
4.1 Register Maps

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>TRPTTR1 (WW_PTTR3)</b>		
	Mod	ThR - 49 . active ThR - 49 . Blo TripCmd ThR - 49 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Op	ThR - 49 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>ULPTOC1 (WW_PTOC4)</b>		
	Mod	I2>[1] - 46 . active I2>[1] - 46 . Blo TripCmd I2>[1] - 46 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	I2>[1] - 46 . Alarm
	Op	I2>[1] - 46 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>ULPTOC2 (WW_PTOC4)</b>		
	Mod	I2>[2] - 46 . active I2>[2] - 46 . Blo TripCmd I2>[2] - 46 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	I2>[2] - 46 . Alarm
	Op	I2>[2] - 46 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>ULPTOC3 (WW_PTOC4)</b>		
	Mod	I2>G[1] - 46G . active I2>G[1] - 46G . Blo TripCmd I2>G[1] - 46G . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	I2>G[1] - 46G . Alarm
	Op	I2>G[1] - 46G . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>ULPTOC4 (WW_PTOC4)</b>		
	Mod	I2>G[2] - 46G . active I2>G[2] - 46G . Blo TripCmd I2>G[2] - 46G . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	I2>G[2] - 46G . Alarm
	Op	I2>G[2] - 46G . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>VAPTOV1* (WW_PTOV3)</b>		
	Mod	V012[1] - 47 . active V012[1] - 47 . Blo TripCmd V012[1] - 47 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V012[1] - 47 . Alarm
	Op	V012[1] - 47 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>VAPTOV2* (WW_PTOV3)</b>		
	Mod	V012[2] - 47 . active V012[2] - 47 . Blo TripCmd V012[2] - 47 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V012[2] - 47 . Alarm
	Op	V012[2] - 47 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>VAPTOV3* (WW_PTOV3)</b>		
	Mod	V012[3] - 47 . active V012[3] - 47 . Blo TripCmd V012[3] - 47 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V012[3] - 47 . Alarm
	Op	V012[3] - 47 . Trip

4 Appendix  
4.1 Register Maps

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>VAPTOV4* (WW_PTOV3)</b>		
	Mod	V012[4] - 47 . active V012[4] - 47 . Blo TripCmd V012[4] - 47 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V012[4] - 47 . Alarm
	Op	V012[4] - 47 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>VAPTOV5* (WW_PTOV3)</b>		
	Mod	V012[5] - 47 . active V012[5] - 47 . Blo TripCmd V012[5] - 47 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V012[5] - 47 . Alarm
	Op	V012[5] - 47 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>VAPTOV6* (WW_PTOV3)</b>		
	Mod	V012[6] - 47 . active V012[6] - 47 . Blo TripCmd V012[6] - 47 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V012[6] - 47 . Alarm
	Op	V012[6] - 47 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>VAPTUV1* (WW_PTUV3)</b>		
	Mod	V012[1] - 47 . active V012[1] - 47 . Blo TripCmd V012[1] - 47 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V012[1] - 47 . Alarm
	Op	V012[1] - 47 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>VAPTUV2* (WW_PTUV3)</b>		
	Mod	V012[2] - 47 . active V012[2] - 47 . Blo TripCmd V012[2] - 47 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V012[2] - 47 . Alarm
	Op	V012[2] - 47 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>VAPTUV3* (WW_PTUV3)</b>		
	Mod	V012[3] - 47 . active V012[3] - 47 . Blo TripCmd V012[3] - 47 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V012[3] - 47 . Alarm
	Op	V012[3] - 47 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>VAPTUV4* (WW_PTUV3)</b>		
	Mod	V012[4] - 47 . active V012[4] - 47 . Blo TripCmd V012[4] - 47 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V012[4] - 47 . Alarm
	Op	V012[4] - 47 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>VAPTUV5* (WW_PTUV3)</b>		
	Mod	V012[5] - 47 . active V012[5] - 47 . Blo TripCmd V012[5] - 47 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V012[5] - 47 . Alarm
	Op	V012[5] - 47 . Trip

4 Appendix  
4.1 Register Maps

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>VAPTUV6* (WW_PTUV3)</b>		
	Mod	V012[6] - 47 . active V012[6] - 47 . Blo TripCmd V012[6] - 47 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V012[6] - 47 . Alarm
	Op	V012[6] - 47 . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>VSPTOV1* (WW_PTOV1)</b>		
	Mod	VG[1] - 27A, 59N,A . active VG[1] - 27A, 59N,A . Blo TripCmd VG[1] - 27A, 59N,A . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	VG[1] - 27A, 59N,A . Alarm
	Op	VG[1] - 27A, 59N,A . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>VSPTOV2* (WW_PTOV1)</b>		
	Mod	VG[2] - 27A, 59N,A . active VG[2] - 27A, 59N,A . Blo TripCmd VG[2] - 27A, 59N,A . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	VG[2] - 27A, 59N,A . Alarm
	Op	VG[2] - 27A, 59N,A . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>VSPTUV1* (WW_PTUV1)</b>		
	Mod	VG[1] - 27A, 59N,A . active VG[1] - 27A, 59N,A . Blo TripCmd VG[1] - 27A, 59N,A . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	VG[1] - 27A, 59N,A . Alarm
	Op	VG[1] - 27A, 59N,A . Trip

Logical Node	Data Object	Module ( - ANSI/IEEE Device Number ) . Name
<b>VSPTUV2* (WW_PTUV1)</b>		
	Mod	VG[2] - 27A, 59N,A . active VG[2] - 27A, 59N,A . Blo TripCmd VG[2] - 27A, 59N,A . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	VG[2] - 27A, 59N,A . Alarm
	Op	VG[2] - 27A, 59N,A . Trip

## 4.2 Device Planning Dependencies

The availability of Logical Node instances in the generated ICD file depends on the settings in the “Device planning” menu.

The following list gives an overview about those settings for every module that have an effect on the availability of a Logical Node.

Module ( - ANSI/IEEE Device Number ) . Name	Value
<b>CILO1</b>	
SG[1] . SwitchgearType	Controlled SG
SG[1] . SwitchgearType	Controlled Make Break SG
<b>CILO2</b>	
SG[2] . SwitchgearType	Controlled SG
SG[2] . SwitchgearType	Controlled Make Break SG
<b>CILO3</b>	
SG[3] . SwitchgearType	Controlled SG
SG[3] . SwitchgearType	Controlled Make Break SG
<b>CILO4</b>	
SG[4] . SwitchgearType	Controlled SG
SG[4] . SwitchgearType	Controlled Make Break SG
<b>CILO5</b>	
SG[5] . SwitchgearType	Controlled SG
SG[5] . SwitchgearType	Controlled Make Break SG
<b>CILO6</b>	
SG[6] . SwitchgearType	Controlled SG
SG[6] . SwitchgearType	Controlled Make Break SG
<b>CSWI1</b>	
SG[1] . SwitchgearType	Controlled SG
SG[1] . SwitchgearType	Controlled Make Break SG
<b>CSWI2</b>	
SG[2] . SwitchgearType	Controlled SG
SG[2] . SwitchgearType	Controlled Make Break SG
<b>CSWI3</b>	
SG[3] . SwitchgearType	Controlled SG
SG[3] . SwitchgearType	Controlled Make Break SG
<b>CSWI4</b>	
SG[4] . SwitchgearType	Controlled SG
SG[4] . SwitchgearType	Controlled Make Break SG
<b>CSWI5</b>	



<b>Module ( - ANSI/IEEE Device Number ) . Name</b>	<b>Value</b>
SG[5] . SwitchgearType	Controlled SG
SG[5] . SwitchgearType	Controlled Make Break SG
<b>CSWI6</b>	
SG[6] . SwitchgearType	Controlled SG
SG[6] . SwitchgearType	Controlled Make Break SG
<b>XCBR1</b>	
SG[1] . SwitchgearType	Monitored Make Break SG
SG[1] . SwitchgearType	Controlled Make Break SG
<b>XCBR2</b>	
SG[2] . SwitchgearType	Monitored Make Break SG
SG[2] . SwitchgearType	Controlled Make Break SG
<b>XCBR3</b>	
SG[3] . SwitchgearType	Monitored Make Break SG
SG[3] . SwitchgearType	Controlled Make Break SG
<b>XCBR4</b>	
SG[4] . SwitchgearType	Monitored Make Break SG
SG[4] . SwitchgearType	Controlled Make Break SG
<b>XCBR5</b>	
SG[5] . SwitchgearType	Monitored Make Break SG
SG[5] . SwitchgearType	Controlled Make Break SG
<b>XCBR6</b>	
SG[6] . SwitchgearType	Monitored Make Break SG
SG[6] . SwitchgearType	Controlled Make Break SG
<b>XSWI1</b>	
SG[1] . SwitchgearType	Monitored SG
SG[1] . SwitchgearType	Controlled SG
<b>XSWI2</b>	
SG[2] . SwitchgearType	Monitored SG
SG[2] . SwitchgearType	Controlled SG
<b>XSWI3</b>	
SG[3] . SwitchgearType	Monitored SG
SG[3] . SwitchgearType	Controlled SG
<b>XSWI4</b>	
SG[4] . SwitchgearType	Monitored SG
SG[4] . SwitchgearType	Controlled SG
<b>XSWI5</b>	
SG[5] . SwitchgearType	Monitored SG

Module ( - ANSI/IEEE Device Number ) . Name	Value
SG[5] . SwitchgearType	Controlled SG
<b>XSWI6</b>	
SG[6] . SwitchgearType	Monitored SG
SG[6] . SwitchgearType	Controlled SG
<b>LoEPDUP1</b>	
LoE-Z1[1] - 40 . Mode	use
<b>LoEPDUP2</b>	
LoE-Z2[1] - 40 . Mode	use
<b>LoEPDUP3</b>	
LoE-Z1[2] - 40 . Mode	use
<b>LoEPDUP4</b>	
LoE-Z2[2] - 40 . Mode	use
<b>OEPVPH1</b>	
V/f>[1] - 24 . Mode	use
<b>OEPVPH2</b>	
V/f>[2] - 24 . Mode	use
<b>OSTPPAM1</b>	
OST - 78 . Mode	use
<b>PDOP1</b>	
P[1] - 32R . Mode	P>
P[1] - 32R . Mode	Pr>
<b>PDOP2</b>	
Q - 32 . Mode	Q>
Q - 32 . Mode	Qr>
<b>PDOP3</b>	
PQS[1] - 32, 37 . Mode	P>
PQS[1] - 32, 37 . Mode	Pr>
PQS[1] - 32, 37 . Mode	Q>
PQS[1] - 32, 37 . Mode	Qr>
PQS[1] - 32, 37 . Mode	S>
<b>PDOP4</b>	
PQS[2] - 32, 37 . Mode	P>
PQS[2] - 32, 37 . Mode	Pr>
PQS[2] - 32, 37 . Mode	Q>
PQS[2] - 32, 37 . Mode	Qr>
PQS[2] - 32, 37 . Mode	S>
<b>PDOP5</b>	

<b>Module ( - ANSI/IEEE Device Number ) . Name</b>	<b>Value</b>
PQS[3] - 32, 37 . Mode	P>
PQS[3] - 32, 37 . Mode	Pr>
PQS[3] - 32, 37 . Mode	Q>
PQS[3] - 32, 37 . Mode	Qr>
PQS[3] - 32, 37 . Mode	S>
<b>PDOP6</b>	
PQS[4] - 32, 37 . Mode	P>
PQS[4] - 32, 37 . Mode	Pr>
PQS[4] - 32, 37 . Mode	Q>
PQS[4] - 32, 37 . Mode	Qr>
PQS[4] - 32, 37 . Mode	S>
<b>PDOP7</b>	
PQS[5] - 32, 37 . Mode	P>
PQS[5] - 32, 37 . Mode	Pr>
PQS[5] - 32, 37 . Mode	Q>
PQS[5] - 32, 37 . Mode	Qr>
PQS[5] - 32, 37 . Mode	S>
<b>PDOP8</b>	
PQS[6] - 32, 37 . Mode	P>
PQS[6] - 32, 37 . Mode	Pr>
PQS[6] - 32, 37 . Mode	Q>
PQS[6] - 32, 37 . Mode	Qr>
PQS[6] - 32, 37 . Mode	S>
<b>PDUP3</b>	
PQS[1] - 32, 37 . Mode	P<
PQS[1] - 32, 37 . Mode	Pr<
PQS[1] - 32, 37 . Mode	Q<
PQS[1] - 32, 37 . Mode	Qr<
PQS[1] - 32, 37 . Mode	S<
<b>PDUP4</b>	
PQS[2] - 32, 37 . Mode	P<
PQS[2] - 32, 37 . Mode	Pr<
PQS[2] - 32, 37 . Mode	Q<
PQS[2] - 32, 37 . Mode	Qr<
PQS[2] - 32, 37 . Mode	S<
<b>PDUP5</b>	
PQS[3] - 32, 37 . Mode	P<

<b>Module ( - ANSI/IEEE Device Number ) . Name</b>	<b>Value</b>
PQS[3] - 32, 37 . Mode	Pr<
PQS[3] - 32, 37 . Mode	Q<
PQS[3] - 32, 37 . Mode	Qr<
PQS[3] - 32, 37 . Mode	S<
<b>PDUP6</b>	
PQS[4] - 32, 37 . Mode	P<
PQS[4] - 32, 37 . Mode	Pr<
PQS[4] - 32, 37 . Mode	Q<
PQS[4] - 32, 37 . Mode	Qr<
PQS[4] - 32, 37 . Mode	S<
<b>PDUP7</b>	
PQS[5] - 32, 37 . Mode	P<
PQS[5] - 32, 37 . Mode	Pr<
PQS[5] - 32, 37 . Mode	Q<
PQS[5] - 32, 37 . Mode	Qr<
PQS[5] - 32, 37 . Mode	S<
<b>PDUP8</b>	
PQS[6] - 32, 37 . Mode	P<
PQS[6] - 32, 37 . Mode	Pr<
PQS[6] - 32, 37 . Mode	Q<
PQS[6] - 32, 37 . Mode	Qr<
PQS[6] - 32, 37 . Mode	S<
<b>PFRC1</b>	
df/dt - 81R . Mode	use
<b>PFRC3</b>	
f[1] - 81 . Mode	f< and df/dt
f[1] - 81 . Mode	f> and df/dt
f[1] - 81 . Mode	f< and DF/DT
f[1] - 81 . Mode	f> and DF/DT
f[1] - 81 . Mode	df/dt
<b>PFRC4</b>	
f[2] - 81 . Mode	f< and df/dt
f[2] - 81 . Mode	f> and df/dt
f[2] - 81 . Mode	f< and DF/DT
f[2] - 81 . Mode	f> and DF/DT
f[2] - 81 . Mode	df/dt
<b>PFRC5</b>	

Module ( - ANSI/IEEE Device Number ) . Name	Value
f[3] - 81 . Mode	f< and df/dt
f[3] - 81 . Mode	f> and df/dt
f[3] - 81 . Mode	f< and DF/DT
f[3] - 81 . Mode	f> and DF/DT
f[3] - 81 . Mode	df/dt
<b>PFRC6</b>	
f[4] - 81 . Mode	f< and df/dt
f[4] - 81 . Mode	f> and df/dt
f[4] - 81 . Mode	f< and DF/DT
f[4] - 81 . Mode	f> and DF/DT
f[4] - 81 . Mode	df/dt
<b>PFRC7</b>	
f[5] - 81 . Mode	f< and df/dt
f[5] - 81 . Mode	f> and df/dt
f[5] - 81 . Mode	f< and DF/DT
f[5] - 81 . Mode	f> and DF/DT
f[5] - 81 . Mode	df/dt
<b>PFRC8</b>	
f[6] - 81 . Mode	f< and df/dt
f[6] - 81 . Mode	f> and df/dt
f[6] - 81 . Mode	f< and DF/DT
f[6] - 81 . Mode	f> and DF/DT
f[6] - 81 . Mode	df/dt
<b>PPAM2</b>	
delta phi - 78V . Mode	use
<b>PPAM3</b>	
f[1] - 81 . Mode	delta phi
<b>PPAM4</b>	
f[2] - 81 . Mode	delta phi
<b>PPAM5</b>	
f[3] - 81 . Mode	delta phi
<b>PPAM6</b>	
f[4] - 81 . Mode	delta phi
<b>PPAM7</b>	
f[5] - 81 . Mode	delta phi
<b>PPAM8</b>	
f[6] - 81 . Mode	delta phi

Module ( - ANSI/IEEE Device Number ) . Name	Value
<b>PSBRPSB2</b>	
PSB - 68 . Mode	use
<b>PTOF3</b>	
f[1] - 81 . Mode	f>
<b>PTOF4</b>	
f[2] - 81 . Mode	f>
<b>PTOF5</b>	
f[3] - 81 . Mode	f>
<b>PTOF6</b>	
f[4] - 81 . Mode	f>
<b>PTOF7</b>	
f[5] - 81 . Mode	f>
<b>PTOF8</b>	
f[6] - 81 . Mode	f>
<b>PTOV1</b>	
V[1] - 27, 59 . Mode	V>
<b>PTOV2</b>	
V[2] - 27, 59 . Mode	V>
<b>PTOV3</b>	
V[3] - 27, 59 . Mode	V>
<b>PTOV4</b>	
V[4] - 27, 59 . Mode	V>
<b>PTOV5</b>	
V[5] - 27, 59 . Mode	V>
<b>PTOV6</b>	
V[6] - 27, 59 . Mode	V>
<b>PTUF3</b>	
f[1] - 81 . Mode	f<
<b>PTUF4</b>	
f[2] - 81 . Mode	f<
<b>PTUF5</b>	
f[3] - 81 . Mode	f<
<b>PTUF6</b>	
f[4] - 81 . Mode	f<
<b>PTUF7</b>	
f[5] - 81 . Mode	f<
<b>PTUF8</b>	


Module ( - ANSI/IEEE Device Number ) . Name	Value
f[6] - 81 . Mode	f<
<b>PTUV1</b>	
V[1] - 27, 59 . Mode	V<
<b>PTUV2</b>	
V[2] - 27, 59 . Mode	V<
<b>PTUV3</b>	
V[3] - 27, 59 . Mode	V<
<b>PTUV4</b>	
V[4] - 27, 59 . Mode	V<
<b>PTUV5</b>	
V[5] - 27, 59 . Mode	V<
<b>PTUV6</b>	
V[6] - 27, 59 . Mode	V<
<b>VAPTOV1</b>	
V012[1] - 47 . Mode	V1>
V012[1] - 47 . Mode	V2>
<b>VAPTOV2</b>	
V012[2] - 47 . Mode	V1>
V012[2] - 47 . Mode	V2>
<b>VAPTOV3</b>	
V012[3] - 47 . Mode	V1>
V012[3] - 47 . Mode	V2>
<b>VAPTOV4</b>	
V012[4] - 47 . Mode	V1>
V012[4] - 47 . Mode	V2>
<b>VAPTOV5</b>	
V012[5] - 47 . Mode	V1>
V012[5] - 47 . Mode	V2>
<b>VAPTOV6</b>	
V012[6] - 47 . Mode	V1>
V012[6] - 47 . Mode	V2>
<b>VAPTUV1</b>	
V012[1] - 47 . Mode	V1<
<b>VAPTUV2</b>	
V012[2] - 47 . Mode	V1<
<b>VAPTUV3</b>	
V012[3] - 47 . Mode	V1<

<b>Module (- ANSI/IEEE Device Number ) . Name</b>	<b>Value</b>
<b>VAPTUV4</b>	
V012[4] - 47 . Mode	V1<
<b>VAPTUV5</b>	
V012[5] - 47 . Mode	V1<
<b>VAPTUV6</b>	
V012[6] - 47 . Mode	V1<
<b>VSPTOV1</b>	
VG[1] - 27A, 59N,A . Mode	V>
<b>VSPTOV2</b>	
VG[2] - 27A, 59N,A . Mode	V>
<b>VSPTUV1</b>	
VG[1] - 27A, 59N,A . Mode	V<
<b>VSPTUV2</b>	
VG[2] - 27A, 59N,A . Mode	V<



**High PROTEC**

docs.SEGelectronics.de/HighPROTEC



SEG Electronics GmbH reserves the right to update any portion of this publication at any time. Information provided by SEG Electronics GmbH is believed to be correct and reliable. However, SEG Electronics GmbH assumes no responsibility unless otherwise expressly undertaken.



SEG Electronics GmbH  
Krefelder Weg 47 • D-47906 Kempen (Germany)  
Postfach 10 07 55 (P.O.Box) • D-47884 Kempen (Germany)  
Telephone: +49 (0) 21 52 145 1

Internet: [www.SEGelectronics.de](http://www.SEGelectronics.de)

Sales  
Telephone: +49 (0) 21 52 145 331  
Fax: +49 (0) 21 52 145 354

Service  
Telephone: +49 (0) 21 52 145 614  
Fax: +49 (0) 21 52 145 354

SEG Electronics has company-owned plants, subsidiaries, and branches, as well as authorized distributors and other authorized service and sales facilities throughout the world.

Complete address / phone / fax / email information for all locations is available on our website.