

IEC 61850 – MICS

High **PROTEC** | PROTECTION TECHNOLOGY
MADE SIMPLE

MCDLV4 |

Model Implementation Conformance Statement (MICS)

UCA International Users Group Testing Sub Committee

Version: 3.7

Original document

English

Original reference manual

SEG Electronics GmbH

Krefelder Weg 47 • D-47906 Kempen (Germany)

Telephone: +49 (0) 21 52 145 1

Internet: www.SEGelectronics.de

Sales

Telephone: +49 (0) 21 52 145 331

Fax: +49 (0) 21 52 145 354

E-mail: info@SEGelectronics.de

Service

Telephone: +49 (0) 21 52 145 614

Fax: +49 (0) 21 52 145 354

E-mail: info@SEGelectronics.de

© 2020 SEG Electronics GmbH. All rights reserved.

Table of Contents

1	Introduction	7
2	Logical Nodes	8
2.1	Logical Nodes List	8
2.2	Logical Node Definitions	10
2.3	WW_CILO1	12
2.4	WW_CSWI1	12
2.5	WW_GAPC1	12
2.6	WW_GGIO1	13
2.7	WW_GGIO4	14
2.8	WW_GGIO6	15
2.9	WW_GGIO10	16
2.10	WW_GGIO11	17
2.11	WW_GGIO14	18
2.12	WW_IHMI1	19
2.13	WW_ITPC1	20
2.14	WW_LLNOCON	20
2.15	WW_LLNOMEA	21
2.16	WW_LLNOPRO	21
2.17	WW_LLNOREC	21
2.18	WW_LLNOSYS	22
2.19	WW_LPHDCON	22
2.20	WW_LPHDMEA	22
2.21	WW_LPHDPRO	23
2.22	WW_LPHDREC	23
2.23	WW_LPHDSYS	23
2.24	WW_MMTR1	24
2.25	WW_MMXU3	24
2.26	WW_MMXU6	25
2.27	WW_MMXU7	25
2.28	WW_MMXU8	26

Table of Contents

2.29	WW_MSTA1	26
2.30	WW_MSTA2	27
2.31	WW_MSTA3	28
2.32	WW_PDIF1	28
2.33	WW_PDIF2	29
2.34	WW_PDIF3	29
2.35	WW_PDIF4	30
2.36	WW_PDOP1	30
2.37	WW_PDUP1	31
2.38	WW_PFRC1	31
2.39	WW_PFRC2	31
2.40	WW_PHAR1	32
2.41	WW_PPAM1	32
2.42	WW_PRTT1	33
2.43	WW_PSOFF1	33
2.44	WW_PTOC1	34
2.45	WW_PTOC3	34
2.46	WW_PTOC4	35
2.47	WW_PTOF1	35
2.48	WW_PTOV1	36
2.49	WW_PTOV2	36
2.50	WW_PTOV3	36
2.51	WW_PTTR3	37
2.52	WW_PTUF1	37
2.53	WW_PTUV1	38
2.54	WW_PTUV2	38
2.55	WW_PTUV3	39
2.56	WW_PTUV5	39
2.57	WW_PUPF1	40
2.58	WW_PVPH1	40
2.59	WW_PSDE1	40
2.60	WW_PSDE2	41

2.61	WW_RBRF1	41
2.62	WW_RDRE1	42
2.63	WW_RREC1	42
2.64	WW_RSYN2	43
2.65	WW_SCBR1	43
2.66	WW_XCBR2	44
2.67	WW_XSWI1	44
3	Common Data Class	46
3.1	Common Data Class Definitions	46
3.1.1	WW_ACD1	47
3.1.2	WW_ACT1	47
3.1.3	WW_BCR1	47
3.1.4	WW_CMV2	47
3.1.5	WW_DEL2	48
3.1.6	WW_DPC1	48
3.1.7	WW_DPC2	48
3.1.8	WW_DPL1	49
3.1.9	WW_INC1	49
3.1.10	WW_INS1	49
3.1.11	WW_INS2	50
3.1.12	WW_INS3	50
3.1.13	WW_INS4	50
3.1.14	WW_INS5	50
3.1.15	WW_LPL1	51
3.1.16	WW_LPL2	51
3.1.17	WW_LPL3	51
3.1.18	WW_MV1	51
3.1.19	WW_SPC1	52
3.1.20	WW_SPC2	52
3.1.21	WW_SPS1	52
3.1.22	WW_WYE2	53
3.1.23	WW_WYE3	53

3.2	Common Data Attributes Type Definitions	54
3.2.1	WW_analogValue1	54
3.2.2	WW_Cancel1	54
3.2.3	WW_Oper1	54
3.2.4	WW_origin1	54
3.2.5	WW_units1	55
3.2.6	WW_vector1	55
3.3	Enumerated type definitions	56
3.3.1	AutoRecSt	56
3.3.2	Beh	56
3.3.3	CBOPCap	56
3.3.4	ctlModel	56
3.3.5	Dbpos	57
3.3.6	ACDdir	57
3.3.7	Health	57
3.3.8	Mod	57
3.3.9	MotorCycle	58
3.3.10	multiplier	58
3.3.11	orCategory	59
3.3.12	sboClass	59
3.3.13	SIUnit	59
4	Appendix	62
4.1	Register Maps	62
4.2	Device Planning Dependencies	111

1 Introduction

This model implementation conformance statement is applicable to the MCDLV4 version 3.7.

This MICS document specifies the modelling extensions compared to IEC 61850 edition 1.

Clause 2 contains the list of implemented logical nodes.

Clause 3 describes the new and extended logical nodes.

Clause 4 describes the existing common data classes.

Clause 5 describes the existing enum types.

2 Logical Nodes

2.1 Logical Nodes List

The following table contains the list of logical nodes implemented in the device:

L: System Logical Nodes
LLNO (Logical Node device)
LPHD (Physical device)

P: Logical Nodes for protection functions
PDIF (Differential)
PDOP (Directional overpower)
PDUP (Directional underpower)
PFRC (Rate of change of frequency)
PHAR (Harmonic restraint)
PPAM (Phase angle or out-of-step protection)
PRTT (Remote transfer trips)
PSDE (Sensitive directional earthfault)
PSOF (Switch Onto Fault)
PTOC (Time overcurrent)
PTOF (Overfrequency)
PTOV (Overvoltage)
PTTR (Thermal overload protection)
PTUF (Underfrequency)
PTUV (Undervoltage)
PUPF (Underpower factor)
PVPH (Volts per Hz)

R: Logical Nodes for protection related functions
RBRF (Breaker failure)
RDRE (Disturbance recorder function)
RREC (Autoreclosing)
RSYN (Synchronism-check or synchronising)

G: Logical Nodes for generic references
GAPC (Generic automatic process control)
GGIO (Generic process I/O)

M: Logical Nodes for metering and measurement

MMTR (Metering)

MMXU (Measurement)

MSTA (Metering Statistics)

X: Logical Nodes for switchgear

XCBR (Circuit Breaker)

XSWI (Circuit Switch)

C: Logical Nodes for control

CILO (Interlocking)

CSWI (Switch controller)

I: Logical Nodes for interfacing and archiving

IHMI (Human machine interface)

ITPC (Teleprotection communication interfaces)

S: Logical Nodes for sensors and monitoring

SCBR (Circuit breaker monitoring)

2.2 Logical Node Definitions

Abbreviations used in the following table:

- **M**: Data is mandatory in the IEC 61850-7-4.
- **O**: Data is optional in the IEC 61850-7-4 and is used in the device.
- **E**: Data is an extension to the IEC 61850-7-4.

LN Type	LN Class	Description
WW_CILO1	CILO	Interlocking
WW_CSWI1	CSWI	Switch controller
WW_GAPC1	GAPC	Generic automatic process control
WW_GGIO1	GGIO	Generic process I/O
WW_GGIO10	GGIO	Generic process I/O
WW_GGIO11	GGIO	Generic process I/O
WW_GGIO14	GGIO	Generic process I/O
WW_GGIO4	GGIO	Generic process I/O
WW_GGIO6	GGIO	Generic process I/O
WW_IHMI1	IHMI	Human machine interface
WW_ITPC1	ITPC	Teleprotection communication interfaces
WW_LLNOCON	LLNO	Logical Node device
WW_LLNOMEA	LLNO	Logical Node device
WW_LLNOPRO	LLNO	Logical Node device
WW_LLNOREC	LLNO	Logical Node device
WW_LLNOSYS	LLNO	Logical Node device
WW_LPHDCON	LPHD	Physical device
WW_LPHDMEA	LPHD	Physical device
WW_LPHDPRO	LPHD	Physical device
WW_LPHDREC	LPHD	Physical device
WW_LPHDSYS	LPHD	Physical device
WW_MMTR1	MMTR	Metering
WW_MMXU3	MMXU	Measurement
WW_MMXU6	MMXU	Measurement
WW_MMXU7	MMXU	Measurement
WW_MMXU8	MMXU	Measurement
WW_MSTA1	MSTA	Metering Statistics
WW_MSTA2	MSTA	Metering Statistics
WW_MSTA3	MSTA	Metering Statistics
WW_PDIF1	PDIF	Differential
WW_PDIF2	PDIF	Differential

LN Type	LN Class	Description
WW_PDIF3	PDIF	Differential
WW_PDIF4	PDIF	Differential
WW_PDOP1	PDOP	Directional overpower
WW_PDUP1	PDUP	Directional underpower
WW_PFRC1	PFRC	Rate of change of frequency
WW_PFRC2	PFRC	Rate of change of frequency
WW_PHAR1	PHAR	Harmonic restraint
WW_PPAM1	PPAM	Phase angle or out-of-step protection
WW_PRTT1	PRTT	Remote transfer trips
WW_PSDE1	PSDE	Sensitive directional earthfault
WW_PSDE2	PSDE	Sensitive directional earthfault
WW_PSO1	PSOF	Switch Onto Fault
WW_PTOC1	PTOC	Time overcurrent
WW_PTOC3	PTOC	Time overcurrent
WW_PTOC4	PTOC	Time overcurrent
WW_PTOF1	PTOF	Overfrequency
WW_PTOV1	PTOV	Overvoltage
WW_PTOV2	PTOV	Overvoltage
WW_PTOV3	PTOV	Overvoltage
WW_PTTR3	PTTR	Thermal overload protection
WW_PTUF1	PTUF	Underfrequency
WW_PTUV1	PTUV	Undervoltage
WW_PTUV2	PTUV	Undervoltage
WW_PTUV3	PTUV	Undervoltage
WW_PTUV5	PTUV	Undervoltage
WW_PUPF1	PUPF	Underpower factor
WW_PVPH1	PVPH	Volts per Hz
WW_RBRF1	RBRF	Breaker failure
WW_RDRE1	RDRE	Disturbance recorder function
WW_RREC1	RREC	Autoreclosing
WW_RSYN2	RSYN	Synchronism-check or synchronising
WW_SCBR1	SCBR	Circuit breaker monitoring
WW_XCBR2	XCBR	Circuit Breaker
WW_XSWI1	XSWI	Circuit Switch

2.3 WW_CILO1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
CILO class				
CILO	WW_CILO1	Interlocking		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behavior	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
EnaOpn	WW_SPS1	Enable Open	M	
EnaCls	WW_SPS1	Enable Close	M	

2.4 WW_CSWI1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
CSWI class				
CSWI	WW_CSWI1	Switch Controller		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
Loc	WW_SPS1	Local operation	O	
<i>Controls</i>				
Pos	WW_DPC2	Switch position	M	

2.5 WW_GAPC1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
GAPC class				
GAPC	WW_GAPC1	Generic automatic process control		

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
Loc	WW_SPS1	Local operation	O	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

2.6 WW_GGIO1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
GGIO class				
GGIO	WW_GGIO1	Generic process I/O		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Ind1	WW_SPS1	General indication (binary input)	O	
Ind2	WW_SPS1	General indication (binary input)	O	
Ind3	WW_SPS1	General indication (binary input)	O	
Ind4	WW_SPS1	General indication (binary input)	O	
Ind5	WW_SPS1	General indication (binary input)	O	
Ind6	WW_SPS1	General indication (binary input)	O	
Ind7	WW_SPS1	General indication (binary input)	O	
Ind8	WW_SPS1	General indication (binary input)	O	
Ind9	WW_SPS1	General indication (binary input)	O	
Ind10	WW_SPS1	General indication (binary input)	O	
Ind11	WW_SPS1	General indication (binary input)	O	
Ind12	WW_SPS1	General indication (binary input)	O	

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
Ind13	WW_SPS1	General indication (binary input)	O	
Ind14	WW_SPS1	General indication (binary input)	O	
Ind15	WW_SPS1	General indication (binary input)	O	
Ind16	WW_SPS1	General indication (binary input)	O	

2.7 WW_GGIO4

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
GGIO class				
GGIO	WW_GGIO4	Generic process I/O		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Ind1	WW_SPS1	General indication (binary input)	O	
Ind2	WW_SPS1	General indication (binary input)	O	
Ind3	WW_SPS1	General indication (binary input)	O	
Ind4	WW_SPS1	General indication (binary input)	O	
Ind5	WW_SPS1	General indication (binary input)	O	
Ind6	WW_SPS1	General indication (binary input)	O	
Ind7	WW_SPS1	General indication (binary input)	O	
Ind8	WW_SPS1	General indication (binary input)	O	
Ind9	WW_SPS1	General indication (binary input)	O	
Ind10	WW_SPS1	General indication (binary input)	O	
Ind11	WW_SPS1	General indication (binary input)	O	
Ind12	WW_SPS1	General indication (binary input)	O	
Ind13	WW_SPS1	General indication (binary input)	O	
Ind14	WW_SPS1	General indication (binary input)	O	
Ind15	WW_SPS1	General indication (binary input)	O	
Ind16	WW_SPS1	General indication (binary input)	O	
Ind17	WW_SPS1	General indication (binary input)	O	
Ind18	WW_SPS1	General indication (binary input)	O	

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
Ind19	WW_SPS1	General indication (binary input)	O	
Ind20	WW_SPS1	General indication (binary input)	O	
Ind21	WW_SPS1	General indication (binary input)	O	
Ind22	WW_SPS1	General indication (binary input)	O	
Ind23	WW_SPS1	General indication (binary input)	O	
Ind24	WW_SPS1	General indication (binary input)	O	
Ind25	WW_SPS1	General indication (binary input)	O	
Ind26	WW_SPS1	General indication (binary input)	O	
Ind27	WW_SPS1	General indication (binary input)	O	
Ind28	WW_SPS1	General indication (binary input)	O	
Ind29	WW_SPS1	General indication (binary input)	O	
Ind30	WW_SPS1	General indication (binary input)	O	
Ind31	WW_SPS1	General indication (binary input)	O	
Ind32	WW_SPS1	General indication (binary input)	O	

2.8 WW_GGIO6

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
GGIO class				
GGIO	WW_GGIO6	Generic process I/O		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Ind1	WW_SPS1	General indication (binary input)	O	
Ind2	WW_SPS1	General indication (binary input)	O	
Ind3	WW_SPS1	General indication (binary input)	O	
Ind4	WW_SPS1	General indication (binary input)	O	

2.9 WW_GGIO10

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
GGIO class				
GGIO	WW_GGI10	Generic process I/O		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Ind1	WW_SPS1	General indication (binary input)	O	
Ind2	WW_SPS1	General indication (binary input)	O	
Ind3	WW_SPS1	General indication (binary input)	O	
Ind4	WW_SPS1	General indication (binary input)	O	
Ind5	WW_SPS1	General indication (binary input)	O	
Ind6	WW_SPS1	General indication (binary input)	O	
Ind7	WW_SPS1	General indication (binary input)	O	
Ind8	WW_SPS1	General indication (binary input)	O	
Ind9	WW_SPS1	General indication (binary input)	O	
Ind10	WW_SPS1	General indication (binary input)	O	
Ind11	WW_SPS1	General indication (binary input)	O	
Ind12	WW_SPS1	General indication (binary input)	O	
Ind13	WW_SPS1	General indication (binary input)	O	
Ind14	WW_SPS1	General indication (binary input)	O	
Ind15	WW_SPS1	General indication (binary input)	O	
Ind16	WW_SPS1	General indication (binary input)	O	
Ind17	WW_SPS1	General indication (binary input)	O	
Ind18	WW_SPS1	General indication (binary input)	O	
Ind19	WW_SPS1	General indication (binary input)	O	
Ind20	WW_SPS1	General indication (binary input)	O	
Ind21	WW_SPS1	General indication (binary input)	O	
Ind22	WW_SPS1	General indication (binary input)	O	
Ind23	WW_SPS1	General indication (binary input)	O	
Ind24	WW_SPS1	General indication (binary input)	O	
Ind25	WW_SPS1	General indication (binary input)	O	
Ind26	WW_SPS1	General indication (binary input)	O	

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
Ind27	WW_SPS1	General indication (binary input)	O	
Ind28	WW_SPS1	General indication (binary input)	O	
Ind29	WW_SPS1	General indication (binary input)	O	
Ind30	WW_SPS1	General indication (binary input)	O	
Ind31	WW_SPS1	General indication (binary input)	O	
Ind32	WW_SPS1	General indication (binary input)	O	

2.10 WW_GGIO11

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
GGIO class				
GGIO	WW_GGI11	Generic process I/O		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Ind1	WW_SPS1	General indication (binary input)	O	
Ind2	WW_SPS1	General indication (binary input)	O	
Ind3	WW_SPS1	General indication (binary input)	O	
Ind4	WW_SPS1	General indication (binary input)	O	
Ind5	WW_SPS1	General indication (binary input)	O	
Ind6	WW_SPS1	General indication (binary input)	O	
Ind7	WW_SPS1	General indication (binary input)	O	
Ind8	WW_SPS1	General indication (binary input)	O	
Ind9	WW_SPS1	General indication (binary input)	O	
Ind10	WW_SPS1	General indication (binary input)	O	
Ind11	WW_SPS1	General indication (binary input)	O	
Ind12	WW_SPS1	General indication (binary input)	O	
Ind13	WW_SPS1	General indication (binary input)	O	
Ind14	WW_SPS1	General indication (binary input)	O	
Ind15	WW_SPS1	General indication (binary input)	O	
Ind16	WW_SPS1	General indication (binary input)	O	

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
Ind17	WW_SPS1	General indication (binary input)	O	
Ind18	WW_SPS1	General indication (binary input)	O	
Ind19	WW_SPS1	General indication (binary input)	O	
Ind20	WW_SPS1	General indication (binary input)	O	
Ind21	WW_SPS1	General indication (binary input)	O	
Ind22	WW_SPS1	General indication (binary input)	O	
Ind23	WW_SPS1	General indication (binary input)	O	
Ind24	WW_SPS1	General indication (binary input)	O	
Ind25	WW_SPS1	General indication (binary input)	O	
Ind26	WW_SPS1	General indication (binary input)	O	
Ind27	WW_SPS1	General indication (binary input)	O	
Ind28	WW_SPS1	General indication (binary input)	O	
Ind29	WW_SPS1	General indication (binary input)	O	
Ind30	WW_SPS1	General indication (binary input)	O	
Ind31	WW_SPS1	General indication (binary input)	O	
Ind32	WW_SPS1	General indication (binary input)	O	

2.11 WW_GGIO14

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
GGIO class				
GGIO	WW_GGI14	Generic process I/O		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
SPCSO1	WW_SPC2	Single point controllable status output	O	
SPCSO2	WW_SPC2	Single point controllable status output	O	
SPCSO3	WW_SPC2	Single point controllable status output	O	
SPCSO4	WW_SPC2	Single point controllable status output	O	
SPCSO5	WW_SPC2	Single point controllable status output	O	
SPCSO6	WW_SPC2	Single point controllable status output	O	

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
SPCSO7	WW_SPC2	Single point controllable status output	O	
SPCSO8	WW_SPC2	Single point controllable status output	O	
SPCSO9	WW_SPC2	Single point controllable status output	O	
SPCSO10	WW_SPC2	Single point controllable status output	O	
SPCSO11	WW_SPC2	Single point controllable status output	O	
SPCSO12	WW_SPC2	Single point controllable status output	O	
SPCSO13	WW_SPC2	Single point controllable status output	O	
SPCSO14	WW_SPC2	Single point controllable status output	O	
SPCSO15	WW_SPC2	Single point controllable status output	O	
SPCSO16	WW_SPC2	Single point controllable status output	O	
SPCSO17	WW_SPC2	Single point controllable status output	O	
SPCSO18	WW_SPC2	Single point controllable status output	O	
SPCSO19	WW_SPC2	Single point controllable status output	O	
SPCSO20	WW_SPC2	Single point controllable status output	O	
SPCSO21	WW_SPC2	Single point controllable status output	O	
SPCSO22	WW_SPC2	Single point controllable status output	O	
SPCSO23	WW_SPC2	Single point controllable status output	O	
SPCSO24	WW_SPC2	Single point controllable status output	O	
SPCSO25	WW_SPC2	Single point controllable status output	O	
SPCSO26	WW_SPC2	Single point controllable status output	O	
SPCSO27	WW_SPC2	Single point controllable status output	O	
SPCSO28	WW_SPC2	Single point controllable status output	O	
SPCSO29	WW_SPC2	Single point controllable status output	O	
SPCSO30	WW_SPC2	Single point controllable status output	O	
SPCSO31	WW_SPC2	Single point controllable status output	O	
SPCSO32	WW_SPC2	Single point controllable status output	O	

2.12 WW_IHMI1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
IHMI class				
IHMI	WW_IHMI1	Human machine interface		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	

2.13 WW_ITPC1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
IHMI class				
ITPC	WW_ITPC1	Teleprotection communication interfaces		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
FrSyn	WW_SPS1	Frames Synchronization	E	
TmSyn	WW_SPS1	Time Synchronization	E	

2.14 WW_LLNOCON

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
LLNO class				
LLNO	WW_LLNOCON	Logical Node device		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL2	Name plate	M	

2.15 WW_LLNOMEA

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
LLNO class				
LLNO	WW_LLNOMEA	Logical Node device		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL2	Name plate	M	

2.16 WW_LLNOPRO

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
LLNO class				
LLNO	WW_LLNOPRO	Logical Node device		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL2	Name plate	M	

2.17 WW_LLNOREC

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
LLNO class				
LLNO	WW_LLNOREC	Logical Node device		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
NamPlt	WW_LPL2	Name plate	M	

2.18 WW_LLNO5SYS

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
LLNO class				
LLNO	WW_LLNO5SYS	Logical Node device		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL2	Name plate	M	

2.19 WW_LPHDCON

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
LPHD class				
LPHD	WW_LPHDCON	Physical device information		
Data				
<i>Common Logical Node Information</i>				
PhyNam	WW_DPL1	Physical device name plate	M	
PhyHealth	WW_INS3	Physical Device Health	M	
Proxy	WW_SPS1	Indicates if this LN is a proxy	M	

2.20 WW_LPHDMEA

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
LPHD class				
LPHD	WW_LPHDMEA	Physical device information		
Data				
<i>Common Logical Node Information</i>				

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PhyNam	WW_DPL1	Physical device name plate	M	
PhyHealth	WW_INS3	Physical Device Health	M	
Proxy	WW_SPS1	Indicates if this LN is a proxy	M	

2.21 WW_LPHDPRO

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
LPHD class				
LPHD	WW_LPHDPRO	Physical device information		
Data				
<i>Common Logical Node Information</i>				
PhyNam	WW_DPL1	Physical device name plate	M	
PhyHealth	WW_INS3	Physical Device Health	M	
Proxy	WW_SPS1	Indicates if this LN is a proxy	M	

2.22 WW_LPHDREC

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
LPHD class				
LPHD	WW_LPHDREC	Physical device information		
Data				
<i>Common Logical Node Information</i>				
PhyNam	WW_DPL1	Physical device name plate	M	
PhyHealth	WW_INS3	Physical Device Health	M	
Proxy	WW_SPS1	Indicates if this LN is a proxy	M	

2.23 WW_LPHDSYS

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
LPHD class				
LPHD	WW_LPHDSYS	Physical device information		
Data				

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<i>Common Logical Node Information</i>				
PhyNam	WW_DPL1	Physical device name plate	M	
PhyHealth	WW_INS3	Physical Device Health	M	
Proxy	WW_SPS1	Indicates if this LN is a proxy	M	

2.24 WW_MMTR1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
MSTA class				
MMTR1	WW_MMTR1	Metering		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Metered values</i>				
TotVAh	WW_BCR1	Absolute Apparent Power Hours	O	
TotWh	WW_BCR1	Absolute Active Power Hours	O	
TotVARh	WW_BCR1	Absolute Reactive Power Hours	O	
SupWh	WW_BCR1	Consumed Active Energy	O	
SupVARh	WW_BCR1	Consumed Reactive Energy	O	
DmdWh	WW_BCR1	Fed Active Energy	O	
DmdVARh	WW_BCR1	Fed Reactive Energy	O	

2.25 WW_MMXU3

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
MMXU class				
MMXU	WW_MMXU3	Measurement		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Measured values</i>				
TotW	WW_MV1	Total Active Power (Total P)	O	
TotVAr	WW_MV1	Total Reactive Power (Total Q)	O	
TotVA	WW_MV1	Total Apparent Power (Total S)	O	
TotPF	WW_MV1	Total Power factor (Total PF)	O	

2.26 WW_MMXU6

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
MMXU class				
MMXU	WW_MMXU6	Measurement		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Measured values</i>				
PPV	WW_DEL2	Phase to phase voltages (VL12, VL23, VL31)	O	
PhV	WW_WYE2	Phase to ground voltages (VL1, VL2, VL3)	O	
Hz	WW_MV1	Frequency	O	

2.27 WW_MMXU7

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
MMXU class				
MMXU	WW_MMXU7	Measurement		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
NamPlt	WW_LPL1	Name plate	M	
<i>Measured values</i>				
A	WW_WYE2	Phase currents (IL1, IL2, IL3)	O	

2.28 WW_MMXU8

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
MMXU class				
MMXU	WW_MMXU8	Measurement		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Measured values</i>				
A	WW_WYE3	Phase currents (IL1, IL2, IL3)	O	

2.29 WW_MSTA1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
MSTA class				
MSTA	WW_MSTA1	Metering Statistics		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Metered values</i>				
AvAPhA	WW_MV1	Average current IL1	E	
AvAPhB	WW_MV1	Average current IL2	E	
AvAPhC	WW_MV1	Average current IL3	E	
MaxAPhA	WW_MV1	Maximum current IL1	E	

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
MaxAphB	WW_MV1	Maximum current IL2	E	
MaxAphC	WW_MV1	Maximum current IL3	E	
MinAphA	WW_MV1	Minimum current IL1	E	
MinAphB	WW_MV1	Minimum current IL2	E	
MinAphC	WW_MV1	Minimum current IL3	E	

2.30 WW_MSTA2

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
MSTA class				
MSTA	WW_MSTA2	Metering Statistics		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Metered values</i>				
AvVPhAB	WW_MV1	Average voltage VL12	E	
AvVPhBC	WW_MV1	Average voltage VL23	E	
AvVPhCA	WW_MV1	Average voltage VL31	E	
MaxVPhAB	WW_MV1	Maximum voltage VL12	E	
MaxVPhBC	WW_MV1	Maximum voltage VL23	E	
MaxVPhCA	WW_MV1	Maximum voltage VL31	E	
MinVPhAB	WW_MV1	Minimum voltage VL12	E	
MinVPhBC	WW_MV1	Minimum voltage VL23	E	
MinVPhCA	WW_MV1	Minimum voltage VL31	E	
AvVPhA	WW_MV1	Average voltage VL1	E	
AvVPhB	WW_MV1	Average voltage VL2	E	
AvVPhC	WW_MV1	Average voltage VL3	E	
MaxVPhA	WW_MV1	Maximum voltage VL1	E	
MaxVPhB	WW_MV1	Maximum voltage VL2	E	
MaxVPhC	WW_MV1	Maximum voltage VL3	E	
MinVPhA	WW_MV1	Minimum voltage VL1	E	
MinVPhB	WW_MV1	Minimum voltage VL2	E	

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
MinVPhB	WW_MV1	Minimum voltage VL3	E	

2.31 WW_MSTA3

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
MSTA class				
MSTA	WW_MSTA3	Metering Statistics		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Metered values</i>				
AvVA	WW_MV1	Average apparent power	O	
MaxVA	WW_MV1	Maximum apparent power	O	
MinVA	WW_MV1	Minimum apparent power	O	
Avw	WW_MV1	Average real power	O	
MaxW	WW_MV1	Maximum real power	O	
MinW	WW_MV1	Minimum real power	O	
AvVAr	WW_MV1	Average reactive power	O	
MaxVAr	WW_MV1	Maximum reactive power	O	
MinVAr	WW_MV1	Minimum reactive power	O	

2.32 WW_PDIF1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PDIF class				
PDIF	WW_PDIF1	Differential		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

2.33 WW_PDIF2

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PDIF class				
PDIF	WW_PDIF2	Differential		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

2.34 WW_PDIF3

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PDIF class				
PDIF	WW_PDIF3	Differential		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
Op	WW_ACT1	Operate	M	

2.35 WW_PDIF4

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PDIF class				
PDIF	WW_PDIF4	Differential		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

2.36 WW_PDOP1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PDOP class				
PDOP	WW_PDOP1	Directional overpower		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

2.37 WW_PDUP1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PDUP class				
PDUP	WW_PDUP1	Directional underpower		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

2.38 WW_PFRC1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PFRC class				
PFRC	WW_PFRC1	Rate of change of frequency		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

2.39 WW_PFRC2

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PFRC class				
PFRC	WW_PFRC2	Rate of change of frequency		

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

2.40 WW_PHAR1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PHAR class				
PHAR	WW_PHAR1	Harmonic restraint		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	

2.41 WW_PPAM1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PPAM class				
PPAM	WW_PPAM1	Phase angle measuring		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

2.42 WW_PRTT1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PRTT class				
PRTT	WW_PRTT1	Remote transfer trips		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Op	WW_ACT1	Operate	M	
PerTr1	WW_SPS1	Permissive for Rx.Trip	E	
PerTr2	WW_SPS1	Permissive for Rx.Trip	E	
PerTr3	WW_SPS1	Permissive for Rx.Trip	E	
PerTr4	WW_SPS1	Permissive for Rx.Trip	E	
RemTr1	WW_SPS1	Status of trip from remote	E	
RemTr2	WW_SPS1	Status of trip from remote	E	
RemTr3	WW_SPS1	Status of trip from remote	E	
RemTr4	WW_SPS1	Status of trip from remote	E	

2.43 WW_PSOFF1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PSOF class				
PSOF	WW_PSOFF1	Protection Switch Onto fault		
Data				
<i>Common Logical Node Information</i>				

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL3	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	

2.44 WW_PTOC1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PTOC class				
PTOC	WW_PTOC1	Time overcurrent		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

2.45 WW_PTOC3

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PTOC class				
PTOC	WW_PTOC3	Time overcurrent		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

2.46 WW_PTOC4

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PTOC class				
PTOC	WW_PTOC4	Time overcurrent		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

2.47 WW_PTOF1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PTOF class				
PTOF	WW_PTOF1	Overfrequency		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

2.48 WW_PTOV1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PTOV class				
PTOV	WW_PTOV1	Overvoltage		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

2.49 WW_PTOV2

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PTOV class				
PTOV	WW_PTOV2	Overvoltage		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

2.50 WW_PTOV3

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PTOV class				
PTOV	WW_PTOV3	Overvoltage		

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

2.51 WW_PTTR3

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PTTR class				
PTTR	WW_PTTR3	Thermal overload		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Op	WW_ACT1	Operate	M	

2.52 WW_PTUF1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PTUF class				
PTUF	WW_PTUF1	Underfrequency		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

2.53 WW_PTUV1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PTUV class				
PTUV	WW_PTUV1	Undervoltage		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

2.54 WW_PTUV2

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PTUV class				
PTUV	WW_PTUV2	Undervoltage		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
Op	WW_ACT1	Operate	M	

2.55 WW_PTUV3

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PTUV class				
PTUV	WW_PTUV3	Undervoltage		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

2.56 WW_PTUV5

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PTUV class				
PTUV	WW_PTUV5	Undervoltage		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

2.57 WW_PUPF1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PUPF class				
PUPF	WW_PUPF1	Underpower factor		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

2.58 WW_PVPH1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PVPH class				
PVPH	WW_PVPH1	Volts per Hz		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

2.59 WW_PSDE1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PSDE class				
PSDE	WW_PSDE1	Wattmetric directional earthfault (IG meas dir)		

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	

2.60 WW_PSDE2

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PSDE class				
PSDE	WW_PSDE2	Wattmetric directional earthfault (IG meas dir)		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	

2.61 WW_RBRF1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
RBRF class				
RBRF	WW_RBRF1	Breaker failure		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
OpEx	WW_ACT1	Breaker failure trip	M	

2.62 WW_RDRE1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
RDRE class				
RDRE	WW_RDRE1	Disturbance recorder function		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
RcdMade	WW_SPS1	Recording made	M	
FltNum	WW_INS2	Fault Number	M	
GriFltNum	WW_INS2	Grid Fault Number	O	
RcdStr	WW_SPS1	Recording started	O	

2.63 WW_RREC1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
RREC class				
RREC	WW_RREC1	Autoreclosing		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Op	WW_ACT1	Operate (used here to provide close to XCBR)	M	

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
AutoRecSt	WW_INS4	Autoreclosing Status	M	

2.64 WW_RSYN2

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
RSYN class				
RSYN	WW_RSYN2	Synchronism-check or synchronising		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Rel	WW_SPS1	Release	M	
AngInd	WW_SPS1	Phase Angle difference to high	E	
HzInd	WW_SPS1	Frequency difference to high	E	
VInd	WW_SPS1	Voltage difference to high	E	
<i>Measured Values</i>				
DifAngClc	WW_MV1	Phase Angle difference value	E	
DifHzClc	WW_MV1	Frequency difference value	E	
DifVClc	WW_MV1	Voltage difference value	E	

2.65 WW_SCBR1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
RBRF class				
SCBR	WW_SCBR1	Circuit breaker monitoring		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
<i>Status Information</i>				
TrCctAlm	WW_ACD1	Alarm signal	E	

2.66 WW_XCBR2

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
XCBR class				
XCBR	WW_XCBR2	Circuit Breaker		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
Loc	WW_SPS1	Local operation	M	
OpCnt	WW_INS2	Operation counter	M	
<i>Status Information</i>				
CBOpCap	WW_INS5	Circuit breaker operating capability	M	
<i>Controls</i>				
Pos	WW_DPC1	Switch position	M	
BlkOpn	WW_SPC1	Block opening	M	
BlkCls	WW_SPC1	Block closing	M	

2.67 WW_XSWI1

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
XSWI class				
XSWI	WW_XSWI1	Circuit switch		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
Loc	WW_SPS1	Local operation	M	
OpCnt	WW_INS2	Operation counter	M	
<i>Status Information</i>				
SwTyp	WW_INS5	Switch type	M	
SwOpCap	WW_INS5	Switch operating capability	M	
<i>Controls</i>				
Pos	WW_DPC1	Switch position	M	
BlkOpn	WW_SPC1	Block opening	M	
BlkCls	WW_SPC1	Block closing	M	

3 Common Data Class

3.1 Common Data Class Definitions

The following table contains the list of Common Data Classes implemented in the device:

CDC Type	CDC Class	Description
WW_ACD1	ACD	Directional Protection activation information
WW_ACT1	ACT	Protection Activation Information
WW_analogValue1	analogValue	Analogue value
WW_BCR1	BCR	Binary Counter Reading
WW_Cancel1	Cancel	Cancel operating
WW_CMV2	CMV	Complex measured value
WW_DEL2	DEL	Delta
WW_DPC1	DPC	Controllable Double Point
WW_DPC2	DPC	Controllable Double Point
WW_DPL1	DPL	Device name plate
WW_INC1	INC	Controllable Integer Status
WW_INS1	INS	Integer Status
WW_INS2	INS	Integer Status
WW_INS3	INS	Integer Status
WW_INS4	INS	Integer Status
WW_INS5	INS	Integer Status
WW_LPL1	LPL	Logical node name plate
WW_LPL2	LPL	Logical node name plate
WW_LPL3	LPL	Logical node name plate
WW_MV1	MV	Measured Value
WW_Oper1	Oper	Start/Select operating
WW_origin1	origin	Originator
WW_SPC1	SPC	Controllable Single Point
WW_SPC2	SPC	Controllable Single Point
WW_SPS1	SPS	Single Point Status
WW_units1	units	Unit definition
WW_vector1	vector	Vector definition
WW_WYE2	WYE	Phase to ground related measured values of a three phase system
WW_WYE3	WYE	Phase to ground related measured values of a three phase system

3.1.1 WW_ACD1

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
ACD class						
General	BOOLEAN	ST	dchg		M	
dirGeneral	Enum	ST	dchg	ACDdir	M	
q	Quality	ST	qchg		M	
t	Timestamp	ST			M	

3.1.2 WW_ACT1

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
ACT class						
General	BOOLEAN	ST	dchg		M	
q	Quality	ST	qchg		M	
t	Timestamp	ST			M	

3.1.3 WW_BCR1

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
BCR class						
actVal	INT32	ST	dchg		M	
q	Quality	ST	qchg		M	
t	Timestamp	ST			M	
pulsQty	FLOAT32	CF			M	
units	Struct	CF			O	

3.1.4 WW_CMV2

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
CMV class						
cVal	Struct	MX		WW_vector1	M	
q	Quality	ST	qchg		M	
t	Timestamp	ST			M	

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
instCVal	Struct	MX		WW_vector1	O	
units	Struct	CF		WW_units1	O	
db	INT32U	CF			O	
dbAng	INT32U	CF			E	

3.1.5 WW_DEL2

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
DEL class						
phsAB	WW_CMV2					
phsBC	WW_CMV2					
phsCA	WW_CMV2					

3.1.6 WW_DPC1

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
DPC class						
stVal	Dbpos	ST	dchg	Dbpos	M	
q	Quality	ST	qchg		M	
t	Timestamp	ST			M	
ctlModel	Enum	CF		ctlModel	M	

3.1.7 WW_DPC2

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
DPC class						
origin	Struct	ST		WW_origin1	O	
ctlNum	INT8U	ST			O	
stVal	Dbpos	ST	dchg	Dbpos	M	
q	Quality	ST	qchg		M	
t	Timestamp	ST			M	
stSeld	BOOLEAN	ST	dchg		O	

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
ctlModel	Enum	CF		ctlModel	M	
sboTimeout	INT32U	CF			O	
sboClass	Enum	CF		sboClass	O	
cdcNs	VisString255	EX			O	
Oper	Struct	CO		WW_Oper1		
SBOw	Struct	CO		WW_Oper1		
Cancel	Struct	CO		WW_Cancel1		

3.1.8 WW_DPL1

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
DPL class						
vendor	VisString255	DC			M	

3.1.9 WW_INC1

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
INC class						
stVal	Enum	ST	dchg	Mode	M	
q	Quality	ST	qchg		M	
t	Timestamp	ST			M	
ctlModel	Enum	CF		ctlModel	M	

3.1.10 WW_INS1

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
INS class						
stVal	Enum	ST	dchg	Behaviour	M	
q	Quality	ST	qchg		M	
t	Timestamp	ST			M	

3.1.11 WW_INS2

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
INS class						
stVal	INT32	ST	dchg		M	
q	Quality	ST	qchg		M	
t	Timestamp	ST			M	

3.1.12 WW_INS3

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
INS class						
stVal	Enum	ST	dchg	AutoRecSt	M	
q	Quality	ST	qchg		M	
t	Timestamp	ST			M	

3.1.13 WW_INS4

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
INS class						
stVal	Enum	ST	dchg	Health	M	
q	Quality	ST	qchg		M	
t	Timestamp	ST			M	

3.1.14 WW_INS5

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
INS class						
stVal	Enum	ST	dchg	CBOpCap	M	
q	Quality	ST	qchg		M	
t	Timestamp	ST			M	

3.1.15 WW_LPL1

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
LPL class						
vendor	visString255	DC			M	
swRev	visString255	DC			M	
d	visString255	DC			M	

3.1.16 WW_LPL2

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
LPL class						
vendor	visString255	DC			M	
swRev	visString255	DC			M	
d	visString255	DC			M	
ldNs	visString255	EX				

3.1.17 WW_LPL3

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
LPL class						
vendor	visString255	DC			M	
swRev	visString255	DC			M	
d	visString255	DC			M	
LnNS	visString255	EX				

3.1.18 WW_MV1

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
MV class						
mag	Struct	MX		WW_analogValue1	M	
q	Quality	ST	qchg		M	
t	Timestamp	ST			M	
units	Struct	CF		WW_units1	O	

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
db	INT32U	CF			O	
d	visString255	DC			O	
dataNs	visString255	DC			O	

3.1.19 WW_SPC1

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
SPC class						
stVal	BOOLEAN	ST	dchg		M	
q	Quality	ST	dchg		M	
t	Timestamp	ST			M	
ctlModel	Enum	CF		ctlModel	M	

3.1.20 WW_SPC2

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
SPC class						
Oper	Struct	CO		WW_Oper1		
stVal	BOOLEAN	ST	dchg		M	
q	Quality	ST	dchg		M	
t	Timestamp	ST			M	
ctlModel	Enum	CF		ctlModel	M	

3.1.21 WW_SPS1

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
SPS class						
stVal	BOOLEAN	ST	dchg		M	
q	Quality	ST	qchg		M	
t	Timestamp	ST			M	

3.1.22 WW_WYE2

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
WYE class						
phsAB	WW_CMV2					
phsBC	WW_CMV2					
phsCA	WW_CMV2					
neut	WW_CMV2					

3.1.23 WW_WYE3

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
WYE class						
phsAB	WW_CMV2					
phsBC	WW_CMV2					
phsCA	WW_CMV2					

3.2 Common Data Attributes Type Definitions

3.2.1 WW_analogValue1

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
analogValue class						
f	FLOAT32	MX			M	

3.2.2 WW_Cancel1

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
Cancel class						
ctlval	BOOLEAN	CO			M	
origin	Struct	ST		WW_origin1	O	
ctlNum	INT8U	ST			O	
T	Timestamp	CO			O	
Test	BOOLEAN	CO			O	

3.2.3 WW_Oper1

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
Oper class						
ctlval	BOOLEAN	CO			M	
origin	Struct	ST		WW_origin1	O	
ctlNum	INT8U	ST			O	
T	Timestamp	CO			O	
Test	BOOLEAN	CO			O	
Check	Check	CO			O	

3.2.4 WW_origin1

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
origin class						
orCat	Enum	ST		orCategory	M	

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
orIdent	Octet64	ST			M	

3.2.5 WW_units1

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
unit class						
SIUnit	Enum			SIUnit	M	
multiplier	Enum			multiplier	O	

3.2.6 WW_vector1

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
vector class						
mag	Struct			WW_analogValue1	M	
ang	Struct			WW_analogValue1	O	

3.3 Enumerated type definitions

3.3.1 AutoRecSt

Ordinal	Semantic
1	Ready
2	InProgress
3	Successful

3.3.2 Beh

Ordinal	Semantic
1	on
2	blocked
3	test
4	test/blocked
5	off

3.3.3 CBOpCap

Ordinal	Semantic
1	None
2	Open
3	Close-Open
4	Open-Close-Open
5	Close-Open-Close-Open

3.3.4 ctIModel

Ordinal	Semantic
1	status-only
2	direct-with-normal-security
3	sbo-with-normal-security
4	direct-with-enhanced-security

Ordinal	Semantic
5	sbo-with-enhanced-security

3.3.5 Dbpos

Ordinal	Semantic
1	intermediate
2	off
3	on
4	bad

3.3.6 ACDDir

Ordinal	Semantic
0	unknown
1	forward
2	backward
3	both

3.3.7 Health

Ordinal	Semantic
1	Ok
2	Warning
3	Alarm

3.3.8 Mod

Ordinal	Semantic
1	on
2	blocked
3	test
4	test/block

Ordinal	Semantic
5	off

3.3.9 MotorCycle

Ordinal	Semantic
0	Trip/Off
1	Stop
2	Start
3	Run

3.3.10 multiplier

Ordinal	Semantic
-24	y
-21	z
-18	a
-15	f
-12	p
-9	n
-6	μ
-3	m
-2	c
-1	d
0	
1	da
2	h
3	k
6	M
9	G
12	T
15	P
18	E

Ordinal	Semantic
21	Z
24	Y

3.3.11 orCategory

Ordinal	Semantic
0	not-supported
1	bay-control
2	station-control
3	remote-control
4	automatic-bay
5	automatic-station
6	automatic-remote
7	maintenance
8	process

3.3.12 sboClass

Ordinal	Semantic
0	operate-once
1	operate-many

3.3.13 SIUnit

Ordinal	Semantic
1	none
2	m
3	kg
4	s
5	A
6	K
7	mol
8	cd

Ordinal	Semantic
9	deg
10	rad
11	sr
21	Gy
22	q
23	°C
24	Sv
25	F
26	C
27	S
28	H
29	V
30	ohm
31	J
32	N
33	Hz
34	lx
35	Lm
36	Wb
37	T
38	W
39	Pa
41	m ²
42	m ³
43	m/s
44	m/s ²
45	m ³ /s
46	m/m ³
47	M
48	kg/m ³
49	m ² /s
50	W/m K

Ordinal	Semantic
51	J/K
52	ppm
53	1/s
54	rad/s
61	VA
62	Watts
63	VAr
64	phi
65	cos(phi)
66	Vs
67	V ²
68	As
69	A ²
70	A ² t
71	VAh
72	Wh
73	VArh
74	V/Hz

4 Appendix

4.1 Register Maps

Legend: * The Logical Node is dependent on the settings in the “Device planning”. (See [↪ “4.2 Device Planning Dependencies”](#)).

LDevice::CTRL

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
CILO1* (WW_CILO1)		
	Mod	
	Beh	
	Health	
	NamPlt	
	EnaOpn	SG[1] . Interl OFF
	EnaCls	SG[1] . Interl ON

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
CILO2* (WW_CILO1)		
	Mod	
	Beh	
	Health	
	NamPlt	
	EnaOpn	SG[2] . Interl OFF
	EnaCls	SG[2] . Interl ON

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
CILO3* (WW_CILO1)		
	Mod	
	Beh	
	Health	
	NamPlt	
	EnaOpn	SG[3] . Interl OFF
	EnaCls	SG[3] . Interl ON

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
CILO4* (WW_CILO1)		
	Mod	
	Beh	
	Health	

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
CILO4* (WW_CILO1)		
	NamPlt	
	EnaOpn	SG[4] . Interl OFF
	EnaCls	SG[4] . Interl ON

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
CILO5* (WW_CILO1)		
	Mod	
	Beh	
	Health	
	NamPlt	
	EnaOpn	SG[5] . Interl OFF
	EnaCls	SG[5] . Interl ON

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
CILO6* (WW_CILO1)		
	Mod	
	Beh	
	Health	
	NamPlt	
	EnaOpn	SG[6] . Interl OFF
	EnaCls	SG[6] . Interl ON

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
CSWI1* (WW_CSWI1)		
	Mod	
	Beh	
	Health	
	NamPlt	
	Loc	
	Pos	SG[1] . Pos

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
CSWI2* (WW_CSWI1)		
	Mod	
	Beh	
	Health	
	NamPlt	

4 Appendix
4.1 Register Maps

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
CSWI2* (WW_CSWI1)		
	Loc	
	Pos	SG[2] . Pos

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
CSWI3* (WW_CSWI1)		
	Mod	
	Beh	
	Health	
	NamPlt	
	Loc	
	Pos	SG[3] . Pos

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
CSWI4* (WW_CSWI1)		
	Mod	
	Beh	
	Health	
	NamPlt	
	Loc	
	Pos	SG[4] . Pos

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
CSWI5* (WW_CSWI1)		
	Mod	
	Beh	
	Health	
	NamPlt	
	Loc	
	Pos	SG[5] . Pos

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
CSWI6* (WW_CSWI1)		
	Mod	
	Beh	
	Health	
	NamPlt	
	Loc	

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
CSWI6* (WW_CSWI1)		
	Pos	SG[6] . Pos

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
LLN0 (WW_LLNOCON)		
	Mod	
	Beh	
	Health	
	NamPlt	

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
LPHD1 (WW_LPHDCON)		
	PhyNam	
	PhyHealth	
	Proxy	

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
TCSSCBR1 (WW_SCBR1)		
	Mod	TCS - 74TC . active
	Beh	
	Health	
	NamPlt	
	TrCctAlm	TCS - 74TC . Alarm

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
XCBR1* (WW_XCBR2)		
	Mod	
	Beh	
	Health	
	NamPlt	
	Loc	
	OpCnt	
	Pos	SG[1] . Pos
	BlkOpn	
	BlkCls	
	CBOpCap	

4 Appendix
 4.1 Register Maps

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
XCBR2* (WW_XCBR2)		
	Mod	
	Beh	
	Health	
	NamPlt	
	Loc	
	OpCnt	
	Pos	SG[2] . Pos
	BlkOpn	
	BlkCls	
	CBOpCap	

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
XCBR3* (WW_XCBR2)		
	Mod	
	Beh	
	Health	
	NamPlt	
	Loc	
	OpCnt	
	Pos	SG[3] . Pos
	BlkOpn	
	BlkCls	
	CBOpCap	

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
XCBR4* (WW_XCBR2)		
	Mod	
	Beh	
	Health	
	NamPlt	
	Loc	
	OpCnt	
	Pos	SG[4] . Pos
	BlkOpn	
	BlkCls	
	CBOpCap	

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
XCBR5* (WW_XCBR2)		
	Mod	
	Beh	
	Health	
	NamPlt	
	Loc	
	OpCnt	
	Pos	SG[5] . Pos
	BlkOpn	
	BlkCls	
	CBOpCap	

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
XCBR6* (WW_XCBR2)		
	Mod	
	Beh	
	Health	
	NamPlt	
	Loc	
	OpCnt	
	Pos	SG[6] . Pos
	BlkOpn	
	BlkCls	
	CBOpCap	

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
XSWI1* (WW_XSWI1)		
	Mod	
	Beh	
	Health	
	NamPlt	
	Loc	
	OpCnt	
	Pos	SG[1] . Pos
	BlkOpn	
	BlkCls	
	SwTyp	
	SwOpCap	

4 Appendix
4.1 Register Maps

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
XSWI2* (WW_XSWI1)		
	Mod	
	Beh	
	Health	
	NamPlt	
	Loc	
	OpCnt	
	Pos	SG[2] . Pos
	BlkOpn	
	BlkCls	
	SwTyp	
	SwOpCap	

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
XSWI3* (WW_XSWI1)		
	Mod	
	Beh	
	Health	
	NamPlt	
	Loc	
	OpCnt	
	Pos	SG[3] . Pos
	BlkOpn	
	BlkCls	
	SwTyp	
	SwOpCap	

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
XSWI4* (WW_XSWI1)		
	Mod	
	Beh	
	Health	
	NamPlt	
	Loc	
	OpCnt	
	Pos	SG[4] . Pos
	BlkOpn	
	BlkCls	

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
XSWI4* (WW_XSWI1)		
	SwTyp	
	SwOpCap	

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
XSWI5* (WW_XSWI1)		
	Mod	
	Beh	
	Health	
	NamPlt	
	Loc	
	OpCnt	
	Pos	SG[5] . Pos
	BlkOpn	
	BlkCls	
	SwTyp	
	SwOpCap	

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
XSWI6* (WW_XSWI1)		
	Mod	
	Beh	
	Health	
	NamPlt	
	Loc	
	OpCnt	
	Pos	SG[6] . Pos
	BlkOpn	
	BlkCls	
	SwTyp	
	SwOpCap	

LDevice::DR

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
LLN0 (WW_LLNOREC)		
	Mod	
	Beh	
	Health	

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
LLN0 (WW_LLNOREC)		
	NamPlt	

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
LPHD1 (WW_LPHDREC)		
	PhyNam	
	PhyHealth	
	Proxy	

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
RDRE1 (WW_RDRE1)		
	Mod	
	Beh	
	Health	
	NamPlt	
	RcdMade	Disturb rec . recording
	FltNum	
	GriFltNum	
	RcdStr	Disturb rec . recording

LDevice::EXT

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
COUFGGIO1 (WW_GGIO4)		
	Mod	
	Beh	
	Health	
	NamPlt	
	Ind1	IEC 61850 . COUFGGIO1.Ind1.stVal-I
	Ind2	IEC 61850 . COUFGGIO1.Ind2.stVal-I
	Ind3	IEC 61850 . COUFGGIO1.Ind3.stVal-I
	Ind4	IEC 61850 . COUFGGIO1.Ind4.stVal-I
	Ind5	IEC 61850 . COUFGGIO1.Ind5.stVal-I
	Ind6	IEC 61850 . COUFGGIO1.Ind6.stVal-I
	Ind7	IEC 61850 . COUFGGIO1.Ind7.stVal-I
	Ind8	IEC 61850 . COUFGGIO1.Ind8.stVal-I
	Ind9	IEC 61850 . COUFGGIO1.Ind9.stVal-I
	Ind10	IEC 61850 . COUFGGIO1.Ind10.stVal-I
	Ind11	IEC 61850 . COUFGGIO1.Ind11.stVal-I

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
COUFGGIO1 (WW_GGIO4)		
	Ind12	IEC 61850 . COUFGGIO1.Ind12.stVal-I
	Ind13	IEC 61850 . COUFGGIO1.Ind13.stVal-I
	Ind14	IEC 61850 . COUFGGIO1.Ind14.stVal-I
	Ind15	IEC 61850 . COUFGGIO1.Ind15.stVal-I
	Ind16	IEC 61850 . COUFGGIO1.Ind16.stVal-I
	Ind17	IEC 61850 . COUFGGIO1.Ind17.stVal-I
	Ind18	IEC 61850 . COUFGGIO1.Ind18.stVal-I
	Ind19	IEC 61850 . COUFGGIO1.Ind19.stVal-I
	Ind20	IEC 61850 . COUFGGIO1.Ind20.stVal-I
	Ind21	IEC 61850 . COUFGGIO1.Ind21.stVal-I
	Ind22	IEC 61850 . COUFGGIO1.Ind22.stVal-I
	Ind23	IEC 61850 . COUFGGIO1.Ind23.stVal-I
	Ind24	IEC 61850 . COUFGGIO1.Ind24.stVal-I
	Ind25	IEC 61850 . COUFGGIO1.Ind25.stVal-I
	Ind26	IEC 61850 . COUFGGIO1.Ind26.stVal-I
	Ind27	IEC 61850 . COUFGGIO1.Ind27.stVal-I
	Ind28	IEC 61850 . COUFGGIO1.Ind28.stVal-I
	Ind29	IEC 61850 . COUFGGIO1.Ind29.stVal-I
	Ind30	IEC 61850 . COUFGGIO1.Ind30.stVal-I
	Ind31	IEC 61850 . COUFGGIO1.Ind31.stVal-I
	Ind32	IEC 61850 . COUFGGIO1.Ind32.stVal-I

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
COUFGGIO2 (WW_GGIO4)		
	Mod	
	Beh	
	Health	
	NamPlt	
	Ind1	IEC 61850 . COUFGGIO2.Ind1.stVal-I
	Ind2	IEC 61850 . COUFGGIO2.Ind2.stVal-I
	Ind3	IEC 61850 . COUFGGIO2.Ind3.stVal-I
	Ind4	IEC 61850 . COUFGGIO2.Ind4.stVal-I
	Ind5	IEC 61850 . COUFGGIO2.Ind5.stVal-I
	Ind6	IEC 61850 . COUFGGIO2.Ind6.stVal-I
	Ind7	IEC 61850 . COUFGGIO2.Ind7.stVal-I
	Ind8	IEC 61850 . COUFGGIO2.Ind8.stVal-I
	Ind9	IEC 61850 . COUFGGIO2.Ind9.stVal-I

4 Appendix
 4.1 Register Maps

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
COUFGGIO2 (WW_GGIO4)		
	Ind10	IEC 61850 . COUFGGIO2.Ind10.stVal-I
	Ind11	IEC 61850 . COUFGGIO2.Ind11.stVal-I
	Ind12	IEC 61850 . COUFGGIO2.Ind12.stVal-I
	Ind13	IEC 61850 . COUFGGIO2.Ind13.stVal-I
	Ind14	IEC 61850 . COUFGGIO2.Ind14.stVal-I
	Ind15	IEC 61850 . COUFGGIO2.Ind15.stVal-I
	Ind16	IEC 61850 . COUFGGIO2.Ind16.stVal-I
	Ind17	IEC 61850 . COUFGGIO2.Ind17.stVal-I
	Ind18	IEC 61850 . COUFGGIO2.Ind18.stVal-I
	Ind19	IEC 61850 . COUFGGIO2.Ind19.stVal-I
	Ind20	IEC 61850 . COUFGGIO2.Ind20.stVal-I
	Ind21	IEC 61850 . COUFGGIO2.Ind21.stVal-I
	Ind22	IEC 61850 . COUFGGIO2.Ind22.stVal-I
	Ind23	IEC 61850 . COUFGGIO2.Ind23.stVal-I
	Ind24	IEC 61850 . COUFGGIO2.Ind24.stVal-I
	Ind25	IEC 61850 . COUFGGIO2.Ind25.stVal-I
	Ind26	IEC 61850 . COUFGGIO2.Ind26.stVal-I
	Ind27	IEC 61850 . COUFGGIO2.Ind27.stVal-I
	Ind28	IEC 61850 . COUFGGIO2.Ind28.stVal-I
	Ind29	IEC 61850 . COUFGGIO2.Ind29.stVal-I
	Ind30	IEC 61850 . COUFGGIO2.Ind30.stVal-I
	Ind31	IEC 61850 . COUFGGIO2.Ind31.stVal-I
	Ind32	IEC 61850 . COUFGGIO2.Ind32.stVal-I

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
CTLGGIO1 (WW_GGIO14)		
	Mod	
	Beh	
	Health	
	NamPlt	
	SPCSO1	
	SPCSO2	
	SPCSO3	
	SPCSO4	
	SPCSO5	
	SPCSO6	
	SPCSO7	

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
CTLGGIO1 (WW_GGIO14)		
	SPCSO8	
	SPCSO9	
	SPCSO10	
	SPCSO11	
	SPCSO12	
	SPCSO13	
	SPCSO14	
	SPCSO15	
	SPCSO16	
	SPCSO17	
	SPCSO18	
	SPCSO19	
	SPCSO20	
	SPCSO21	
	SPCSO22	
	SPCSO23	
	SPCSO24	
	SPCSO25	
	SPCSO26	
	SPCSO27	
	SPCSO28	
	SPCSO29	
	SPCSO30	
	SPCSO31	
	SPCSO32	

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
EPGAPC1 (WW_GAPC1)		
	Mod	Intertripping . active Intertripping . Blo TripCmd Intertripping . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	Intertripping . Alarm
	Op	Intertripping . Trip

4 Appendix
4.1 Register Maps

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
EPGAPC10 (WW_GAPC1)		
	Mod	Ext Temp Superv[3] . active Ext Temp Superv[3] . Blo TripCmd Ext Temp Superv[3] . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	Ext Temp Superv[3] . Alarm
	Op	Ext Temp Superv[3] . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
EPGAPC2 (WW_GAPC1)		
	Mod	Exp[1] . active Exp[1] . Blo TripCmd Exp[1] . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	Exp[1] . Alarm
	Op	Exp[1] . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
EPGAPC3 (WW_GAPC1)		
	Mod	Exp[2] . active Exp[2] . Blo TripCmd Exp[2] . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	Exp[2] . Alarm
	Op	Exp[2] . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
EPGAPC4 (WW_GAPC1)		
	Mod	Exp[3] . active Exp[3] . Blo TripCmd Exp[3] . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	Exp[3] . Alarm
	Op	Exp[3] . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
EPGAPC5 (WW_GAPC1)		
	Mod	Exp[4] . active Exp[4] . Blo TripCmd Exp[4] . ExBlo TripCmd

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
EPGAPC5 (WW_GAPC1)		
	Beh	
	Health	
	NamPlt	
	Str	ExpP[4] . Alarm
	Op	ExpP[4] . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
EPGAPC6 (WW_GAPC1)		
	Mod	Ext Sudd Press . active Ext Sudd Press . Blo TripCmd Ext Sudd Press . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	Ext Sudd Press . Alarm
	Op	Ext Sudd Press . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
EPGAPC7 (WW_GAPC1)		
	Mod	Ext Oil Temp . active Ext Oil Temp . Blo TripCmd Ext Oil Temp . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	Ext Oil Temp . Alarm
	Op	Ext Oil Temp . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
EPGAPC8 (WW_GAPC1)		
	Mod	Ext Temp Superv[1] . active Ext Temp Superv[1] . Blo TripCmd Ext Temp Superv[1] . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	Ext Temp Superv[1] . Alarm
	Op	Ext Temp Superv[1] . Trip

4 Appendix
 4.1 Register Maps

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
EPGAPC9 (WW_GAPC1)		
	Mod	Ext Temp Superv[2] . active Ext Temp Superv[2] . Blo TripCmd Ext Temp Superv[2] . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	Ext Temp Superv[2] . Alarm
	Op	Ext Temp Superv[2] . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
GOSINGGIO1 (WW_GGIO11)		
	Mod	
	Beh	
	Health	
	NamPlt	
	Ind1	
	Ind2	
	Ind3	
	Ind4	
	Ind5	
	Ind6	
	Ind7	
	Ind8	
	Ind9	
	Ind10	
	Ind11	
	Ind12	
	Ind13	
	Ind14	
	Ind15	
	Ind16	
	Ind17	
	Ind18	
	Ind19	
	Ind20	
	Ind21	
	Ind22	
	Ind23	

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
GOSINGGIO1 (WW_GGIO11)		
	Ind24	
	Ind25	
	Ind26	
	Ind27	
	Ind28	
	Ind29	
	Ind30	
	Ind31	
	Ind32	

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
GOSINGGIO2 (WW_GGIO10)		
	Mod	
	Beh	
	Health	
	NamPlt	
	Ind1	
	Ind2	
	Ind3	
	Ind4	
	Ind5	
	Ind6	
	Ind7	
	Ind8	
	Ind9	
	Ind10	
	Ind11	
	Ind12	
	Ind13	
	Ind14	
	Ind15	
	Ind16	
	Ind17	
	Ind18	
	Ind19	
	Ind20	
	Ind21	

4 Appendix
4.1 Register Maps

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
GOSINGGIO2 (WW_GGIO10)		
	Ind22	
	Ind23	
	Ind24	
	Ind25	
	Ind26	
	Ind27	
	Ind28	
	Ind29	
	Ind30	
	Ind31	
	Ind32	

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
LLN0 (WW_LLNSYS)		
	Mod	
	Beh	
	Health	
	NamPlt	

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
LPHD1 (WW_LPHDSYS)		
	PhyNam	
	PhyHealth	
	Proxy	

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
TSGGIO1 (WW_GGIO1)		
	Mod	Sig-Trans - 85 . active
	Beh	
	Health	
	NamPlt	
	Ind1	Sig-Trans - 85 . Rx.Signal1
	Ind2	Sig-Trans - 85 . Rx.Signal2
	Ind3	Sig-Trans - 85 . Rx.Signal3
	Ind4	Sig-Trans - 85 . Rx.Signal4
	Ind5	Sig-Trans - 85 . Rx.Signal5
	Ind6	Sig-Trans - 85 . Rx.Signal6

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
TSGGIO1 (WW_GGIO1)		
	Ind7	Sig-Trans - 85 . Rx.Signal7
	Ind8	Sig-Trans - 85 . Rx.Signal8
	Ind9	Sig-Trans - 85 . Rx.Signal9
	Ind10	Sig-Trans - 85 . Rx.Signal10
	Ind11	Sig-Trans - 85 . Rx.Signal11
	Ind12	Sig-Trans - 85 . Rx.Signal12
	Ind13	Sig-Trans - 85 . Rx.Signal13
	Ind14	Sig-Trans - 85 . Rx.Signal14
	Ind15	Sig-Trans - 85 . Rx.Signal15
	Ind16	Sig-Trans - 85 . Rx.Signal16

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
TTGGIO1 (WW_GGIO6)		
	Mod	
	Beh	
	Health	
	NamPlt	
	Ind1	Trip-Trans - 85 . Rx.Trip1.Input
	Ind2	Trip-Trans - 85 . Rx.Trip2.Input
	Ind3	Trip-Trans - 85 . Rx.Trip3.Input
	Ind4	Trip-Trans - 85 . Rx.Trip4.Input

LDevice::MEAS

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
CMMXU1 (WW_MMXU7)		
	Mod	
	Beh	
	Health	
	NamPlt	
	A	CT Local . IL1 RMS CT Local . phi IL1 CT Local . IL2 RMS CT Local . phi IL2 CT Local . IL3 RMS CT Local . phi IL3 CT Local . IG meas RMS CT Local . phi IG meas CT Local . IG calc RMS CT Local . phi IG calc

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
CMSTA1 (WW_MSTA1)		
	Mod	
	Beh	

4 Appendix
4.1 Register Maps

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
CMSTA1 (WW_MSTA1)		
	Health	
	NamPlt	
	AvAPhsA	CT Local . IL1 avg
	AvAPhsB	CT Local . IL2 avg
	AvAPhsC	CT Local . IL3 avg
	MaxAPhsA	CT Local . IL1 max
	MaxAPhsB	CT Local . IL2 max
	MaxAPhsC	CT Local . IL3 max
	MinAPhsA	CT Local . IL1 min
	MinAPhsB	CT Local . IL2 min
	MinAPhsC	CT Local . IL3 min

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
ECMMTR1 (WW_MMTR1)		
	Mod	
	Beh	
	Health	
	NamPlt	
	SupWh	PQSCr . Wp+
	DmdWh	PQSCr . Wp-
	SupVArh	PQSCr . Wq+
	DmdVArh	PQSCr . Wq-
	TotWh	PQSCr . Wp Net
	TotVArh	PQSCr . Wq Net
	TotVAh	PQSCr . Ws Net

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
LLNO (WW_LLNO MEA)		
	Mod	
	Beh	
	Health	
	NamPlt	

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
LPHD1 (WW_LPHD MEA)		
	PhyNam	
	PhyHealth	

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
LPHD1 (WW_LPHDMEA)		
	Proxy	

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PMMXU1 (WW_MMXU3)		
	Mod	
	Beh	
	Health	
	NamPlt	
	TotW	PQSCr . P RMS
	TotVAr	PQSCr . Q
	TotVA	PQSCr . S RMS
	TotPF	PQSCr . cos phi RMS

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PMSTA1 (WW_MSTA3)		
	Mod	
	Beh	
	Health	
	NamPlt	
	AvVA	PQSCr . S avg (Demand)
	MaxVA	PQSCr . S max
	MinVA	PQSCr . S min
	AvW	PQSCr . P avg
	MaxW	PQSCr . P max
	MinW	PQSCr . P min
	AvVAr	PQSCr . Q avg (Demand)
	MaxVAr	PQSCr . Q max
	MinVAr	PQSCr . Q min

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
RCMMXU1 (WW_MMXU8)		
	Mod	
	Beh	
	Health	
	NamPlt	
	A	CT Remote . IL1 CT Remote . phi IL1 CT Remote . IL2 CT Remote . phi IL2 CT Remote . IL3 CT Remote . phi IL3

4 Appendix
4.1 Register Maps

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
VMMXU1 (WW_MMXU6)		
	Mod	
	Beh	
	Health	
	NamPlt	
	PPV	VT . VL12 RMS VT . phi VL12 VT . VL23 RMS VT . phi VL23 VT . VL31 RMS VT . phi VL31
	PhV	VT . VL1 RMS VT . phi VL1 VT . VL2 RMS VT . phi VL2 VT . VL3 RMS VT . phi VL3 VT . VX meas RMS VT . phi VX meas VT . VG calc RMS VT . phi VG calc
	Hz	VT . f

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
VMSTA1 (WW_MSTA2)		
	Mod	
	Beh	
	Health	
	NamPlt	
	AvVPhsAB	VT . VL12 avg
	AvVPhsBC	VT . VL23 avg
	AvVPhsCA	VT . VL31 avg
	MaxVPhsAB	VT . VL12 max
	MaxVPhsBC	VT . VL23 max
	MaxVPhsCA	VT . VL31 max
	MinVPhsAB	VT . VL12 min
	MinVPhsBC	VT . VL23 min
	MinVPhsCA	VT . VL31 min
	AvVPhsA	VT . VL1 avg
	AvVPhsB	VT . VL2 avg
	AvVPhsC	VT . VL3 avg
	MaxVPhsA	VT . VL1 max
	MaxVPhsB	VT . VL2 max
	MaxVPhsC	VT . VL3 max
	MinVPhsA	VT . VL1 min
	MinVPhsB	VT . VL2 min
	MinVPhsC	VT . VL3 min

LDevice::PROT

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
GFPTOC1 (WW_PTOC3)		
	Mod	IG[1] - 50N, 51N . active IG[1] - 50N, 51N . Blo TripCmd IG[1] - 50N, 51N . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	IG[1] - 50N, 51N . Alarm
	Op	IG[1] - 50N, 51N . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
GFPTOC2 (WW_PTOC3)		
	Mod	IG[2] - 50N, 51N . active IG[2] - 50N, 51N . Blo TripCmd IG[2] - 50N, 51N . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	IG[2] - 50N, 51N . Alarm
	Op	IG[2] - 50N, 51N . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
GFPTOC3 (WW_PTOC3)		
	Mod	IG[3] - 50N, 51N . active IG[3] - 50N, 51N . Blo TripCmd IG[3] - 50N, 51N . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	IG[3] - 50N, 51N . Alarm
	Op	IG[3] - 50N, 51N . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
GFPTOC4 (WW_PTOC3)		
	Mod	IG[4] - 50N, 51N . active IG[4] - 50N, 51N . Blo TripCmd IG[4] - 50N, 51N . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	IG[4] - 50N, 51N . Alarm
	Op	IG[4] - 50N, 51N . Trip

4 Appendix
4.1 Register Maps

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
GPDIF1 (WW_PDIF3)		
	Mod	IdGH - 87N . active IdGH - 87N . Blo TripCmd IdGH - 87N . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	IdGH - 87N . Alarm
	Op	IdGH - 87N . TripCmd

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
HRGPDIF1 (WW_PDIF4)		
	Mod	IdH - 87 . active IdH - 87 . Blo TripCmd IdH - 87 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	IdH - 87 . Alarm
	Op	IdH - 87 . TripCmd

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
HSPPDIF1 (WW_PDIF2)		
	Mod	IdG - 87N . active IdG - 87N . Blo TripCmd IdG - 87N . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	IdG - 87N . Alarm
	Op	IdG - 87N . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
IHMI1 (WW_IHMI1)		
	Mod	
	Beh	
	Health	
	NamPlt	

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
INRPHAR1 (WW_PHAR1)		
	Mod	IH2 . active
	Beh	

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
INRPHAR1 (WW_PHAR1)		
	Health	
	NamPlt	
	Str	IH2 . 3-ph Blo

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
ITPC1 (WW_ITPC1)		
	Mod	ProtCom . active ProtCom . inactive ProtCom . ExBlo
	Beh	
	Health	
	NamPlt	
	SynOk	ProtCom . Comm.Ok
	FrSyn	ProtCom . FrameSync
	TmSyn	ProtCom . TimeSync

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
LLN0 (WW_LLNOPRO)		
	Mod	
	Beh	
	Health	
	NamPlt	

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
LPHD1 (WW_LPHDPRO)		
	PhyNam	
	PhyHealth	
	Proxy	

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
LSPFDPFRC1 (WW_PFRC2)		
	Mod	UFLS . active UFLS . ExBlo UFLS . Fuse Fail VT Blo
	Beh	
	Health	
	NamPlt	
	Str	UFLS . Alarm
	Op	UFLS . Trip

4 Appendix
4.1 Register Maps

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
OEVPVPH1* (WW_PVPH1)		
	Mod	V/f>[1] - 24 . active V/f>[1] - 24 . Blo TripCmd V/f>[1] - 24 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V/f>[1] - 24 . Alarm
	Op	V/f>[1] - 24 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
OEVPVPH2* (WW_PVPH1)		
	Mod	V/f>[2] - 24 . active V/f>[2] - 24 . Blo TripCmd V/f>[2] - 24 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V/f>[2] - 24 . Alarm
	Op	V/f>[2] - 24 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PDOP1* (WW_PDOP1)		
	Mod	P - 32R . active P - 32R . Blo TripCmd P - 32R . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	P - 32R . Alarm
	Op	P - 32R . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PDOP2* (WW_PDOP1)		
	Mod	Q - 32 . active Q - 32 . Blo TripCmd Q - 32 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	Q - 32 . Alarm
	Op	Q - 32 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PDOP3* (WW_PDOP1)		
	Mod	PQS[1] - 32, 37 . active PQS[1] - 32, 37 . Blo TripCmd PQS[1] - 32, 37 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	PQS[1] - 32, 37 . Alarm
	Op	PQS[1] - 32, 37 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PDOP4* (WW_PDOP1)		
	Mod	PQS[2] - 32, 37 . active PQS[2] - 32, 37 . Blo TripCmd PQS[2] - 32, 37 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	PQS[2] - 32, 37 . Alarm
	Op	PQS[2] - 32, 37 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PDOP5* (WW_PDOP1)		
	Mod	PQS[3] - 32, 37 . active PQS[3] - 32, 37 . Blo TripCmd PQS[3] - 32, 37 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	PQS[3] - 32, 37 . Alarm
	Op	PQS[3] - 32, 37 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PDOP6* (WW_PDOP1)		
	Mod	PQS[4] - 32, 37 . active PQS[4] - 32, 37 . Blo TripCmd PQS[4] - 32, 37 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	PQS[4] - 32, 37 . Alarm
	Op	PQS[4] - 32, 37 . Trip

4 Appendix
4.1 Register Maps

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PDOP7* (WW_PDOP1)		
	Mod	PQS[5] - 32, 37 . active PQS[5] - 32, 37 . Blo TripCmd PQS[5] - 32, 37 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	PQS[5] - 32, 37 . Alarm
	Op	PQS[5] - 32, 37 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PDOP8* (WW_PDOP1)		
	Mod	PQS[6] - 32, 37 . active PQS[6] - 32, 37 . Blo TripCmd PQS[6] - 32, 37 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	PQS[6] - 32, 37 . Alarm
	Op	PQS[6] - 32, 37 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PDUP1* (WW_PDUP1)		
	Mod	P - 32R . active P - 32R . Blo TripCmd P - 32R . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	P - 32R . Alarm
	Op	P - 32R . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PDUP2* (WW_PDUP1)		
	Mod	Q - 32 . active Q - 32 . Blo TripCmd Q - 32 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	Q - 32 . Alarm
	Op	Q - 32 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PDUP3* (WW_PDUP1)		
	Mod	PQS[1] - 32, 37 . active PQS[1] - 32, 37 . Blo TripCmd PQS[1] - 32, 37 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	PQS[1] - 32, 37 . Alarm
	Op	PQS[1] - 32, 37 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PDUP4* (WW_PDUP1)		
	Mod	PQS[2] - 32, 37 . active PQS[2] - 32, 37 . Blo TripCmd PQS[2] - 32, 37 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	PQS[2] - 32, 37 . Alarm
	Op	PQS[2] - 32, 37 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PDUP5* (WW_PDUP1)		
	Mod	PQS[3] - 32, 37 . active PQS[3] - 32, 37 . Blo TripCmd PQS[3] - 32, 37 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	PQS[3] - 32, 37 . Alarm
	Op	PQS[3] - 32, 37 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PDUP6* (WW_PDUP1)		
	Mod	PQS[4] - 32, 37 . active PQS[4] - 32, 37 . Blo TripCmd PQS[4] - 32, 37 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	PQS[4] - 32, 37 . Alarm
	Op	PQS[4] - 32, 37 . Trip

4 Appendix
4.1 Register Maps

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PDUP7* (WW_PDUP1)		
	Mod	PQS[5] - 32, 37 . active PQS[5] - 32, 37 . Blo TripCmd PQS[5] - 32, 37 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	PQS[5] - 32, 37 . Alarm
	Op	PQS[5] - 32, 37 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PDUP8* (WW_PDUP1)		
	Mod	PQS[6] - 32, 37 . active PQS[6] - 32, 37 . Blo TripCmd PQS[6] - 32, 37 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	PQS[6] - 32, 37 . Alarm
	Op	PQS[6] - 32, 37 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PFRC1* (WW_PFRC1)		
	Mod	df/dt - 81R . active df/dt - 81R . Blo TripCmd df/dt - 81R . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	df/dt - 81R . Alarm
	Op	df/dt - 81R . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PFRC2* (WW_PFRC1)		
	Mod	delta phi - 78V . active delta phi - 78V . Blo TripCmd delta phi - 78V . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	delta phi - 78V . Alarm
	Op	delta phi - 78V . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PFRC3* (WW_PFRC1)		
	Mod	f[1] - 81 . active f[1] - 81 . Blo TripCmd f[1] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[1] - 81 . Alarm
	Op	f[1] - 81 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PFRC4* (WW_PFRC1)		
	Mod	f[2] - 81 . active f[2] - 81 . Blo TripCmd f[2] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[2] - 81 . Alarm
	Op	f[2] - 81 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PFRC5* (WW_PFRC1)		
	Mod	f[3] - 81 . active f[3] - 81 . Blo TripCmd f[3] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[3] - 81 . Alarm
	Op	f[3] - 81 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PFRC6* (WW_PFRC1)		
	Mod	f[4] - 81 . active f[4] - 81 . Blo TripCmd f[4] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[4] - 81 . Alarm
	Op	f[4] - 81 . Trip

4 Appendix
4.1 Register Maps

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PFRC7* (WW_PFRC1)		
	Mod	f[5] - 81 . active f[5] - 81 . Blo TripCmd f[5] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[5] - 81 . Alarm
	Op	f[5] - 81 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PFRC8* (WW_PFRC1)		
	Mod	f[6] - 81 . active f[6] - 81 . Blo TripCmd f[6] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[6] - 81 . Alarm
	Op	f[6] - 81 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PPAM1* (WW_PPAM1)		
	Mod	df/dt - 81R . active df/dt - 81R . Blo TripCmd df/dt - 81R . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	df/dt - 81R . Alarm
	Op	df/dt - 81R . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PPAM2* (WW_PPAM1)		
	Mod	delta phi - 78V . active delta phi - 78V . Blo TripCmd delta phi - 78V . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	delta phi - 78V . Alarm
	Op	delta phi - 78V . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PPAM3* (WW_PPAM1)		
	Mod	f[1] - 81 . active f[1] - 81 . Blo TripCmd f[1] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[1] - 81 . Alarm
	Op	f[1] - 81 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PPAM4* (WW_PPAM1)		
	Mod	f[2] - 81 . active f[2] - 81 . Blo TripCmd f[2] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[2] - 81 . Alarm
	Op	f[2] - 81 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PPAM5* (WW_PPAM1)		
	Mod	f[3] - 81 . active f[3] - 81 . Blo TripCmd f[3] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[3] - 81 . Alarm
	Op	f[3] - 81 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PPAM6* (WW_PPAM1)		
	Mod	f[4] - 81 . active f[4] - 81 . Blo TripCmd f[4] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[4] - 81 . Alarm
	Op	f[4] - 81 . Trip

4 Appendix
4.1 Register Maps

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PPAM7* (WW_PPAM1)		
	Mod	f[5] - 81 . active f[5] - 81 . Blo TripCmd f[5] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[5] - 81 . Alarm
	Op	f[5] - 81 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PPAM8* (WW_PPAM1)		
	Mod	f[6] - 81 . active f[6] - 81 . Blo TripCmd f[6] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[6] - 81 . Alarm
	Op	f[6] - 81 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PPDIF1 (WW_PDIF1)		
	Mod	Id - 87 . active Id - 87 . Blo TripCmd Id - 87 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	Id - 87 . Alarm
	Op	Id - 87 . TripCmd

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PRTT1 (WW_PRTT1)		
	Mod	Trip-Trans - 85 . active Trip-Trans - 85 . Blo TripCmd Trip-Trans - 85 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Op	Trip-Trans - 85 . Trip
	PerTr1	Trip-Trans - 85 . Rx.Trip1.Permissive
	PerTr2	Trip-Trans - 85 . Rx.Trip2.Permissive
	PerTr3	Trip-Trans - 85 . Rx.Trip3.Permissive
	PerTr4	Trip-Trans - 85 . Rx.Trip4.Permissive

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PRTT1 (WW_PRTT1)		
	RemTr1	Trip-Trans - 85 . Rx.Trip1
	RemTr2	Trip-Trans - 85 . Rx.Trip2
	RemTr3	Trip-Trans - 85 . Rx.Trip3
	RemTr4	Trip-Trans - 85 . Rx.Trip4

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PSDE1 (WW_PSDE1)		
	Mod	VT . IG meas dir wattm
	Beh	
	Health	
	NamPlt	
	Str	

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PSDE2 (WW_PSDE2)		
	Mod	VT . IG calc dir wattm
	Beh	
	Health	
	NamPlt	
	Str	

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PSOF1 (WW_PSOF1)		
	Mod	SOTF . active SOTF . ExBlo SOTF . Ex rev Interl
	Beh	
	Health	
	NamPlt	
	Str	SOTF . enabled

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTOC1 (WW_PTOC1)		
	Mod	I[1] - 50, 51 . active I[1] - 50, 51 . Blo TripCmd I[1] - 50, 51 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	I[1] - 50, 51 . Alarm
	Op	I[1] - 50, 51 . Trip

4 Appendix
4.1 Register Maps

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTOC2 (WW_PTOC1)		
	Mod	I[2] - 50, 51 . active I[2] - 50, 51 . Blo TripCmd I[2] - 50, 51 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	I[2] - 50, 51 . Alarm
	Op	I[2] - 50, 51 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTOC3 (WW_PTOC1)		
	Mod	I[3] - 50, 51 . active I[3] - 50, 51 . Blo TripCmd I[3] - 50, 51 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	I[3] - 50, 51 . Alarm
	Op	I[3] - 50, 51 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTOC4 (WW_PTOC1)		
	Mod	I[4] - 50, 51 . active I[4] - 50, 51 . Blo TripCmd I[4] - 50, 51 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	I[4] - 50, 51 . Alarm
	Op	I[4] - 50, 51 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTOC5 (WW_PTOC1)		
	Mod	I[5] - 50, 51 . active I[5] - 50, 51 . Blo TripCmd I[5] - 50, 51 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	I[5] - 50, 51 . Alarm
	Op	I[5] - 50, 51 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTOC6 (WW_PTOC1)		
	Mod	I[6] - 50, 51 . active I[6] - 50, 51 . Blo TripCmd I[6] - 50, 51 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	I[6] - 50, 51 . Alarm
	Op	I[6] - 50, 51 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTOF1* (WW_PTOF1)		
	Mod	df/dt - 81R . active df/dt - 81R . Blo TripCmd df/dt - 81R . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	df/dt - 81R . Alarm
	Op	df/dt - 81R . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTOF2* (WW_PTOF1)		
	Mod	delta phi - 78V . active delta phi - 78V . Blo TripCmd delta phi - 78V . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	delta phi - 78V . Alarm
	Op	delta phi - 78V . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTOF3* (WW_PTOF1)		
	Mod	f[1] - 81 . active f[1] - 81 . Blo TripCmd f[1] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[1] - 81 . Alarm
	Op	f[1] - 81 . Trip

4 Appendix
 4.1 Register Maps

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTOF4* (WW_PTOF1)		
	Mod	f[2] - 81 . active f[2] - 81 . Blo TripCmd f[2] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[2] - 81 . Alarm
	Op	f[2] - 81 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTOF5* (WW_PTOF1)		
	Mod	f[3] - 81 . active f[3] - 81 . Blo TripCmd f[3] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[3] - 81 . Alarm
	Op	f[3] - 81 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTOF6* (WW_PTOF1)		
	Mod	f[4] - 81 . active f[4] - 81 . Blo TripCmd f[4] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[4] - 81 . Alarm
	Op	f[4] - 81 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTOF7* (WW_PTOF1)		
	Mod	f[5] - 81 . active f[5] - 81 . Blo TripCmd f[5] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[5] - 81 . Alarm
	Op	f[5] - 81 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTOF8* (WW_PTOF1)		
	Mod	f[6] - 81 . active f[6] - 81 . Blo TripCmd f[6] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[6] - 81 . Alarm
	Op	f[6] - 81 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTOV1* (WW_PTOV2)		
	Mod	V[1] - 27, 59 . active V[1] - 27, 59 . Blo TripCmd V[1] - 27, 59 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V[1] - 27, 59 . Alarm
	Op	V[1] - 27, 59 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTOV2* (WW_PTOV2)		
	Mod	V[2] - 27, 59 . active V[2] - 27, 59 . Blo TripCmd V[2] - 27, 59 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V[2] - 27, 59 . Alarm
	Op	V[2] - 27, 59 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTOV3* (WW_PTOV2)		
	Mod	V[3] - 27, 59 . active V[3] - 27, 59 . Blo TripCmd V[3] - 27, 59 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V[3] - 27, 59 . Alarm
	Op	V[3] - 27, 59 . Trip

4 Appendix
 4.1 Register Maps

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTOV4* (WW_PTOV2)		
	Mod	V[4] - 27, 59 . active V[4] - 27, 59 . Blo TripCmd V[4] - 27, 59 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V[4] - 27, 59 . Alarm
	Op	V[4] - 27, 59 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTOV5* (WW_PTOV2)		
	Mod	V[5] - 27, 59 . active V[5] - 27, 59 . Blo TripCmd V[5] - 27, 59 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V[5] - 27, 59 . Alarm
	Op	V[5] - 27, 59 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTOV6* (WW_PTOV2)		
	Mod	V[6] - 27, 59 . active V[6] - 27, 59 . Blo TripCmd V[6] - 27, 59 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V[6] - 27, 59 . Alarm
	Op	V[6] - 27, 59 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTUF1* (WW_PTUF1)		
	Mod	df/dt - 81R . active df/dt - 81R . Blo TripCmd df/dt - 81R . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	df/dt - 81R . Alarm
	Op	df/dt - 81R . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTUF2* (WW_PTUF1)		
	Mod	delta phi - 78V . active delta phi - 78V . Blo TripCmd delta phi - 78V . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	delta phi - 78V . Alarm
	Op	delta phi - 78V . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTUF3* (WW_PTUF1)		
	Mod	f[1] - 81 . active f[1] - 81 . Blo TripCmd f[1] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[1] - 81 . Alarm
	Op	f[1] - 81 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTUF4* (WW_PTUF1)		
	Mod	f[2] - 81 . active f[2] - 81 . Blo TripCmd f[2] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[2] - 81 . Alarm
	Op	f[2] - 81 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTUF5* (WW_PTUF1)		
	Mod	f[3] - 81 . active f[3] - 81 . Blo TripCmd f[3] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[3] - 81 . Alarm
	Op	f[3] - 81 . Trip

4 Appendix
 4.1 Register Maps

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTUF6* (WW_PTUF1)		
	Mod	f[4] - 81 . active f[4] - 81 . Blo TripCmd f[4] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[4] - 81 . Alarm
	Op	f[4] - 81 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTUF7* (WW_PTUF1)		
	Mod	f[5] - 81 . active f[5] - 81 . Blo TripCmd f[5] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[5] - 81 . Alarm
	Op	f[5] - 81 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTUF8* (WW_PTUF1)		
	Mod	f[6] - 81 . active f[6] - 81 . Blo TripCmd f[6] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[6] - 81 . Alarm
	Op	f[6] - 81 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTUV1* (WW_PTUV2)		
	Mod	V[1] - 27, 59 . active V[1] - 27, 59 . Blo TripCmd V[1] - 27, 59 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V[1] - 27, 59 . Alarm
	Op	V[1] - 27, 59 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTUV2* (WW_PTUV2)		
	Mod	V[2] - 27, 59 . active V[2] - 27, 59 . Blo TripCmd V[2] - 27, 59 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V[2] - 27, 59 . Alarm
	Op	V[2] - 27, 59 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTUV3* (WW_PTUV2)		
	Mod	V[3] - 27, 59 . active V[3] - 27, 59 . Blo TripCmd V[3] - 27, 59 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V[3] - 27, 59 . Alarm
	Op	V[3] - 27, 59 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTUV4* (WW_PTUV2)		
	Mod	V[4] - 27, 59 . active V[4] - 27, 59 . Blo TripCmd V[4] - 27, 59 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V[4] - 27, 59 . Alarm
	Op	V[4] - 27, 59 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTUV5* (WW_PTUV2)		
	Mod	V[5] - 27, 59 . active V[5] - 27, 59 . Blo TripCmd V[5] - 27, 59 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V[5] - 27, 59 . Alarm
	Op	V[5] - 27, 59 . Trip

4 Appendix
4.1 Register Maps

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTUV6* (WW_PTUV2)		
	Mod	V[6] - 27, 59 . active V[6] - 27, 59 . Blo TripCmd V[6] - 27, 59 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V[6] - 27, 59 . Alarm
	Op	V[6] - 27, 59 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PUPF1 (WW_PUPF1)		
	Mod	PF[1] - 55 . active PF[1] - 55 . Blo TripCmd PF[1] - 55 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	PF[1] - 55 . Alarm
	Op	PF[1] - 55 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PUPF2 (WW_PUPF1)		
	Mod	PF[2] - 55 . active PF[2] - 55 . Blo TripCmd PF[2] - 55 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	PF[2] - 55 . Alarm
	Op	PF[2] - 55 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
QVPTUV1 (WW_PTUV5)		
	Mod	Q->&V< . active Q->&V< . ExBlo Q->&V< . Fuse Fail VT Blo
	Beh	
	Health	
	NamPlt	
	Str	Q->&V< . Alarm
	Op	Q->&V< . Decoupling Distr. Generator

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
RBRF1 (WW_RBRF1)		
	Mod	CBF - 50BF, 62BF . active CBF - 50BF, 62BF . ExBlo CBF - 50BF, 62BF . ExBlo
	Beh	
	Health	
	NamPlt	
	Str	CBF - 50BF, 62BF . running
	OpEx	CBF - 50BF, 62BF . Alarm

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
RREC1 (WW_RREC1)		
	Mod	AR - 79 . active AR - 79 . ExBlo AR - 79 . ExBlo
	Beh	
	Health	
	NamPlt	
	Op	AR - 79 . CB ON Cmd
	AutoRecSt	AR - 79 . ARRecCState

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
RSYN1 (WW_RSYN2)		
	Mod	Sync - 25 . active Sync - 25 . ExBlo Sync - 25 . ExBlo
	Beh	
	Health	
	NamPlt	
	Rel	Sync - 25 . Ready to Close
	AngInd	Sync - 25 . AngleDiffTooHigh
	HZInd	Sync - 25 . SlipTooHigh
	VInd	Sync - 25 . VDiffTooHigh
	DifAngClc	Sync - 25 . Angle Diff
	DifHzClc	Sync - 25 . Slip Freq
	DifVClc	Sync - 25 . Volt Diff

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
TRPTR1 (WW_PTTR3)		
	Mod	ThR - 49 . active ThR - 49 . Blo TripCmd ThR - 49 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	

4 Appendix
4.1 Register Maps

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
TRPTTR1 (WW_PTTR3)		
	Op	ThR - 49 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
ULPTOC1 (WW_PTOC4)		
	Mod	I2>[1] - 46 . active I2>[1] - 46 . Blo TripCmd I2>[1] - 46 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	I2>[1] - 46 . Alarm
	Op	I2>[1] - 46 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
ULPTOC2 (WW_PTOC4)		
	Mod	I2>[2] - 46 . active I2>[2] - 46 . Blo TripCmd I2>[2] - 46 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	I2>[2] - 46 . Alarm
	Op	I2>[2] - 46 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
VAPTOV1* (WW_PTOV3)		
	Mod	V012[1] - 47 . active V012[1] - 47 . Blo TripCmd V012[1] - 47 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V012[1] - 47 . Alarm
	Op	V012[1] - 47 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
VAPTOV2* (WW_PTOV3)		
	Mod	V012[2] - 47 . active V012[2] - 47 . Blo TripCmd V012[2] - 47 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
VAPTOV2* (WW_PTOV3)		
	Str	V012[2] - 47 . Alarm
	Op	V012[2] - 47 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
VAPTOV3* (WW_PTOV3)		
	Mod	V012[3] - 47 . active V012[3] - 47 . Blo TripCmd V012[3] - 47 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V012[3] - 47 . Alarm
	Op	V012[3] - 47 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
VAPTOV4* (WW_PTOV3)		
	Mod	V012[4] - 47 . active V012[4] - 47 . Blo TripCmd V012[4] - 47 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V012[4] - 47 . Alarm
	Op	V012[4] - 47 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
VAPTOV5* (WW_PTOV3)		
	Mod	V012[5] - 47 . active V012[5] - 47 . Blo TripCmd V012[5] - 47 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V012[5] - 47 . Alarm
	Op	V012[5] - 47 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
VAPTOV6* (WW_PTOV3)		
	Mod	V012[6] - 47 . active V012[6] - 47 . Blo TripCmd V012[6] - 47 . ExBlo TripCmd
	Beh	
	Health	

4 Appendix
4.1 Register Maps

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
VAPTOV6* (WW_PTOV3)		
	NamPlt	
	Str	V012[6] - 47 . Alarm
	Op	V012[6] - 47 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
VAPTUV1* (WW_PTUV3)		
	Mod	V012[1] - 47 . active V012[1] - 47 . Blo TripCmd V012[1] - 47 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V012[1] - 47 . Alarm
	Op	V012[1] - 47 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
VAPTUV2* (WW_PTUV3)		
	Mod	V012[2] - 47 . active V012[2] - 47 . Blo TripCmd V012[2] - 47 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V012[2] - 47 . Alarm
	Op	V012[2] - 47 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
VAPTUV3* (WW_PTUV3)		
	Mod	V012[3] - 47 . active V012[3] - 47 . Blo TripCmd V012[3] - 47 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V012[3] - 47 . Alarm
	Op	V012[3] - 47 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
VAPTUV4* (WW_PTUV3)		
	Mod	V012[4] - 47 . active V012[4] - 47 . Blo TripCmd V012[4] - 47 . ExBlo TripCmd
	Beh	

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
VAPTUV4* (WW_PTUV3)		
	Health	
	NamPlt	
	Str	V012[4] - 47 . Alarm
	Op	V012[4] - 47 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
VAPTUV5* (WW_PTUV3)		
	Mod	V012[5] - 47 . active V012[5] - 47 . Blo TripCmd V012[5] - 47 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V012[5] - 47 . Alarm
	Op	V012[5] - 47 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
VAPTUV6* (WW_PTUV3)		
	Mod	V012[6] - 47 . active V012[6] - 47 . Blo TripCmd V012[6] - 47 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V012[6] - 47 . Alarm
	Op	V012[6] - 47 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
VSPTOV1* (WW_PTOV1)		
	Mod	VG[1] - 27A, 59N,A . active VG[1] - 27A, 59N,A . Blo TripCmd VG[1] - 27A, 59N,A . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	VG[1] - 27A, 59N,A . Alarm
	Op	VG[1] - 27A, 59N,A . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
VSPTOV2* (WW_PTOV1)		
	Mod	VG[2] - 27A, 59N,A . active VG[2] - 27A, 59N,A . Blo TripCmd VG[2] - 27A, 59N,A . ExBlo TripCmd

4 Appendix
4.1 Register Maps

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
VSPTOV2* (WW_PTOV1)		
	Beh	
	Health	
	NamPlt	
	Str	VG[2] - 27A, 59N,A . Alarm
	Op	VG[2] - 27A, 59N,A . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
VSPTUV1* (WW_PTUV1)		
	Mod	VG[1] - 27A, 59N,A . active VG[1] - 27A, 59N,A . Blo TripCmd VG[1] - 27A, 59N,A . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	VG[1] - 27A, 59N,A . Alarm
	Op	VG[1] - 27A, 59N,A . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
VSPTUV2* (WW_PTUV1)		
	Mod	VG[2] - 27A, 59N,A . active VG[2] - 27A, 59N,A . Blo TripCmd VG[2] - 27A, 59N,A . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	VG[2] - 27A, 59N,A . Alarm
	Op	VG[2] - 27A, 59N,A . Trip

4.2 Device Planning Dependencies

The availability of Logical Node instances in the generated ICD file depends on the settings in the “Device planning” menu.

The following list gives an overview about those settings for every module that have an effect on the availability of a Logical Node.

Module (- ANSI/IEEE Device Number) . Name	Value
CILO1	
SG[1] . SwitchgearType	Controlled SG
SG[1] . SwitchgearType	Controlled Make Break SG
CILO2	
SG[2] . SwitchgearType	Controlled SG
SG[2] . SwitchgearType	Controlled Make Break SG
CILO3	
SG[3] . SwitchgearType	Controlled SG
SG[3] . SwitchgearType	Controlled Make Break SG
CILO4	
SG[4] . SwitchgearType	Controlled SG
SG[4] . SwitchgearType	Controlled Make Break SG
CILO5	
SG[5] . SwitchgearType	Controlled SG
SG[5] . SwitchgearType	Controlled Make Break SG
CILO6	
SG[6] . SwitchgearType	Controlled SG
SG[6] . SwitchgearType	Controlled Make Break SG
CSWI1	
SG[1] . SwitchgearType	Controlled SG
SG[1] . SwitchgearType	Controlled Make Break SG
CSWI2	
SG[2] . SwitchgearType	Controlled SG
SG[2] . SwitchgearType	Controlled Make Break SG
CSWI3	
SG[3] . SwitchgearType	Controlled SG
SG[3] . SwitchgearType	Controlled Make Break SG
CSWI4	
SG[4] . SwitchgearType	Controlled SG
SG[4] . SwitchgearType	Controlled Make Break SG
CSWI5	

Module (- ANSI/IEEE Device Number) . Name	Value
SG[5] . SwitchgearType	Controlled SG
SG[5] . SwitchgearType	Controlled Make Break SG
CSWI6	
SG[6] . SwitchgearType	Controlled SG
SG[6] . SwitchgearType	Controlled Make Break SG
XCBR1	
SG[1] . SwitchgearType	Monitored Make Break SG
SG[1] . SwitchgearType	Controlled Make Break SG
XCBR2	
SG[2] . SwitchgearType	Monitored Make Break SG
SG[2] . SwitchgearType	Controlled Make Break SG
XCBR3	
SG[3] . SwitchgearType	Monitored Make Break SG
SG[3] . SwitchgearType	Controlled Make Break SG
XCBR4	
SG[4] . SwitchgearType	Monitored Make Break SG
SG[4] . SwitchgearType	Controlled Make Break SG
XCBR5	
SG[5] . SwitchgearType	Monitored Make Break SG
SG[5] . SwitchgearType	Controlled Make Break SG
XCBR6	
SG[6] . SwitchgearType	Monitored Make Break SG
SG[6] . SwitchgearType	Controlled Make Break SG
XSWI1	
SG[1] . SwitchgearType	Monitored SG
SG[1] . SwitchgearType	Controlled SG
XSWI2	
SG[2] . SwitchgearType	Monitored SG
SG[2] . SwitchgearType	Controlled SG
XSWI3	
SG[3] . SwitchgearType	Monitored SG
SG[3] . SwitchgearType	Controlled SG
XSWI4	
SG[4] . SwitchgearType	Monitored SG
SG[4] . SwitchgearType	Controlled SG
XSWI5	
SG[5] . SwitchgearType	Monitored SG

Module (- ANSI/IEEE Device Number) . Name	Value
SG[5] . SwitchgearType	Controlled SG
XSWI6	
SG[6] . SwitchgearType	Monitored SG
SG[6] . SwitchgearType	Controlled SG
OEVPVPH1	
V/f>[1] - 24 . Mode	use
OEVPVPH2	
V/f>[2] - 24 . Mode	use
PDOP1	
P - 32R . Mode	P>
P - 32R . Mode	Pr>
PDOP2	
Q - 32 . Mode	Q>
Q - 32 . Mode	Qr>
PDOP3	
PQS[1] - 32, 37 . Mode	P>
PQS[1] - 32, 37 . Mode	Pr>
PQS[1] - 32, 37 . Mode	Q>
PQS[1] - 32, 37 . Mode	Qr>
PQS[1] - 32, 37 . Mode	S>
PDOP4	
PQS[2] - 32, 37 . Mode	P>
PQS[2] - 32, 37 . Mode	Pr>
PQS[2] - 32, 37 . Mode	Q>
PQS[2] - 32, 37 . Mode	Qr>
PQS[2] - 32, 37 . Mode	S>
PDOP5	
PQS[3] - 32, 37 . Mode	P>
PQS[3] - 32, 37 . Mode	Pr>
PQS[3] - 32, 37 . Mode	Q>
PQS[3] - 32, 37 . Mode	Qr>
PQS[3] - 32, 37 . Mode	S>
PDOP6	
PQS[4] - 32, 37 . Mode	P>
PQS[4] - 32, 37 . Mode	Pr>
PQS[4] - 32, 37 . Mode	Q>
PQS[4] - 32, 37 . Mode	Qr>

Module (- ANSI/IEEE Device Number) . Name	Value
PQS[4] - 32, 37 . Mode	S>
PDOP7	
PQS[5] - 32, 37 . Mode	P>
PQS[5] - 32, 37 . Mode	Pr>
PQS[5] - 32, 37 . Mode	Q>
PQS[5] - 32, 37 . Mode	Qr>
PQS[5] - 32, 37 . Mode	S>
PDOP8	
PQS[6] - 32, 37 . Mode	P>
PQS[6] - 32, 37 . Mode	Pr>
PQS[6] - 32, 37 . Mode	Q>
PQS[6] - 32, 37 . Mode	Qr>
PQS[6] - 32, 37 . Mode	S>
PDUP3	
PQS[1] - 32, 37 . Mode	P<
PQS[1] - 32, 37 . Mode	Pr<
PQS[1] - 32, 37 . Mode	Q<
PQS[1] - 32, 37 . Mode	Qr<
PQS[1] - 32, 37 . Mode	S<
PDUP4	
PQS[2] - 32, 37 . Mode	P<
PQS[2] - 32, 37 . Mode	Pr<
PQS[2] - 32, 37 . Mode	Q<
PQS[2] - 32, 37 . Mode	Qr<
PQS[2] - 32, 37 . Mode	S<
PDUP5	
PQS[3] - 32, 37 . Mode	P<
PQS[3] - 32, 37 . Mode	Pr<
PQS[3] - 32, 37 . Mode	Q<
PQS[3] - 32, 37 . Mode	Qr<
PQS[3] - 32, 37 . Mode	S<
PDUP6	
PQS[4] - 32, 37 . Mode	P<
PQS[4] - 32, 37 . Mode	Pr<
PQS[4] - 32, 37 . Mode	Q<
PQS[4] - 32, 37 . Mode	Qr<
PQS[4] - 32, 37 . Mode	S<

Module (- ANSI/IEEE Device Number) . Name	Value
PDUP7	
PQS[5] - 32, 37 . Mode	P<
PQS[5] - 32, 37 . Mode	Pr<
PQS[5] - 32, 37 . Mode	Q<
PQS[5] - 32, 37 . Mode	Qr<
PQS[5] - 32, 37 . Mode	S<
PDUP8	
PQS[6] - 32, 37 . Mode	P<
PQS[6] - 32, 37 . Mode	Pr<
PQS[6] - 32, 37 . Mode	Q<
PQS[6] - 32, 37 . Mode	Qr<
PQS[6] - 32, 37 . Mode	S<
PFRC1	
df/dt - 81R . Mode	use
PFRC3	
f[1] - 81 . Mode	f< and df/dt
f[1] - 81 . Mode	f> and df/dt
f[1] - 81 . Mode	f< and DF/DT
f[1] - 81 . Mode	f> and DF/DT
f[1] - 81 . Mode	df/dt
PFRC4	
f[2] - 81 . Mode	f< and df/dt
f[2] - 81 . Mode	f> and df/dt
f[2] - 81 . Mode	f< and DF/DT
f[2] - 81 . Mode	f> and DF/DT
f[2] - 81 . Mode	df/dt
PFRC5	
f[3] - 81 . Mode	f< and df/dt
f[3] - 81 . Mode	f> and df/dt
f[3] - 81 . Mode	f< and DF/DT
f[3] - 81 . Mode	f> and DF/DT
f[3] - 81 . Mode	df/dt
PFRC6	
f[4] - 81 . Mode	f< and df/dt
f[4] - 81 . Mode	f> and df/dt
f[4] - 81 . Mode	f< and DF/DT
f[4] - 81 . Mode	f> and DF/DT

Module (- ANSI/IEEE Device Number) . Name	Value
f[4] - 81 . Mode	df/dt
PFRC7	
f[5] - 81 . Mode	f< and df/dt
f[5] - 81 . Mode	f> and df/dt
f[5] - 81 . Mode	f< and DF/DT
f[5] - 81 . Mode	f> and DF/DT
f[5] - 81 . Mode	df/dt
PFRC8	
f[6] - 81 . Mode	f< and df/dt
f[6] - 81 . Mode	f> and df/dt
f[6] - 81 . Mode	f< and DF/DT
f[6] - 81 . Mode	f> and DF/DT
f[6] - 81 . Mode	df/dt
PPAM2	
delta phi - 78V . Mode	use
PPAM3	
f[1] - 81 . Mode	delta phi
PPAM4	
f[2] - 81 . Mode	delta phi
PPAM5	
f[3] - 81 . Mode	delta phi
PPAM6	
f[4] - 81 . Mode	delta phi
PPAM7	
f[5] - 81 . Mode	delta phi
PPAM8	
f[6] - 81 . Mode	delta phi
PTOF3	
f[1] - 81 . Mode	f>
PTOF4	
f[2] - 81 . Mode	f>
PTOF5	
f[3] - 81 . Mode	f>
PTOF6	
f[4] - 81 . Mode	f>
PTOF7	
f[5] - 81 . Mode	f>


Module (- ANSI/IEEE Device Number) . Name	Value
PTOF8	
f[6] - 81 . Mode	f>
PTOV1	
V[1] - 27, 59 . Mode	V>
PTOV2	
V[2] - 27, 59 . Mode	V>
PTOV3	
V[3] - 27, 59 . Mode	V>
PTOV4	
V[4] - 27, 59 . Mode	V>
PTOV5	
V[5] - 27, 59 . Mode	V>
PTOV6	
V[6] - 27, 59 . Mode	V>
PTUF3	
f[1] - 81 . Mode	f<
PTUF4	
f[2] - 81 . Mode	f<
PTUF5	
f[3] - 81 . Mode	f<
PTUF6	
f[4] - 81 . Mode	f<
PTUF7	
f[5] - 81 . Mode	f<
PTUF8	
f[6] - 81 . Mode	f<
PTUV1	
V[1] - 27, 59 . Mode	V<
PTUV2	
V[2] - 27, 59 . Mode	V<
PTUV3	
V[3] - 27, 59 . Mode	V<
PTUV4	
V[4] - 27, 59 . Mode	V<
PTUV5	
V[5] - 27, 59 . Mode	V<
PTUV6	

Module (- ANSI/IEEE Device Number) . Name	Value
V[6] - 27, 59 . Mode	V<
VAPTOV1	
V012[1] - 47 . Mode	V1>
V012[1] - 47 . Mode	V2>
VAPTOV2	
V012[2] - 47 . Mode	V1>
V012[2] - 47 . Mode	V2>
VAPTOV3	
V012[3] - 47 . Mode	V1>
V012[3] - 47 . Mode	V2>
VAPTOV4	
V012[4] - 47 . Mode	V1>
V012[4] - 47 . Mode	V2>
VAPTOV5	
V012[5] - 47 . Mode	V1>
V012[5] - 47 . Mode	V2>
VAPTOV6	
V012[6] - 47 . Mode	V1>
V012[6] - 47 . Mode	V2>
VAPTUV1	
V012[1] - 47 . Mode	V1<
VAPTUV2	
V012[2] - 47 . Mode	V1<
VAPTUV3	
V012[3] - 47 . Mode	V1<
VAPTUV4	
V012[4] - 47 . Mode	V1<
VAPTUV5	
V012[5] - 47 . Mode	V1<
VAPTUV6	
V012[6] - 47 . Mode	V1<
VSPTOV1	
VG[1] - 27A, 59N,A . Mode	V>
VSPTOV2	
VG[2] - 27A, 59N,A . Mode	V>
VSPTUV1	
VG[1] - 27A, 59N,A . Mode	V<

Module (- ANSI/IEEE Device Number) . Name	Value
VSPTUV2	
VG[2] - 27A, 59N,A . Mode	V<

High PROTEC

docs.SEGelectronics.de/HighPROTEC



SEG Electronics GmbH reserves the right to update any portion of this publication at any time. Information provided by SEG Electronics GmbH is believed to be correct and reliable. However, SEG Electronics GmbH assumes no responsibility unless otherwise expressly undertaken.



SEG Electronics GmbH
Krefelder Weg 47 • D-47906 Kempen (Germany)
Telephone: +49 (0) 21 52 145 1

Internet: www.SEGelectronics.de

Sales
Telephone: +49 (0) 21 52 145 331
Fax: +49 (0) 21 52 145 354

Service
Telephone: +49 (0) 21 52 145 614
Fax: +49 (0) 21 52 145 354

Complete address / phone / fax / email information for all locations is available on our website.