



High **PROTEC**

**MCDTV4-3.7-EN-IEC61850-MICS**

---

**MCDTV4**

**Enhanced Transformer Differential Protection**

**IEC 61850 - MICS**

Model Implementation Conformance Statement (MICS)

UCA International Users Group Testing Sub Committee

**Version: 3.7**

**Original document · English**

**Revision: - 47545 · © 2020**

## **Woodward Kempen GmbH**

Krefelder Weg 47 • D-47906 Kempen (Germany)

Postfach 10 07 55 (P.O.Box) • D-47884 Kempen (Germany)

Telephone: +49 (0) 21 52 145 1

Internet: [www.woodward.com](http://www.woodward.com)

### Sales

Telephone: +49 (0) 21 52 145 331

Fax: +49 (0) 21 52 145 354

Email: [SalesPGD\\_EMEA@woodward.com](mailto:SalesPGD_EMEA@woodward.com)

### Service

Telephone: +49 (0) 21 52 145 614

Fax: +49 (0) 21 52 145 354

Email: [industrial.support@woodward.com](mailto:industrial.support@woodward.com)

© 2020 Woodward Kempen GmbH

# Table of Contents

|          |                                |          |
|----------|--------------------------------|----------|
| <b>1</b> | <b>Introduction</b> .....      | <b>7</b> |
| <b>2</b> | <b>Logical Nodes</b> .....     | <b>8</b> |
| 2.1      | Logical Nodes List .....       | 8        |
| 2.2      | Logical Node Definitions ..... | 10       |
| 2.3      | WW_CILO1 .....                 | 12       |
| 2.4      | WW_CSWI1 .....                 | 12       |
| 2.5      | WW_GAPC1 .....                 | 12       |
| 2.6      | WW_GGIO4 .....                 | 13       |
| 2.7      | WW_GGIO10 .....                | 14       |
| 2.8      | WW_GGIO11 .....                | 15       |
| 2.9      | WW_GGIO14 .....                | 17       |
| 2.10     | WW_IHMI1 .....                 | 18       |
| 2.11     | WW_LLNOCON .....               | 18       |
| 2.12     | WW_LLNOMEA .....               | 19       |
| 2.13     | WW_LLNOPRO .....               | 19       |
| 2.14     | WW_LLNOREC .....               | 20       |
| 2.15     | WW_LLNOSYS .....               | 20       |
| 2.16     | WW_LPHDCON .....               | 20       |
| 2.17     | WW_LPHDMEA .....               | 21       |
| 2.18     | WW_LPHDPRO .....               | 21       |
| 2.19     | WW_LPHDREC .....               | 21       |
| 2.20     | WW_LPHDSYS .....               | 22       |
| 2.21     | WW_MMTR1 .....                 | 22       |
| 2.22     | WW_MMXU3 .....                 | 22       |
| 2.23     | WW_MMXU6 .....                 | 23       |
| 2.24     | WW_MMXU7 .....                 | 23       |
| 2.25     | WW_MSTA1 .....                 | 24       |
| 2.26     | WW_MSTA2 .....                 | 25       |
| 2.27     | WW_MSTA3 .....                 | 25       |
| 2.28     | WW_PDIF1 .....                 | 26       |

Table of Contents

|      |                |    |
|------|----------------|----|
| 2.29 | WW_PDIF2 ..... | 27 |
| 2.30 | WW_PDIF3 ..... | 27 |
| 2.31 | WW_PDIF4 ..... | 27 |
| 2.32 | WW_PDOP1 ..... | 28 |
| 2.33 | WW_PDUP1 ..... | 28 |
| 2.34 | WW_PFRC1 ..... | 29 |
| 2.35 | WW_PFRC2 ..... | 29 |
| 2.36 | WW_PHAR1 ..... | 30 |
| 2.37 | WW_PPAM1 ..... | 30 |
| 2.38 | WW_PSO1 .....  | 31 |
| 2.39 | WW_PTOC1 ..... | 31 |
| 2.40 | WW_PTOC3 ..... | 31 |
| 2.41 | WW_PTOC4 ..... | 32 |
| 2.42 | WW_PTOF1 ..... | 32 |
| 2.43 | WW_PTOV1 ..... | 33 |
| 2.44 | WW_PTOV2 ..... | 33 |
| 2.45 | WW_PTOV3 ..... | 34 |
| 2.46 | WW_PTTR3 ..... | 34 |
| 2.47 | WW_PTTR4 ..... | 35 |
| 2.48 | WW_PTUF1 ..... | 35 |
| 2.49 | WW_PTUV1 ..... | 35 |
| 2.50 | WW_PTUV2 ..... | 36 |
| 2.51 | WW_PTUV3 ..... | 36 |
| 2.52 | WW_PTUV5 ..... | 37 |
| 2.53 | WW_PUPF1 ..... | 37 |
| 2.54 | WW_PVPH1 ..... | 38 |
| 2.55 | WW_PSDE1 ..... | 38 |
| 2.56 | WW_PSDE2 ..... | 39 |
| 2.57 | WW_RBRF1 ..... | 39 |
| 2.58 | WW_RDRE1 ..... | 39 |
| 2.59 | WW_RSYN2 ..... | 40 |
| 2.60 | WW_SCBR1 ..... | 41 |

|          |   |           |
|----------|---|-----------|
| 2.61     | WW_XCBR2                                | 41        |
| 2.62     | WW_XSWI1                                | 42        |
| <b>3</b> | <b>Common Data Class</b>                | <b>43</b> |
| 3.1      | Common Data Class Definitions           | 43        |
| 3.1.1    | WW_ACD1                                 | 44        |
| 3.1.2    | WW_ACT1                                 | 44        |
| 3.1.3    | WW_BCR1                                 | 44        |
| 3.1.4    | WW_CMV2                                 | 44        |
| 3.1.5    | WW_DEL2                                 | 45        |
| 3.1.6    | WW_DPC1                                 | 45        |
| 3.1.7    | WW_DPC2                                 | 45        |
| 3.1.8    | WW_DPL1                                 | 46        |
| 3.1.9    | WW_INC1                                 | 46        |
| 3.1.10   | WW_INS1                                 | 46        |
| 3.1.11   | WW_INS2                                 | 47        |
| 3.1.12   | WW_INS3                                 | 47        |
| 3.1.13   | WW_INS5                                 | 47        |
| 3.1.14   | WW_LPL1                                 | 47        |
| 3.1.15   | WW_LPL2                                 | 48        |
| 3.1.16   | WW_LPL3                                 | 48        |
| 3.1.17   | WW_MV1                                  | 48        |
| 3.1.18   | WW_SPC1                                 | 48        |
| 3.1.19   | WW_SPC2                                 | 49        |
| 3.1.20   | WW_SPS1                                 | 49        |
| 3.1.21   | WW_WYE2                                 | 49        |
| 3.2      | Common Data Attributes Type Definitions | 50        |
| 3.2.1    | WW_analogValue1                         | 50        |
| 3.2.2    | WW_Cancel1                              | 50        |
| 3.2.3    | WW_Oper1                                | 50        |
| 3.2.4    | WW_origin1                              | 50        |
| 3.2.5    | WW_units1                               | 51        |
| 3.2.6    | WW_vector1                              | 51        |

|          |  |           |
|----------|--|-----------|
| 3.3      | Enumerated type definitions . . . . .  | 52        |
| 3.3.1    | AutoRecSt . . . . .                    | 52        |
| 3.3.2    | Beh . . . . .                          | 52        |
| 3.3.3    | CBOpCap . . . . .                      | 52        |
| 3.3.4    | ctlModel . . . . .                     | 52        |
| 3.3.5    | Dbpos . . . . .                        | 53        |
| 3.3.6    | ACDdir . . . . .                       | 53        |
| 3.3.7    | Health . . . . .                       | 53        |
| 3.3.8    | Mod . . . . .                          | 53        |
| 3.3.9    | MotorCycle . . . . .                   | 54        |
| 3.3.10   | multiplier . . . . .                   | 54        |
| 3.3.11   | orCategory . . . . .                   | 55        |
| 3.3.12   | sboClass . . . . .                     | 55        |
| 3.3.13   | SIUnit . . . . .                       | 55        |
| <b>4</b> | <b>Appendix . . . . .</b>              | <b>58</b> |
| 4.1      | Register Maps . . . . .                | 58        |
| 4.2      | Device Planning Dependencies . . . . . | 107       |

# 1 Introduction

This model implementation conformance statement is applicable to the MCDTV4 version 3.7.

This MICS document specifies the modelling extensions compared to IEC 61850 edition 1.

Clause 2 contains the list of implemented logical nodes.

Clause 3 describes the new and extended logical nodes.

Clause 4 describes the existing common data classes.

Clause 5 describes the existing enum types.

## 2 Logical Nodes

### 2.1 Logical Nodes List

The following table contains the list of logical nodes implemented in the device:

|  |
|--|
| <b>L: System Logical Nodes</b>                           |
| <b>LLNO</b> (Logical Node device)                        |
| <b>LPHD</b> (Physical device)                            |
| <b>P: Logical Nodes for protection functions</b>         |
| <b>PDIF</b> (Differential)                               |
| <b>PDOP</b> (Directional overpower)                      |
| <b>PDUP</b> (Directional underpower)                     |
| <b>PFRC</b> (Rate of change of frequency)                |
| <b>PHAR</b> (Harmonic restraint)                         |
| <b>PPAM</b> (Phase angle or out-of-step protection)      |
| <b>PSDE</b> (Sensitive directional earthfault)           |
| <b>PSOF</b> (Switch Onto Fault)                          |
| <b>PTOC</b> (Time overcurrent)                           |
| <b>PTOF</b> (Overfrequency)                              |
| <b>PTOV</b> (Overvoltage)                                |
| <b>PTTR</b> (Thermal overload protection)                |
| <b>PTUF</b> (Underfrequency)                             |
| <b>PTUV</b> (Undervoltage)                               |
| <b>PUPF</b> (Underpower factor)                          |
| <b>VVPH</b> (Volts per Hz)                               |
| <b>R: Logical Nodes for protection related functions</b> |
| <b>RBRF</b> (Breaker failure)                            |
| <b>RDRE</b> (Disturbance recorder function)              |
| <b>RSYN</b> (Synchronism-check or synchronising)         |
| <b>G: Logical Nodes for generic references</b>           |
| <b>GAPC</b> (Generic automatic process control)          |
| <b>GGIO</b> (Generic process I/O)                        |
| <b>M: Logical Nodes for metering and measurement</b>     |
| <b>MMTR</b> (Metering)                                   |
| <b>MMXU</b> (Measurement)                                |



**M: Logical Nodes for metering and measurement**

**MSTA** (Metering Statistics)

**X: Logical Nodes for switchgear**

**XCBR** (Circuit Breaker)

**XSWI** (Circuit Switch)

**C: Logical Nodes for control**

**CILO** (Interlocking)

**CSWI** (Switch controller)

**I: Logical Nodes for interfacing and archiving**

**IHMI** (Human machine interface)

**S: Logical Nodes for sensors and monitoring**

**SCBR** (Circuit breaker monitoring)

## 2.2 Logical Node Definitions

Abbreviations used in the following table:

- **M**: Data is mandatory in the IEC 61850-7-4.
- **O**: Data is optional in the IEC 61850-7-4 and is used in the device.
- **E**: Data is an extension to the IEC 61850-7-4.

| LN Type    | LN Class | Description                       |
|------------|----------|-----------------------------------|
| WW_CILO1   | CILO     | Interlocking                      |
| WW_CSWI1   | CSWI     | Switch controller                 |
| WW_GAPC1   | GAPC     | Generic automatic process control |
| WW_GGIO10  | GGIO     | Generic process I/O               |
| WW_GGIO11  | GGIO     | Generic process I/O               |
| WW_GGIO14  | GGIO     | Generic process I/O               |
| WW_GGIO4   | GGIO     | Generic process I/O               |
| WW_IHMI1   | IHMI     | Human machine interface           |
| WW_LLNOCON | LLNO     | Logical Node device               |
| WW_LLNOMEA | LLNO     | Logical Node device               |
| WW_LLNOPRO | LLNO     | Logical Node device               |
| WW_LLNOREC | LLNO     | Logical Node device               |
| WW_LLNOSYS | LLNO     | Logical Node device               |
| WW_LPHDCON | LPHD     | Physical device                   |
| WW_LPHDMEA | LPHD     | Physical device                   |
| WW_LPHDPRO | LPHD     | Physical device                   |
| WW_LPHDREC | LPHD     | Physical device                   |
| WW_LPHDSYS | LPHD     | Physical device                   |
| WW_MMTR1   | MMTR     | Metering                          |
| WW_MMXU3   | MMXU     | Measurement                       |
| WW_MMXU6   | MMXU     | Measurement                       |
| WW_MMXU7   | MMXU     | Measurement                       |
| WW_MSTA1   | MSTA     | Metering Statistics               |
| WW_MSTA2   | MSTA     | Metering Statistics               |
| WW_MSTA3   | MSTA     | Metering Statistics               |
| WW_PDIF1   | PDIF     | Differential                      |
| WW_PDIF2   | PDIF     | Differential                      |
| WW_PDIF3   | PDIF     | Differential                      |
| WW_PDIF4   | PDIF     | Differential                      |
| WW_PDOP1   | PDOP     | Directional overpower             |
| WW_PDUP1   | PDUP     | Directional underpower            |

| <b>LN Type</b> | <b>LN Class</b> | <b>Description</b>                    |
|----------------|-----------------|---------------------------------------|
| WW_PFRC1       | PFRC            | Rate of change of frequency           |
| WW_PFRC2       | PFRC            | Rate of change of frequency           |
| WW_PHAR1       | PHAR            | Harmonic restraint                    |
| WW_PPAM1       | PPAM            | Phase angle or out-of-step protection |
| WW_PSDE1       | PSDE            | Sensitive directional earthfault      |
| WW_PSDE2       | PSDE            | Sensitive directional earthfault      |
| WW_PSOFF1      | PSOF            | Switch Onto Fault                     |
| WW_PTOC1       | PTOC            | Time overcurrent                      |
| WW_PTOC3       | PTOC            | Time overcurrent                      |
| WW_PTOC4       | PTOC            | Time overcurrent                      |
| WW_PTOF1       | PTOF            | Overfrequency                         |
| WW_PTOV1       | PTOV            | Overvoltage                           |
| WW_PTOV2       | PTOV            | Overvoltage                           |
| WW_PTOV3       | PTOV            | Overvoltage                           |
| WW_PTTR3       | PTTR            | Thermal overload protection           |
| WW_PTTR4       | PTTR            | Thermal overload protection           |
| WW_PTUF1       | PTUF            | Underfrequency                        |
| WW_PTUV1       | PTUV            | Undervoltage                          |
| WW_PTUV2       | PTUV            | Undervoltage                          |
| WW_PTUV3       | PTUV            | Undervoltage                          |
| WW_PTUV5       | PTUV            | Undervoltage                          |
| WW_PUPF1       | PUPF            | Underpower factor                     |
| WW_PVPH1       | PVPH            | Volts per Hz                          |
| WW_RBRF1       | RBRF            | Breaker failure                       |
| WW_RDRE1       | RDRE            | Disturbance recorder function         |
| WW_RSYN2       | RSYN            | Synchronism-check or synchronising    |
| WW_SCBR1       | SCBR            | Circuit breaker monitoring            |
| WW_XCBR2       | XCBR            | Circuit Breaker                       |
| WW_XSWI1       | XSWI            | Circuit Switch                        |

## 2.3 WW\_CILO1

| Attribute Name                         | Attribute Type | Explanation  | M/O/E | Remarks     |
|--|----------------|--------------|-------|-------------|
| <b>CILO class</b>                      |                |              |       |             |
| CILO                                   | WW_CILO1       | Interlocking |       |             |
| <b>Data</b>                            |                |              |       |             |
| <i>Common Logical Node Information</i> |                |              |       |             |
| Mod                                    | WW_INC1        | Mode         | M     | Status-only |
| Beh                                    | WW_INS1        | Behavior     | M     |             |
| Health                                 | WW_INS3        | Health       | M     |             |
| NamPlt                                 | WW_LPL1        | Name plate   | M     |             |
| <i>Status Information</i>              |                |              |       |             |
| EnaOpn                                 | WW_SPS1        | Enable Open  | M     |             |
| EnaCls                                 | WW_SPS1        | Enable Close | M     |             |

## 2.4 WW\_CSWI1

| Attribute Name                         | Attribute Type | Explanation       | M/O/E | Remarks     |
|--|----------------|-------------------|-------|-------------|
| <b>CSWI class</b>                      |                |                   |       |             |
| CSWI                                   | WW_CSWI1       | Switch Controller |       |             |
| <b>Data</b>                            |                |                   |       |             |
| <i>Common Logical Node Information</i> |                |                   |       |             |
| Mod                                    | WW_INC1        | Mode              | M     | Status-only |
| Beh                                    | WW_INS1        | Behaviour         | M     |             |
| Health                                 | WW_INS3        | Health            | M     |             |
| NamPlt                                 | WW_LPL1        | Name plate        | M     |             |
| Loc                                    | WW_SPS1        | Local operation   | O     |             |
| <i>Controls</i>                        |                |                   |       |             |
| Pos                                    | WW_DPC2        | Switch position   | M     |             |

## 2.5 WW\_GAPC1

| Attribute Name    | Attribute Type | Explanation                       | M/O/E | Remarks |
|-------------------|----------------|-----------------------------------|-------|---------|
| <b>GAPC class</b> |                |                                   |       |         |
| GAPC              | WW_GAPC1       | Generic automatic process control |       |         |

| Attribute Name                         | Attribute Type | Explanation     | M/O/E | Remarks     |
|--|----------------|-----------------|-------|-------------|
| <b>Data</b>                            |                |                 |       |             |
| <i>Common Logical Node Information</i> |                |                 |       |             |
| Mod                                    | WW_INC1        | Mode            | M     | Status-only |
| Beh                                    | WW_INS1        | Behaviour       | M     |             |
| Health                                 | WW_INS3        | Health          | M     |             |
| NamPlt                                 | WW_LPL1        | Name plate      | M     |             |
| Loc                                    | WW_SPS1        | Local operation | O     |             |
| <i>Status Information</i>              |                |                 |       |             |
| Str                                    | WW_ACD1        | Start           | M     |             |
| Op                                     | WW_ACT1        | Operate         | M     |             |

## 2.6 WW\_GGIO4

| Attribute Name                         | Attribute Type | Explanation                       | M/O/E | Remarks     |
|--|----------------|-----------------------------------|-------|-------------|
| <b>GGIO class</b>                      |                |                                   |       |             |
| GGIO                                   | WW_GGIO4       | Generic process I/O               |       |             |
| <b>Data</b>                            |                |                                   |       |             |
| <i>Common Logical Node Information</i> |                |                                   |       |             |
| Mod                                    | WW_INC1        | Mode                              | M     | Status-only |
| Beh                                    | WW_INS1        | Behaviour                         | M     |             |
| Health                                 | WW_INS3        | Health                            | M     |             |
| NamPlt                                 | WW_LPL1        | Name plate                        | M     |             |
| <i>Status Information</i>              |                |                                   |       |             |
| Ind1                                   | WW_SPS1        | General indication (binary input) | O     |             |
| Ind2                                   | WW_SPS1        | General indication (binary input) | O     |             |
| Ind3                                   | WW_SPS1        | General indication (binary input) | O     |             |
| Ind4                                   | WW_SPS1        | General indication (binary input) | O     |             |
| Ind5                                   | WW_SPS1        | General indication (binary input) | O     |             |
| Ind6                                   | WW_SPS1        | General indication (binary input) | O     |             |
| Ind7                                   | WW_SPS1        | General indication (binary input) | O     |             |
| Ind8                                   | WW_SPS1        | General indication (binary input) | O     |             |
| Ind9                                   | WW_SPS1        | General indication (binary input) | O     |             |
| Ind10                                  | WW_SPS1        | General indication (binary input) | O     |             |
| Ind11                                  | WW_SPS1        | General indication (binary input) | O     |             |
| Ind12                                  | WW_SPS1        | General indication (binary input) | O     |             |

| Attribute Name | Attribute Type | Explanation                       | M/O/E | Remarks |
|----------------|----------------|-----------------------------------|-------|---------|
| Ind13          | WW_SPS1        | General indication (binary input) | O     |         |
| Ind14          | WW_SPS1        | General indication (binary input) | O     |         |
| Ind15          | WW_SPS1        | General indication (binary input) | O     |         |
| Ind16          | WW_SPS1        | General indication (binary input) | O     |         |
| Ind17          | WW_SPS1        | General indication (binary input) | O     |         |
| Ind18          | WW_SPS1        | General indication (binary input) | O     |         |
| Ind19          | WW_SPS1        | General indication (binary input) | O     |         |
| Ind20          | WW_SPS1        | General indication (binary input) | O     |         |
| Ind21          | WW_SPS1        | General indication (binary input) | O     |         |
| Ind22          | WW_SPS1        | General indication (binary input) | O     |         |
| Ind23          | WW_SPS1        | General indication (binary input) | O     |         |
| Ind24          | WW_SPS1        | General indication (binary input) | O     |         |
| Ind25          | WW_SPS1        | General indication (binary input) | O     |         |
| Ind26          | WW_SPS1        | General indication (binary input) | O     |         |
| Ind27          | WW_SPS1        | General indication (binary input) | O     |         |
| Ind28          | WW_SPS1        | General indication (binary input) | O     |         |
| Ind29          | WW_SPS1        | General indication (binary input) | O     |         |
| Ind30          | WW_SPS1        | General indication (binary input) | O     |         |
| Ind31          | WW_SPS1        | General indication (binary input) | O     |         |
| Ind32          | WW_SPS1        | General indication (binary input) | O     |         |

## 2.7 WW\_GGIO10

| Attribute Name                         | Attribute Type | Explanation                       | M/O/E | Remarks     |
|--|----------------|-----------------------------------|-------|-------------|
| <b>GGIO class</b>                      |                |                                   |       |             |
| GGIO                                   | WW_GGI10       | Generic process I/O               |       |             |
| <b>Data</b>                            |                |                                   |       |             |
| <i>Common Logical Node Information</i> |                |                                   |       |             |
| Mod                                    | WW_INC1        | Mode                              | M     | Status-only |
| Beh                                    | WW_INS1        | Behaviour                         | M     |             |
| Health                                 | WW_INS3        | Health                            | M     |             |
| NamPlt                                 | WW_LPL1        | Name plate                        | M     |             |
| <i>Status Information</i>              |                |                                   |       |             |
| Ind1                                   | WW_SPS1        | General indication (binary input) | O     |             |
| Ind2                                   | WW_SPS1        | General indication (binary input) | O     |             |

| Attribute Name | Attribute Type | Explanation                       | M/O/E | Remarks |
|----------------|----------------|-----------------------------------|-------|---------|
| Ind3           | WW_SPS1        | General indication (binary input) | 0     |         |
| Ind4           | WW_SPS1        | General indication (binary input) | 0     |         |
| Ind5           | WW_SPS1        | General indication (binary input) | 0     |         |
| Ind6           | WW_SPS1        | General indication (binary input) | 0     |         |
| Ind7           | WW_SPS1        | General indication (binary input) | 0     |         |
| Ind8           | WW_SPS1        | General indication (binary input) | 0     |         |
| Ind9           | WW_SPS1        | General indication (binary input) | 0     |         |
| Ind10          | WW_SPS1        | General indication (binary input) | 0     |         |
| Ind11          | WW_SPS1        | General indication (binary input) | 0     |         |
| Ind12          | WW_SPS1        | General indication (binary input) | 0     |         |
| Ind13          | WW_SPS1        | General indication (binary input) | 0     |         |
| Ind14          | WW_SPS1        | General indication (binary input) | 0     |         |
| Ind15          | WW_SPS1        | General indication (binary input) | 0     |         |
| Ind16          | WW_SPS1        | General indication (binary input) | 0     |         |
| Ind17          | WW_SPS1        | General indication (binary input) | 0     |         |
| Ind18          | WW_SPS1        | General indication (binary input) | 0     |         |
| Ind19          | WW_SPS1        | General indication (binary input) | 0     |         |
| Ind20          | WW_SPS1        | General indication (binary input) | 0     |         |
| Ind21          | WW_SPS1        | General indication (binary input) | 0     |         |
| Ind22          | WW_SPS1        | General indication (binary input) | 0     |         |
| Ind23          | WW_SPS1        | General indication (binary input) | 0     |         |
| Ind24          | WW_SPS1        | General indication (binary input) | 0     |         |
| Ind25          | WW_SPS1        | General indication (binary input) | 0     |         |
| Ind26          | WW_SPS1        | General indication (binary input) | 0     |         |
| Ind27          | WW_SPS1        | General indication (binary input) | 0     |         |
| Ind28          | WW_SPS1        | General indication (binary input) | 0     |         |
| Ind29          | WW_SPS1        | General indication (binary input) | 0     |         |
| Ind30          | WW_SPS1        | General indication (binary input) | 0     |         |
| Ind31          | WW_SPS1        | General indication (binary input) | 0     |         |
| Ind32          | WW_SPS1        | General indication (binary input) | 0     |         |

## 2.8 WW\_GGIO11

| Attribute Name    | Attribute Type | Explanation | M/O/E | Remarks |
|-------------------|----------------|-------------|-------|---------|
| <b>GGIO class</b> |                |             |       |         |

| Attribute Name                         | Attribute Type | Explanation                       | M/O/E | Remarks     |
|--|----------------|-----------------------------------|-------|-------------|
| GGIO                                   | WW_GGI11       | Generic process I/O               |       |             |
| <b>Data</b>                            |                |                                   |       |             |
| <i>Common Logical Node Information</i> |                |                                   |       |             |
| Mod                                    | WW_INC1        | Mode                              | M     | Status-only |
| Beh                                    | WW_INS1        | Behaviour                         | M     |             |
| Health                                 | WW_INS3        | Health                            | M     |             |
| NamPlt                                 | WW_LPL1        | Name plate                        | M     |             |
| <i>Status Information</i>              |                |                                   |       |             |
| Ind1                                   | WW_SPS1        | General indication (binary input) | O     |             |
| Ind2                                   | WW_SPS1        | General indication (binary input) | O     |             |
| Ind3                                   | WW_SPS1        | General indication (binary input) | O     |             |
| Ind4                                   | WW_SPS1        | General indication (binary input) | O     |             |
| Ind5                                   | WW_SPS1        | General indication (binary input) | O     |             |
| Ind6                                   | WW_SPS1        | General indication (binary input) | O     |             |
| Ind7                                   | WW_SPS1        | General indication (binary input) | O     |             |
| Ind8                                   | WW_SPS1        | General indication (binary input) | O     |             |
| Ind9                                   | WW_SPS1        | General indication (binary input) | O     |             |
| Ind10                                  | WW_SPS1        | General indication (binary input) | O     |             |
| Ind11                                  | WW_SPS1        | General indication (binary input) | O     |             |
| Ind12                                  | WW_SPS1        | General indication (binary input) | O     |             |
| Ind13                                  | WW_SPS1        | General indication (binary input) | O     |             |
| Ind14                                  | WW_SPS1        | General indication (binary input) | O     |             |
| Ind15                                  | WW_SPS1        | General indication (binary input) | O     |             |
| Ind16                                  | WW_SPS1        | General indication (binary input) | O     |             |
| Ind17                                  | WW_SPS1        | General indication (binary input) | O     |             |
| Ind18                                  | WW_SPS1        | General indication (binary input) | O     |             |
| Ind19                                  | WW_SPS1        | General indication (binary input) | O     |             |
| Ind20                                  | WW_SPS1        | General indication (binary input) | O     |             |
| Ind21                                  | WW_SPS1        | General indication (binary input) | O     |             |
| Ind22                                  | WW_SPS1        | General indication (binary input) | O     |             |
| Ind23                                  | WW_SPS1        | General indication (binary input) | O     |             |
| Ind24                                  | WW_SPS1        | General indication (binary input) | O     |             |
| Ind25                                  | WW_SPS1        | General indication (binary input) | O     |             |
| Ind26                                  | WW_SPS1        | General indication (binary input) | O     |             |
| Ind27                                  | WW_SPS1        | General indication (binary input) | O     |             |
| Ind28                                  | WW_SPS1        | General indication (binary input) | O     |             |



| Attribute Name | Attribute Type | Explanation                       | M/O/E | Remarks |
|----------------|----------------|-----------------------------------|-------|---------|
| Ind29          | WW_SPS1        | General indication (binary input) | O     |         |
| Ind30          | WW_SPS1        | General indication (binary input) | O     |         |
| Ind31          | WW_SPS1        | General indication (binary input) | O     |         |
| Ind32          | WW_SPS1        | General indication (binary input) | O     |         |

## 2.9 WW\_GGIO14

| Attribute Name                         | Attribute Type | Explanation                             | M/O/E | Remarks     |
|--|----------------|---|-------|-------------|
| <b>GGIO class</b>                      |                |   |       |             |
| GGIO                                   | WW_GGI14       | Generic process I/O                     |       |             |
| <b>Data</b>                            |                |   |       |             |
| <i>Common Logical Node Information</i> |                |   |       |             |
| Mod                                    | WW_INC1        | Mode                                    | M     | Status-only |
| Beh                                    | WW_INS1        | Behaviour                               | M     |             |
| Health                                 | WW_INS3        | Health                                  | M     |             |
| NamPlt                                 | WW_LPL1        | Name plate                              | M     |             |
| <i>Status Information</i>              |                |   |       |             |
| SPCSO1                                 | WW_SPC2        | Single point controllable status output | O     |             |
| SPCSO2                                 | WW_SPC2        | Single point controllable status output | O     |             |
| SPCSO3                                 | WW_SPC2        | Single point controllable status output | O     |             |
| SPCSO4                                 | WW_SPC2        | Single point controllable status output | O     |             |
| SPCSO5                                 | WW_SPC2        | Single point controllable status output | O     |             |
| SPCSO6                                 | WW_SPC2        | Single point controllable status output | O     |             |
| SPCSO7                                 | WW_SPC2        | Single point controllable status output | O     |             |
| SPCSO8                                 | WW_SPC2        | Single point controllable status output | O     |             |
| SPCSO9                                 | WW_SPC2        | Single point controllable status output | O     |             |
| SPCSO10                                | WW_SPC2        | Single point controllable status output | O     |             |
| SPCSO11                                | WW_SPC2        | Single point controllable status output | O     |             |
| SPCSO12                                | WW_SPC2        | Single point controllable status output | O     |             |
| SPCSO13                                | WW_SPC2        | Single point controllable status output | O     |             |
| SPCSO14                                | WW_SPC2        | Single point controllable status output | O     |             |
| SPCSO15                                | WW_SPC2        | Single point controllable status output | O     |             |
| SPCSO16                                | WW_SPC2        | Single point controllable status output | O     |             |
| SPCSO17                                | WW_SPC2        | Single point controllable status output | O     |             |
| SPCSO18                                | WW_SPC2        | Single point controllable status output | O     |             |

| Attribute Name | Attribute Type | Explanation                             | M/O/E | Remarks |
|----------------|----------------|---|-------|---------|
| SPCSO19        | WW_SPC2        | Single point controllable status output | O     |         |
| SPCSO20        | WW_SPC2        | Single point controllable status output | O     |         |
| SPCSO21        | WW_SPC2        | Single point controllable status output | O     |         |
| SPCSO22        | WW_SPC2        | Single point controllable status output | O     |         |
| SPCSO23        | WW_SPC2        | Single point controllable status output | O     |         |
| SPCSO24        | WW_SPC2        | Single point controllable status output | O     |         |
| SPCSO25        | WW_SPC2        | Single point controllable status output | O     |         |
| SPCSO26        | WW_SPC2        | Single point controllable status output | O     |         |
| SPCSO27        | WW_SPC2        | Single point controllable status output | O     |         |
| SPCSO28        | WW_SPC2        | Single point controllable status output | O     |         |
| SPCSO29        | WW_SPC2        | Single point controllable status output | O     |         |
| SPCSO30        | WW_SPC2        | Single point controllable status output | O     |         |
| SPCSO31        | WW_SPC2        | Single point controllable status output | O     |         |
| SPCSO32        | WW_SPC2        | Single point controllable status output | O     |         |

## 2.10 WW\_IHMI1

| Attribute Name                         | Attribute Type | Explanation             | M/O/E | Remarks     |
|--|----------------|-------------------------|-------|-------------|
| <b>IHMI class</b>                      |                |                         |       |             |
| IHMI                                   | WW_IHMI1       | Human machine interface |       |             |
| <b>Data</b>                            |                |                         |       |             |
| <i>Common Logical Node Information</i> |                |                         |       |             |
| Mod                                    | WW_INC1        | Mode                    | M     | Status-only |
| Beh                                    | WW_INS1        | Behaviour               | M     |             |
| Health                                 | WW_INS3        | Health                  | M     |             |
| NamPlt                                 | WW_LPL1        | Name plate              | M     |             |

## 2.11 WW\_LLNOCON

| Attribute Name                         | Attribute Type | Explanation         | M/O/E | Remarks |
|--|----------------|---------------------|-------|---------|
| <b>LLNO class</b>                      |                |                     |       |         |
| LLNO                                   | WW_LLNOCON     | Logical Node device |       |         |
| <b>Data</b>                            |                |                     |       |         |
| <i>Common Logical Node Information</i> |                |                     |       |         |

| Attribute Name | Attribute Type | Explanation | M/O/E | Remarks     |
|----------------|----------------|-------------|-------|-------------|
| Mod            | WW_INC1        | Mode        | M     | Status-only |
| Beh            | WW_INS1        | Behaviour   | M     |             |
| Health         | WW_INS3        | Health      | M     |             |
| NamPlt         | WW_LPL2        | Name plate  | M     |             |

## 2.12 WW\_LLNOMEA

| Attribute Name                         | Attribute Type | Explanation         | M/O/E | Remarks     |
|--|----------------|---------------------|-------|-------------|
| <b>LLNO class</b>                      |                |                     |       |             |
| LLNO                                   | WW_LLNOMEA     | Logical Node device |       |             |
| <b>Data</b>                            |                |                     |       |             |
| <i>Common Logical Node Information</i> |                |                     |       |             |
| Mod                                    | WW_INC1        | Mode                | M     | Status-only |
| Beh                                    | WW_INS1        | Behaviour           | M     |             |
| Health                                 | WW_INS3        | Health              | M     |             |
| NamPlt                                 | WW_LPL2        | Name plate          | M     |             |

## 2.13 WW\_LLNOPRO

| Attribute Name                         | Attribute Type | Explanation         | M/O/E | Remarks     |
|--|----------------|---------------------|-------|-------------|
| <b>LLNO class</b>                      |                |                     |       |             |
| LLNO                                   | WW_LLNOPRO     | Logical Node device |       |             |
| <b>Data</b>                            |                |                     |       |             |
| <i>Common Logical Node Information</i> |                |                     |       |             |
| Mod                                    | WW_INC1        | Mode                | M     | Status-only |
| Beh                                    | WW_INS1        | Behaviour           | M     |             |
| Health                                 | WW_INS3        | Health              | M     |             |
| NamPlt                                 | WW_LPL2        | Name plate          | M     |             |

## 2.14 WW\_LLNOREC

| Attribute Name                         | Attribute Type | Explanation         | M/O/E | Remarks     |
|--|----------------|---------------------|-------|-------------|
| <b>LLNO class</b>                      |                |                     |       |             |
| LLNO                                   | WW_LLNOREC     | Logical Node device |       |             |
| <b>Data</b>                            |                |                     |       |             |
| <i>Common Logical Node Information</i> |                |                     |       |             |
| Mod                                    | WW_INC1        | Mode                | M     | Status-only |
| Beh                                    | WW_INS1        | Behaviour           | M     |             |
| Health                                 | WW_INS3        | Health              | M     |             |
| NamPlt                                 | WW_LPL2        | Name plate          | M     |             |

## 2.15 WW\_LLNO5SYS

| Attribute Name                         | Attribute Type | Explanation         | M/O/E | Remarks     |
|--|----------------|---------------------|-------|-------------|
| <b>LLNO class</b>                      |                |                     |       |             |
| LLNO                                   | WW_LLNO5SYS    | Logical Node device |       |             |
| <b>Data</b>                            |                |                     |       |             |
| <i>Common Logical Node Information</i> |                |                     |       |             |
| Mod                                    | WW_INC1        | Mode                | M     | Status-only |
| Beh                                    | WW_INS1        | Behaviour           | M     |             |
| Health                                 | WW_INS3        | Health              | M     |             |
| NamPlt                                 | WW_LPL2        | Name plate          | M     |             |

## 2.16 WW\_LPHDCON

| Attribute Name                         | Attribute Type | Explanation                     | M/O/E | Remarks |
|--|----------------|---------------------------------|-------|---------|
| <b>LPHD class</b>                      |                |                                 |       |         |
| LPHD                                   | WW_LPHDCON     | Physical device information     |       |         |
| <b>Data</b>                            |                |                                 |       |         |
| <i>Common Logical Node Information</i> |                |                                 |       |         |
| PhyNam                                 | WW_DPL1        | Physical device name plate      | M     |         |
| PhyHealth                              | WW_INS3        | Physical Device Health          | M     |         |
| Proxy                                  | WW_SPS1        | Indicates if this LN is a proxy | M     |         |

## 2.17 WW\_LPHDMEA

| Attribute Name                         | Attribute Type | Explanation                     | M/O/E | Remarks |
|--|----------------|---------------------------------|-------|---------|
| <b>LPHD class</b>                      |                |                                 |       |         |
| LPHD                                   | WW_LPHDMEA     | Physical device information     |       |         |
| <b>Data</b>                            |                |                                 |       |         |
| <i>Common Logical Node Information</i> |                |                                 |       |         |
| PhyNam                                 | WW_DPL1        | Physical device name plate      | M     |         |
| PhyHealth                              | WW_INS3        | Physical Device Health          | M     |         |
| Proxy                                  | WW_SPS1        | Indicates if this LN is a proxy | M     |         |

## 2.18 WW\_LPHDPRO

| Attribute Name                         | Attribute Type | Explanation                     | M/O/E | Remarks |
|--|----------------|---------------------------------|-------|---------|
| <b>LPHD class</b>                      |                |                                 |       |         |
| LPHD                                   | WW_LPHDPRO     | Physical device information     |       |         |
| <b>Data</b>                            |                |                                 |       |         |
| <i>Common Logical Node Information</i> |                |                                 |       |         |
| PhyNam                                 | WW_DPL1        | Physical device name plate      | M     |         |
| PhyHealth                              | WW_INS3        | Physical Device Health          | M     |         |
| Proxy                                  | WW_SPS1        | Indicates if this LN is a proxy | M     |         |

## 2.19 WW\_LPHDREC

| Attribute Name                         | Attribute Type | Explanation                     | M/O/E | Remarks |
|--|----------------|---------------------------------|-------|---------|
| <b>LPHD class</b>                      |                |                                 |       |         |
| LPHD                                   | WW_LPHDREC     | Physical device information     |       |         |
| <b>Data</b>                            |                |                                 |       |         |
| <i>Common Logical Node Information</i> |                |                                 |       |         |
| PhyNam                                 | WW_DPL1        | Physical device name plate      | M     |         |
| PhyHealth                              | WW_INS3        | Physical Device Health          | M     |         |
| Proxy                                  | WW_SPS1        | Indicates if this LN is a proxy | M     |         |

## 2.20 WW\_LPHDSYS

| Attribute Name                         | Attribute Type | Explanation                     | M/O/E | Remarks |
|--|----------------|---------------------------------|-------|---------|
| <b>LPHD class</b>                      |                |                                 |       |         |
| LPHD                                   | WW_LPHDSYS     | Physical device information     |       |         |
| <b>Data</b>                            |                |                                 |       |         |
| <i>Common Logical Node Information</i> |                |                                 |       |         |
| PhyNam                                 | WW_DPL1        | Physical device name plate      | M     |         |
| PhyHealth                              | WW_INS3        | Physical Device Health          | M     |         |
| Proxy                                  | WW_SPS1        | Indicates if this LN is a proxy | M     |         |

## 2.21 WW\_MMTR1

| Attribute Name                         | Attribute Type | Explanation                   | M/O/E | Remarks     |
|--|----------------|-------------------------------|-------|-------------|
| <b>MSTA class</b>                      |                |                               |       |             |
| MMTR1                                  | WW_MMTR1       | Metering                      |       |             |
| <b>Data</b>                            |                |                               |       |             |
| <i>Common Logical Node Information</i> |                |                               |       |             |
| Mod                                    | WW_INC1        | Mode                          | M     | Status-only |
| Beh                                    | WW_INS1        | Behaviour                     | M     |             |
| Health                                 | WW_INS3        | Health                        | M     |             |
| NamPlt                                 | WW_LPL1        | Name plate                    | M     |             |
| <i>Metered values</i>                  |                |                               |       |             |
| TotVAh                                 | WW_BCR1        | Absolute Apparent Power Hours | O     |             |
| TotWh                                  | WW_BCR1        | Absolute Active Power Hours   | O     |             |
| TotVARh                                | WW_BCR1        | Absolute Reactive Power Hours | O     |             |
| SupWh                                  | WW_BCR1        | Consumed Active Energy        | O     |             |
| SupVARh                                | WW_BCR1        | Consumed Reactive Energy      | O     |             |
| DmdWh                                  | WW_BCR1        | Fed Active Energy             | O     |             |
| DmdVARh                                | WW_BCR1        | Fed Reactive Energy           | O     |             |

## 2.22 WW\_MMXU3

| Attribute Name    | Attribute Type | Explanation | M/O/E | Remarks |
|-------------------|----------------|-------------|-------|---------|
| <b>MMXU class</b> |                |             |       |         |

| Attribute Name                         | Attribute Type | Explanation                    | M/O/E | Remarks     |
|--|----------------|--------------------------------|-------|-------------|
| MMXU                                   | WW_MMXU3       | Measurement                    |       |             |
| <b>Data</b>                            |                |                                |       |             |
| <i>Common Logical Node Information</i> |                |                                |       |             |
| Mod                                    | WW_INC1        | Mode                           | M     | Status-only |
| Beh                                    | WW_INS1        | Behaviour                      | M     |             |
| Health                                 | WW_INS3        | Health                         | M     |             |
| NamPlt                                 | WW_LPL1        | Name plate                     | M     |             |
| <i>Measured values</i>                 |                |                                |       |             |
| TotW                                   | WW_MV1         | Total Active Power (Total P)   | O     |             |
| TotVAr                                 | WW_MV1         | Total Reactive Power (Total Q) | O     |             |
| TotVA                                  | WW_MV1         | Total Apparent Power (Total S) | O     |             |
| TotPF                                  | WW_MV1         | Total Power factor (Total PF)  | O     |             |

## 2.23 WW\_MMXU6

| Attribute Name                         | Attribute Type | Explanation                                | M/O/E | Remarks     |
|--|----------------|--|-------|-------------|
| <b>MMXU class</b>                      |                |  |       |             |
| MMXU                                   | WW_MMXU6       | Measurement                                |       |             |
| <b>Data</b>                            |                |  |       |             |
| <i>Common Logical Node Information</i> |                |  |       |             |
| Mod                                    | WW_INC1        | Mode                                       | M     | Status-only |
| Beh                                    | WW_INS1        | Behaviour                                  | M     |             |
| Health                                 | WW_INS3        | Health                                     | M     |             |
| NamPlt                                 | WW_LPL1        | Name plate                                 | M     |             |
| <i>Measured values</i>                 |                |  |       |             |
| PPV                                    | WW_DEL2        | Phase to phase voltages (VL12, VL23, VL31) | O     |             |
| PhV                                    | WW_WYE2        | Phase to ground voltages (VL1, VL2, VL3)   | O     |             |
| Hz                                     | WW_MV1         | Frequency                                  | O     |             |

## 2.24 WW\_MMXU7

| Attribute Name    | Attribute Type | Explanation | M/O/E | Remarks |
|-------------------|----------------|-------------|-------|---------|
| <b>MMXU class</b> |                |             |       |         |
| MMXU              | WW_MMXU7       | Measurement |       |         |

| Attribute Name                         | Attribute Type | Explanation                    | M/O/E | Remarks     |
|--|----------------|--------------------------------|-------|-------------|
| <b>Data</b>                            |                |                                |       |             |
| <i>Common Logical Node Information</i> |                |                                |       |             |
| Mod                                    | WW_INC1        | Mode                           | M     | Status-only |
| Beh                                    | WW_INS1        | Behaviour                      | M     |             |
| Health                                 | WW_INS3        | Health                         | M     |             |
| NamPlt                                 | WW_LPL1        | Name plate                     | M     |             |
| <i>Measured values</i>                 |                |                                |       |             |
| A                                      | WW_WYE2        | Phase currents (IL1, IL2, IL3) | O     |             |

## 2.25 WW\_MSTA1

| Attribute Name                         | Attribute Type | Explanation         | M/O/E | Remarks     |
|--|----------------|---------------------|-------|-------------|
| <b>MSTA class</b>                      |                |                     |       |             |
| MSTA                                   | WW_MSTA1       | Metering Statistics |       |             |
| <b>Data</b>                            |                |                     |       |             |
| <i>Common Logical Node Information</i> |                |                     |       |             |
| Mod                                    | WW_INC1        | Mode                | M     | Status-only |
| Beh                                    | WW_INS1        | Behaviour           | M     |             |
| Health                                 | WW_INS3        | Health              | M     |             |
| NamPlt                                 | WW_LPL1        | Name plate          | M     |             |
| <i>Metered values</i>                  |                |                     |       |             |
| AvAPhA                                 | WW_MV1         | Average current IL1 | E     |             |
| AvAPhB                                 | WW_MV1         | Average current IL2 | E     |             |
| AvAPhC                                 | WW_MV1         | Average current IL3 | E     |             |
| MaxAPhA                                | WW_MV1         | Maximum current IL1 | E     |             |
| MaxAPhB                                | WW_MV1         | Maximum current IL2 | E     |             |
| MaxAPhC                                | WW_MV1         | Maximum current IL3 | E     |             |
| MinAPhA                                | WW_MV1         | Minimum current IL1 | E     |             |
| MinAPhB                                | WW_MV1         | Minimum current IL2 | E     |             |
| MinAPhC                                | WW_MV1         | Minimum current IL3 | E     |             |



## 2.26 WW\_MSTA2

| Attribute Name                         | Attribute Type | Explanation          | M/O/E | Remarks     |
|--|----------------|----------------------|-------|-------------|
| <b>MSTA class</b>                      |                |                      |       |             |
| MSTA                                   | WW_MSTA2       | Metering Statistics  |       |             |
| <b>Data</b>                            |                |                      |       |             |
| <i>Common Logical Node Information</i> |                |                      |       |             |
| Mod                                    | WW_INC1        | Mode                 | M     | Status-only |
| Beh                                    | WW_INS1        | Behaviour            | M     |             |
| Health                                 | WW_INS3        | Health               | M     |             |
| NamPlt                                 | WW_LPL1        | Name plate           | M     |             |
| <i>Metered values</i>                  |                |                      |       |             |
| AvVPhAB                                | WW_MV1         | Average voltage VL12 | E     |             |
| AvVPhBC                                | WW_MV1         | Average voltage VL23 | E     |             |
| AvVPhCA                                | WW_MV1         | Average voltage VL31 | E     |             |
| MaxVPhAB                               | WW_MV1         | Maximum voltage VL12 | E     |             |
| MaxVPhBC                               | WW_MV1         | Maximum voltage VL23 | E     |             |
| MaxVPhCA                               | WW_MV1         | Maximum voltage VL31 | E     |             |
| MinVPhAB                               | WW_MV1         | Minimum voltage VL12 | E     |             |
| MinVPhBC                               | WW_MV1         | Minimum voltage VL23 | E     |             |
| MinVPhCA                               | WW_MV1         | Minimum voltage VL31 | E     |             |
| AvVPhA                                 | WW_MV1         | Average voltage VL1  | E     |             |
| AvVPhB                                 | WW_MV1         | Average voltage VL2  | E     |             |
| AvVPhC                                 | WW_MV1         | Average voltage VL3  | E     |             |
| MaxVPhA                                | WW_MV1         | Maximum voltage VL1  | E     |             |
| MaxVPhB                                | WW_MV1         | Maximum voltage VL2  | E     |             |
| MaxVPhC                                | WW_MV1         | Maximum voltage VL3  | E     |             |
| MinVPhA                                | WW_MV1         | Minimum voltage VL1  | E     |             |
| MinVPhB                                | WW_MV1         | Minimum voltage VL2  | E     |             |
| MinVPhC                                | WW_MV1         | Minimum voltage VL3  | E     |             |

## 2.27 WW\_MSTA3

| Attribute Name    | Attribute Type | Explanation         | M/O/E | Remarks |
|-------------------|----------------|---------------------|-------|---------|
| <b>MSTA class</b> |                |                     |       |         |
| MSTA              | WW_MSTA3       | Metering Statistics |       |         |

| Attribute Name                         | Attribute Type | Explanation            | M/O/E | Remarks     |
|--|----------------|------------------------|-------|-------------|
| <b>Data</b>                            |                |                        |       |             |
| <i>Common Logical Node Information</i> |                |                        |       |             |
| Mod                                    | WW_INC1        | Mode                   | M     | Status-only |
| Beh                                    | WW_INS1        | Behaviour              | M     |             |
| Health                                 | WW_INS3        | Health                 | M     |             |
| NamPlt                                 | WW_LPL1        | Name plate             | M     |             |
| <i>Metered values</i>                  |                |                        |       |             |
| AvVA                                   | WW_MV1         | Average apparent power | O     |             |
| MaxVA                                  | WW_MV1         | Maximum apparent power | O     |             |
| MinVA                                  | WW_MV1         | Minimum apparent power | O     |             |
| Avw                                    | WW_MV1         | Average real power     | O     |             |
| MaxW                                   | WW_MV1         | Maximum real power     | O     |             |
| MinW                                   | WW_MV1         | Minimum real power     | O     |             |
| AvVAr                                  | WW_MV1         | Average reactive power | O     |             |
| MaxVAr                                 | WW_MV1         | Maximum reactive power | O     |             |
| MinVAr                                 | WW_MV1         | Minimum reactive power | O     |             |

## 2.28 WW\_PDIF1

| Attribute Name                         | Attribute Type | Explanation  | M/O/E | Remarks     |
|--|----------------|--------------|-------|-------------|
| <b>PDIF class</b>                      |                |              |       |             |
| PDIF                                   | WW_PDIF1       | Differential |       |             |
| <b>Data</b>                            |                |              |       |             |
| <i>Common Logical Node Information</i> |                |              |       |             |
| Mod                                    | WW_INC1        | Mode         | M     | Status-only |
| Beh                                    | WW_INS1        | Behaviour    | M     |             |
| Health                                 | WW_INS3        | Health       | M     |             |
| NamPlt                                 | WW_LPL1        | Name plate   | M     |             |
| <i>Status Information</i>              |                |              |       |             |
| Str                                    | WW_ACD1        | Start        | M     |             |
| Op                                     | WW_ACT1        | Operate      | M     |             |

## 2.29 WW\_PDIF2

| Attribute Name                         | Attribute Type | Explanation  | M/O/E | Remarks     |
|--|----------------|--------------|-------|-------------|
| <b>PDIF class</b>                      |                |              |       |             |
| PDIF                                   | WW_PDIF2       | Differential |       |             |
| <b>Data</b>                            |                |              |       |             |
| <i>Common Logical Node Information</i> |                |              |       |             |
| Mod                                    | WW_INC1        | Mode         | M     | Status-only |
| Beh                                    | WW_INS1        | Behaviour    | M     |             |
| Health                                 | WW_INS3        | Health       | M     |             |
| NamPlt                                 | WW_LPL1        | Name plate   | M     |             |
| <i>Status Information</i>              |                |              |       |             |
| Str                                    | WW_ACD1        | Start        | M     |             |
| Op                                     | WW_ACT1        | Operate      | M     |             |

## 2.30 WW\_PDIF3

| Attribute Name                         | Attribute Type | Explanation  | M/O/E | Remarks     |
|--|----------------|--------------|-------|-------------|
| <b>PDIF class</b>                      |                |              |       |             |
| PDIF                                   | WW_PDIF3       | Differential |       |             |
| <b>Data</b>                            |                |              |       |             |
| <i>Common Logical Node Information</i> |                |              |       |             |
| Mod                                    | WW_INC1        | Mode         | M     | Status-only |
| Beh                                    | WW_INS1        | Behaviour    | M     |             |
| Health                                 | WW_INS3        | Health       | M     |             |
| NamPlt                                 | WW_LPL1        | Name plate   | M     |             |
| <i>Status Information</i>              |                |              |       |             |
| Str                                    | WW_ACD1        | Start        | M     |             |
| Op                                     | WW_ACT1        | Operate      | M     |             |

## 2.31 WW\_PDIF4

| Attribute Name    | Attribute Type | Explanation  | M/O/E | Remarks |
|-------------------|----------------|--------------|-------|---------|
| <b>PDIF class</b> |                |              |       |         |
| PDIF              | WW_PDIF4       | Differential |       |         |

| Attribute Name                         | Attribute Type | Explanation | M/O/E | Remarks     |
|--|----------------|-------------|-------|-------------|
| <b>Data</b>                            |                |             |       |             |
| <i>Common Logical Node Information</i> |                |             |       |             |
| Mod                                    | WW_INC1        | Mode        | M     | Status-only |
| Beh                                    | WW_INS1        | Behaviour   | M     |             |
| Health                                 | WW_INS3        | Health      | M     |             |
| NamPlt                                 | WW_LPL1        | Name plate  | M     |             |
| <i>Status Information</i>              |                |             |       |             |
| Str                                    | WW_ACD1        | Start       | M     |             |
| Op                                     | WW_ACT1        | Operate     | M     |             |

## 2.32 WW\_PDOP1

| Attribute Name                         | Attribute Type | Explanation           | M/O/E | Remarks     |
|--|----------------|-----------------------|-------|-------------|
| <b>PDOP class</b>                      |                |                       |       |             |
| PDOP                                   | WW_PDOP1       | Directional overpower |       |             |
| <b>Data</b>                            |                |                       |       |             |
| <i>Common Logical Node Information</i> |                |                       |       |             |
| Mod                                    | WW_INC1        | Mode                  | M     | Status-only |
| Beh                                    | WW_INS1        | Behaviour             | M     |             |
| Health                                 | WW_INS3        | Health                | M     |             |
| NamPlt                                 | WW_LPL1        | Name plate            | M     |             |
| <i>Status Information</i>              |                |                       |       |             |
| Str                                    | WW_ACD1        | Start                 | M     |             |
| Op                                     | WW_ACT1        | Operate               | M     |             |

## 2.33 WW\_PDUP1

| Attribute Name                         | Attribute Type | Explanation            | M/O/E | Remarks     |
|--|----------------|------------------------|-------|-------------|
| <b>PDUP class</b>                      |                |                        |       |             |
| PDUP                                   | WW_PDUP1       | Directional underpower |       |             |
| <b>Data</b>                            |                |                        |       |             |
| <i>Common Logical Node Information</i> |                |                        |       |             |
| Mod                                    | WW_INC1        | Mode                   | M     | Status-only |
| Beh                                    | WW_INS1        | Behaviour              | M     |             |

| Attribute Name            | Attribute Type | Explanation | M/O/E | Remarks |
|---------------------------|----------------|-------------|-------|---------|
| Health                    | WW_INS3        | Health      | M     |         |
| NamPlt                    | WW_LPL1        | Name plate  | M     |         |
| <i>Status Information</i> |                |             |       |         |
| Str                       | WW_ACD1        | Start       | M     |         |
| Op                        | WW_ACT1        | Operate     | M     |         |

## 2.34 WW\_PFC1

| Attribute Name                         | Attribute Type | Explanation                 | M/O/E | Remarks     |
|--|----------------|-----------------------------|-------|-------------|
| <b>PFRC class</b>                      |                |                             |       |             |
| PFRC                                   | WW_PFC1        | Rate of change of frequency |       |             |
| <b>Data</b>                            |                |                             |       |             |
| <i>Common Logical Node Information</i> |                |                             |       |             |
| Mod                                    | WW_INC1        | Mode                        | M     | Status-only |
| Beh                                    | WW_INS1        | Behaviour                   | M     |             |
| Health                                 | WW_INS3        | Health                      | M     |             |
| NamPlt                                 | WW_LPL1        | Name plate                  | M     |             |
| <i>Status Information</i>              |                |                             |       |             |
| Str                                    | WW_ACD1        | Start                       | M     |             |
| Op                                     | WW_ACT1        | Operate                     | M     |             |

## 2.35 WW\_PFC2

| Attribute Name                         | Attribute Type | Explanation                 | M/O/E | Remarks     |
|--|----------------|-----------------------------|-------|-------------|
| <b>PFRC class</b>                      |                |                             |       |             |
| PFRC                                   | WW_PFC2        | Rate of change of frequency |       |             |
| <b>Data</b>                            |                |                             |       |             |
| <i>Common Logical Node Information</i> |                |                             |       |             |
| Mod                                    | WW_INC1        | Mode                        | M     | Status-only |
| Beh                                    | WW_INS1        | Behaviour                   | M     |             |
| Health                                 | WW_INS3        | Health                      | M     |             |
| NamPlt                                 | WW_LPL1        | Name plate                  | M     |             |
| <i>Status Information</i>              |                |                             |       |             |
| Str                                    | WW_ACD1        | Start                       | M     |             |

| Attribute Name | Attribute Type | Explanation | M/O/E | Remarks |
|----------------|----------------|-------------|-------|---------|
| Op             | WW_ACT1        | Operate     | M     |         |

## 2.36 WW\_PHAR1

| Attribute Name                         | Attribute Type | Explanation        | M/O/E | Remarks     |
|--|----------------|--------------------|-------|-------------|
| <b>PHAR class</b>                      |                |                    |       |             |
| PHAR                                   | WW_PHAR1       | Harmonic restraint |       |             |
| <b>Data</b>                            |                |                    |       |             |
| <i>Common Logical Node Information</i> |                |                    |       |             |
| Mod                                    | WW_INC1        | Mode               | M     | Status-only |
| Beh                                    | WW_INS1        | Behaviour          | M     |             |
| Health                                 | WW_INS3        | Health             | M     |             |
| NamPlt                                 | WW_LPL1        | Name plate         | M     |             |
| <i>Status Information</i>              |                |                    |       |             |
| Str                                    | WW_ACD1        | Start              | M     |             |

## 2.37 WW\_PPAM1

| Attribute Name                         | Attribute Type | Explanation           | M/O/E | Remarks     |
|--|----------------|-----------------------|-------|-------------|
| <b>PPAM class</b>                      |                |                       |       |             |
| PPAM                                   | WW_PPAM1       | Phase angle measuring |       |             |
| <b>Data</b>                            |                |                       |       |             |
| <i>Common Logical Node Information</i> |                |                       |       |             |
| Mod                                    | WW_INC1        | Mode                  | M     | Status-only |
| Beh                                    | WW_INS1        | Behaviour             | M     |             |
| Health                                 | WW_INS3        | Health                | M     |             |
| NamPlt                                 | WW_LPL1        | Name plate            | M     |             |
| <i>Status Information</i>              |                |                       |       |             |
| Str                                    | WW_ACD1        | Start                 | M     |             |
| Op                                     | WW_ACT1        | Operate               | M     |             |

## 2.38 WW\_PSO1

| Attribute Name                         | Attribute Type | Explanation                  | M/O/E | Remarks     |
|--|----------------|------------------------------|-------|-------------|
| <b>PSOF class</b>                      |                |                              |       |             |
| PSOF                                   | WW_PSO1        | Protection Switch Onto fault |       |             |
| <b>Data</b>                            |                |                              |       |             |
| <i>Common Logical Node Information</i> |                |                              |       |             |
| Mod                                    | WW_INC1        | Mode                         | M     | Status-only |
| Beh                                    | WW_INS1        | Behaviour                    | M     |             |
| Health                                 | WW_INS3        | Health                       | M     |             |
| NamPlt                                 | WW_LPL3        | Name plate                   | M     |             |
| <i>Status Information</i>              |                |                              |       |             |
| Str                                    | WW_ACD1        | Start                        | M     |             |

## 2.39 WW\_PTOC1

| Attribute Name                         | Attribute Type | Explanation      | M/O/E | Remarks     |
|--|----------------|------------------|-------|-------------|
| <b>PTOC class</b>                      |                |                  |       |             |
| PTOC                                   | WW_PTOC1       | Time overcurrent |       |             |
| <b>Data</b>                            |                |                  |       |             |
| <i>Common Logical Node Information</i> |                |                  |       |             |
| Mod                                    | WW_INC1        | Mode             | M     | Status-only |
| Beh                                    | WW_INS1        | Behaviour        | M     |             |
| Health                                 | WW_INS3        | Health           | M     |             |
| NamPlt                                 | WW_LPL1        | Name plate       | M     |             |
| <i>Status Information</i>              |                |                  |       |             |
| Str                                    | WW_ACD1        | Start            | M     |             |
| Op                                     | WW_ACT1        | Operate          | M     |             |

## 2.40 WW\_PTOC3

| Attribute Name    | Attribute Type | Explanation      | M/O/E | Remarks |
|-------------------|----------------|------------------|-------|---------|
| <b>PTOC class</b> |                |                  |       |         |
| PTOC              | WW_PTOC3       | Time overcurrent |       |         |
| <b>Data</b>       |                |                  |       |         |

| Attribute Name                         | Attribute Type | Explanation | M/O/E | Remarks     |
|--|----------------|-------------|-------|-------------|
| <i>Common Logical Node Information</i> |                |             |       |             |
| Mod                                    | WW_INC1        | Mode        | M     | Status-only |
| Beh                                    | WW_INS1        | Behaviour   | M     |             |
| Health                                 | WW_INS3        | Health      | M     |             |
| NamPlt                                 | WW_LPL1        | Name plate  | M     |             |
| <i>Status Information</i>              |                |             |       |             |
| Str                                    | WW_ACD1        | Start       | M     |             |
| Op                                     | WW_ACT1        | Operate     | M     |             |

## 2.41 WW\_PTOC4

| Attribute Name                         | Attribute Type | Explanation      | M/O/E | Remarks     |
|--|----------------|------------------|-------|-------------|
| <b>PTOC class</b>                      |                |                  |       |             |
| PTOC                                   | WW_PTOC4       | Time overcurrent |       |             |
| <b>Data</b>                            |                |                  |       |             |
| <i>Common Logical Node Information</i> |                |                  |       |             |
| Mod                                    | WW_INC1        | Mode             | M     | Status-only |
| Beh                                    | WW_INS1        | Behaviour        | M     |             |
| Health                                 | WW_INS3        | Health           | M     |             |
| NamPlt                                 | WW_LPL1        | Name plate       | M     |             |
| <i>Status Information</i>              |                |                  |       |             |
| Str                                    | WW_ACD1        | Start            | M     |             |
| Op                                     | WW_ACT1        | Operate          | M     |             |

## 2.42 WW\_PTOF1

| Attribute Name                         | Attribute Type | Explanation   | M/O/E | Remarks     |
|--|----------------|---------------|-------|-------------|
| <b>PTOF class</b>                      |                |               |       |             |
| PTOF                                   | WW_PTOF1       | Overfrequency |       |             |
| <b>Data</b>                            |                |               |       |             |
| <i>Common Logical Node Information</i> |                |               |       |             |
| Mod                                    | WW_INC1        | Mode          | M     | Status-only |
| Beh                                    | WW_INS1        | Behaviour     | M     |             |
| Health                                 | WW_INS3        | Health        | M     |             |



| Attribute Name            | Attribute Type | Explanation | M/O/E | Remarks |
|---------------------------|----------------|-------------|-------|---------|
| NamPlt                    | WW_LPL1        | Name plate  | M     |         |
| <i>Status Information</i> |                |             |       |         |
| Str                       | WW_ACD1        | Start       | M     |         |
| Op                        | WW_ACT1        | Operate     | M     |         |

## 2.43 WW\_PTOV1

| Attribute Name                         | Attribute Type | Explanation | M/O/E | Remarks     |
|--|----------------|-------------|-------|-------------|
| <b>PTOV class</b>                      |                |             |       |             |
| PTOV                                   | WW_PTOV1       | Overvoltage |       |             |
| <b>Data</b>                            |                |             |       |             |
| <i>Common Logical Node Information</i> |                |             |       |             |
| Mod                                    | WW_INC1        | Mode        | M     | Status-only |
| Beh                                    | WW_INS1        | Behaviour   | M     |             |
| Health                                 | WW_INS3        | Health      | M     |             |
| NamPlt                                 | WW_LPL1        | Name plate  | M     |             |
| <i>Status Information</i>              |                |             |       |             |
| Str                                    | WW_ACD1        | Start       | M     |             |
| Op                                     | WW_ACT1        | Operate     | M     |             |

## 2.44 WW\_PTOV2

| Attribute Name                         | Attribute Type | Explanation | M/O/E | Remarks     |
|--|----------------|-------------|-------|-------------|
| <b>PTOV class</b>                      |                |             |       |             |
| PTOV                                   | WW_PTOV2       | Overvoltage |       |             |
| <b>Data</b>                            |                |             |       |             |
| <i>Common Logical Node Information</i> |                |             |       |             |
| Mod                                    | WW_INC1        | Mode        | M     | Status-only |
| Beh                                    | WW_INS1        | Behaviour   | M     |             |
| Health                                 | WW_INS3        | Health      | M     |             |
| NamPlt                                 | WW_LPL1        | Name plate  | M     |             |
| <i>Status Information</i>              |                |             |       |             |
| Str                                    | WW_ACD1        | Start       | M     |             |

| Attribute Name | Attribute Type | Explanation | M/O/E | Remarks |
|----------------|----------------|-------------|-------|---------|
| Op             | WW_ACT1        | Operate     | M     |         |

## 2.45 WW\_PTOV3

| Attribute Name                         | Attribute Type | Explanation | M/O/E | Remarks     |
|--|----------------|-------------|-------|-------------|
| <b>PTOV class</b>                      |                |             |       |             |
| PTOV                                   | WW_PTOV3       | Overvoltage |       |             |
| <b>Data</b>                            |                |             |       |             |
| <i>Common Logical Node Information</i> |                |             |       |             |
| Mod                                    | WW_INC1        | Mode        | M     | Status-only |
| Beh                                    | WW_INS1        | Behaviour   | M     |             |
| Health                                 | WW_INS3        | Health      | M     |             |
| NamPlt                                 | WW_LPL1        | Name plate  | M     |             |
| <i>Status Information</i>              |                |             |       |             |
| Str                                    | WW_ACD1        | Start       | M     |             |
| Op                                     | WW_ACT1        | Operate     | M     |             |

## 2.46 WW\_PTTR3

| Attribute Name                         | Attribute Type | Explanation      | M/O/E | Remarks     |
|--|----------------|------------------|-------|-------------|
| <b>PTTR class</b>                      |                |                  |       |             |
| PTTR                                   | WW_PTTR3       | Thermal overload |       |             |
| <b>Data</b>                            |                |                  |       |             |
| <i>Common Logical Node Information</i> |                |                  |       |             |
| Mod                                    | WW_INC1        | Mode             | M     | Status-only |
| Beh                                    | WW_INS1        | Behaviour        | M     |             |
| Health                                 | WW_INS3        | Health           | M     |             |
| NamPlt                                 | WW_LPL1        | Name plate       | M     |             |
| <i>Status Information</i>              |                |                  |       |             |
| Op                                     | WW_ACT1        | Operate          | M     |             |

## 2.47 WW\_PTTR4

| Attribute Name                         | Attribute Type | Explanation      | M/O/E | Remarks     |
|--|----------------|------------------|-------|-------------|
| <b>PTTR class</b>                      |                |                  |       |             |
| PTTR                                   | WW_PTTR4       | Thermal overload |       |             |
| <b>Data</b>                            |                |                  |       |             |
| <i>Common Logical Node Information</i> |                |                  |       |             |
| Mod                                    | WW_INC1        | Mode             | M     | Status-only |
| Beh                                    | WW_INS1        | Behaviour        | M     |             |
| Health                                 | WW_INS3        | Health           | M     |             |
| NamPlt                                 | WW_LPL1        | Name plate       | M     |             |
| <i>Status Information</i>              |                |                  |       |             |
| Op                                     | WW_ACT1        | Operate          | M     |             |

## 2.48 WW\_PTUF1

| Attribute Name                         | Attribute Type | Explanation    | M/O/E | Remarks     |
|--|----------------|----------------|-------|-------------|
| <b>PTUF class</b>                      |                |                |       |             |
| PTUF                                   | WW_PTUF1       | Underfrequency |       |             |
| <b>Data</b>                            |                |                |       |             |
| <i>Common Logical Node Information</i> |                |                |       |             |
| Mod                                    | WW_INC1        | Mode           | M     | Status-only |
| Beh                                    | WW_INS1        | Behaviour      | M     |             |
| Health                                 | WW_INS3        | Health         | M     |             |
| NamPlt                                 | WW_LPL1        | Name plate     | M     |             |
| <i>Status Information</i>              |                |                |       |             |
| Str                                    | WW_ACD1        | Start          | M     |             |
| Op                                     | WW_ACT1        | Operate        | M     |             |

## 2.49 WW\_PTUV1

| Attribute Name    | Attribute Type | Explanation  | M/O/E | Remarks |
|-------------------|----------------|--------------|-------|---------|
| <b>PTUV class</b> |                |              |       |         |
| PTUV              | WW_PTUV1       | Undervoltage |       |         |
| <b>Data</b>       |                |              |       |         |

| Attribute Name                         | Attribute Type | Explanation | M/O/E | Remarks     |
|--|----------------|-------------|-------|-------------|
| <i>Common Logical Node Information</i> |                |             |       |             |
| Mod                                    | WW_INC1        | Mode        | M     | Status-only |
| Beh                                    | WW_INS1        | Behaviour   | M     |             |
| Health                                 | WW_INS3        | Health      | M     |             |
| NamPlt                                 | WW_LPL1        | Name plate  | M     |             |
| <i>Status Information</i>              |                |             |       |             |
| Str                                    | WW_ACD1        | Start       | M     |             |
| Op                                     | WW_ACT1        | Operate     | M     |             |

## 2.50 WW\_PTUV2

| Attribute Name                         | Attribute Type | Explanation  | M/O/E | Remarks     |
|--|----------------|--------------|-------|-------------|
| <b>PTUV class</b>                      |                |              |       |             |
| PTUV                                   | WW_PTUV2       | Undervoltage |       |             |
| <b>Data</b>                            |                |              |       |             |
| <i>Common Logical Node Information</i> |                |              |       |             |
| Mod                                    | WW_INC1        | Mode         | M     | Status-only |
| Beh                                    | WW_INS1        | Behaviour    | M     |             |
| Health                                 | WW_INS3        | Health       | M     |             |
| NamPlt                                 | WW_LPL1        | Name plate   | M     |             |
| <i>Status Information</i>              |                |              |       |             |
| Str                                    | WW_ACD1        | Start        | M     |             |
| Op                                     | WW_ACT1        | Operate      | M     |             |

## 2.51 WW\_PTUV3

| Attribute Name                         | Attribute Type | Explanation  | M/O/E | Remarks     |
|--|----------------|--------------|-------|-------------|
| <b>PTUV class</b>                      |                |              |       |             |
| PTUV                                   | WW_PTUV3       | Undervoltage |       |             |
| <b>Data</b>                            |                |              |       |             |
| <i>Common Logical Node Information</i> |                |              |       |             |
| Mod                                    | WW_INC1        | Mode         | M     | Status-only |
| Beh                                    | WW_INS1        | Behaviour    | M     |             |
| Health                                 | WW_INS3        | Health       | M     |             |

| Attribute Name            | Attribute Type | Explanation | M/O/E | Remarks |
|---------------------------|----------------|-------------|-------|---------|
| NamPlt                    | WW_LPL1        | Name plate  | M     |         |
| <i>Status Information</i> |                |             |       |         |
| Str                       | WW_ACD1        | Start       | M     |         |
| Op                        | WW_ACT1        | Operate     | M     |         |

## 2.52 WW\_PTUV5

| Attribute Name                         | Attribute Type | Explanation  | M/O/E | Remarks     |
|--|----------------|--------------|-------|-------------|
| <b>PTUV class</b>                      |                |              |       |             |
| PTUV                                   | WW_PTUV5       | Undervoltage |       |             |
| <b>Data</b>                            |                |              |       |             |
| <i>Common Logical Node Information</i> |                |              |       |             |
| Mod                                    | WW_INC1        | Mode         | M     | Status-only |
| Beh                                    | WW_INS1        | Behaviour    | M     |             |
| Health                                 | WW_INS3        | Health       | M     |             |
| NamPlt                                 | WW_LPL1        | Name plate   | M     |             |
| <i>Status Information</i>              |                |              |       |             |
| Str                                    | WW_ACD1        | Start        | M     |             |
| Op                                     | WW_ACT1        | Operate      | M     |             |

## 2.53 WW\_PUPF1

| Attribute Name                         | Attribute Type | Explanation       | M/O/E | Remarks     |
|--|----------------|-------------------|-------|-------------|
| <b>PUPF class</b>                      |                |                   |       |             |
| PUPF                                   | WW_PUPF1       | Underpower factor |       |             |
| <b>Data</b>                            |                |                   |       |             |
| <i>Common Logical Node Information</i> |                |                   |       |             |
| Mod                                    | WW_INC1        | Mode              | M     | Status-only |
| Beh                                    | WW_INS1        | Behaviour         | M     |             |
| Health                                 | WW_INS3        | Health            | M     |             |
| NamPlt                                 | WW_LPL1        | Name plate        | M     |             |
| <i>Status Information</i>              |                |                   |       |             |
| Str                                    | WW_ACD1        | Start             | M     |             |

| Attribute Name | Attribute Type | Explanation | M/O/E | Remarks |
|----------------|----------------|-------------|-------|---------|
| Op             | WW_ACT1        | Operate     | M     |         |

## 2.54 WW\_PVPH1

| Attribute Name                         | Attribute Type | Explanation  | M/O/E | Remarks     |
|--|----------------|--------------|-------|-------------|
| <b>PVPH class</b>                      |                |              |       |             |
| PVPH                                   | WW_PVPH1       | Volts per Hz |       |             |
| <b>Data</b>                            |                |              |       |             |
| <i>Common Logical Node Information</i> |                |              |       |             |
| Mod                                    | WW_INC1        | Mode         | M     | Status-only |
| Beh                                    | WW_INS1        | Behaviour    | M     |             |
| Health                                 | WW_INS3        | Health       | M     |             |
| NamPlt                                 | WW_LPL1        | Name plate   | M     |             |
| <i>Status Information</i>              |                |              |       |             |
| Str                                    | WW_ACD1        | Start        | M     |             |
| Op                                     | WW_ACT1        | Operate      | M     |             |

## 2.55 WW\_PSDE1

| Attribute Name                         | Attribute Type | Explanation                                     | M/O/E | Remarks     |
|--|----------------|---|-------|-------------|
| <b>PSDE class</b>                      |                |   |       |             |
| PSDE                                   | WW_PSDE1       | Wattmetric directional earthfault (IG meas dir) |       |             |
| <b>Data</b>                            |                |   |       |             |
| <i>Common Logical Node Information</i> |                |   |       |             |
| Mod                                    | WW_INC1        | Mode  | M     | Status-only |
| Beh                                    | WW_INS1        | Behaviour                                       | M     |             |
| Health                                 | WW_INS3        | Health  | M     |             |
| NamPlt                                 | WW_LPL1        | Name plate                                      | M     |             |
| <i>Status Information</i>              |                |   |       |             |
| Str                                    | WW_ACD1        | Start   | M     |             |

## 2.56 WW\_PSDE2

| Attribute Name                         | Attribute Type | Explanation                                     | M/O/E | Remarks     |
|--|----------------|---|-------|-------------|
| <b>PSDE class</b>                      |                |   |       |             |
| PSDE                                   | WW_PSDE2       | Wattmetric directional earthfault (IG meas dir) |       |             |
| <b>Data</b>                            |                |   |       |             |
| <i>Common Logical Node Information</i> |                |   |       |             |
| Mod                                    | WW_INC1        | Mode  | M     | Status-only |
| Beh                                    | WW_INS1        | Behaviour                                       | M     |             |
| Health                                 | WW_INS3        | Health  | M     |             |
| NamPlt                                 | WW_LPL1        | Name plate                                      | M     |             |
| <i>Status Information</i>              |                |   |       |             |
| Str                                    | WW_ACD1        | Start   | M     |             |

## 2.57 WW\_RBRF1

| Attribute Name                         | Attribute Type | Explanation          | M/O/E | Remarks     |
|--|----------------|----------------------|-------|-------------|
| <b>RBRF class</b>                      |                |                      |       |             |
| RBRF                                   | WW_RBRF1       | Breaker failure      |       |             |
| <b>Data</b>                            |                |                      |       |             |
| <i>Common Logical Node Information</i> |                |                      |       |             |
| Mod                                    | WW_INC1        | Mode                 | M     | Status-only |
| Beh                                    | WW_INS1        | Behaviour            | M     |             |
| Health                                 | WW_INS3        | Health               | M     |             |
| NamPlt                                 | WW_LPL1        | Name plate           | M     |             |
| <i>Status Information</i>              |                |                      |       |             |
| Str                                    | WW_ACD1        | Start                | M     |             |
| OpEx                                   | WW_ACT1        | Breaker failure trip | M     |             |

## 2.58 WW\_RDRE1

| Attribute Name    | Attribute Type | Explanation                   | M/O/E | Remarks |
|-------------------|----------------|-------------------------------|-------|---------|
| <b>RDRE class</b> |                |                               |       |         |
| RDRE              | WW_RDRE1       | Disturbance recorder function |       |         |
| <b>Data</b>       |                |                               |       |         |

| Attribute Name                         | Attribute Type | Explanation       | M/O/E | Remarks     |
|--|----------------|-------------------|-------|-------------|
| <i>Common Logical Node Information</i> |                |                   |       |             |
| Mod                                    | WW_INC1        | Mode              | M     | Status-only |
| Beh                                    | WW_INS1        | Behaviour         | M     |             |
| Health                                 | WW_INS3        | Health            | M     |             |
| NamPlt                                 | WW_LPL1        | Name plate        | M     |             |
| <i>Status Information</i>              |                |                   |       |             |
| RcdMade                                | WW_SPS1        | Recording made    | M     |             |
| FltNum                                 | WW_INS2        | Fault Number      | M     |             |
| GriFltNum                              | WW_INS2        | Grid Fault Number | O     |             |
| RcdStr                                 | WW_SPS1        | Recording started | O     |             |

## 2.59 WW\_RSYN2

| Attribute Name                         | Attribute Type | Explanation                        | M/O/E | Remarks     |
|--|----------------|------------------------------------|-------|-------------|
| <b>RSYN class</b>                      |                |                                    |       |             |
| RSYN                                   | WW_RSYN2       | Synchronism-check or synchronising |       |             |
| <b>Data</b>                            |                |                                    |       |             |
| <i>Common Logical Node Information</i> |                |                                    |       |             |
| Mod                                    | WW_INC1        | Mode                               | M     | Status-only |
| Beh                                    | WW_INS1        | Behaviour                          | M     |             |
| Health                                 | WW_INS3        | Health                             | M     |             |
| NamPlt                                 | WW_LPL1        | Name plate                         | M     |             |
| <i>Status Information</i>              |                |                                    |       |             |
| Rel                                    | WW_SPS1        | Release                            | M     |             |
| AngInd                                 | WW_SPS1        | Phase Angle difference to high     | E     |             |
| HzInd                                  | WW_SPS1        | Frequency difference to high       | E     |             |
| VInd                                   | WW_SPS1        | Voltage difference to high         | E     |             |
| <i>Measured Values</i>                 |                |                                    |       |             |
| DifAngClc                              | WW_MV1         | Phase Angle difference value       | E     |             |
| DifHzClc                               | WW_MV1         | Frequency difference value         | E     |             |
| DifVClc                                | WW_MV1         | Voltage difference value           | E     |             |



## 2.60 WW\_SCBR1

| Attribute Name                         | Attribute Type | Explanation                | M/O/E | Remarks     |
|--|----------------|----------------------------|-------|-------------|
| <b>RBRF class</b>                      |                |                            |       |             |
| SCBR                                   | WW_SCBR1       | Circuit breaker monitoring |       |             |
| <b>Data</b>                            |                |                            |       |             |
| <i>Common Logical Node Information</i> |                |                            |       |             |
| Mod                                    | WW_INC1        | Mode                       | M     | Status-only |
| Beh                                    | WW_INS1        | Behaviour                  | M     |             |
| Health                                 | WW_INS3        | Health                     | M     |             |
| NamPlt                                 | WW_LPL1        | Name plate                 | M     |             |
| <i>Status Information</i>              |                |                            |       |             |
| TrCctAlm                               | WW_ACD1        | Alarm signal               | E     |             |

## 2.61 WW\_XCBR2

| Attribute Name                         | Attribute Type | Explanation                          | M/O/E | Remarks     |
|--|----------------|--------------------------------------|-------|-------------|
| <b>XCBR class</b>                      |                |                                      |       |             |
| XCBR                                   | WW_XCBR2       | Circuit Breaker                      |       |             |
| <b>Data</b>                            |                |                                      |       |             |
| <i>Common Logical Node Information</i> |                |                                      |       |             |
| Mod                                    | WW_INC1        | Mode                                 | M     | Status-only |
| Beh                                    | WW_INS1        | Behaviour                            | M     |             |
| Health                                 | WW_INS3        | Health                               | M     |             |
| NamPlt                                 | WW_LPL1        | Name plate                           | M     |             |
| Loc                                    | WW_SPS1        | Local operation                      | M     |             |
| OpCnt                                  | WW_INS2        | Operation counter                    | M     |             |
| <i>Status Information</i>              |                |                                      |       |             |
| CBOpCap                                | WW_INS5        | Circuit breaker operating capability | M     |             |
| <i>Controls</i>                        |                |                                      |       |             |
| Pos                                    | WW_DPC1        | Switch position                      | M     |             |
| BlkOpn                                 | WW_SPC1        | Block opening                        | M     |             |
| BlkCls                                 | WW_SPC1        | Block closing                        | M     |             |

## 2.62 WW\_XSWI1

| Attribute Name                         | Attribute Type | Explanation                 | M/O/E | Remarks     |
|--|----------------|-----------------------------|-------|-------------|
| <b>XSWI class</b>                      |                |                             |       |             |
| XSWI                                   | WW_XSWI1       | Circuit switch              |       |             |
| <b>Data</b>                            |                |                             |       |             |
| <i>Common Logical Node Information</i> |                |                             |       |             |
| Mod                                    | WW_INC1        | Mode                        | M     | Status-only |
| Beh                                    | WW_INS1        | Behaviour                   | M     |             |
| Health                                 | WW_INS3        | Health                      | M     |             |
| NamPlt                                 | WW_LPL1        | Name plate                  | M     |             |
| Loc                                    | WW_SPS1        | Local operation             | M     |             |
| OpCnt                                  | WW_INS2        | Operation counter           | M     |             |
| <i>Status Information</i>              |                |                             |       |             |
| SwTyp                                  | WW_INS5        | Switch type                 | M     |             |
| SwOpCap                                | WW_INS5        | Switch operating capability | M     |             |
| <i>Controls</i>                        |                |                             |       |             |
| Pos                                    | WW_DPC1        | Switch position             | M     |             |
| BlkOpn                                 | WW_SPC1        | Block opening               | M     |             |
| BlkCls                                 | WW_SPC1        | Block closing               | M     |             |

## 3 Common Data Class

### 3.1 Common Data Class Definitions

The following table contains the list of Common Data Classes implemented in the device:

| CDC Type        | CDC Class   | Description   |
|-----------------|-------------|---|
| WW_ACD1         | ACD         | Directional Protection activation information                   |
| WW_ACT1         | ACT         | Protection Activation Information                               |
| WW_analogValue1 | analogValue | Analogue value  |
| WW_BCR1         | BCR         | Binary Counter Reading  |
| WW_Cancel1      | Cancel      | Cancel operating  |
| WW_CMV2         | CMV         | Complex measured value  |
| WW_DEL2         | DEL         | Delta   |
| WW_DPC1         | DPC         | Controllable Double Point                                       |
| WW_DPC2         | DPC         | Controllable Double Point                                       |
| WW_DPL1         | DPL         | Device name plate   |
| WW_INC1         | INC         | Controllable Integer Status                                     |
| WW_INS1         | INS         | Integer Status  |
| WW_INS2         | INS         | Integer Status  |
| WW_INS3         | INS         | Integer Status  |
| WW_INS5         | INS         | Integer Status  |
| WW_LPL1         | LPL         | Logical node name plate   |
| WW_LPL2         | LPL         | Logical node name plate   |
| WW_LPL3         | LPL         | Logical node name plate   |
| WW_MV1          | MV          | Measured Value  |
| WW_Oper1        | Oper        | Start/Select operating  |
| WW_origin1      | origin      | Originator  |
| WW_SPC1         | SPC         | Controllable Single Point                                       |
| WW_SPC2         | SPC         | Controllable Single Point                                       |
| WW_SPS1         | SPS         | Single Point Status   |
| WW_units1       | units       | Unit definition   |
| WW_vector1      | vector      | Vector definition   |
| WW_WYE2         | WYE         | Phase to ground related measured values of a three phase system |

**3.1.1 WW\_ACD1**

| Attribute Name   | Attribute Type | FC | TrgOp | Value / Value Range | M/O/E | Remarks |
|------------------|----------------|----|-------|---------------------|-------|---------|
| <b>ACD class</b> |                |    |       |                     |       |         |
| General          | BOOLEAN        | ST | dchg  |                     | M     |         |
| dirGeneral       | Enum           | ST | dchg  | ACDdir              | M     |         |
| q                | Quality        | ST | qchg  |                     | M     |         |
| t                | Timestamp      | ST |       |                     | M     |         |

**3.1.2 WW\_ACT1**

| Attribute Name   | Attribute Type | FC | TrgOp | Value / Value Range | M/O/E | Remarks |
|------------------|----------------|----|-------|---------------------|-------|---------|
| <b>ACT class</b> |                |    |       |                     |       |         |
| General          | BOOLEAN        | ST | dchg  |                     | M     |         |
| q                | Quality        | ST | qchg  |                     | M     |         |
| t                | Timestamp      | ST |       |                     | M     |         |

**3.1.3 WW\_BCR1**

| Attribute Name   | Attribute Type | FC | TrgOp | Value / Value Range | M/O/E | Remarks |
|------------------|----------------|----|-------|---------------------|-------|---------|
| <b>BCR class</b> |                |    |       |                     |       |         |
| actVal           | INT32          | ST | dchg  |                     | M     |         |
| q                | Quality        | ST | qchg  |                     | M     |         |
| t                | Timestamp      | ST |       |                     | M     |         |
| pulsQty          | FLOAT32        | CF |       |                     | M     |         |
| units            | Struct         | CF |       |                     | O     |         |

**3.1.4 WW\_CMV2**

| Attribute Name   | Attribute Type | FC | TrgOp | Value / Value Range | M/O/E | Remarks |
|------------------|----------------|----|-------|---------------------|-------|---------|
| <b>CMV class</b> |                |    |       |                     |       |         |
| cVal             | Struct         | MX |       | WW_vector1          | M     |         |
| q                | Quality        | ST | qchg  |                     | M     |         |
| t                | Timestamp      | ST |       |                     | M     |         |

| Attribute Name | Attribute Type | FC | TrgOp | Value / Value Range | M/O/E | Remarks |
|----------------|----------------|----|-------|---------------------|-------|---------|
| instCVal       | Struct         | MX |       | WW_vector1          | O     |         |
| units          | Struct         | CF |       | WW_units1           | O     |         |
| db             | INT32U         | CF |       |                     | O     |         |
| dbAng          | INT32U         | CF |       |                     | E     |         |

### 3.1.5 WW\_DEL2

| Attribute Name   | Attribute Type | FC | TrgOp | Value / Value Range | M/O/E | Remarks |
|------------------|----------------|----|-------|---------------------|-------|---------|
| <b>DEL class</b> |                |    |       |                     |       |         |
| phsAB            | WW_CMV2        |    |       |                     |       |         |
| phsBC            | WW_CMV2        |    |       |                     |       |         |
| phsCA            | WW_CMV2        |    |       |                     |       |         |

### 3.1.6 WW\_DPC1

| Attribute Name   | Attribute Type | FC | TrgOp | Value / Value Range | M/O/E | Remarks |
|------------------|----------------|----|-------|---------------------|-------|---------|
| <b>DPC class</b> |                |    |       |                     |       |         |
| stVal            | Dbpos          | ST | dchg  | Dbpos               | M     |         |
| q                | Quality        | ST | qchg  |                     | M     |         |
| t                | Timestamp      | ST |       |                     | M     |         |
| ctlModel         | Enum           | CF |       | ctlModel            | M     |         |

### 3.1.7 WW\_DPC2

| Attribute Name   | Attribute Type | FC | TrgOp | Value / Value Range | M/O/E | Remarks |
|------------------|----------------|----|-------|---------------------|-------|---------|
| <b>DPC class</b> |                |    |       |                     |       |         |
| origin           | Struct         | ST |       | WW_origin1          | O     |         |
| ctlNum           | INT8U          | ST |       |                     | O     |         |
| stVal            | Dbpos          | ST | dchg  | Dbpos               | M     |         |
| q                | Quality        | ST | qchg  |                     | M     |         |
| t                | Timestamp      | ST |       |                     | M     |         |
| stSeld           | BOOLEAN        | ST | dchg  |                     | O     |         |

### 3 Common Data Class

#### 3.1.8 WW\_DPL1

| Attribute Name | Attribute Type | FC | TrgOp | Value / Value Range | M/O/E | Remarks |
|----------------|----------------|----|-------|---------------------|-------|---------|
| ctlModel       | Enum           | CF |       | ctlModel            | M     |         |
| sboTimeout     | INT32U         | CF |       |                     | O     |         |
| sboClass       | Enum           | CF |       | sboClass            | O     |         |
| cdcNs          | VisString255   | EX |       |                     | O     |         |
| Oper           | Struct         | CO |       | WW_Oper1            |       |         |
| SBOw           | Struct         | CO |       | WW_Oper1            |       |         |
| Cancel         | Struct         | CO |       | WW_Cancel1          |       |         |

#### 3.1.8 WW\_DPL1

| Attribute Name   | Attribute Type | FC | TrgOp | Value / Value Range | M/O/E | Remarks |
|------------------|----------------|----|-------|---------------------|-------|---------|
| <b>DPL class</b> |                |    |       |                     |       |         |
| vendor           | VisString255   | DC |       |                     | M     |         |

#### 3.1.9 WW\_INC1

| Attribute Name   | Attribute Type | FC | TrgOp | Value / Value Range | M/O/E | Remarks |
|------------------|----------------|----|-------|---------------------|-------|---------|
| <b>INC class</b> |                |    |       |                     |       |         |
| stVal            | Enum           | ST | dchg  | Mode                | M     |         |
| q                | Quality        | ST | qchg  |                     | M     |         |
| t                | Timestamp      | ST |       |                     | M     |         |
| ctlModel         | Enum           | CF |       | ctlModel            | M     |         |

#### 3.1.10 WW\_INS1

| Attribute Name   | Attribute Type | FC | TrgOp | Value / Value Range | M/O/E | Remarks |
|------------------|----------------|----|-------|---------------------|-------|---------|
| <b>INS class</b> |                |    |       |                     |       |         |
| stVal            | Enum           | ST | dchg  | Behaviour           | M     |         |
| q                | Quality        | ST | qchg  |                     | M     |         |
| t                | Timestamp      | ST |       |                     | M     |         |

**3.1.11 WW\_INS2**

| Attribute Name   | Attribute Type | FC | TrgOp | Value / Value Range | M/O/E | Remarks |
|------------------|----------------|----|-------|---------------------|-------|---------|
| <b>INS class</b> |                |    |       |                     |       |         |
| stVal            | INT32          | ST | dchg  |                     | M     |         |
| q                | Quality        | ST | qchg  |                     | M     |         |
| t                | Timestamp      | ST |       |                     | M     |         |

**3.1.12 WW\_INS3**

| Attribute Name   | Attribute Type | FC | TrgOp | Value / Value Range | M/O/E | Remarks |
|------------------|----------------|----|-------|---------------------|-------|---------|
| <b>INS class</b> |                |    |       |                     |       |         |
| stVal            | Enum           | ST | dchg  | AutoRecSt           | M     |         |
| q                | Quality        | ST | qchg  |                     | M     |         |
| t                | Timestamp      | ST |       |                     | M     |         |

**3.1.13 WW\_INS5**

| Attribute Name   | Attribute Type | FC | TrgOp | Value / Value Range | M/O/E | Remarks |
|------------------|----------------|----|-------|---------------------|-------|---------|
| <b>INS class</b> |                |    |       |                     |       |         |
| stVal            | Enum           | ST | dchg  | CBOpCap             | M     |         |
| q                | Quality        | ST | qchg  |                     | M     |         |
| t                | Timestamp      | ST |       |                     | M     |         |

**3.1.14 WW\_LPL1**

| Attribute Name   | Attribute Type | FC | TrgOp | Value / Value Range | M/O/E | Remarks |
|------------------|----------------|----|-------|---------------------|-------|---------|
| <b>LPL class</b> |                |    |       |                     |       |         |
| vendor           | visString255   | DC |       |                     | M     |         |
| swRev            | visString255   | DC |       |                     | M     |         |
| d                | visString255   | DC |       |                     | M     |         |

### 3.1.15 WW\_LPL2

| Attribute Name   | Attribute Type | FC | TrgOp | Value / Value Range | M/O/E | Remarks |
|------------------|----------------|----|-------|---------------------|-------|---------|
| <b>LPL class</b> |                |    |       |                     |       |         |
| vendor           | visString255   | DC |       |                     | M     |         |
| swRev            | visString255   | DC |       |                     | M     |         |
| d                | visString255   | DC |       |                     | M     |         |
| ldNs             | visString255   | EX |       |                     |       |         |

### 3.1.16 WW\_LPL3

| Attribute Name   | Attribute Type | FC | TrgOp | Value / Value Range | M/O/E | Remarks |
|------------------|----------------|----|-------|---------------------|-------|---------|
| <b>LPL class</b> |                |    |       |                     |       |         |
| vendor           | visString255   | DC |       |                     | M     |         |
| swRev            | visString255   | DC |       |                     | M     |         |
| d                | visString255   | DC |       |                     | M     |         |
| LnNS             | visString255   | EX |       |                     |       |         |

### 3.1.17 WW\_MV1

| Attribute Name  | Attribute Type | FC | TrgOp | Value / Value Range | M/O/E | Remarks |
|-----------------|----------------|----|-------|---------------------|-------|---------|
| <b>MV class</b> |                |    |       |                     |       |         |
| mag             | Struct         | MX |       | WW_analogValue1     | M     |         |
| q               | Quality        | ST | qchg  |                     | M     |         |
| t               | Timestamp      | ST |       |                     | M     |         |
| units           | Struct         | CF |       | WW_units1           | O     |         |
| db              | INT32U         | CF |       |                     | O     |         |
| d               | visString255   | DC |       |                     | O     |         |
| dataNs          | visString255   | DC |       |                     | O     |         |

### 3.1.18 WW\_SPC1

| Attribute Name   | Attribute Type | FC | TrgOp | Value / Value Range | M/O/E | Remarks |
|------------------|----------------|----|-------|---------------------|-------|---------|
| <b>SPC class</b> |                |    |       |                     |       |         |



| Attribute Name | Attribute Type | FC | TrgOp | Value / Value Range | M/O/E | Remarks |
|----------------|----------------|----|-------|---------------------|-------|---------|
| stVal          | BOOLEAN        | ST | dchg  |                     | M     |         |
| q              | Quality        | ST | dchg  |                     | M     |         |
| t              | Timestamp      | ST |       |                     | M     |         |
| ctlModel       | Enum           | CF |       | ctlModel            | M     |         |

### 3.1.19 WW\_SPC2

| Attribute Name   | Attribute Type | FC | TrgOp | Value / Value Range | M/O/E | Remarks |
|------------------|----------------|----|-------|---------------------|-------|---------|
| <b>SPC class</b> |                |    |       |                     |       |         |
| Oper             | Struct         | CO |       | WW_Oper1            |       |         |
| stVal            | BOOLEAN        | ST | dchg  |                     | M     |         |
| q                | Quality        | ST | dchg  |                     | M     |         |
| t                | Timestamp      | ST |       |                     | M     |         |
| ctlModel         | Enum           | CF |       | ctlModel            | M     |         |

### 3.1.20 WW\_SPS1

| Attribute Name   | Attribute Type | FC | TrgOp | Value / Value Range | M/O/E | Remarks |
|------------------|----------------|----|-------|---------------------|-------|---------|
| <b>SPS class</b> |                |    |       |                     |       |         |
| stVal            | BOOLEAN        | ST | dchg  |                     | M     |         |
| q                | Quality        | ST | qchg  |                     | M     |         |
| t                | Timestamp      | ST |       |                     | M     |         |

### 3.1.21 WW\_WYE2

| Attribute Name   | Attribute Type | FC | TrgOp | Value / Value Range | M/O/E | Remarks |
|------------------|----------------|----|-------|---------------------|-------|---------|
| <b>WYE class</b> |                |    |       |                     |       |         |
| phsAB            | WW_CMV2        |    |       |                     |       |         |
| phsBC            | WW_CMV2        |    |       |                     |       |         |
| phsCA            | WW_CMV2        |    |       |                     |       |         |
| neut             | WW_CMV2        |    |       |                     |       |         |

## 3.2 Common Data Attributes Type Definitions

### 3.2.1 WW\_analogValue1

| Attribute Name           | Attribute Type | FC | TrgOp | Value / Value Range | M/O/E | Remarks |
|--------------------------|----------------|----|-------|---------------------|-------|---------|
| <b>analogValue class</b> |                |    |       |                     |       |         |
| f                        | FLOAT32        | MX |       |                     | M     |         |

### 3.2.2 WW\_Cancel1

| Attribute Name      | Attribute Type | FC | TrgOp | Value / Value Range | M/O/E | Remarks |
|---------------------|----------------|----|-------|---------------------|-------|---------|
| <b>Cancel class</b> |                |    |       |                     |       |         |
| ctlval              | BOOLEAN        | CO |       |                     | M     |         |
| origin              | Struct         | ST |       | WW_origin1          | O     |         |
| ctlNum              | INT8U          | ST |       |                     | O     |         |
| T                   | Timestamp      | CO |       |                     | O     |         |
| Test                | BOOLEAN        | CO |       |                     | O     |         |

### 3.2.3 WW\_Oper1

| Attribute Name    | Attribute Type | FC | TrgOp | Value / Value Range | M/O/E | Remarks |
|-------------------|----------------|----|-------|---------------------|-------|---------|
| <b>Oper class</b> |                |    |       |                     |       |         |
| ctlval            | BOOLEAN        | CO |       |                     | M     |         |
| origin            | Struct         | ST |       | WW_origin1          | O     |         |
| ctlNum            | INT8U          | ST |       |                     | O     |         |
| T                 | Timestamp      | CO |       |                     | O     |         |
| Test              | BOOLEAN        | CO |       |                     | O     |         |
| Check             | Check          | CO |       |                     | O     |         |

### 3.2.4 WW\_origin1

| Attribute Name      | Attribute Type | FC | TrgOp | Value / Value Range | M/O/E | Remarks |
|---------------------|----------------|----|-------|---------------------|-------|---------|
| <b>origin class</b> |                |    |       |                     |       |         |
| orCat               | Enum           | ST |       | orCategory          | M     |         |

| Attribute Name | Attribute Type | FC | TrgOp | Value / Value Range | M/O/E | Remarks |
|----------------|----------------|----|-------|---------------------|-------|---------|
| orIdent        | Octet64        | ST |       |                     | M     |         |

### 3.2.5 WW\_units1

| Attribute Name    | Attribute Type | FC | TrgOp | Value / Value Range | M/O/E | Remarks |
|-------------------|----------------|----|-------|---------------------|-------|---------|
| <b>unit class</b> |                |    |       |                     |       |         |
| SIUnit            | Enum           |    |       | SIUnit              | M     |         |
| multiplier        | Enum           |    |       | multiplier          | O     |         |

### 3.2.6 WW\_vector1

| Attribute Name      | Attribute Type | FC | TrgOp | Value / Value Range | M/O/E | Remarks |
|---------------------|----------------|----|-------|---------------------|-------|---------|
| <b>vector class</b> |                |    |       |                     |       |         |
| mag                 | Struct         |    |       | WW_analogValue1     | M     |         |
| ang                 | Struct         |    |       | WW_analogValue1     | O     |         |

### 3.3 Enumerated type definitions

#### 3.3.1 AutoRecSt

| Ordinal | Semantic   |
|---------|------------|
| 1       | Ready      |
| 2       | InProgress |
| 3       | Successful |

#### 3.3.2 Beh

| Ordinal | Semantic     |
|---------|--------------|
| 1       | on           |
| 2       | blocked      |
| 3       | test         |
| 4       | test/blocked |
| 5       | off          |

#### 3.3.3 CBOpCap

| Ordinal | Semantic              |
|---------|-----------------------|
| 1       | None                  |
| 2       | Open                  |
| 3       | Close-Open            |
| 4       | Open-Close-Open       |
| 5       | Close-Open-Close-Open |

#### 3.3.4 ctIModel

| Ordinal | Semantic                      |
|---------|-------------------------------|
| 1       | status-only                   |
| 2       | direct-with-normal-security   |
| 3       | sbo-with-normal-security      |
| 4       | direct-with-enhanced-security |

| Ordinal | Semantic                   |
|---------|----------------------------|
| 5       | sbo-with-enhanced-security |

### 3.3.5 Dbpos

| Ordinal | Semantic     |
|---------|--------------|
| 1       | intermediate |
| 2       | off          |
| 3       | on           |
| 4       | bad          |

### 3.3.6 ACDDir

| Ordinal | Semantic |
|---------|----------|
| 0       | unknown  |
| 1       | forward  |
| 2       | backward |
| 3       | both     |

### 3.3.7 Health

| Ordinal | Semantic |
|---------|----------|
| 1       | Ok       |
| 2       | Warning  |
| 3       | Alarm    |

### 3.3.8 Mod

| Ordinal | Semantic   |
|---------|------------|
| 1       | on         |
| 2       | blocked    |
| 3       | test       |
| 4       | test/block |

| Ordinal | Semantic |
|---------|----------|
| 5       | off      |

### 3.3.9 MotorCycle

| Ordinal | Semantic |
|---------|----------|
| 0       | Trip/Off |
| 1       | Stop     |
| 2       | Start    |
| 3       | Run      |

### 3.3.10 multiplier

| Ordinal | Semantic |
|---------|----------|
| -24     | y        |
| -21     | z        |
| -18     | a        |
| -15     | f        |
| -12     | p        |
| -9      | n        |
| -6      | μ        |
| -3      | m        |
| -2      | c        |
| -1      | d        |
| 0       |          |
| 1       | da       |
| 2       | h        |
| 3       | k        |
| 6       | M        |
| 9       | G        |
| 12      | T        |
| 15      | P        |
| 18      | E        |

| Ordinal | Semantic |
|---------|----------|
| 21      | Z        |
| 24      | Y        |

### 3.3.11 orCategory

| Ordinal | Semantic          |
|---------|-------------------|
| 0       | not-supported     |
| 1       | bay-control       |
| 2       | station-control   |
| 3       | remote-control    |
| 4       | automatic-bay     |
| 5       | automatic-station |
| 6       | automatic-remote  |
| 7       | maintenance       |
| 8       | process           |

### 3.3.12 sboClass

| Ordinal | Semantic     |
|---------|--------------|
| 0       | operate-once |
| 1       | operate-many |

### 3.3.13 SIUnit

| Ordinal | Semantic |
|---------|----------|
| 1       | none     |
| 2       | m        |
| 3       | kg       |
| 4       | s        |
| 5       | A        |
| 6       | K        |
| 7       | mol      |
| 8       | cd       |

| Ordinal | Semantic          |
|---------|-------------------|
| 9       | deg               |
| 10      | rad               |
| 11      | sr                |
| 21      | Gy                |
| 22      | q                 |
| 23      | °C                |
| 24      | Sv                |
| 25      | F                 |
| 26      | C                 |
| 27      | S                 |
| 28      | H                 |
| 29      | V                 |
| 30      | ohm               |
| 31      | J                 |
| 32      | N                 |
| 33      | Hz                |
| 34      | lx                |
| 35      | Lm                |
| 36      | Wb                |
| 37      | T                 |
| 38      | W                 |
| 39      | Pa                |
| 41      | m <sup>2</sup>    |
| 42      | m <sup>3</sup>    |
| 43      | m/s               |
| 44      | m/s <sup>2</sup>  |
| 45      | m <sup>3</sup> /s |
| 46      | m/m <sup>3</sup>  |
| 47      | M                 |
| 48      | kg/m <sup>3</sup> |
| 49      | m <sup>2</sup> /s |
| 50      | W/m K             |



| <b>Ordinal</b> | <b>Semantic</b>  |
|----------------|------------------|
| 51             | J/K              |
| 52             | ppm              |
| 53             | 1/s              |
| 54             | rad/s            |
| 61             | VA               |
| 62             | Watts            |
| 63             | VAr              |
| 64             | phi              |
| 65             | cos(phi)         |
| 66             | Vs               |
| 67             | V <sup>2</sup>   |
| 68             | As               |
| 69             | A <sup>2</sup>   |
| 70             | A <sup>2</sup> t |
| 71             | VAh              |
| 72             | Wh               |
| 73             | VArh             |
| 74             | V/Hz             |

# 4 Appendix

## 4.1 Register Maps

Legend: \* The Logical Node is dependent on the settings in the “Device planning”. (See [↪ “4.2 Device Planning Dependencies”](#)).

***LDevice::CTRL***

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|--------------------------|-------------|---|
| <b>CILO1* (WW_CILO1)</b> |             |   |
|                          | Mod         |   |
|                          | Beh         |   |
|                          | Health      |   |
|                          | NamPlt      |   |
|                          | EnaOpn      | SG[1] . Interl OFF                          |
|                          | EnaCls      | SG[1] . Interl ON                           |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|--------------------------|-------------|---|
| <b>CILO2* (WW_CILO1)</b> |             |   |
|                          | Mod         |   |
|                          | Beh         |   |
|                          | Health      |   |
|                          | NamPlt      |   |
|                          | EnaOpn      | SG[2] . Interl OFF                          |
|                          | EnaCls      | SG[2] . Interl ON                           |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|--------------------------|-------------|---|
| <b>CILO3* (WW_CILO1)</b> |             |   |
|                          | Mod         |   |
|                          | Beh         |   |
|                          | Health      |   |
|                          | NamPlt      |   |
|                          | EnaOpn      | SG[3] . Interl OFF                          |
|                          | EnaCls      | SG[3] . Interl ON                           |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|--------------------------|-------------|---|
| <b>CILO4* (WW_CILO1)</b> |             |   |
|                          | Mod         |   |
|                          | Beh         |   |
|                          | Health      |   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|--------------------------|-------------|---|
| <b>CILO4* (WW_CILO1)</b> |             |   |
|                          | NamPlt      |   |
|                          | EnaOpn      | SG[4] . Interl OFF                          |
|                          | EnaCls      | SG[4] . Interl ON                           |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|--------------------------|-------------|---|
| <b>CILO5* (WW_CILO1)</b> |             |   |
|                          | Mod         |   |
|                          | Beh         |   |
|                          | Health      |   |
|                          | NamPlt      |   |
|                          | EnaOpn      | SG[5] . Interl OFF                          |
|                          | EnaCls      | SG[5] . Interl ON                           |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|--------------------------|-------------|---|
| <b>CILO6* (WW_CILO1)</b> |             |   |
|                          | Mod         |   |
|                          | Beh         |   |
|                          | Health      |   |
|                          | NamPlt      |   |
|                          | EnaOpn      | SG[6] . Interl OFF                          |
|                          | EnaCls      | SG[6] . Interl ON                           |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|--------------------------|-------------|---|
| <b>CSWI1* (WW_CSWI1)</b> |             |   |
|                          | Mod         |   |
|                          | Beh         |   |
|                          | Health      |   |
|                          | NamPlt      |   |
|                          | Loc         |   |
|                          | Pos         | SG[1] . Pos                                 |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|--------------------------|-------------|---|
| <b>CSWI2* (WW_CSWI1)</b> |             |   |
|                          | Mod         |   |
|                          | Beh         |   |
|                          | Health      |   |
|                          | NamPlt      |   |

4 Appendix  
 4.1 Register Maps

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|--------------------------|-------------|---|
| <b>CSWI2* (WW_CSWI1)</b> |             |   |
|                          | Loc         |   |
|                          | Pos         | SG[2] . Pos                                 |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|--------------------------|-------------|---|
| <b>CSWI3* (WW_CSWI1)</b> |             |   |
|                          | Mod         |   |
|                          | Beh         |   |
|                          | Health      |   |
|                          | NamPlt      |   |
|                          | Loc         |   |
|                          | Pos         | SG[3] . Pos                                 |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|--------------------------|-------------|---|
| <b>CSWI4* (WW_CSWI1)</b> |             |   |
|                          | Mod         |   |
|                          | Beh         |   |
|                          | Health      |   |
|                          | NamPlt      |   |
|                          | Loc         |   |
|                          | Pos         | SG[4] . Pos                                 |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|--------------------------|-------------|---|
| <b>CSWI5* (WW_CSWI1)</b> |             |   |
|                          | Mod         |   |
|                          | Beh         |   |
|                          | Health      |   |
|                          | NamPlt      |   |
|                          | Loc         |   |
|                          | Pos         | SG[5] . Pos                                 |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|--------------------------|-------------|---|
| <b>CSWI6* (WW_CSWI1)</b> |             |   |
|                          | Mod         |   |
|                          | Beh         |   |
|                          | Health      |   |
|                          | NamPlt      |   |
|                          | Loc         |   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|--------------------------|-------------|---|
| <b>CSWI6* (WW_CSWI1)</b> |             |   |
|                          | Pos         | SG[6] . Pos                                 |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|--------------------------|-------------|---|
| <b>LLN0 (WW_LLNOCON)</b> |             |   |
|                          | Mod         |   |
|                          | Beh         |   |
|                          | Health      |   |
|                          | NamPlt      |   |

| Logical Node              | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|---------------------------|-------------|---|
| <b>LPHD1 (WW_LPHDCON)</b> |             |   |
|                           | PhyNam      |   |
|                           | PhyHealth   |   |
|                           | Proxy       |   |

| Logical Node               | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|----------------------------|-------------|---|
| <b>TCSSCBR1 (WW_SCBR1)</b> |             |   |
|                            | Mod         | TCS[1] - 74TC . active                      |
|                            | Beh         |   |
|                            | Health      |   |
|                            | NamPlt      |   |
|                            | TrCctAlm    | TCS[1] - 74TC . Alarm                       |

| Logical Node               | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|----------------------------|-------------|---|
| <b>TCSSCBR2 (WW_SCBR1)</b> |             |   |
|                            | Mod         | TCS[2] - 74TC . active                      |
|                            | Beh         |   |
|                            | Health      |   |
|                            | NamPlt      |   |
|                            | TrCctAlm    | TCS[2] - 74TC . Alarm                       |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|--------------------------|-------------|---|
| <b>XCBR1* (WW_XCBR2)</b> |             |   |
|                          | Mod         |   |
|                          | Beh         |   |
|                          | Health      |   |
|                          | NamPlt      |   |
|                          | Loc         |   |

4 Appendix  
4.1 Register Maps

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|--------------------------|-------------|---|
| <b>XCBR1* (WW_XCBR2)</b> |             |   |
|                          | OpCnt       |   |
|                          | Pos         | SG[1] . Pos                                 |
|                          | BlkOpn      |   |
|                          | BlkCls      |   |
|                          | CBOpCap     |   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|--------------------------|-------------|---|
| <b>XCBR2* (WW_XCBR2)</b> |             |   |
|                          | Mod         |   |
|                          | Beh         |   |
|                          | Health      |   |
|                          | NamPlt      |   |
|                          | Loc         |   |
|                          | OpCnt       |   |
|                          | Pos         | SG[2] . Pos                                 |
|                          | BlkOpn      |   |
|                          | BlkCls      |   |
|                          | CBOpCap     |   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|--------------------------|-------------|---|
| <b>XCBR3* (WW_XCBR2)</b> |             |   |
|                          | Mod         |   |
|                          | Beh         |   |
|                          | Health      |   |
|                          | NamPlt      |   |
|                          | Loc         |   |
|                          | OpCnt       |   |
|                          | Pos         | SG[3] . Pos                                 |
|                          | BlkOpn      |   |
|                          | BlkCls      |   |
|                          | CBOpCap     |   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|--------------------------|-------------|---|
| <b>XCBR4* (WW_XCBR2)</b> |             |   |
|                          | Mod         |   |
|                          | Beh         |   |
|                          | Health      |   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|--------------------------|-------------|---|
| <b>XCBR4* (WW_XCBR2)</b> |             |   |
|                          | NamPlt      |   |
|                          | Loc         |   |
|                          | OpCnt       |   |
|                          | Pos         | SG[4] . Pos                                 |
|                          | BlkOpn      |   |
|                          | BlkCls      |   |
|                          | CBOpCap     |   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|--------------------------|-------------|---|
| <b>XCBR5* (WW_XCBR2)</b> |             |   |
|                          | Mod         |   |
|                          | Beh         |   |
|                          | Health      |   |
|                          | NamPlt      |   |
|                          | Loc         |   |
|                          | OpCnt       |   |
|                          | Pos         | SG[5] . Pos                                 |
|                          | BlkOpn      |   |
|                          | BlkCls      |   |
|                          | CBOpCap     |   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|--------------------------|-------------|---|
| <b>XCBR6* (WW_XCBR2)</b> |             |   |
|                          | Mod         |   |
|                          | Beh         |   |
|                          | Health      |   |
|                          | NamPlt      |   |
|                          | Loc         |   |
|                          | OpCnt       |   |
|                          | Pos         | SG[6] . Pos                                 |
|                          | BlkOpn      |   |
|                          | BlkCls      |   |
|                          | CBOpCap     |   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|--------------------------|-------------|---|
| <b>XSWI1* (WW_XSWI1)</b> |             |   |
|                          | Mod         |   |

4 Appendix  
4.1 Register Maps

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|--------------------------|-------------|---|
| <b>XSWI1* (WW_XSWI1)</b> |             |   |
|                          | Beh         |   |
|                          | Health      |   |
|                          | NamPlt      |   |
|                          | Loc         |   |
|                          | OpCnt       |   |
|                          | Pos         | SG[1] . Pos                                 |
|                          | BlkOpn      |   |
|                          | BlkCls      |   |
|                          | SwTyp       |   |
|                          | SwOpCap     |   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|--------------------------|-------------|---|
| <b>XSWI2* (WW_XSWI1)</b> |             |   |
|                          | Mod         |   |
|                          | Beh         |   |
|                          | Health      |   |
|                          | NamPlt      |   |
|                          | Loc         |   |
|                          | OpCnt       |   |
|                          | Pos         | SG[2] . Pos                                 |
|                          | BlkOpn      |   |
|                          | BlkCls      |   |
|                          | SwTyp       |   |
|                          | SwOpCap     |   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|--------------------------|-------------|---|
| <b>XSWI3* (WW_XSWI1)</b> |             |   |
|                          | Mod         |   |
|                          | Beh         |   |
|                          | Health      |   |
|                          | NamPlt      |   |
|                          | Loc         |   |
|                          | OpCnt       |   |
|                          | Pos         | SG[3] . Pos                                 |
|                          | BlkOpn      |   |
|                          | BlkCls      |   |
|                          | SwTyp       |   |



| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|--------------------------|-------------|---|
| <b>XSWI3* (WW_XSWI1)</b> |             |   |
|                          | SwOpCap     |   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|--------------------------|-------------|---|
| <b>XSWI4* (WW_XSWI1)</b> |             |   |
|                          | Mod         |   |
|                          | Beh         |   |
|                          | Health      |   |
|                          | NamPlt      |   |
|                          | Loc         |   |
|                          | OpCnt       |   |
|                          | Pos         | SG[4] . Pos                                 |
|                          | BlkOpn      |   |
|                          | BlkCls      |   |
|                          | SwTyp       |   |
|                          | SwOpCap     |   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|--------------------------|-------------|---|
| <b>XSWI5* (WW_XSWI1)</b> |             |   |
|                          | Mod         |   |
|                          | Beh         |   |
|                          | Health      |   |
|                          | NamPlt      |   |
|                          | Loc         |   |
|                          | OpCnt       |   |
|                          | Pos         | SG[5] . Pos                                 |
|                          | BlkOpn      |   |
|                          | BlkCls      |   |
|                          | SwTyp       |   |
|                          | SwOpCap     |   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|--------------------------|-------------|---|
| <b>XSWI6* (WW_XSWI1)</b> |             |   |
|                          | Mod         |   |
|                          | Beh         |   |
|                          | Health      |   |
|                          | NamPlt      |   |
|                          | Loc         |   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|--------------------------|-------------|---|
| <b>XSWI6* (WW_XSWI1)</b> |             |   |
|                          | OpCnt       |   |
|                          | Pos         | SG[6] . Pos                                 |
|                          | BlkOpn      |   |
|                          | BlkCls      |   |
|                          | SwTyp       |   |
|                          | SwOpCap     |   |

***LDevice::DR***

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|--------------------------|-------------|---|
| <b>LLN0 (WW_LLNOREC)</b> |             |   |
|                          | Mod         |   |
|                          | Beh         |   |
|                          | Health      |   |
|                          | NamPlt      |   |

| Logical Node              | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|---------------------------|-------------|---|
| <b>LPHD1 (WW_LPHDREC)</b> |             |   |
|                           | PhyNam      |   |
|                           | PhyHealth   |   |
|                           | Proxy       |   |

| Logical Node            | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|-------------------------|-------------|---|
| <b>RDRE1 (WW_RDRE1)</b> |             |   |
|                         | Mod         |   |
|                         | Beh         |   |
|                         | Health      |   |
|                         | NamPlt      |   |
|                         | RcdMade     | Disturb rec . recording                     |
|                         | FltNum      |   |
|                         | GriFltNum   |   |
|                         | RcdStr      | Disturb rec . recording                     |

***LDevice::EXT***

| Logical Node                | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|-----------------------------|-------------|---|
| <b>COUTGGIO1 (WW_GGIO4)</b> |             |   |
|                             | Mod         |   |
|                             | Beh         |   |

| Logical Node                | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|-----------------------------|-------------|---|
| <b>COUTGGIO1 (WW_GGIO4)</b> |             |   |
|                             | Health      |   |
|                             | NamPlt      |   |
|                             | Ind1        | IEC 61850 . COUTGGIO1.Ind1.stVal-I          |
|                             | Ind2        | IEC 61850 . COUTGGIO1.Ind2.stVal-I          |
|                             | Ind3        | IEC 61850 . COUTGGIO1.Ind3.stVal-I          |
|                             | Ind4        | IEC 61850 . COUTGGIO1.Ind4.stVal-I          |
|                             | Ind5        | IEC 61850 . COUTGGIO1.Ind5.stVal-I          |
|                             | Ind6        | IEC 61850 . COUTGGIO1.Ind6.stVal-I          |
|                             | Ind7        | IEC 61850 . COUTGGIO1.Ind7.stVal-I          |
|                             | Ind8        | IEC 61850 . COUTGGIO1.Ind8.stVal-I          |
|                             | Ind9        | IEC 61850 . COUTGGIO1.Ind9.stVal-I          |
|                             | Ind10       | IEC 61850 . COUTGGIO1.Ind10.stVal-I         |
|                             | Ind11       | IEC 61850 . COUTGGIO1.Ind11.stVal-I         |
|                             | Ind12       | IEC 61850 . COUTGGIO1.Ind12.stVal-I         |
|                             | Ind13       | IEC 61850 . COUTGGIO1.Ind13.stVal-I         |
|                             | Ind14       | IEC 61850 . COUTGGIO1.Ind14.stVal-I         |
|                             | Ind15       | IEC 61850 . COUTGGIO1.Ind15.stVal-I         |
|                             | Ind16       | IEC 61850 . COUTGGIO1.Ind16.stVal-I         |
|                             | Ind17       | IEC 61850 . COUTGGIO1.Ind17.stVal-I         |
|                             | Ind18       | IEC 61850 . COUTGGIO1.Ind18.stVal-I         |
|                             | Ind19       | IEC 61850 . COUTGGIO1.Ind19.stVal-I         |
|                             | Ind20       | IEC 61850 . COUTGGIO1.Ind20.stVal-I         |
|                             | Ind21       | IEC 61850 . COUTGGIO1.Ind21.stVal-I         |
|                             | Ind22       | IEC 61850 . COUTGGIO1.Ind22.stVal-I         |
|                             | Ind23       | IEC 61850 . COUTGGIO1.Ind23.stVal-I         |
|                             | Ind24       | IEC 61850 . COUTGGIO1.Ind24.stVal-I         |
|                             | Ind25       | IEC 61850 . COUTGGIO1.Ind25.stVal-I         |
|                             | Ind26       | IEC 61850 . COUTGGIO1.Ind26.stVal-I         |
|                             | Ind27       | IEC 61850 . COUTGGIO1.Ind27.stVal-I         |
|                             | Ind28       | IEC 61850 . COUTGGIO1.Ind28.stVal-I         |
|                             | Ind29       | IEC 61850 . COUTGGIO1.Ind29.stVal-I         |
|                             | Ind30       | IEC 61850 . COUTGGIO1.Ind30.stVal-I         |
|                             | Ind31       | IEC 61850 . COUTGGIO1.Ind31.stVal-I         |
|                             | Ind32       | IEC 61850 . COUTGGIO1.Ind32.stVal-I         |

4 Appendix  
 4.1 Register Maps

| Logical Node                | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|-----------------------------|-------------|---|
| <b>COUTGGIO2 (WW_GGIO4)</b> |             |   |
|                             | Mod         |   |
|                             | Beh         |   |
|                             | Health      |   |
|                             | NamPlt      |   |
|                             | Ind1        | IEC 61850 . COUTGGIO2.Ind1.stVal-I          |
|                             | Ind2        | IEC 61850 . COUTGGIO2.Ind2.stVal-I          |
|                             | Ind3        | IEC 61850 . COUTGGIO2.Ind3.stVal-I          |
|                             | Ind4        | IEC 61850 . COUTGGIO2.Ind4.stVal-I          |
|                             | Ind5        | IEC 61850 . COUTGGIO2.Ind5.stVal-I          |
|                             | Ind6        | IEC 61850 . COUTGGIO2.Ind6.stVal-I          |
|                             | Ind7        | IEC 61850 . COUTGGIO2.Ind7.stVal-I          |
|                             | Ind8        | IEC 61850 . COUTGGIO2.Ind8.stVal-I          |
|                             | Ind9        | IEC 61850 . COUTGGIO2.Ind9.stVal-I          |
|                             | Ind10       | IEC 61850 . COUTGGIO2.Ind10.stVal-I         |
|                             | Ind11       | IEC 61850 . COUTGGIO2.Ind11.stVal-I         |
|                             | Ind12       | IEC 61850 . COUTGGIO2.Ind12.stVal-I         |
|                             | Ind13       | IEC 61850 . COUTGGIO2.Ind13.stVal-I         |
|                             | Ind14       | IEC 61850 . COUTGGIO2.Ind14.stVal-I         |
|                             | Ind15       | IEC 61850 . COUTGGIO2.Ind15.stVal-I         |
|                             | Ind16       | IEC 61850 . COUTGGIO2.Ind16.stVal-I         |
|                             | Ind17       | IEC 61850 . COUTGGIO2.Ind17.stVal-I         |
|                             | Ind18       | IEC 61850 . COUTGGIO2.Ind18.stVal-I         |
|                             | Ind19       | IEC 61850 . COUTGGIO2.Ind19.stVal-I         |
|                             | Ind20       | IEC 61850 . COUTGGIO2.Ind20.stVal-I         |
|                             | Ind21       | IEC 61850 . COUTGGIO2.Ind21.stVal-I         |
|                             | Ind22       | IEC 61850 . COUTGGIO2.Ind22.stVal-I         |
|                             | Ind23       | IEC 61850 . COUTGGIO2.Ind23.stVal-I         |
|                             | Ind24       | IEC 61850 . COUTGGIO2.Ind24.stVal-I         |
|                             | Ind25       | IEC 61850 . COUTGGIO2.Ind25.stVal-I         |
|                             | Ind26       | IEC 61850 . COUTGGIO2.Ind26.stVal-I         |
|                             | Ind27       | IEC 61850 . COUTGGIO2.Ind27.stVal-I         |
|                             | Ind28       | IEC 61850 . COUTGGIO2.Ind28.stVal-I         |
|                             | Ind29       | IEC 61850 . COUTGGIO2.Ind29.stVal-I         |
|                             | Ind30       | IEC 61850 . COUTGGIO2.Ind30.stVal-I         |
|                             | Ind31       | IEC 61850 . COUTGGIO2.Ind31.stVal-I         |
|                             | Ind32       | IEC 61850 . COUTGGIO2.Ind32.stVal-I         |

| Logical Node                | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|-----------------------------|-------------|---|
| <b>CTLGGIO1 (WW_GGIO14)</b> |             |   |
|                             | Mod         |   |
|                             | Beh         |   |
|                             | Health      |   |
|                             | NamPlt      |   |
|                             | SPCSO1      |   |
|                             | SPCSO2      |   |
|                             | SPCSO3      |   |
|                             | SPCSO4      |   |
|                             | SPCSO5      |   |
|                             | SPCSO6      |   |
|                             | SPCSO7      |   |
|                             | SPCSO8      |   |
|                             | SPCSO9      |   |
|                             | SPCSO10     |   |
|                             | SPCSO11     |   |
|                             | SPCSO12     |   |
|                             | SPCSO13     |   |
|                             | SPCSO14     |   |
|                             | SPCSO15     |   |
|                             | SPCSO16     |   |
|                             | SPCSO17     |   |
|                             | SPCSO18     |   |
|                             | SPCSO19     |   |
|                             | SPCSO20     |   |
|                             | SPCSO21     |   |
|                             | SPCSO22     |   |
|                             | SPCSO23     |   |
|                             | SPCSO24     |   |
|                             | SPCSO25     |   |
|                             | SPCSO26     |   |
|                             | SPCSO27     |   |
|                             | SPCSO28     |   |
|                             | SPCSO29     |   |
|                             | SPCSO30     |   |
|                             | SPCSO31     |   |
|                             | SPCSO32     |   |

4 Appendix  
4.1 Register Maps

| Logical Node              | Data Object | Module ( - ANSI/IEEE Device Number ) . Name   |
|---------------------------|-------------|---|
| <b>EPGAPC1 (WW_GAPC1)</b> |             |   |
|                           | Mod         | Intertripping . active Intertripping . Blo TripCmd<br>Intertripping . ExBlo TripCmd |
|                           | Beh         |   |
|                           | Health      |   |
|                           | NamPlt      |   |
|                           | Str         | Intertripping . Alarm   |
|                           | Op          | Intertripping . Trip  |

| Logical Node               | Data Object | Module ( - ANSI/IEEE Device Number ) . Name  |
|----------------------------|-------------|--|
| <b>EPGAPC10 (WW_GAPC1)</b> |             |  |
|                            | Mod         | Ext Temp Superv[3] . active Ext Temp Superv[3] . Blo<br>TripCmd Ext Temp Superv[3] . ExBlo TripCmd |
|                            | Beh         |  |
|                            | Health      |  |
|                            | NamPlt      |  |
|                            | Str         | Ext Temp Superv[3] . Alarm   |
|                            | Op          | Ext Temp Superv[3] . Trip  |

| Logical Node              | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                 |
|---------------------------|-------------|---|
| <b>EPGAPC2 (WW_GAPC1)</b> |             |   |
|                           | Mod         | Exp[1] . active Exp[1] . Blo TripCmd Exp[1] . ExBlo TripCmd |
|                           | Beh         |   |
|                           | Health      |   |
|                           | NamPlt      |   |
|                           | Str         | Exp[1] . Alarm  |
|                           | Op          | Exp[1] . Trip   |

| Logical Node              | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                 |
|---------------------------|-------------|---|
| <b>EPGAPC3 (WW_GAPC1)</b> |             |   |
|                           | Mod         | Exp[2] . active Exp[2] . Blo TripCmd Exp[2] . ExBlo TripCmd |
|                           | Beh         |   |
|                           | Health      |   |
|                           | NamPlt      |   |
|                           | Str         | Exp[2] . Alarm  |
|                           | Op          | Exp[2] . Trip   |

| Logical Node              | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                 |
|---------------------------|-------------|---|
| <b>EPGAPC4 (WW_GAPC1)</b> |             |   |
|                           | Mod         | Exp[3] . active Exp[3] . Blo TripCmd Exp[3] . ExBlo TripCmd |
|                           | Beh         |   |
|                           | Health      |   |
|                           | NamPlt      |   |
|                           | Str         | Exp[3] . Alarm  |
|                           | Op          | Exp[3] . Trip   |

| Logical Node              | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                 |
|---------------------------|-------------|---|
| <b>EPGAPC5 (WW_GAPC1)</b> |             |   |
|                           | Mod         | Exp[4] . active Exp[4] . Blo TripCmd Exp[4] . ExBlo TripCmd |
|                           | Beh         |   |
|                           | Health      |   |
|                           | NamPlt      |   |
|                           | Str         | Exp[4] . Alarm  |
|                           | Op          | Exp[4] . Trip   |

| Logical Node              | Data Object | Module ( - ANSI/IEEE Device Number ) . Name   |
|---------------------------|-------------|---|
| <b>EPGAPC6 (WW_GAPC1)</b> |             |   |
|                           | Mod         | Ext Sudd Press . active Ext Sudd Press . Blo TripCmd Ext Sudd Press . ExBlo TripCmd |
|                           | Beh         |   |
|                           | Health      |   |
|                           | NamPlt      |   |
|                           | Str         | Ext Sudd Press . Alarm  |
|                           | Op          | Ext Sudd Press . Trip   |

| Logical Node              | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                                   |
|---------------------------|-------------|---|
| <b>EPGAPC7 (WW_GAPC1)</b> |             |   |
|                           | Mod         | Ext Oil Temp . active Ext Oil Temp . Blo TripCmd Ext Oil Temp . ExBlo TripCmd |
|                           | Beh         |   |
|                           | Health      |   |
|                           | NamPlt      |   |
|                           | Str         | Ext Oil Temp . Alarm  |
|                           | Op          | Ext Oil Temp . Trip   |

4 Appendix  
 4.1 Register Maps

| Logical Node              | Data Object | Module ( - ANSI/IEEE Device Number ) . Name   |
|---------------------------|-------------|---|
| <b>EPGAPC8 (WW_GAPC1)</b> |             |   |
|                           | Mod         | Ext Temp Superv[1] . active Ext Temp Superv[1] . Blo TripCmd Ext Temp Superv[1] . ExBlo TripCmd |
|                           | Beh         |   |
|                           | Health      |   |
|                           | NamPlt      |   |
|                           | Str         | Ext Temp Superv[1] . Alarm  |
|                           | Op          | Ext Temp Superv[1] . Trip   |

| Logical Node              | Data Object | Module ( - ANSI/IEEE Device Number ) . Name   |
|---------------------------|-------------|---|
| <b>EPGAPC9 (WW_GAPC1)</b> |             |   |
|                           | Mod         | Ext Temp Superv[2] . active Ext Temp Superv[2] . Blo TripCmd Ext Temp Superv[2] . ExBlo TripCmd |
|                           | Beh         |   |
|                           | Health      |   |
|                           | NamPlt      |   |
|                           | Str         | Ext Temp Superv[2] . Alarm  |
|                           | Op          | Ext Temp Superv[2] . Trip   |

| Logical Node                  | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|-------------------------------|-------------|---|
| <b>GOSINGGIO1 (WW_GGIO11)</b> |             |   |
|                               | Mod         |   |
|                               | Beh         |   |
|                               | Health      |   |
|                               | NamPlt      |   |
|                               | Ind1        |   |
|                               | Ind2        |   |
|                               | Ind3        |   |
|                               | Ind4        |   |
|                               | Ind5        |   |
|                               | Ind6        |   |
|                               | Ind7        |   |
|                               | Ind8        |   |
|                               | Ind9        |   |
|                               | Ind10       |   |
|                               | Ind11       |   |
|                               | Ind12       |   |
|                               | Ind13       |   |
|                               | Ind14       |   |



| Logical Node                  | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|-------------------------------|-------------|---|
| <b>GOSINGGIO1 (WW_GGIO11)</b> |             |   |
|                               | Ind15       |   |
|                               | Ind16       |   |
|                               | Ind17       |   |
|                               | Ind18       |   |
|                               | Ind19       |   |
|                               | Ind20       |   |
|                               | Ind21       |   |
|                               | Ind22       |   |
|                               | Ind23       |   |
|                               | Ind24       |   |
|                               | Ind25       |   |
|                               | Ind26       |   |
|                               | Ind27       |   |
|                               | Ind28       |   |
|                               | Ind29       |   |
|                               | Ind30       |   |
|                               | Ind31       |   |
|                               | Ind32       |   |

| Logical Node                  | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|-------------------------------|-------------|---|
| <b>GOSINGGIO2 (WW_GGIO10)</b> |             |   |
|                               | Mod         |   |
|                               | Beh         |   |
|                               | Health      |   |
|                               | NamPlt      |   |
|                               | Ind1        |   |
|                               | Ind2        |   |
|                               | Ind3        |   |
|                               | Ind4        |   |
|                               | Ind5        |   |
|                               | Ind6        |   |
|                               | Ind7        |   |
|                               | Ind8        |   |
|                               | Ind9        |   |
|                               | Ind10       |   |
|                               | Ind11       |   |
|                               | Ind12       |   |

4 Appendix  
4.1 Register Maps

| Logical Node                  | Data Object | Module (- ANSI/IEEE Device Number ) . Name |
|-------------------------------|-------------|--|
| <b>GOSINGGIO2 (WW_GGIO10)</b> |             |  |
|                               | Ind13       |  |
|                               | Ind14       |  |
|                               | Ind15       |  |
|                               | Ind16       |  |
|                               | Ind17       |  |
|                               | Ind18       |  |
|                               | Ind19       |  |
|                               | Ind20       |  |
|                               | Ind21       |  |
|                               | Ind22       |  |
|                               | Ind23       |  |
|                               | Ind24       |  |
|                               | Ind25       |  |
|                               | Ind26       |  |
|                               | Ind27       |  |
|                               | Ind28       |  |
|                               | Ind29       |  |
|                               | Ind30       |  |
|                               | Ind31       |  |
|                               | Ind32       |  |

| Logical Node            | Data Object | Module (- ANSI/IEEE Device Number ) . Name |
|-------------------------|-------------|--|
| <b>LLN0 (WW_LLNSYS)</b> |             |  |
|                         | Mod         |  |
|                         | Beh         |  |
|                         | Health      |  |
|                         | NamPlt      |  |

| Logical Node              | Data Object | Module (- ANSI/IEEE Device Number ) . Name |
|---------------------------|-------------|--|
| <b>LPHD1 (WW_LPHDSYS)</b> |             |  |
|                           | PhyNam      |  |
|                           | PhyHealth   |  |
|                           | Proxy       |  |

**LDevice::MEAS**

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name   |
|--------------------------|-------------|---|
| <b>CMMXU1 (WW_MMXU7)</b> |             |   |
|                          | Mod         |   |
|                          | Beh         |   |
|                          | Health      |   |
|                          | NamPlt      |   |
|                          | A           | CT W1 . IL1 RMS CT W1 . phi IL1 CT W1 . IL2 RMS CT W1 . phi IL2 CT W1 . IL3 RMS CT W1 . phi IL3 CT W1 . IG meas RMS CT W1 . phi IG meas CT W1 . IG calc RMS CT W1 . phi IG calc |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name   |
|--------------------------|-------------|---|
| <b>CMMXU2 (WW_MMXU7)</b> |             |   |
|                          | Mod         |   |
|                          | Beh         |   |
|                          | Health      |   |
|                          | NamPlt      |   |
|                          | A           | CT W2 . IL1 RMS CT W2 . phi IL1 CT W2 . IL2 RMS CT W2 . phi IL2 CT W2 . IL3 RMS CT W2 . phi IL3 CT W2 . IG meas RMS CT W2 . phi IG meas CT W2 . IG calc RMS CT W2 . phi IG calc |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|--------------------------|-------------|---|
| <b>CMSTA1 (WW_MSTA1)</b> |             |   |
|                          | Mod         |   |
|                          | Beh         |   |
|                          | Health      |   |
|                          | NamPlt      |   |
|                          | AvAPhsA     | CT W1 . IL1 avg                             |
|                          | AvAPhsB     | CT W1 . IL2 avg                             |
|                          | AvAPhsC     | CT W1 . IL3 avg                             |
|                          | MaxAPhsA    | CT W1 . IL1 max                             |
|                          | MaxAPhsB    | CT W1 . IL2 max                             |
|                          | MaxAPhsC    | CT W1 . IL3 max                             |
|                          | MinAPhsA    | CT W1 . IL1 min                             |
|                          | MinAPhsB    | CT W1 . IL2 min                             |
|                          | MinAPhsC    | CT W1 . IL3 min                             |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|--------------------------|-------------|---|
| <b>CMSTA2 (WW_MSTA1)</b> |             |   |
|                          | Mod         |   |

4 Appendix  
4.1 Register Maps

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|--------------------------|-------------|---|
| <b>CMSTA2 (WW_MSTA1)</b> |             |   |
|                          | Beh         |   |
|                          | Health      |   |
|                          | NamPlt      |   |
|                          | AvAPhsA     | CT W2 . IL1 avg                             |
|                          | AvAPhsB     | CT W2 . IL2 avg                             |
|                          | AvAPhsC     | CT W2 . IL3 avg                             |
|                          | MaxAPhsA    | CT W2 . IL1 max                             |
|                          | MaxAPhsB    | CT W2 . IL2 max                             |
|                          | MaxAPhsC    | CT W2 . IL3 max                             |
|                          | MinAPhsA    | CT W2 . IL1 min                             |
|                          | MinAPhsB    | CT W2 . IL2 min                             |
|                          | MinAPhsC    | CT W2 . IL3 min                             |

| Logical Node              | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|---------------------------|-------------|---|
| <b>ECMMTR1 (WW_MMTR1)</b> |             |   |
|                           | Mod         |   |
|                           | Beh         |   |
|                           | Health      |   |
|                           | NamPlt      |   |
|                           | SupWh       | PQSCr . Wp+                                 |
|                           | DmdWh       | PQSCr . Wp-                                 |
|                           | SupVArh     | PQSCr . Wq+                                 |
|                           | DmdVArh     | PQSCr . Wq-                                 |
|                           | TotWh       | PQSCr . Wp Net                              |
|                           | TotVArh     | PQSCr . Wq Net                              |
|                           | TotVAh      | PQSCr . Ws Net                              |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|--------------------------|-------------|---|
| <b>LLN0 (WW_LLNAMEA)</b> |             |   |
|                          | Mod         |   |
|                          | Beh         |   |
|                          | Health      |   |
|                          | NamPlt      |   |

| Logical Node              | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|---------------------------|-------------|---|
| <b>LPHD1 (WW_LPHDMEA)</b> |             |   |
|                           | PhyNam      |   |

| Logical Node              | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|---------------------------|-------------|---|
| <b>LPHD1 (WW_LPHDMEA)</b> |             |   |
|                           | PhyHealth   |   |
|                           | Proxy       |   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|--------------------------|-------------|---|
| <b>PMMXU1 (WW_MMXU3)</b> |             |   |
|                          | Mod         |   |
|                          | Beh         |   |
|                          | Health      |   |
|                          | NamPlt      |   |
|                          | TotW        | PQSCr . P RMS                               |
|                          | TotVAr      | PQSCr . Q                                   |
|                          | TotVA       | PQSCr . S RMS                               |
|                          | TotPF       | PQSCr . cos phi RMS                         |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|--------------------------|-------------|---|
| <b>PMSTA1 (WW_MSTA3)</b> |             |   |
|                          | Mod         |   |
|                          | Beh         |   |
|                          | Health      |   |
|                          | NamPlt      |   |
|                          | AvVA        | PQSCr . S avg (Demand)                      |
|                          | MaxVA       | PQSCr . S max                               |
|                          | MinVA       | PQSCr . S min                               |
|                          | AvW         | PQSCr . P avg                               |
|                          | MaxW        | PQSCr . P max                               |
|                          | MinW        | PQSCr . P min                               |
|                          | AvVAr       | PQSCr . Q avg (Demand)                      |
|                          | MaxVAr      | PQSCr . Q max                               |
|                          | MinVAr      | PQSCr . Q min                               |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name  |
|--------------------------|-------------|--|
| <b>VMMXU1 (WW_MMXU6)</b> |             |  |
|                          | Mod         |  |
|                          | Beh         |  |
|                          | Health      |  |
|                          | NamPlt      |  |
|                          | PPV         | VT . VL12 RMS VT . phi VL12 VT . VL23 RMS VT . phi VL23<br>VT . VL31 RMS VT . phi VL31 |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name   |
|--------------------------|-------------|---|
| <b>VMMXU1 (WW_MMXU6)</b> |             |   |
|                          | PhV         | VT . VL1 RMS VT . phi VL1 VT . VL2 RMS VT . phi VL2 VT . VL3 RMS VT . phi VL3 VT . VX meas RMS VT . phi VX meas VT . VG calc RMS VT . phi VG calc |
|                          | Hz          | VT . f  |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|--------------------------|-------------|---|
| <b>VMSTA1 (WW_MSTA2)</b> |             |   |
|                          | Mod         |   |
|                          | Beh         |   |
|                          | Health      |   |
|                          | NamPlt      |   |
|                          | AvVPhsAB    | VT . VL12 avg                               |
|                          | AvVPhsBC    | VT . VL23 avg                               |
|                          | AvVPhsCA    | VT . VL31 avg                               |
|                          | MaxVPhsAB   | VT . VL12 max                               |
|                          | MaxVPhsBC   | VT . VL23 max                               |
|                          | MaxVPhsCA   | VT . VL31 max                               |
|                          | MinVPhsAB   | VT . VL12 min                               |
|                          | MinVPhsBC   | VT . VL23 min                               |
|                          | MinVPhsCA   | VT . VL31 min                               |
|                          | AvVPhsA     | VT . VL1 avg                                |
|                          | AvVPhsB     | VT . VL2 avg                                |
|                          | AvVPhsC     | VT . VL3 avg                                |
|                          | MaxVPhsA    | VT . VL1 max                                |
|                          | MaxVPhsB    | VT . VL2 max                                |
|                          | MaxVPhsC    | VT . VL3 max                                |
|                          | MinVPhsA    | VT . VL1 min                                |
|                          | MinVPhsB    | VT . VL2 min                                |
|                          | MinVPhsC    | VT . VL3 min                                |

***LDevice::PROT***

| Logical Node              | Data Object | Module ( - ANSI/IEEE Device Number ) . Name  |
|---------------------------|-------------|--|
| <b>GFPTOC1 (WW_PTOC3)</b> |             |  |
|                           | Mod         | IG[1] - 50N, 51N . active IG[1] - 50N, 51N . Blo TripCmd<br>IG[1] - 50N, 51N . ExBlo TripCmd |
|                           | Beh         |  |
|                           | Health      |  |
|                           | NamPlt      |  |

| Logical Node              | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|---------------------------|-------------|---|
| <b>GFPTOC1 (WW_PTOC3)</b> |             |   |
|                           | Str         | IG[1] - 50N, 51N . Alarm                    |
|                           | Op          | IG[1] - 50N, 51N . Trip                     |

| Logical Node              | Data Object | Module ( - ANSI/IEEE Device Number ) . Name  |
|---------------------------|-------------|--|
| <b>GFPTOC2 (WW_PTOC3)</b> |             |  |
|                           | Mod         | IG[2] - 50N, 51N . active IG[2] - 50N, 51N . Blo TripCmd<br>IG[2] - 50N, 51N . ExBlo TripCmd |
|                           | Beh         |  |
|                           | Health      |  |
|                           | NamPlt      |  |
|                           | Str         | IG[2] - 50N, 51N . Alarm   |
|                           | Op          | IG[2] - 50N, 51N . Trip  |

| Logical Node              | Data Object | Module ( - ANSI/IEEE Device Number ) . Name  |
|---------------------------|-------------|--|
| <b>GFPTOC3 (WW_PTOC3)</b> |             |  |
|                           | Mod         | IG[3] - 50N, 51N . active IG[3] - 50N, 51N . Blo TripCmd<br>IG[3] - 50N, 51N . ExBlo TripCmd |
|                           | Beh         |  |
|                           | Health      |  |
|                           | NamPlt      |  |
|                           | Str         | IG[3] - 50N, 51N . Alarm   |
|                           | Op          | IG[3] - 50N, 51N . Trip  |

| Logical Node              | Data Object | Module ( - ANSI/IEEE Device Number ) . Name  |
|---------------------------|-------------|--|
| <b>GFPTOC4 (WW_PTOC3)</b> |             |  |
|                           | Mod         | IG[4] - 50N, 51N . active IG[4] - 50N, 51N . Blo TripCmd<br>IG[4] - 50N, 51N . ExBlo TripCmd |
|                           | Beh         |  |
|                           | Health      |  |
|                           | NamPlt      |  |
|                           | Str         | IG[4] - 50N, 51N . Alarm   |
|                           | Op          | IG[4] - 50N, 51N . Trip  |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name   |
|--------------------------|-------------|---|
| <b>GPDIF1 (WW_PDIF3)</b> |             |   |
|                          | Mod         | IdGH[1] - 87N . active IdGH[1] - 87N . Blo TripCmd IdGH[1] -<br>87N . ExBlo TripCmd |
|                          | Beh         |   |
|                          | Health      |   |

4 Appendix  
4.1 Register Maps

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|--------------------------|-------------|---|
| <b>GPDIF1 (WW_PDIF3)</b> |             |   |
|                          | NamPlt      |   |
|                          | Str         | IdGH[1] - 87N . Alarm                       |
|                          | Op          | IdGH[1] - 87N . TripCmd                     |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                                      |
|--------------------------|-------------|--|
| <b>GPDIF2 (WW_PDIF3)</b> |             |  |
|                          | Mod         | IdGH[2] - 87N . active IdGH[2] - 87N . Blo TripCmd IdGH[2] - 87N . ExBlo TripCmd |
|                          | Beh         |  |
|                          | Health      |  |
|                          | NamPlt      |  |
|                          | Str         | IdGH[2] - 87N . Alarm  |
|                          | Op          | IdGH[2] - 87N . TripCmd  |

| Logical Node               | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                       |
|----------------------------|-------------|---|
| <b>HRGPDIF1 (WW_PDIF4)</b> |             |   |
|                            | Mod         | IdH - 87 . active IdH - 87 . Blo TripCmd IdH - 87 . ExBlo TripCmd |
|                            | Beh         |   |
|                            | Health      |   |
|                            | NamPlt      |   |
|                            | Str         | IdH - 87 . Alarm  |
|                            | Op          | IdH - 87 . TripCmd  |

| Logical Node               | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                                   |
|----------------------------|-------------|---|
| <b>HSPPDIF1 (WW_PDIF2)</b> |             |   |
|                            | Mod         | IdG[1] - 87N . active IdG[1] - 87N . Blo TripCmd IdG[1] - 87N . ExBlo TripCmd |
|                            | Beh         |   |
|                            | Health      |   |
|                            | NamPlt      |   |
|                            | Str         | IdG[1] - 87N . Alarm  |
|                            | Op          | IdG[1] - 87N . Trip   |

| Logical Node               | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                                   |
|----------------------------|-------------|---|
| <b>HSPPDIF2 (WW_PDIF2)</b> |             |   |
|                            | Mod         | IdG[2] - 87N . active IdG[2] - 87N . Blo TripCmd IdG[2] - 87N . ExBlo TripCmd |
|                            | Beh         |   |



| Logical Node               | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|----------------------------|-------------|---|
| <b>HSPPDIF2 (WW_PDIF2)</b> |             |   |
|                            | Health      |   |
|                            | NamPlt      |   |
|                            | Str         | IdG[2] - 87N . Alarm                        |
|                            | Op          | IdG[2] - 87N . Trip                         |

| Logical Node            | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|-------------------------|-------------|---|
| <b>IHMI1 (WW_IHMI1)</b> |             |   |
|                         | Mod         |   |
|                         | Beh         |   |
|                         | Health      |   |
|                         | NamPlt      |   |

| Logical Node               | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|----------------------------|-------------|---|
| <b>INRPHAR1 (WW_PHAR1)</b> |             |   |
|                            | Mod         | IH2[1] . active                             |
|                            | Beh         |   |
|                            | Health      |   |
|                            | NamPlt      |   |
|                            | Str         | IH2[1] . 3-ph Blo                           |

| Logical Node               | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|----------------------------|-------------|---|
| <b>INRPHAR2 (WW_PHAR1)</b> |             |   |
|                            | Mod         | IH2[2] . active                             |
|                            | Beh         |   |
|                            | Health      |   |
|                            | NamPlt      |   |
|                            | Str         | IH2[2] . 3-ph Blo                           |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|--------------------------|-------------|---|
| <b>LLN0 (WW_LLNOPRO)</b> |             |   |
|                          | Mod         |   |
|                          | Beh         |   |
|                          | Health      |   |
|                          | NamPlt      |   |

| Logical Node              | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|---------------------------|-------------|---|
| <b>LPHD1 (WW_LPHDPRO)</b> |             |   |
|                           | PhyNam      |   |

4 Appendix  
 4.1 Register Maps

| Logical Node              | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|---------------------------|-------------|---|
| <b>LPHD1 (WW_LPHDPRO)</b> |             |   |
|                           | PhyHealth   |   |
|                           | Proxy       |   |

| Logical Node                 | Data Object | Module ( - ANSI/IEEE Device Number ) . Name        |
|------------------------------|-------------|--|
| <b>LSPFDPFRC1 (WW_PFRC2)</b> |             |  |
|                              | Mod         | UFLS . active UFLS . ExBlo UFLS . Fuse Fail VT Blo |
|                              | Beh         |  |
|                              | Health      |  |
|                              | NamPlt      |  |
|                              | Str         | UFLS . Alarm                                       |
|                              | Op          | UFLS . Trip  |

| Logical Node               | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                                   |
|----------------------------|-------------|---|
| <b>OEPVPH1* (WW_PVPH1)</b> |             |   |
|                            | Mod         | V/f>[1] - 24 . active V/f>[1] - 24 . Blo TripCmd V/f>[1] - 24 . ExBlo TripCmd |
|                            | Beh         |   |
|                            | Health      |   |
|                            | NamPlt      |   |
|                            | Str         | V/f>[1] - 24 . Alarm  |
|                            | Op          | V/f>[1] - 24 . Trip   |

| Logical Node               | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                                   |
|----------------------------|-------------|---|
| <b>OEPVPH2* (WW_PVPH1)</b> |             |   |
|                            | Mod         | V/f>[2] - 24 . active V/f>[2] - 24 . Blo TripCmd V/f>[2] - 24 . ExBlo TripCmd |
|                            | Beh         |   |
|                            | Health      |   |
|                            | NamPlt      |   |
|                            | Str         | V/f>[2] - 24 . Alarm  |
|                            | Op          | V/f>[2] - 24 . Trip   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                    |
|--------------------------|-------------|--|
| <b>PDOP1* (WW_PDOP1)</b> |             |  |
|                          | Mod         | P - 32R . active P - 32R . Blo TripCmd P - 32R . ExBlo TripCmd |
|                          | Beh         |  |
|                          | Health      |  |
|                          | NamPlt      |  |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|--------------------------|-------------|---|
| <b>PDOP1* (WW_PDOP1)</b> |             |   |
|                          | Str         | P - 32R . Alarm                             |
|                          | Op          | P - 32R . Trip                              |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                 |
|--------------------------|-------------|---|
| <b>PDOP2* (WW_PDOP1)</b> |             |   |
|                          | Mod         | Q - 32 . active Q - 32 . Blo TripCmd Q - 32 . ExBlo TripCmd |
|                          | Beh         |   |
|                          | Health      |   |
|                          | NamPlt      |   |
|                          | Str         | Q - 32 . Alarm  |
|                          | Op          | Q - 32 . Trip   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name   |
|--------------------------|-------------|---|
| <b>PDOP3* (WW_PDOP1)</b> |             |   |
|                          | Mod         | PQS[1] - 32, 37 . active PQS[1] - 32, 37 . Blo TripCmd<br>PQS[1] - 32, 37 . ExBlo TripCmd |
|                          | Beh         |   |
|                          | Health      |   |
|                          | NamPlt      |   |
|                          | Str         | PQS[1] - 32, 37 . Alarm   |
|                          | Op          | PQS[1] - 32, 37 . Trip  |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name   |
|--------------------------|-------------|---|
| <b>PDOP4* (WW_PDOP1)</b> |             |   |
|                          | Mod         | PQS[2] - 32, 37 . active PQS[2] - 32, 37 . Blo TripCmd<br>PQS[2] - 32, 37 . ExBlo TripCmd |
|                          | Beh         |   |
|                          | Health      |   |
|                          | NamPlt      |   |
|                          | Str         | PQS[2] - 32, 37 . Alarm   |
|                          | Op          | PQS[2] - 32, 37 . Trip  |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name   |
|--------------------------|-------------|---|
| <b>PDOP5* (WW_PDOP1)</b> |             |   |
|                          | Mod         | PQS[3] - 32, 37 . active PQS[3] - 32, 37 . Blo TripCmd<br>PQS[3] - 32, 37 . ExBlo TripCmd |
|                          | Beh         |   |
|                          | Health      |   |
|                          | NamPlt      |   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|--------------------------|-------------|---|
| <b>PDOP5* (WW_PDOP1)</b> |             |   |
|                          | Str         | PQS[3] - 32, 37 . Alarm                     |
|                          | Op          | PQS[3] - 32, 37 . Trip                      |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name   |
|--------------------------|-------------|---|
| <b>PDOP6* (WW_PDOP1)</b> |             |   |
|                          | Mod         | PQS[4] - 32, 37 . active PQS[4] - 32, 37 . Blo TripCmd<br>PQS[4] - 32, 37 . ExBlo TripCmd |
|                          | Beh         |   |
|                          | Health      |   |
|                          | NamPlt      |   |
|                          | Str         | PQS[4] - 32, 37 . Alarm   |
|                          | Op          | PQS[4] - 32, 37 . Trip  |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name   |
|--------------------------|-------------|---|
| <b>PDOP7* (WW_PDOP1)</b> |             |   |
|                          | Mod         | PQS[5] - 32, 37 . active PQS[5] - 32, 37 . Blo TripCmd<br>PQS[5] - 32, 37 . ExBlo TripCmd |
|                          | Beh         |   |
|                          | Health      |   |
|                          | NamPlt      |   |
|                          | Str         | PQS[5] - 32, 37 . Alarm   |
|                          | Op          | PQS[5] - 32, 37 . Trip  |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name   |
|--------------------------|-------------|---|
| <b>PDOP8* (WW_PDOP1)</b> |             |   |
|                          | Mod         | PQS[6] - 32, 37 . active PQS[6] - 32, 37 . Blo TripCmd<br>PQS[6] - 32, 37 . ExBlo TripCmd |
|                          | Beh         |   |
|                          | Health      |   |
|                          | NamPlt      |   |
|                          | Str         | PQS[6] - 32, 37 . Alarm   |
|                          | Op          | PQS[6] - 32, 37 . Trip  |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                    |
|--------------------------|-------------|--|
| <b>PDUP1* (WW_PDUP1)</b> |             |  |
|                          | Mod         | P - 32R . active P - 32R . Blo TripCmd P - 32R . ExBlo TripCmd |
|                          | Beh         |  |
|                          | Health      |  |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|--------------------------|-------------|---|
| <b>PDUP1* (WW_PDUP1)</b> |             |   |
|                          | NamPlt      |   |
|                          | Str         | P - 32R . Alarm                             |
|                          | Op          | P - 32R . Trip                              |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                 |
|--------------------------|-------------|---|
| <b>PDUP2* (WW_PDUP1)</b> |             |   |
|                          | Mod         | Q - 32 . active Q - 32 . Blo TripCmd Q - 32 . ExBlo TripCmd |
|                          | Beh         |   |
|                          | Health      |   |
|                          | NamPlt      |   |
|                          | Str         | Q - 32 . Alarm  |
|                          | Op          | Q - 32 . Trip   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name   |
|--------------------------|-------------|---|
| <b>PDUP3* (WW_PDUP1)</b> |             |   |
|                          | Mod         | PQS[1] - 32, 37 . active PQS[1] - 32, 37 . Blo TripCmd<br>PQS[1] - 32, 37 . ExBlo TripCmd |
|                          | Beh         |   |
|                          | Health      |   |
|                          | NamPlt      |   |
|                          | Str         | PQS[1] - 32, 37 . Alarm   |
|                          | Op          | PQS[1] - 32, 37 . Trip  |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name   |
|--------------------------|-------------|---|
| <b>PDUP4* (WW_PDUP1)</b> |             |   |
|                          | Mod         | PQS[2] - 32, 37 . active PQS[2] - 32, 37 . Blo TripCmd<br>PQS[2] - 32, 37 . ExBlo TripCmd |
|                          | Beh         |   |
|                          | Health      |   |
|                          | NamPlt      |   |
|                          | Str         | PQS[2] - 32, 37 . Alarm   |
|                          | Op          | PQS[2] - 32, 37 . Trip  |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name   |
|--------------------------|-------------|---|
| <b>PDUP5* (WW_PDUP1)</b> |             |   |
|                          | Mod         | PQS[3] - 32, 37 . active PQS[3] - 32, 37 . Blo TripCmd<br>PQS[3] - 32, 37 . ExBlo TripCmd |
|                          | Beh         |   |
|                          | Health      |   |

4 Appendix  
 4.1 Register Maps

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|--------------------------|-------------|---|
| <b>PDUP5* (WW_PDUP1)</b> |             |   |
|                          | NamPlt      |   |
|                          | Str         | PQS[3] - 32, 37 . Alarm                     |
|                          | Op          | PQS[3] - 32, 37 . Trip                      |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name   |
|--------------------------|-------------|---|
| <b>PDUP6* (WW_PDUP1)</b> |             |   |
|                          | Mod         | PQS[4] - 32, 37 . active PQS[4] - 32, 37 . Blo TripCmd<br>PQS[4] - 32, 37 . ExBlo TripCmd |
|                          | Beh         |   |
|                          | Health      |   |
|                          | NamPlt      |   |
|                          | Str         | PQS[4] - 32, 37 . Alarm   |
|                          | Op          | PQS[4] - 32, 37 . Trip  |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name   |
|--------------------------|-------------|---|
| <b>PDUP7* (WW_PDUP1)</b> |             |   |
|                          | Mod         | PQS[5] - 32, 37 . active PQS[5] - 32, 37 . Blo TripCmd<br>PQS[5] - 32, 37 . ExBlo TripCmd |
|                          | Beh         |   |
|                          | Health      |   |
|                          | NamPlt      |   |
|                          | Str         | PQS[5] - 32, 37 . Alarm   |
|                          | Op          | PQS[5] - 32, 37 . Trip  |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name   |
|--------------------------|-------------|---|
| <b>PDUP8* (WW_PDUP1)</b> |             |   |
|                          | Mod         | PQS[6] - 32, 37 . active PQS[6] - 32, 37 . Blo TripCmd<br>PQS[6] - 32, 37 . ExBlo TripCmd |
|                          | Beh         |   |
|                          | Health      |   |
|                          | NamPlt      |   |
|                          | Str         | PQS[6] - 32, 37 . Alarm   |
|                          | Op          | PQS[6] - 32, 37 . Trip  |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                                   |
|--------------------------|-------------|---|
| <b>PFRC1* (WW_PFRC1)</b> |             |   |
|                          | Mod         | df/dt - 81R . active df/dt - 81R . Blo TripCmd df/dt - 81R .<br>ExBlo TripCmd |
|                          | Beh         |   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|--------------------------|-------------|---|
| <b>PFRC1* (WW_PFRC1)</b> |             |   |
|                          | Health      |   |
|                          | NamPlt      |   |
|                          | Str         | df/dt - 81R . Alarm                         |
|                          | Op          | df/dt - 81R . Trip                          |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name  |
|--------------------------|-------------|--|
| <b>PFRC2* (WW_PFRC1)</b> |             |  |
|                          | Mod         | delta phi - 78V . active delta phi - 78V . Blo TripCmd delta phi - 78V . ExBlo TripCmd |
|                          | Beh         |  |
|                          | Health      |  |
|                          | NamPlt      |  |
|                          | Str         | delta phi - 78V . Alarm  |
|                          | Op          | delta phi - 78V . Trip   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                          |
|--------------------------|-------------|--|
| <b>PFRC3* (WW_PFRC1)</b> |             |  |
|                          | Mod         | f[1] - 81 . active f[1] - 81 . Blo TripCmd f[1] - 81 . ExBlo TripCmd |
|                          | Beh         |  |
|                          | Health      |  |
|                          | NamPlt      |  |
|                          | Str         | f[1] - 81 . Alarm  |
|                          | Op          | f[1] - 81 . Trip   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                          |
|--------------------------|-------------|--|
| <b>PFRC4* (WW_PFRC1)</b> |             |  |
|                          | Mod         | f[2] - 81 . active f[2] - 81 . Blo TripCmd f[2] - 81 . ExBlo TripCmd |
|                          | Beh         |  |
|                          | Health      |  |
|                          | NamPlt      |  |
|                          | Str         | f[2] - 81 . Alarm  |
|                          | Op          | f[2] - 81 . Trip   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                          |
|--------------------------|-------------|--|
| <b>PFRC5* (WW_PFRC1)</b> |             |  |
|                          | Mod         | f[3] - 81 . active f[3] - 81 . Blo TripCmd f[3] - 81 . ExBlo TripCmd |

4 Appendix  
4.1 Register Maps

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|--------------------------|-------------|---|
| <b>PFRC5* (WW_PFRC1)</b> |             |   |
|                          | Beh         |   |
|                          | Health      |   |
|                          | NamPlt      |   |
|                          | Str         | f[3] - 81 . Alarm                           |
|                          | Op          | f[3] - 81 . Trip                            |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                          |
|--------------------------|-------------|--|
| <b>PFRC6* (WW_PFRC1)</b> |             |  |
|                          | Mod         | f[4] - 81 . active f[4] - 81 . Blo TripCmd f[4] - 81 . ExBlo TripCmd |
|                          | Beh         |  |
|                          | Health      |  |
|                          | NamPlt      |  |
|                          | Str         | f[4] - 81 . Alarm  |
|                          | Op          | f[4] - 81 . Trip   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                          |
|--------------------------|-------------|--|
| <b>PFRC7* (WW_PFRC1)</b> |             |  |
|                          | Mod         | f[5] - 81 . active f[5] - 81 . Blo TripCmd f[5] - 81 . ExBlo TripCmd |
|                          | Beh         |  |
|                          | Health      |  |
|                          | NamPlt      |  |
|                          | Str         | f[5] - 81 . Alarm  |
|                          | Op          | f[5] - 81 . Trip   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                          |
|--------------------------|-------------|--|
| <b>PFRC8* (WW_PFRC1)</b> |             |  |
|                          | Mod         | f[6] - 81 . active f[6] - 81 . Blo TripCmd f[6] - 81 . ExBlo TripCmd |
|                          | Beh         |  |
|                          | Health      |  |
|                          | NamPlt      |  |
|                          | Str         | f[6] - 81 . Alarm  |
|                          | Op          | f[6] - 81 . Trip   |



| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                                |
|--------------------------|-------------|--|
| <b>PPAM1* (WW_PPAM1)</b> |             |  |
|                          | Mod         | df/dt - 81R . active df/dt - 81R . Blo TripCmd df/dt - 81R . ExBlo TripCmd |
|                          | Beh         |  |
|                          | Health      |  |
|                          | NamPlt      |  |
|                          | Str         | df/dt - 81R . Alarm  |
|                          | Op          | df/dt - 81R . Trip   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name  |
|--------------------------|-------------|--|
| <b>PPAM2* (WW_PPAM1)</b> |             |  |
|                          | Mod         | delta phi - 78V . active delta phi - 78V . Blo TripCmd delta phi - 78V . ExBlo TripCmd |
|                          | Beh         |  |
|                          | Health      |  |
|                          | NamPlt      |  |
|                          | Str         | delta phi - 78V . Alarm  |
|                          | Op          | delta phi - 78V . Trip   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                          |
|--------------------------|-------------|--|
| <b>PPAM3* (WW_PPAM1)</b> |             |  |
|                          | Mod         | f[1] - 81 . active f[1] - 81 . Blo TripCmd f[1] - 81 . ExBlo TripCmd |
|                          | Beh         |  |
|                          | Health      |  |
|                          | NamPlt      |  |
|                          | Str         | f[1] - 81 . Alarm  |
|                          | Op          | f[1] - 81 . Trip   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                          |
|--------------------------|-------------|--|
| <b>PPAM4* (WW_PPAM1)</b> |             |  |
|                          | Mod         | f[2] - 81 . active f[2] - 81 . Blo TripCmd f[2] - 81 . ExBlo TripCmd |
|                          | Beh         |  |
|                          | Health      |  |
|                          | NamPlt      |  |
|                          | Str         | f[2] - 81 . Alarm  |
|                          | Op          | f[2] - 81 . Trip   |

4 Appendix  
 4.1 Register Maps

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                          |
|--------------------------|-------------|--|
| <b>PPAM5* (WW_PPAM1)</b> |             |  |
|                          | Mod         | f[3] - 81 . active f[3] - 81 . Blo TripCmd f[3] - 81 . ExBlo TripCmd |
|                          | Beh         |  |
|                          | Health      |  |
|                          | NamPlt      |  |
|                          | Str         | f[3] - 81 . Alarm  |
|                          | Op          | f[3] - 81 . Trip   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                          |
|--------------------------|-------------|--|
| <b>PPAM6* (WW_PPAM1)</b> |             |  |
|                          | Mod         | f[4] - 81 . active f[4] - 81 . Blo TripCmd f[4] - 81 . ExBlo TripCmd |
|                          | Beh         |  |
|                          | Health      |  |
|                          | NamPlt      |  |
|                          | Str         | f[4] - 81 . Alarm  |
|                          | Op          | f[4] - 81 . Trip   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                          |
|--------------------------|-------------|--|
| <b>PPAM7* (WW_PPAM1)</b> |             |  |
|                          | Mod         | f[5] - 81 . active f[5] - 81 . Blo TripCmd f[5] - 81 . ExBlo TripCmd |
|                          | Beh         |  |
|                          | Health      |  |
|                          | NamPlt      |  |
|                          | Str         | f[5] - 81 . Alarm  |
|                          | Op          | f[5] - 81 . Trip   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                          |
|--------------------------|-------------|--|
| <b>PPAM8* (WW_PPAM1)</b> |             |  |
|                          | Mod         | f[6] - 81 . active f[6] - 81 . Blo TripCmd f[6] - 81 . ExBlo TripCmd |
|                          | Beh         |  |
|                          | Health      |  |
|                          | NamPlt      |  |
|                          | Str         | f[6] - 81 . Alarm  |
|                          | Op          | f[6] - 81 . Trip   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                    |
|--------------------------|-------------|--|
| <b>PPDIF1 (WW_PDIF1)</b> |             |  |
|                          | Mod         | Id - 87 . active Id - 87 . Blo TripCmd Id - 87 . ExBlo TripCmd |
|                          | Beh         |  |
|                          | Health      |  |
|                          | NamPlt      |  |
|                          | Str         | Id - 87 . Alarm  |
|                          | Op          | Id - 87 . TripCmd  |

| Logical Node            | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|-------------------------|-------------|---|
| <b>PSDE1 (WW_PSDE1)</b> |             |   |
|                         | Mod         | VT . IG meas dir wattm                      |
|                         | Beh         |   |
|                         | Health      |   |
|                         | NamPlt      |   |
|                         | Str         |   |

| Logical Node            | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|-------------------------|-------------|---|
| <b>PSDE2 (WW_PSDE2)</b> |             |   |
|                         | Mod         | VT . IG calc dir wattm                      |
|                         | Beh         |   |
|                         | Health      |   |
|                         | NamPlt      |   |
|                         | Str         |   |

| Logical Node            | Data Object | Module ( - ANSI/IEEE Device Number ) . Name     |
|-------------------------|-------------|---|
| <b>PSOF1 (WW_PSOF1)</b> |             |   |
|                         | Mod         | SOTF . active SOTF . ExBlo SOTF . Ex rev Interl |
|                         | Beh         |   |
|                         | Health      |   |
|                         | NamPlt      |   |
|                         | Str         | SOTF . enabled                                  |

| Logical Node            | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                                      |
|-------------------------|-------------|--|
| <b>PTOC1 (WW_PTOC1)</b> |             |  |
|                         | Mod         | I[1] - 50, 51 . active I[1] - 50, 51 . Blo TripCmd I[1] - 50, 51 . ExBlo TripCmd |
|                         | Beh         |  |
|                         | Health      |  |
|                         | NamPlt      |  |

4 Appendix  
4.1 Register Maps

| Logical Node            | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|-------------------------|-------------|---|
| <b>PTOC1 (WW_PTOC1)</b> |             |   |
|                         | Str         | I[1] - 50, 51 . Alarm                       |
|                         | Op          | I[1] - 50, 51 . Trip                        |

| Logical Node            | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                                      |
|-------------------------|-------------|--|
| <b>PTOC2 (WW_PTOC1)</b> |             |  |
|                         | Mod         | I[2] - 50, 51 . active I[2] - 50, 51 . Blo TripCmd I[2] - 50, 51 . ExBlo TripCmd |
|                         | Beh         |  |
|                         | Health      |  |
|                         | NamPlt      |  |
|                         | Str         | I[2] - 50, 51 . Alarm  |
|                         | Op          | I[2] - 50, 51 . Trip   |

| Logical Node            | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                                      |
|-------------------------|-------------|--|
| <b>PTOC3 (WW_PTOC1)</b> |             |  |
|                         | Mod         | I[3] - 50, 51 . active I[3] - 50, 51 . Blo TripCmd I[3] - 50, 51 . ExBlo TripCmd |
|                         | Beh         |  |
|                         | Health      |  |
|                         | NamPlt      |  |
|                         | Str         | I[3] - 50, 51 . Alarm  |
|                         | Op          | I[3] - 50, 51 . Trip   |

| Logical Node            | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                                      |
|-------------------------|-------------|--|
| <b>PTOC4 (WW_PTOC1)</b> |             |  |
|                         | Mod         | I[4] - 50, 51 . active I[4] - 50, 51 . Blo TripCmd I[4] - 50, 51 . ExBlo TripCmd |
|                         | Beh         |  |
|                         | Health      |  |
|                         | NamPlt      |  |
|                         | Str         | I[4] - 50, 51 . Alarm  |
|                         | Op          | I[4] - 50, 51 . Trip   |

| Logical Node            | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                                      |
|-------------------------|-------------|--|
| <b>PTOC5 (WW_PTOC1)</b> |             |  |
|                         | Mod         | I[5] - 50, 51 . active I[5] - 50, 51 . Blo TripCmd I[5] - 50, 51 . ExBlo TripCmd |
|                         | Beh         |  |
|                         | Health      |  |

| Logical Node            | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|-------------------------|-------------|---|
| <b>PTOC5 (WW_PTOC1)</b> |             |   |
|                         | NamPlt      |   |
|                         | Str         | I[5] - 50, 51 . Alarm                       |
|                         | Op          | I[5] - 50, 51 . Trip                        |

| Logical Node            | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                                      |
|-------------------------|-------------|--|
| <b>PTOC6 (WW_PTOC1)</b> |             |  |
|                         | Mod         | I[6] - 50, 51 . active I[6] - 50, 51 . Blo TripCmd I[6] - 50, 51 . ExBlo TripCmd |
|                         | Beh         |  |
|                         | Health      |  |
|                         | NamPlt      |  |
|                         | Str         | I[6] - 50, 51 . Alarm  |
|                         | Op          | I[6] - 50, 51 . Trip   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                                |
|--------------------------|-------------|--|
| <b>PTOF1* (WW_PTOF1)</b> |             |  |
|                          | Mod         | df/dt - 81R . active df/dt - 81R . Blo TripCmd df/dt - 81R . ExBlo TripCmd |
|                          | Beh         |  |
|                          | Health      |  |
|                          | NamPlt      |  |
|                          | Str         | df/dt - 81R . Alarm  |
|                          | Op          | df/dt - 81R . Trip   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name  |
|--------------------------|-------------|--|
| <b>PTOF2* (WW_PTOF1)</b> |             |  |
|                          | Mod         | delta phi - 78V . active delta phi - 78V . Blo TripCmd delta phi - 78V . ExBlo TripCmd |
|                          | Beh         |  |
|                          | Health      |  |
|                          | NamPlt      |  |
|                          | Str         | delta phi - 78V . Alarm  |
|                          | Op          | delta phi - 78V . Trip   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                          |
|--------------------------|-------------|--|
| <b>PTOF3* (WW_PTOF1)</b> |             |  |
|                          | Mod         | f[1] - 81 . active f[1] - 81 . Blo TripCmd f[1] - 81 . ExBlo TripCmd |
|                          | Beh         |  |

4 Appendix  
4.1 Register Maps

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|--------------------------|-------------|---|
| <b>PTOF3* (WW_PTOF1)</b> |             |   |
|                          | Health      |   |
|                          | NamPlt      |   |
|                          | Str         | f[1] - 81 . Alarm                           |
|                          | Op          | f[1] - 81 . Trip                            |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                          |
|--------------------------|-------------|--|
| <b>PTOF4* (WW_PTOF1)</b> |             |  |
|                          | Mod         | f[2] - 81 . active f[2] - 81 . Blo TripCmd f[2] - 81 . ExBlo TripCmd |
|                          | Beh         |  |
|                          | Health      |  |
|                          | NamPlt      |  |
|                          | Str         | f[2] - 81 . Alarm  |
|                          | Op          | f[2] - 81 . Trip   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                          |
|--------------------------|-------------|--|
| <b>PTOF5* (WW_PTOF1)</b> |             |  |
|                          | Mod         | f[3] - 81 . active f[3] - 81 . Blo TripCmd f[3] - 81 . ExBlo TripCmd |
|                          | Beh         |  |
|                          | Health      |  |
|                          | NamPlt      |  |
|                          | Str         | f[3] - 81 . Alarm  |
|                          | Op          | f[3] - 81 . Trip   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                          |
|--------------------------|-------------|--|
| <b>PTOF6* (WW_PTOF1)</b> |             |  |
|                          | Mod         | f[4] - 81 . active f[4] - 81 . Blo TripCmd f[4] - 81 . ExBlo TripCmd |
|                          | Beh         |  |
|                          | Health      |  |
|                          | NamPlt      |  |
|                          | Str         | f[4] - 81 . Alarm  |
|                          | Op          | f[4] - 81 . Trip   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                          |
|--------------------------|-------------|--|
| <b>PTOF7* (WW_PTOF1)</b> |             |  |
|                          | Mod         | f[5] - 81 . active f[5] - 81 . Blo TripCmd f[5] - 81 . ExBlo TripCmd |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|--------------------------|-------------|---|
| <b>PTOF7* (WW_PTOF1)</b> |             |   |
|                          | Beh         |   |
|                          | Health      |   |
|                          | NamPlt      |   |
|                          | Str         | f[5] - 81 . Alarm                           |
|                          | Op          | f[5] - 81 . Trip                            |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                          |
|--------------------------|-------------|--|
| <b>PTOF8* (WW_PTOF1)</b> |             |  |
|                          | Mod         | f[6] - 81 . active f[6] - 81 . Blo TripCmd f[6] - 81 . ExBlo TripCmd |
|                          | Beh         |  |
|                          | Health      |  |
|                          | NamPlt      |  |
|                          | Str         | f[6] - 81 . Alarm  |
|                          | Op          | f[6] - 81 . Trip   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                                      |
|--------------------------|-------------|--|
| <b>PTOV1* (WW_PTOV2)</b> |             |  |
|                          | Mod         | V[1] - 27, 59 . active V[1] - 27, 59 . Blo TripCmd V[1] - 27, 59 . ExBlo TripCmd |
|                          | Beh         |  |
|                          | Health      |  |
|                          | NamPlt      |  |
|                          | Str         | V[1] - 27, 59 . Alarm  |
|                          | Op          | V[1] - 27, 59 . Trip   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                                      |
|--------------------------|-------------|--|
| <b>PTOV2* (WW_PTOV2)</b> |             |  |
|                          | Mod         | V[2] - 27, 59 . active V[2] - 27, 59 . Blo TripCmd V[2] - 27, 59 . ExBlo TripCmd |
|                          | Beh         |  |
|                          | Health      |  |
|                          | NamPlt      |  |
|                          | Str         | V[2] - 27, 59 . Alarm  |
|                          | Op          | V[2] - 27, 59 . Trip   |

4 Appendix  
4.1 Register Maps

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                                      |
|--------------------------|-------------|--|
| <b>PTOV3* (WW_PTOV2)</b> |             |  |
|                          | Mod         | V[3] - 27, 59 . active V[3] - 27, 59 . Blo TripCmd V[3] - 27, 59 . ExBlo TripCmd |
|                          | Beh         |  |
|                          | Health      |  |
|                          | NamPlt      |  |
|                          | Str         | V[3] - 27, 59 . Alarm  |
|                          | Op          | V[3] - 27, 59 . Trip   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                                      |
|--------------------------|-------------|--|
| <b>PTOV4* (WW_PTOV2)</b> |             |  |
|                          | Mod         | V[4] - 27, 59 . active V[4] - 27, 59 . Blo TripCmd V[4] - 27, 59 . ExBlo TripCmd |
|                          | Beh         |  |
|                          | Health      |  |
|                          | NamPlt      |  |
|                          | Str         | V[4] - 27, 59 . Alarm  |
|                          | Op          | V[4] - 27, 59 . Trip   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                                      |
|--------------------------|-------------|--|
| <b>PTOV5* (WW_PTOV2)</b> |             |  |
|                          | Mod         | V[5] - 27, 59 . active V[5] - 27, 59 . Blo TripCmd V[5] - 27, 59 . ExBlo TripCmd |
|                          | Beh         |  |
|                          | Health      |  |
|                          | NamPlt      |  |
|                          | Str         | V[5] - 27, 59 . Alarm  |
|                          | Op          | V[5] - 27, 59 . Trip   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                                      |
|--------------------------|-------------|--|
| <b>PTOV6* (WW_PTOV2)</b> |             |  |
|                          | Mod         | V[6] - 27, 59 . active V[6] - 27, 59 . Blo TripCmd V[6] - 27, 59 . ExBlo TripCmd |
|                          | Beh         |  |
|                          | Health      |  |
|                          | NamPlt      |  |
|                          | Str         | V[6] - 27, 59 . Alarm  |
|                          | Op          | V[6] - 27, 59 . Trip   |



| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                                |
|--------------------------|-------------|--|
| <b>PTUF1* (WW_PTUF1)</b> |             |  |
|                          | Mod         | df/dt - 81R . active df/dt - 81R . Blo TripCmd df/dt - 81R . ExBlo TripCmd |
|                          | Beh         |  |
|                          | Health      |  |
|                          | NamPlt      |  |
|                          | Str         | df/dt - 81R . Alarm  |
|                          | Op          | df/dt - 81R . Trip   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name  |
|--------------------------|-------------|--|
| <b>PTUF2* (WW_PTUF1)</b> |             |  |
|                          | Mod         | delta phi - 78V . active delta phi - 78V . Blo TripCmd delta phi - 78V . ExBlo TripCmd |
|                          | Beh         |  |
|                          | Health      |  |
|                          | NamPlt      |  |
|                          | Str         | delta phi - 78V . Alarm  |
|                          | Op          | delta phi - 78V . Trip   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                          |
|--------------------------|-------------|--|
| <b>PTUF3* (WW_PTUF1)</b> |             |  |
|                          | Mod         | f[1] - 81 . active f[1] - 81 . Blo TripCmd f[1] - 81 . ExBlo TripCmd |
|                          | Beh         |  |
|                          | Health      |  |
|                          | NamPlt      |  |
|                          | Str         | f[1] - 81 . Alarm  |
|                          | Op          | f[1] - 81 . Trip   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                          |
|--------------------------|-------------|--|
| <b>PTUF4* (WW_PTUF1)</b> |             |  |
|                          | Mod         | f[2] - 81 . active f[2] - 81 . Blo TripCmd f[2] - 81 . ExBlo TripCmd |
|                          | Beh         |  |
|                          | Health      |  |
|                          | NamPlt      |  |
|                          | Str         | f[2] - 81 . Alarm  |
|                          | Op          | f[2] - 81 . Trip   |

4 Appendix  
 4.1 Register Maps

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                          |
|--------------------------|-------------|--|
| <b>PTUF5* (WW_PTUF1)</b> |             |  |
|                          | Mod         | f[3] - 81 . active f[3] - 81 . Blo TripCmd f[3] - 81 . ExBlo TripCmd |
|                          | Beh         |  |
|                          | Health      |  |
|                          | NamPlt      |  |
|                          | Str         | f[3] - 81 . Alarm  |
|                          | Op          | f[3] - 81 . Trip   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                          |
|--------------------------|-------------|--|
| <b>PTUF6* (WW_PTUF1)</b> |             |  |
|                          | Mod         | f[4] - 81 . active f[4] - 81 . Blo TripCmd f[4] - 81 . ExBlo TripCmd |
|                          | Beh         |  |
|                          | Health      |  |
|                          | NamPlt      |  |
|                          | Str         | f[4] - 81 . Alarm  |
|                          | Op          | f[4] - 81 . Trip   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                          |
|--------------------------|-------------|--|
| <b>PTUF7* (WW_PTUF1)</b> |             |  |
|                          | Mod         | f[5] - 81 . active f[5] - 81 . Blo TripCmd f[5] - 81 . ExBlo TripCmd |
|                          | Beh         |  |
|                          | Health      |  |
|                          | NamPlt      |  |
|                          | Str         | f[5] - 81 . Alarm  |
|                          | Op          | f[5] - 81 . Trip   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                          |
|--------------------------|-------------|--|
| <b>PTUF8* (WW_PTUF1)</b> |             |  |
|                          | Mod         | f[6] - 81 . active f[6] - 81 . Blo TripCmd f[6] - 81 . ExBlo TripCmd |
|                          | Beh         |  |
|                          | Health      |  |
|                          | NamPlt      |  |
|                          | Str         | f[6] - 81 . Alarm  |
|                          | Op          | f[6] - 81 . Trip   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                                      |
|--------------------------|-------------|--|
| <b>PTUV1* (WW_PTUV2)</b> |             |  |
|                          | Mod         | V[1] - 27, 59 . active V[1] - 27, 59 . Blo TripCmd V[1] - 27, 59 . ExBlo TripCmd |
|                          | Beh         |  |
|                          | Health      |  |
|                          | NamPlt      |  |
|                          | Str         | V[1] - 27, 59 . Alarm  |
|                          | Op          | V[1] - 27, 59 . Trip   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                                      |
|--------------------------|-------------|--|
| <b>PTUV2* (WW_PTUV2)</b> |             |  |
|                          | Mod         | V[2] - 27, 59 . active V[2] - 27, 59 . Blo TripCmd V[2] - 27, 59 . ExBlo TripCmd |
|                          | Beh         |  |
|                          | Health      |  |
|                          | NamPlt      |  |
|                          | Str         | V[2] - 27, 59 . Alarm  |
|                          | Op          | V[2] - 27, 59 . Trip   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                                      |
|--------------------------|-------------|--|
| <b>PTUV3* (WW_PTUV2)</b> |             |  |
|                          | Mod         | V[3] - 27, 59 . active V[3] - 27, 59 . Blo TripCmd V[3] - 27, 59 . ExBlo TripCmd |
|                          | Beh         |  |
|                          | Health      |  |
|                          | NamPlt      |  |
|                          | Str         | V[3] - 27, 59 . Alarm  |
|                          | Op          | V[3] - 27, 59 . Trip   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                                      |
|--------------------------|-------------|--|
| <b>PTUV4* (WW_PTUV2)</b> |             |  |
|                          | Mod         | V[4] - 27, 59 . active V[4] - 27, 59 . Blo TripCmd V[4] - 27, 59 . ExBlo TripCmd |
|                          | Beh         |  |
|                          | Health      |  |
|                          | NamPlt      |  |
|                          | Str         | V[4] - 27, 59 . Alarm  |
|                          | Op          | V[4] - 27, 59 . Trip   |

4 Appendix  
4.1 Register Maps

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                                      |
|--------------------------|-------------|--|
| <b>PTUV5* (WW_PTUV2)</b> |             |  |
|                          | Mod         | V[5] - 27, 59 . active V[5] - 27, 59 . Blo TripCmd V[5] - 27, 59 . ExBlo TripCmd |
|                          | Beh         |  |
|                          | Health      |  |
|                          | NamPlt      |  |
|                          | Str         | V[5] - 27, 59 . Alarm  |
|                          | Op          | V[5] - 27, 59 . Trip   |

| Logical Node             | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                                      |
|--------------------------|-------------|--|
| <b>PTUV6* (WW_PTUV2)</b> |             |  |
|                          | Mod         | V[6] - 27, 59 . active V[6] - 27, 59 . Blo TripCmd V[6] - 27, 59 . ExBlo TripCmd |
|                          | Beh         |  |
|                          | Health      |  |
|                          | NamPlt      |  |
|                          | Str         | V[6] - 27, 59 . Alarm  |
|                          | Op          | V[6] - 27, 59 . Trip   |

| Logical Node            | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                             |
|-------------------------|-------------|---|
| <b>PUPF1 (WW_PUPF1)</b> |             |   |
|                         | Mod         | PF[1] - 55 . active PF[1] - 55 . Blo TripCmd PF[1] - 55 . ExBlo TripCmd |
|                         | Beh         |   |
|                         | Health      |   |
|                         | NamPlt      |   |
|                         | Str         | PF[1] - 55 . Alarm  |
|                         | Op          | PF[1] - 55 . Trip   |

| Logical Node            | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                             |
|-------------------------|-------------|---|
| <b>PUPF2 (WW_PUPF1)</b> |             |   |
|                         | Mod         | PF[2] - 55 . active PF[2] - 55 . Blo TripCmd PF[2] - 55 . ExBlo TripCmd |
|                         | Beh         |   |
|                         | Health      |   |
|                         | NamPlt      |   |
|                         | Str         | PF[2] - 55 . Alarm  |
|                         | Op          | PF[2] - 55 . Trip   |

| Logical Node              | Data Object | Module ( - ANSI/IEEE Device Number ) . Name              |
|---------------------------|-------------|--|
| <b>QVPTUV1 (WW_PTUV5)</b> |             |  |
|                           | Mod         | Q->&V< . active Q->&V< . ExBlo Q->&V< . Fuse Fail VT Blo |
|                           | Beh         |  |
|                           | Health      |  |
|                           | NamPlt      |  |
|                           | Str         | Q->&V< . Alarm   |
|                           | Op          | Q->&V< . Decoupling Distr. Generator                     |

| Logical Node            | Data Object | Module ( - ANSI/IEEE Device Number ) . Name   |
|-------------------------|-------------|---|
| <b>RBRF1 (WW_RBRF1)</b> |             |   |
|                         | Mod         | CBF[1] - 50BF, 62BF . active CBF[1] - 50BF, 62BF . ExBlo<br>CBF[1] - 50BF, 62BF . ExBlo |
|                         | Beh         |   |
|                         | Health      |   |
|                         | NamPlt      |   |
|                         | Str         | CBF[1] - 50BF, 62BF . running   |
|                         | OpEx        | CBF[1] - 50BF, 62BF . Alarm   |

| Logical Node            | Data Object | Module ( - ANSI/IEEE Device Number ) . Name   |
|-------------------------|-------------|---|
| <b>RBRF2 (WW_RBRF1)</b> |             |   |
|                         | Mod         | CBF[2] - 50BF, 62BF . active CBF[2] - 50BF, 62BF . ExBlo<br>CBF[2] - 50BF, 62BF . ExBlo |
|                         | Beh         |   |
|                         | Health      |   |
|                         | NamPlt      |   |
|                         | Str         | CBF[2] - 50BF, 62BF . running   |
|                         | OpEx        | CBF[2] - 50BF, 62BF . Alarm   |

| Logical Node            | Data Object | Module ( - ANSI/IEEE Device Number ) . Name            |
|-------------------------|-------------|--|
| <b>RSYN1 (WW_RSYN2)</b> |             |  |
|                         | Mod         | Sync - 25 . active Sync - 25 . ExBlo Sync - 25 . ExBlo |
|                         | Beh         |  |
|                         | Health      |  |
|                         | NamPlt      |  |
|                         | Rel         | Sync - 25 . Ready to Close                             |
|                         | AngInd      | Sync - 25 . AngleDiffTooHigh                           |
|                         | HZInd       | Sync - 25 . SlipTooHigh                                |
|                         | VInd        | Sync - 25 . VDiffTooHigh                               |
|                         | DifAngClc   | Sync - 25 . Angle Diff                                 |

4 Appendix  
4.1 Register Maps

| Logical Node            | Data Object | Module ( - ANSI/IEEE Device Number ) . Name |
|-------------------------|-------------|---|
| <b>RSYN1 (WW_RSYN2)</b> |             |   |
|                         | DifHzClc    | Sync - 25 . Slip Freq                       |
|                         | DifVClc     | Sync - 25 . Volt Diff                       |

| Logical Node              | Data Object | Module ( - ANSI/IEEE Device Number ) . Name        |
|---------------------------|-------------|--|
| <b>RTDPTR1 (WW_PTTR4)</b> |             |  |
|                           | Mod         | RTD . active RTD . Blo TripCmd RTD . ExBlo TripCmd |
|                           | Beh         |  |
|                           | Health      |  |
|                           | NamPlt      |  |
|                           | Op          | RTD . Trip   |

| Logical Node              | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                       |
|---------------------------|-------------|---|
| <b>TRPTTR1 (WW_PTTR3)</b> |             |   |
|                           | Mod         | ThR - 49 . active ThR - 49 . Blo TripCmd ThR - 49 . ExBlo TripCmd |
|                           | Beh         |   |
|                           | Health      |   |
|                           | NamPlt      |   |
|                           | Op          | ThR - 49 . Trip   |

| Logical Node              | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                                |
|---------------------------|-------------|--|
| <b>ULPTOC1 (WW_PTOC4)</b> |             |  |
|                           | Mod         | I2>[1] - 46 . active I2>[1] - 46 . Blo TripCmd I2>[1] - 46 . ExBlo TripCmd |
|                           | Beh         |  |
|                           | Health      |  |
|                           | NamPlt      |  |
|                           | Str         | I2>[1] - 46 . Alarm  |
|                           | Op          | I2>[1] - 46 . Trip   |

| Logical Node              | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                                |
|---------------------------|-------------|--|
| <b>ULPTOC2 (WW_PTOC4)</b> |             |  |
|                           | Mod         | I2>[2] - 46 . active I2>[2] - 46 . Blo TripCmd I2>[2] - 46 . ExBlo TripCmd |
|                           | Beh         |  |
|                           | Health      |  |
|                           | NamPlt      |  |
|                           | Str         | I2>[2] - 46 . Alarm  |
|                           | Op          | I2>[2] - 46 . Trip   |

| Logical Node               | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                                   |
|----------------------------|-------------|---|
| <b>VAPTOV1* (WW_PTOV3)</b> |             |   |
|                            | Mod         | V012[1] - 47 . active V012[1] - 47 . Blo TripCmd V012[1] - 47 . ExBlo TripCmd |
|                            | Beh         |   |
|                            | Health      |   |
|                            | NamPlt      |   |
|                            | Str         | V012[1] - 47 . Alarm  |
|                            | Op          | V012[1] - 47 . Trip   |

| Logical Node               | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                                   |
|----------------------------|-------------|---|
| <b>VAPTOV2* (WW_PTOV3)</b> |             |   |
|                            | Mod         | V012[2] - 47 . active V012[2] - 47 . Blo TripCmd V012[2] - 47 . ExBlo TripCmd |
|                            | Beh         |   |
|                            | Health      |   |
|                            | NamPlt      |   |
|                            | Str         | V012[2] - 47 . Alarm  |
|                            | Op          | V012[2] - 47 . Trip   |

| Logical Node               | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                                   |
|----------------------------|-------------|---|
| <b>VAPTOV3* (WW_PTOV3)</b> |             |   |
|                            | Mod         | V012[3] - 47 . active V012[3] - 47 . Blo TripCmd V012[3] - 47 . ExBlo TripCmd |
|                            | Beh         |   |
|                            | Health      |   |
|                            | NamPlt      |   |
|                            | Str         | V012[3] - 47 . Alarm  |
|                            | Op          | V012[3] - 47 . Trip   |

| Logical Node               | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                                   |
|----------------------------|-------------|---|
| <b>VAPTOV4* (WW_PTOV3)</b> |             |   |
|                            | Mod         | V012[4] - 47 . active V012[4] - 47 . Blo TripCmd V012[4] - 47 . ExBlo TripCmd |
|                            | Beh         |   |
|                            | Health      |   |
|                            | NamPlt      |   |
|                            | Str         | V012[4] - 47 . Alarm  |
|                            | Op          | V012[4] - 47 . Trip   |

4 Appendix  
 4.1 Register Maps

| Logical Node               | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                                   |
|----------------------------|-------------|---|
| <b>VAPTOV5* (WW_PTOV3)</b> |             |   |
|                            | Mod         | V012[5] - 47 . active V012[5] - 47 . Blo TripCmd V012[5] - 47 . ExBlo TripCmd |
|                            | Beh         |   |
|                            | Health      |   |
|                            | NamPlt      |   |
|                            | Str         | V012[5] - 47 . Alarm  |
|                            | Op          | V012[5] - 47 . Trip   |

| Logical Node               | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                                   |
|----------------------------|-------------|---|
| <b>VAPTOV6* (WW_PTOV3)</b> |             |   |
|                            | Mod         | V012[6] - 47 . active V012[6] - 47 . Blo TripCmd V012[6] - 47 . ExBlo TripCmd |
|                            | Beh         |   |
|                            | Health      |   |
|                            | NamPlt      |   |
|                            | Str         | V012[6] - 47 . Alarm  |
|                            | Op          | V012[6] - 47 . Trip   |

| Logical Node               | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                                   |
|----------------------------|-------------|---|
| <b>VAPTUV1* (WW_PTUV3)</b> |             |   |
|                            | Mod         | V012[1] - 47 . active V012[1] - 47 . Blo TripCmd V012[1] - 47 . ExBlo TripCmd |
|                            | Beh         |   |
|                            | Health      |   |
|                            | NamPlt      |   |
|                            | Str         | V012[1] - 47 . Alarm  |
|                            | Op          | V012[1] - 47 . Trip   |

| Logical Node               | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                                   |
|----------------------------|-------------|---|
| <b>VAPTUV2* (WW_PTUV3)</b> |             |   |
|                            | Mod         | V012[2] - 47 . active V012[2] - 47 . Blo TripCmd V012[2] - 47 . ExBlo TripCmd |
|                            | Beh         |   |
|                            | Health      |   |
|                            | NamPlt      |   |
|                            | Str         | V012[2] - 47 . Alarm  |
|                            | Op          | V012[2] - 47 . Trip   |



| Logical Node               | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                                   |
|----------------------------|-------------|---|
| <b>VAPTUV3* (WW_PTUV3)</b> |             |   |
|                            | Mod         | V012[3] - 47 . active V012[3] - 47 . Blo TripCmd V012[3] - 47 . ExBlo TripCmd |
|                            | Beh         |   |
|                            | Health      |   |
|                            | NamPlt      |   |
|                            | Str         | V012[3] - 47 . Alarm  |
|                            | Op          | V012[3] - 47 . Trip   |

| Logical Node               | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                                   |
|----------------------------|-------------|---|
| <b>VAPTUV4* (WW_PTUV3)</b> |             |   |
|                            | Mod         | V012[4] - 47 . active V012[4] - 47 . Blo TripCmd V012[4] - 47 . ExBlo TripCmd |
|                            | Beh         |   |
|                            | Health      |   |
|                            | NamPlt      |   |
|                            | Str         | V012[4] - 47 . Alarm  |
|                            | Op          | V012[4] - 47 . Trip   |

| Logical Node               | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                                   |
|----------------------------|-------------|---|
| <b>VAPTUV5* (WW_PTUV3)</b> |             |   |
|                            | Mod         | V012[5] - 47 . active V012[5] - 47 . Blo TripCmd V012[5] - 47 . ExBlo TripCmd |
|                            | Beh         |   |
|                            | Health      |   |
|                            | NamPlt      |   |
|                            | Str         | V012[5] - 47 . Alarm  |
|                            | Op          | V012[5] - 47 . Trip   |

| Logical Node               | Data Object | Module ( - ANSI/IEEE Device Number ) . Name                                   |
|----------------------------|-------------|---|
| <b>VAPTUV6* (WW_PTUV3)</b> |             |   |
|                            | Mod         | V012[6] - 47 . active V012[6] - 47 . Blo TripCmd V012[6] - 47 . ExBlo TripCmd |
|                            | Beh         |   |
|                            | Health      |   |
|                            | NamPlt      |   |
|                            | Str         | V012[6] - 47 . Alarm  |
|                            | Op          | V012[6] - 47 . Trip   |

4 Appendix  
4.1 Register Maps

| Logical Node               | Data Object | Module ( - ANSI/IEEE Device Number ) . Name   |
|----------------------------|-------------|---|
| <b>VSPTOV1* (WW_PTOV1)</b> |             |   |
|                            | Mod         | VG[1] - 27A, 59N,A . active VG[1] - 27A, 59N,A . Blo TripCmd VG[1] - 27A, 59N,A . ExBlo TripCmd |
|                            | Beh         |   |
|                            | Health      |   |
|                            | NamPlt      |   |
|                            | Str         | VG[1] - 27A, 59N,A . Alarm  |
|                            | Op          | VG[1] - 27A, 59N,A . Trip   |

| Logical Node               | Data Object | Module ( - ANSI/IEEE Device Number ) . Name   |
|----------------------------|-------------|---|
| <b>VSPTOV2* (WW_PTOV1)</b> |             |   |
|                            | Mod         | VG[2] - 27A, 59N,A . active VG[2] - 27A, 59N,A . Blo TripCmd VG[2] - 27A, 59N,A . ExBlo TripCmd |
|                            | Beh         |   |
|                            | Health      |   |
|                            | NamPlt      |   |
|                            | Str         | VG[2] - 27A, 59N,A . Alarm  |
|                            | Op          | VG[2] - 27A, 59N,A . Trip   |

| Logical Node               | Data Object | Module ( - ANSI/IEEE Device Number ) . Name   |
|----------------------------|-------------|---|
| <b>VSPTUV1* (WW_PTUV1)</b> |             |   |
|                            | Mod         | VG[1] - 27A, 59N,A . active VG[1] - 27A, 59N,A . Blo TripCmd VG[1] - 27A, 59N,A . ExBlo TripCmd |
|                            | Beh         |   |
|                            | Health      |   |
|                            | NamPlt      |   |
|                            | Str         | VG[1] - 27A, 59N,A . Alarm  |
|                            | Op          | VG[1] - 27A, 59N,A . Trip   |

| Logical Node               | Data Object | Module ( - ANSI/IEEE Device Number ) . Name   |
|----------------------------|-------------|---|
| <b>VSPTUV2* (WW_PTUV1)</b> |             |   |
|                            | Mod         | VG[2] - 27A, 59N,A . active VG[2] - 27A, 59N,A . Blo TripCmd VG[2] - 27A, 59N,A . ExBlo TripCmd |
|                            | Beh         |   |
|                            | Health      |   |
|                            | NamPlt      |   |
|                            | Str         | VG[2] - 27A, 59N,A . Alarm  |
|                            | Op          | VG[2] - 27A, 59N,A . Trip   |

## 4.2 Device Planning Dependencies

The availability of Logical Node instances in the generated ICD file depends on the settings in the “Device planning” menu.

The following list gives an overview about those settings for every module that have an effect on the availability of a Logical Node.

| Module ( - ANSI/IEEE Device Number ) . Name | Value                    |
|---|--------------------------|
| <b>CILO1</b>                                |                          |
| SG[1] . SwitchgearType                      | Controlled SG            |
| SG[1] . SwitchgearType                      | Controlled Make Break SG |
| <b>CILO2</b>                                |                          |
| SG[2] . SwitchgearType                      | Controlled SG            |
| SG[2] . SwitchgearType                      | Controlled Make Break SG |
| <b>CILO3</b>                                |                          |
| SG[3] . SwitchgearType                      | Controlled SG            |
| SG[3] . SwitchgearType                      | Controlled Make Break SG |
| <b>CILO4</b>                                |                          |
| SG[4] . SwitchgearType                      | Controlled SG            |
| SG[4] . SwitchgearType                      | Controlled Make Break SG |
| <b>CILO5</b>                                |                          |
| SG[5] . SwitchgearType                      | Controlled SG            |
| SG[5] . SwitchgearType                      | Controlled Make Break SG |
| <b>CILO6</b>                                |                          |
| SG[6] . SwitchgearType                      | Controlled SG            |
| SG[6] . SwitchgearType                      | Controlled Make Break SG |
| <b>CSWI1</b>                                |                          |
| SG[1] . SwitchgearType                      | Controlled SG            |
| SG[1] . SwitchgearType                      | Controlled Make Break SG |
| <b>CSWI2</b>                                |                          |
| SG[2] . SwitchgearType                      | Controlled SG            |
| SG[2] . SwitchgearType                      | Controlled Make Break SG |
| <b>CSWI3</b>                                |                          |
| SG[3] . SwitchgearType                      | Controlled SG            |
| SG[3] . SwitchgearType                      | Controlled Make Break SG |
| <b>CSWI4</b>                                |                          |
| SG[4] . SwitchgearType                      | Controlled SG            |
| SG[4] . SwitchgearType                      | Controlled Make Break SG |
| <b>CSWI5</b>                                |                          |

| <b>Module ( - ANSI/IEEE Device Number ) . Name</b> | <b>Value</b>             |
|--|--------------------------|
| SG[5] . SwitchgearType                             | Controlled SG            |
| SG[5] . SwitchgearType                             | Controlled Make Break SG |
| <b>CSWI6</b>                                       |                          |
| SG[6] . SwitchgearType                             | Controlled SG            |
| SG[6] . SwitchgearType                             | Controlled Make Break SG |
| <b>XCBR1</b>                                       |                          |
| SG[1] . SwitchgearType                             | Monitored Make Break SG  |
| SG[1] . SwitchgearType                             | Controlled Make Break SG |
| <b>XCBR2</b>                                       |                          |
| SG[2] . SwitchgearType                             | Monitored Make Break SG  |
| SG[2] . SwitchgearType                             | Controlled Make Break SG |
| <b>XCBR3</b>                                       |                          |
| SG[3] . SwitchgearType                             | Monitored Make Break SG  |
| SG[3] . SwitchgearType                             | Controlled Make Break SG |
| <b>XCBR4</b>                                       |                          |
| SG[4] . SwitchgearType                             | Monitored Make Break SG  |
| SG[4] . SwitchgearType                             | Controlled Make Break SG |
| <b>XCBR5</b>                                       |                          |
| SG[5] . SwitchgearType                             | Monitored Make Break SG  |
| SG[5] . SwitchgearType                             | Controlled Make Break SG |
| <b>XCBR6</b>                                       |                          |
| SG[6] . SwitchgearType                             | Monitored Make Break SG  |
| SG[6] . SwitchgearType                             | Controlled Make Break SG |
| <b>XSWI1</b>                                       |                          |
| SG[1] . SwitchgearType                             | Monitored SG             |
| SG[1] . SwitchgearType                             | Controlled SG            |
| <b>XSWI2</b>                                       |                          |
| SG[2] . SwitchgearType                             | Monitored SG             |
| SG[2] . SwitchgearType                             | Controlled SG            |
| <b>XSWI3</b>                                       |                          |
| SG[3] . SwitchgearType                             | Monitored SG             |
| SG[3] . SwitchgearType                             | Controlled SG            |
| <b>XSWI4</b>                                       |                          |
| SG[4] . SwitchgearType                             | Monitored SG             |
| SG[4] . SwitchgearType                             | Controlled SG            |
| <b>XSWI5</b>                                       |                          |
| SG[5] . SwitchgearType                             | Monitored SG             |

| Module ( - ANSI/IEEE Device Number ) . Name | Value         |
|---|---------------|
| SG[5] . SwitchgearType                      | Controlled SG |
| <b>XSWI6</b>                                |               |
| SG[6] . SwitchgearType                      | Monitored SG  |
| SG[6] . SwitchgearType                      | Controlled SG |
| <b>OEVPVPH1</b>                             |               |
| V/f>[1] - 24 . Mode                         | use           |
| <b>OEVPVPH2</b>                             |               |
| V/f>[2] - 24 . Mode                         | use           |
| <b>PDOP1</b>                                |               |
| P - 32R . Mode                              | P>            |
| P - 32R . Mode                              | Pr>           |
| <b>PDOP2</b>                                |               |
| Q - 32 . Mode                               | Q>            |
| Q - 32 . Mode                               | Qr>           |
| <b>PDOP3</b>                                |               |
| PQS[1] - 32, 37 . Mode                      | P>            |
| PQS[1] - 32, 37 . Mode                      | Pr>           |
| PQS[1] - 32, 37 . Mode                      | Q>            |
| PQS[1] - 32, 37 . Mode                      | Qr>           |
| PQS[1] - 32, 37 . Mode                      | S>            |
| <b>PDOP4</b>                                |               |
| PQS[2] - 32, 37 . Mode                      | P>            |
| PQS[2] - 32, 37 . Mode                      | Pr>           |
| PQS[2] - 32, 37 . Mode                      | Q>            |
| PQS[2] - 32, 37 . Mode                      | Qr>           |
| PQS[2] - 32, 37 . Mode                      | S>            |
| <b>PDOP5</b>                                |               |
| PQS[3] - 32, 37 . Mode                      | P>            |
| PQS[3] - 32, 37 . Mode                      | Pr>           |
| PQS[3] - 32, 37 . Mode                      | Q>            |
| PQS[3] - 32, 37 . Mode                      | Qr>           |
| PQS[3] - 32, 37 . Mode                      | S>            |
| <b>PDOP6</b>                                |               |
| PQS[4] - 32, 37 . Mode                      | P>            |
| PQS[4] - 32, 37 . Mode                      | Pr>           |
| PQS[4] - 32, 37 . Mode                      | Q>            |
| PQS[4] - 32, 37 . Mode                      | Qr>           |

| Module ( - ANSI/IEEE Device Number ) . Name | Value |
|---|-------|
| PQS[4] - 32, 37 . Mode                      | S>    |
| <b>PDOP7</b>                                |       |
| PQS[5] - 32, 37 . Mode                      | P>    |
| PQS[5] - 32, 37 . Mode                      | Pr>   |
| PQS[5] - 32, 37 . Mode                      | Q>    |
| PQS[5] - 32, 37 . Mode                      | Qr>   |
| PQS[5] - 32, 37 . Mode                      | S>    |
| <b>PDOP8</b>                                |       |
| PQS[6] - 32, 37 . Mode                      | P>    |
| PQS[6] - 32, 37 . Mode                      | Pr>   |
| PQS[6] - 32, 37 . Mode                      | Q>    |
| PQS[6] - 32, 37 . Mode                      | Qr>   |
| PQS[6] - 32, 37 . Mode                      | S>    |
| <b>PDUP3</b>                                |       |
| PQS[1] - 32, 37 . Mode                      | P<    |
| PQS[1] - 32, 37 . Mode                      | Pr<   |
| PQS[1] - 32, 37 . Mode                      | Q<    |
| PQS[1] - 32, 37 . Mode                      | Qr<   |
| PQS[1] - 32, 37 . Mode                      | S<    |
| <b>PDUP4</b>                                |       |
| PQS[2] - 32, 37 . Mode                      | P<    |
| PQS[2] - 32, 37 . Mode                      | Pr<   |
| PQS[2] - 32, 37 . Mode                      | Q<    |
| PQS[2] - 32, 37 . Mode                      | Qr<   |
| PQS[2] - 32, 37 . Mode                      | S<    |
| <b>PDUP5</b>                                |       |
| PQS[3] - 32, 37 . Mode                      | P<    |
| PQS[3] - 32, 37 . Mode                      | Pr<   |
| PQS[3] - 32, 37 . Mode                      | Q<    |
| PQS[3] - 32, 37 . Mode                      | Qr<   |
| PQS[3] - 32, 37 . Mode                      | S<    |
| <b>PDUP6</b>                                |       |
| PQS[4] - 32, 37 . Mode                      | P<    |
| PQS[4] - 32, 37 . Mode                      | Pr<   |
| PQS[4] - 32, 37 . Mode                      | Q<    |
| PQS[4] - 32, 37 . Mode                      | Qr<   |
| PQS[4] - 32, 37 . Mode                      | S<    |

| Module ( - ANSI/IEEE Device Number ) . Name | Value        |
|---|--------------|
| <b>PDUP7</b>                                |              |
| PQS[5] - 32, 37 . Mode                      | P<           |
| PQS[5] - 32, 37 . Mode                      | Pr<          |
| PQS[5] - 32, 37 . Mode                      | Q<           |
| PQS[5] - 32, 37 . Mode                      | Qr<          |
| PQS[5] - 32, 37 . Mode                      | S<           |
| <b>PDUP8</b>                                |              |
| PQS[6] - 32, 37 . Mode                      | P<           |
| PQS[6] - 32, 37 . Mode                      | Pr<          |
| PQS[6] - 32, 37 . Mode                      | Q<           |
| PQS[6] - 32, 37 . Mode                      | Qr<          |
| PQS[6] - 32, 37 . Mode                      | S<           |
| <b>PFRC1</b>                                |              |
| df/dt - 81R . Mode                          | use          |
| <b>PFRC3</b>                                |              |
| f[1] - 81 . Mode                            | f< and df/dt |
| f[1] - 81 . Mode                            | f> and df/dt |
| f[1] - 81 . Mode                            | f< and DF/DT |
| f[1] - 81 . Mode                            | f> and DF/DT |
| f[1] - 81 . Mode                            | df/dt        |
| <b>PFRC4</b>                                |              |
| f[2] - 81 . Mode                            | f< and df/dt |
| f[2] - 81 . Mode                            | f> and df/dt |
| f[2] - 81 . Mode                            | f< and DF/DT |
| f[2] - 81 . Mode                            | f> and DF/DT |
| f[2] - 81 . Mode                            | df/dt        |
| <b>PFRC5</b>                                |              |
| f[3] - 81 . Mode                            | f< and df/dt |
| f[3] - 81 . Mode                            | f> and df/dt |
| f[3] - 81 . Mode                            | f< and DF/DT |
| f[3] - 81 . Mode                            | f> and DF/DT |
| f[3] - 81 . Mode                            | df/dt        |
| <b>PFRC6</b>                                |              |
| f[4] - 81 . Mode                            | f< and df/dt |
| f[4] - 81 . Mode                            | f> and df/dt |
| f[4] - 81 . Mode                            | f< and DF/DT |
| f[4] - 81 . Mode                            | f> and DF/DT |

| Module ( - ANSI/IEEE Device Number ) . Name | Value        |
|---|--------------|
| f[4] - 81 . Mode                            | df/dt        |
| <b>PFRC7</b>                                |              |
| f[5] - 81 . Mode                            | f< and df/dt |
| f[5] - 81 . Mode                            | f> and df/dt |
| f[5] - 81 . Mode                            | f< and DF/DT |
| f[5] - 81 . Mode                            | f> and DF/DT |
| f[5] - 81 . Mode                            | df/dt        |
| <b>PFRC8</b>                                |              |
| f[6] - 81 . Mode                            | f< and df/dt |
| f[6] - 81 . Mode                            | f> and df/dt |
| f[6] - 81 . Mode                            | f< and DF/DT |
| f[6] - 81 . Mode                            | f> and DF/DT |
| f[6] - 81 . Mode                            | df/dt        |
| <b>PPAM2</b>                                |              |
| delta phi - 78V . Mode                      | use          |
| <b>PPAM3</b>                                |              |
| f[1] - 81 . Mode                            | delta phi    |
| <b>PPAM4</b>                                |              |
| f[2] - 81 . Mode                            | delta phi    |
| <b>PPAM5</b>                                |              |
| f[3] - 81 . Mode                            | delta phi    |
| <b>PPAM6</b>                                |              |
| f[4] - 81 . Mode                            | delta phi    |
| <b>PPAM7</b>                                |              |
| f[5] - 81 . Mode                            | delta phi    |
| <b>PPAM8</b>                                |              |
| f[6] - 81 . Mode                            | delta phi    |
| <b>PTOF3</b>                                |              |
| f[1] - 81 . Mode                            | f>           |
| <b>PTOF4</b>                                |              |
| f[2] - 81 . Mode                            | f>           |
| <b>PTOF5</b>                                |              |
| f[3] - 81 . Mode                            | f>           |
| <b>PTOF6</b>                                |              |
| f[4] - 81 . Mode                            | f>           |
| <b>PTOF7</b>                                |              |
| f[5] - 81 . Mode                            | f>           |



| Module ( - ANSI/IEEE Device Number ) . Name | Value |
|---|-------|
| <b>PTOF8</b>                                |       |
| f[6] - 81 . Mode                            | f>    |
| <b>PTOV1</b>                                |       |
| V[1] - 27, 59 . Mode                        | V>    |
| <b>PTOV2</b>                                |       |
| V[2] - 27, 59 . Mode                        | V>    |
| <b>PTOV3</b>                                |       |
| V[3] - 27, 59 . Mode                        | V>    |
| <b>PTOV4</b>                                |       |
| V[4] - 27, 59 . Mode                        | V>    |
| <b>PTOV5</b>                                |       |
| V[5] - 27, 59 . Mode                        | V>    |
| <b>PTOV6</b>                                |       |
| V[6] - 27, 59 . Mode                        | V>    |
| <b>PTUF3</b>                                |       |
| f[1] - 81 . Mode                            | f<    |
| <b>PTUF4</b>                                |       |
| f[2] - 81 . Mode                            | f<    |
| <b>PTUF5</b>                                |       |
| f[3] - 81 . Mode                            | f<    |
| <b>PTUF6</b>                                |       |
| f[4] - 81 . Mode                            | f<    |
| <b>PTUF7</b>                                |       |
| f[5] - 81 . Mode                            | f<    |
| <b>PTUF8</b>                                |       |
| f[6] - 81 . Mode                            | f<    |
| <b>PTUV1</b>                                |       |
| V[1] - 27, 59 . Mode                        | V<    |
| <b>PTUV2</b>                                |       |
| V[2] - 27, 59 . Mode                        | V<    |
| <b>PTUV3</b>                                |       |
| V[3] - 27, 59 . Mode                        | V<    |
| <b>PTUV4</b>                                |       |
| V[4] - 27, 59 . Mode                        | V<    |
| <b>PTUV5</b>                                |       |
| V[5] - 27, 59 . Mode                        | V<    |
| <b>PTUV6</b>                                |       |

| Module ( - ANSI/IEEE Device Number ) . Name | Value |
|---|-------|
| V[6] - 27, 59 . Mode                        | V<    |
| <b>VAPTOV1</b>                              |       |
| V012[1] - 47 . Mode                         | V1>   |
| V012[1] - 47 . Mode                         | V2>   |
| <b>VAPTOV2</b>                              |       |
| V012[2] - 47 . Mode                         | V1>   |
| V012[2] - 47 . Mode                         | V2>   |
| <b>VAPTOV3</b>                              |       |
| V012[3] - 47 . Mode                         | V1>   |
| V012[3] - 47 . Mode                         | V2>   |
| <b>VAPTOV4</b>                              |       |
| V012[4] - 47 . Mode                         | V1>   |
| V012[4] - 47 . Mode                         | V2>   |
| <b>VAPTOV5</b>                              |       |
| V012[5] - 47 . Mode                         | V1>   |
| V012[5] - 47 . Mode                         | V2>   |
| <b>VAPTOV6</b>                              |       |
| V012[6] - 47 . Mode                         | V1>   |
| V012[6] - 47 . Mode                         | V2>   |
| <b>VAPTUV1</b>                              |       |
| V012[1] - 47 . Mode                         | V1<   |
| <b>VAPTUV2</b>                              |       |
| V012[2] - 47 . Mode                         | V1<   |
| <b>VAPTUV3</b>                              |       |
| V012[3] - 47 . Mode                         | V1<   |
| <b>VAPTUV4</b>                              |       |
| V012[4] - 47 . Mode                         | V1<   |
| <b>VAPTUV5</b>                              |       |
| V012[5] - 47 . Mode                         | V1<   |
| <b>VAPTUV6</b>                              |       |
| V012[6] - 47 . Mode                         | V1<   |
| <b>VSPTOV1</b>                              |       |
| VG[1] - 27A, 59N,A . Mode                   | V>    |
| <b>VSPTOV2</b>                              |       |
| VG[2] - 27A, 59N,A . Mode                   | V>    |
| <b>VSPTUV1</b>                              |       |
| VG[1] - 27A, 59N,A . Mode                   | V<    |

| Module (- ANSI/IEEE Device Number ) .<br>Name | Value |
|---|-------|
| <b>VSPTUV2</b>                                |       |
| VG[2] - 27A, 59N,A . Mode                     | V<    |

**We appreciate your comments about the content of our publications.**

**Send comments to: [kemp.doc@woodward.com](mailto:kemp.doc@woodward.com)**

**Please reference publication MCDTV4-3.7-EN-IEC61850-MICS**

---

**[https://wss.woodward.com/manuals/Library/Protection\\_Relays/HighPROTEC](https://wss.woodward.com/manuals/Library/Protection_Relays/HighPROTEC)**



Woodward Kempen GmbH reserves the right to update any portion of this publication at any time. Information provided by Woodward Kempen GmbH is believed to be correct and reliable. However, Woodward Kempen GmbH assumes no responsibility unless otherwise expressly undertaken.



Woodward Kempen GmbH  
Krefelder Weg 47 • D-47906 Kempen (Germany)  
Postfach 10 07 55 (P.O.Box) • D-47884 Kempen (Germany)  
Telephone: : +49 (0) 21 52 145 1

**Internet: — [www.woodward.com](http://www.woodward.com)**

**Sales**

Telephone: : +49 (0) 21 52 145 331  
Fax: : +49 (0) 21 52 145 354  
Email: : [SalesPGD\\_EMEA@woodward.com](mailto:SalesPGD_EMEA@woodward.com)

**Service**

Telephone: : +49 (0) 21 52 145 614  
Fax: : +49 (0) 21 52 145 354  
Email: : [industrial.support@woodward.com](mailto:industrial.support@woodward.com)

Woodward has company-owned plants, subsidiaries, and branches, as well as authorized distributors and other authorized service and sales facilities throughout the world.

Complete address / phone / fax / email information for all locations is available on our website.