

IEC 61850 – MICS

High PROTEC | PROTECTION TECHNOLOGY
MADE SIMPLE

MRMV4 |

Model Implementation Conformance Statement (MICS)

UCA International Users Group Testing Sub Committee

Version: 3.7

Original document

English

Original reference manual

SEG Electronics GmbH

Krefelder Weg 47 • D-47906 Kempen (Germany)

Postfach 10 07 55 (P.O.Box) • D-47884 Kempen (Germany)

Telephone: +49 (0) 21 52 145 1

Internet: www.SEGelectronics.de

Sales

Telephone: +49 (0) 21 52 145 331

Fax: +49 (0) 21 52 145 354

E-mail: SalesPGD_EMEA@SEGelectronics.de

Service

Telephone: +49 (0) 21 52 145 614

Fax: +49 (0) 21 52 145 354

E-mail: industrial.support@SEGelectronics.de

© 2020 SEG Electronics GmbH. All rights reserved.

Table of Contents

1	Introduction	7
2	Logical Nodes	8
2.1	Logical Nodes List	8
2.2	Logical Node Definitions	10
2.3	WW_CILO1	12
2.4	WW_CSWI1	12
2.5	WW_GAPC1	12
2.6	WW_GGIO4	13
2.7	WW_GGIO10	14
2.8	WW_GGIO11	15
2.9	WW_GGIO14	17
2.10	WW_IHMI1	18
2.11	WW_LLN0CON	18
2.12	WW_LLN0MEA	19
2.13	WW_LLN0PRO	19
2.14	WW_LLN0REC	20
2.15	WW_LLN0SYS	20
2.16	WW_LPHDCON	20
2.17	WW_LPHDMEA	21
2.18	WW_LPHDPRO	21
2.19	WW_LPHDREC	21
2.20	WW_LPHDSYS	22
2.21	WW_MMTR1	22
2.22	WW_MMXU3	22
2.23	WW_MMXU6	23
2.24	WW_MMXU7	23
2.25	WW_MSTA1	24
2.26	WW_MSTA2	25
2.27	WW_MSTA3	25
2.28	WW_PDOP1	26

Table of Contents

2.29	WW_PDUP1	27
2.30	WW_PFRC1	27
2.31	WW_PIOC1	27
2.32	WW_PMRI1	28
2.33	WW_PMSS1	28
2.34	WW_PPAM1	29
2.35	WW_PTOC1	29
2.36	WW_PTOC3	30
2.37	WW_PTOC4	30
2.38	WW_PTOF1	31
2.39	WW_PTOV1	31
2.40	WW_PTOV2	31
2.41	WW_PTOV3	32
2.42	WW_PTTR2	32
2.43	WW_PTTR4	33
2.44	WW_PTUC1	33
2.45	WW_PTUF1	34
2.46	WW_PTUV1	34
2.47	WW_PTUV2	35
2.48	WW_PTUV3	35
2.49	WW_PUPF1	35
2.50	WW_RBRF1	36
2.51	WW_RDRE1	36
2.52	WW_SCBR1	37
2.53	WW_XCBR2	37
2.54	WW_XSWI1	38
3	Common Data Class	39
3.1	Common Data Class Definitions	39
3.1.1	WW_ACD1	40
3.1.2	WW_ACT1	40
3.1.3	WW_BCR1	40
3.1.4	WW_CMV2	40

3.1.5	WW_DEL2	41
3.1.6	WW_DPC1	41
3.1.7	WW_DPC2	41
3.1.8	WW_DPL1	42
3.1.9	WW_INC1	42
3.1.10	WW_INS1	42
3.1.11	WW_INS2	43
3.1.12	WW_INS3	43
3.1.13	WW_INS5	43
3.1.14	WW_INS6	43
3.1.15	WW_LPL1	44
3.1.16	WW_LPL2	44
3.1.17	WW_MV1	44
3.1.18	WW_SPC1	44
3.1.19	WW_SPC2	45
3.1.20	WW_SPS1	45
3.1.21	WW_WYE2	45
3.2	Common Data Attributes Type Definitions	46
3.2.1	WW_analogValue1	46
3.2.2	WW_Cancel1	46
3.2.3	WW_Oper1	46
3.2.4	WW_origin1	46
3.2.5	WW_units1	47
3.2.6	WW_vector1	47
3.3	Enumerated type definitions	48
3.3.1	AutoRecSt	48
3.3.2	Beh	48
3.3.3	CBOpCap	48
3.3.4	ctlModel	48
3.3.5	Dbpos	49
3.3.6	ACDdir	49
3.3.7	Health	49

Table of Contents

3.3.8	Mod	49
3.3.9	MotorCycle	50
3.3.10	multiplier	50
3.3.11	orCategory	51
3.3.12	sboClass	51
3.3.13	SIUnit	51
4	Appendix	54
4.1	Register Maps	54
4.2	Device Planning Dependencies	89

1 Introduction

This model implementation conformance statement is applicable to the MRMV4 version 3.7.

This MICS document specifies the modelling extensions compared to IEC 61850 edition 1.

Clause 2 contains the list of implemented logical nodes.

Clause 3 describes the new and extended logical nodes.

Clause 4 describes the existing common data classes.

Clause 5 describes the existing enum types.

2 Logical Nodes

2.1 Logical Nodes List

The following table contains the list of logical nodes implemented in the device:

L: System Logical Nodes

LLNO (Logical Node device)

LPHD (Physical device)

P: Logical Nodes for protection functions

PDOP (Directional overpower)

PDUP (Directional underpower)

PFRC (Rate of change of frequency)

PIOC (Instantaneous overcurrent)

PMRI (Motor restart inhibition)

PMSS (Motor starting time supervision)

PPAM (Phase angle or out-of-step protection)

PTOC (Time overcurrent)

PTOF (Overfrequency)

PTOV (Overvoltage)

PTTR (Thermal overload protection)

PTUC (Undercurrent)

PTUF (Underfrequency)

PTUV (Undervoltage)

PUPF (Underpower factor)

R: Logical Nodes for protection related functions

RBRF (Breaker failure)

RDRE (Disturbance recorder function)

G: Logical Nodes for generic references

GAPC (Generic automatic process control)

GGIO (Generic process I/O)

M: Logical Nodes for metering and measurement

MMTR (Metering)

MMXU (Measurement)

MSTA (Metering Statistics)

X: Logical Nodes for switchgear

XCBR (Circuit Breaker)

XSWI (Circuit Switch)

C: Logical Nodes for control

CILO (Interlocking)

CSWI (Switch controller)

I: Logical Nodes for interfacing and archiving

IHMI (Human machine interface)

S: Logical Nodes for sensors and monitoring

SCBR (Circuit breaker monitoring)

2.2 Logical Node Definitions

Abbreviations used in the following table:

- **M**: Data is mandatory in the IEC 61850-7-4.
- **O**: Data is optional in the IEC 61850-7-4 and is used in the device.
- **E**: Data is an extension to the IEC 61850-7-4.

LN Type	LN Class	Description
WW_CILO1	CILO	Interlocking
WW_CSWI1	CSWI	Switch controller
WW_GAPC1	GAPC	Generic automatic process control
WW_GGIO10	GGIO	Generic process I/O
WW_GGIO11	GGIO	Generic process I/O
WW_GGIO14	GGIO	Generic process I/O
WW_GGIO4	GGIO	Generic process I/O
WW_IHMI1	IHMI	Human machine interface
WW_LLNOCON	LLNO	Logical Node device
WW_LLNAMEA	LLNO	Logical Node device
WW_LLNOPRO	LLNO	Logical Node device
WW_LLNOREC	LLNO	Logical Node device
WW_LLNO SYS	LLNO	Logical Node device
WW_LPHDCON	LPHD	Physical device
WW_LPHDMEA	LPHD	Physical device
WW_LPHDPRO	LPHD	Physical device
WW_LPHDREC	LPHD	Physical device
WW_LPHDSYS	LPHD	Physical device
WW_MMTR1	MMTR	Metering
WW_MMXU3	MMXU	Measurement
WW_MMXU6	MMXU	Measurement
WW_MMXU7	MMXU	Measurement
WW_MSTA1	MSTA	Metering Statistics
WW_MSTA2	MSTA	Metering Statistics
WW_MSTA3	MSTA	Metering Statistics
WW_PDOP1	PDOP	Directional overpower
WW_PDUP1	PDUP	Directional underpower
WW_PFRC1	PFRC	Rate of change of frequency
WW_PIOC1	PIOC	Instantaneous overcurrent
WW_PMRI1	PMRI	Motor restart inhibition
WW_PMSS1	PMSS	Motor starting time supervision

LN Type	LN Class	Description
WW_PPAM1	PPAM	Phase angle or out-of-step protection
WW_PTOC1	PTOC	Time overcurrent
WW_PTOC3	PTOC	Time overcurrent
WW_PTOC4	PTOC	Time overcurrent
WW_PTOF1	PTOF	Overfrequency
WW_PTOV1	PTOV	Overtension
WW_PTOV2	PTOV	Overtension
WW_PTOV3	PTOV	Overtension
WW_PTTR2	PTTR	Thermal overload protection
WW_PTTR4	PTTR	Thermal overload protection
WW_PTUC1	PTUC	Undercurrent
WW_PTUF1	PTUF	Underfrequency
WW_PTUV1	PTUV	Undervoltage
WW_PTUV2	PTUV	Undervoltage
WW_PTUV3	PTUV	Undervoltage
WW_PUPF1	PUPF	Underpower factor
WW_RBPF1	RBRF	Breaker failure
WW_RDRE1	RDRE	Disturbance recorder function
WW_SCBR1	SCBR	Circuit breaker monitoring
WW_XCBR2	XCBR	Circuit Breaker
WW_XSWI1	XSWI	Circuit Switch

2.3 WW_CILO1

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
CILO class				
CILO	WW_CILO1	Interlocking		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behavior	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
EnaOpn	WW_SPS1	Enable Open	M	
EnaCls	WW_SPS1	Enable Close	M	

2.4 WW_CSWI1

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
CSWI class				
CSWI	WW_CSWI1	Switch Controller		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
Loc	WW_SPS1	Local operation	O	
<i>Controls</i>				
Pos	WW_DPC2	Switch position	M	

2.5 WW_GAPC1

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
GAPC class				
GAPC	WW_GAPC1	Generic automatic process control		

Attribute	Attribute	Explanation	M/O/E	Remarks			
Name	Type						
Data							
<i>Common Logical Node Information</i>							
Mod	WW_INC1	Mode	M	Status-only			
Beh	WW_INS1	Behaviour	M				
Health	WW_INS3	Health	M				
NamPlt	WW_LPL1	Name plate	M				
Loc	WW_SPS1	Local operation	O				
<i>Status Information</i>							
Str	WW_ACD1	Start	M				
Op	WW_ACT1	Operate	M				

2.6 WW_GGIO4

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
GGIO class				
GGIO	WW_GGIO4	Generic process I/O		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Ind1	WW_SPS1	General indication (binary input)	O	
Ind2	WW_SPS1	General indication (binary input)	O	
Ind3	WW_SPS1	General indication (binary input)	O	
Ind4	WW_SPS1	General indication (binary input)	O	
Ind5	WW_SPS1	General indication (binary input)	O	
Ind6	WW_SPS1	General indication (binary input)	O	
Ind7	WW_SPS1	General indication (binary input)	O	
Ind8	WW_SPS1	General indication (binary input)	O	
Ind9	WW_SPS1	General indication (binary input)	O	
Ind10	WW_SPS1	General indication (binary input)	O	
Ind11	WW_SPS1	General indication (binary input)	O	
Ind12	WW_SPS1	General indication (binary input)	O	

2 Logical Nodes

2.7 WW_GGIO10

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
Ind13	WW_SPS1	General indication (binary input)	O	
Ind14	WW_SPS1	General indication (binary input)	O	
Ind15	WW_SPS1	General indication (binary input)	O	
Ind16	WW_SPS1	General indication (binary input)	O	
Ind17	WW_SPS1	General indication (binary input)	O	
Ind18	WW_SPS1	General indication (binary input)	O	
Ind19	WW_SPS1	General indication (binary input)	O	
Ind20	WW_SPS1	General indication (binary input)	O	
Ind21	WW_SPS1	General indication (binary input)	O	
Ind22	WW_SPS1	General indication (binary input)	O	
Ind23	WW_SPS1	General indication (binary input)	O	
Ind24	WW_SPS1	General indication (binary input)	O	
Ind25	WW_SPS1	General indication (binary input)	O	
Ind26	WW_SPS1	General indication (binary input)	O	
Ind27	WW_SPS1	General indication (binary input)	O	
Ind28	WW_SPS1	General indication (binary input)	O	
Ind29	WW_SPS1	General indication (binary input)	O	
Ind30	WW_SPS1	General indication (binary input)	O	
Ind31	WW_SPS1	General indication (binary input)	O	
Ind32	WW_SPS1	General indication (binary input)	O	

2.7 WW_GGIO10

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
GGIO class				
GGIO	WW_GGI10	Generic process I/O		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Ind1	WW_SPS1	General indication (binary input)	O	
Ind2	WW_SPS1	General indication (binary input)	O	

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
Ind3	WW_SPS1	General indication (binary input)	O	
Ind4	WW_SPS1	General indication (binary input)	O	
Ind5	WW_SPS1	General indication (binary input)	O	
Ind6	WW_SPS1	General indication (binary input)	O	
Ind7	WW_SPS1	General indication (binary input)	O	
Ind8	WW_SPS1	General indication (binary input)	O	
Ind9	WW_SPS1	General indication (binary input)	O	
Ind10	WW_SPS1	General indication (binary input)	O	
Ind11	WW_SPS1	General indication (binary input)	O	
Ind12	WW_SPS1	General indication (binary input)	O	
Ind13	WW_SPS1	General indication (binary input)	O	
Ind14	WW_SPS1	General indication (binary input)	O	
Ind15	WW_SPS1	General indication (binary input)	O	
Ind16	WW_SPS1	General indication (binary input)	O	
Ind17	WW_SPS1	General indication (binary input)	O	
Ind18	WW_SPS1	General indication (binary input)	O	
Ind19	WW_SPS1	General indication (binary input)	O	
Ind20	WW_SPS1	General indication (binary input)	O	
Ind21	WW_SPS1	General indication (binary input)	O	
Ind22	WW_SPS1	General indication (binary input)	O	
Ind23	WW_SPS1	General indication (binary input)	O	
Ind24	WW_SPS1	General indication (binary input)	O	
Ind25	WW_SPS1	General indication (binary input)	O	
Ind26	WW_SPS1	General indication (binary input)	O	
Ind27	WW_SPS1	General indication (binary input)	O	
Ind28	WW_SPS1	General indication (binary input)	O	
Ind29	WW_SPS1	General indication (binary input)	O	
Ind30	WW_SPS1	General indication (binary input)	O	
Ind31	WW_SPS1	General indication (binary input)	O	
Ind32	WW_SPS1	General indication (binary input)	O	

2.8 WW_GGIO11

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
GGIO class				

2 Logical Nodes

2.8 WW_GGIO11

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
GGIO	WW_GGI11	Generic process I/O		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Ind1	WW_SPS1	General indication (binary input)	O	
Ind2	WW_SPS1	General indication (binary input)	O	
Ind3	WW_SPS1	General indication (binary input)	O	
Ind4	WW_SPS1	General indication (binary input)	O	
Ind5	WW_SPS1	General indication (binary input)	O	
Ind6	WW_SPS1	General indication (binary input)	O	
Ind7	WW_SPS1	General indication (binary input)	O	
Ind8	WW_SPS1	General indication (binary input)	O	
Ind9	WW_SPS1	General indication (binary input)	O	
Ind10	WW_SPS1	General indication (binary input)	O	
Ind11	WW_SPS1	General indication (binary input)	O	
Ind12	WW_SPS1	General indication (binary input)	O	
Ind13	WW_SPS1	General indication (binary input)	O	
Ind14	WW_SPS1	General indication (binary input)	O	
Ind15	WW_SPS1	General indication (binary input)	O	
Ind16	WW_SPS1	General indication (binary input)	O	
Ind17	WW_SPS1	General indication (binary input)	O	
Ind18	WW_SPS1	General indication (binary input)	O	
Ind19	WW_SPS1	General indication (binary input)	O	
Ind20	WW_SPS1	General indication (binary input)	O	
Ind21	WW_SPS1	General indication (binary input)	O	
Ind22	WW_SPS1	General indication (binary input)	O	
Ind23	WW_SPS1	General indication (binary input)	O	
Ind24	WW_SPS1	General indication (binary input)	O	
Ind25	WW_SPS1	General indication (binary input)	O	
Ind26	WW_SPS1	General indication (binary input)	O	
Ind27	WW_SPS1	General indication (binary input)	O	
Ind28	WW_SPS1	General indication (binary input)	O	

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
Ind29	WW_SPS1	General indication (binary input)	O	
Ind30	WW_SPS1	General indication (binary input)	O	
Ind31	WW_SPS1	General indication (binary input)	O	
Ind32	WW_SPS1	General indication (binary input)	O	

2.9 WW_GGIO14

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
GGIO class				
GGIO	WW_GGI14	Generic process I/O		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
SPCSO1	WW_SPC2	Single point controllable status output	O	
SPCSO2	WW_SPC2	Single point controllable status output	O	
SPCSO3	WW_SPC2	Single point controllable status output	O	
SPCSO4	WW_SPC2	Single point controllable status output	O	
SPCSO5	WW_SPC2	Single point controllable status output	O	
SPCSO6	WW_SPC2	Single point controllable status output	O	
SPCSO7	WW_SPC2	Single point controllable status output	O	
SPCSO8	WW_SPC2	Single point controllable status output	O	
SPCSO9	WW_SPC2	Single point controllable status output	O	
SPCSO10	WW_SPC2	Single point controllable status output	O	
SPCSO11	WW_SPC2	Single point controllable status output	O	
SPCSO12	WW_SPC2	Single point controllable status output	O	
SPCSO13	WW_SPC2	Single point controllable status output	O	
SPCSO14	WW_SPC2	Single point controllable status output	O	
SPCSO15	WW_SPC2	Single point controllable status output	O	
SPCSO16	WW_SPC2	Single point controllable status output	O	
SPCSO17	WW_SPC2	Single point controllable status output	O	
SPCSO18	WW_SPC2	Single point controllable status output	O	

2 Logical Nodes

2.10 WW_IHMI1

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
SPCSO19	WW_SPC2	Single point controllable status output	O	
SPCSO20	WW_SPC2	Single point controllable status output	O	
SPCSO21	WW_SPC2	Single point controllable status output	O	
SPCSO22	WW_SPC2	Single point controllable status output	O	
SPCSO23	WW_SPC2	Single point controllable status output	O	
SPCSO24	WW_SPC2	Single point controllable status output	O	
SPCSO25	WW_SPC2	Single point controllable status output	O	
SPCSO26	WW_SPC2	Single point controllable status output	O	
SPCSO27	WW_SPC2	Single point controllable status output	O	
SPCSO28	WW_SPC2	Single point controllable status output	O	
SPCSO29	WW_SPC2	Single point controllable status output	O	
SPCSO30	WW_SPC2	Single point controllable status output	O	
SPCSO31	WW_SPC2	Single point controllable status output	O	
SPCSO32	WW_SPC2	Single point controllable status output	O	

2.10 WW_IHMI1

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
IHMI class				
IHMI	WW_IHMI1	Human machine interface		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	

2.11 WW_LLNOCON

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
LLNO class				
LLNO	WW_LLNOCON	Logical Node device		
Data				
<i>Common Logical Node Information</i>				

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL2	Name plate	M	

2.12 WW_LLN0MEA

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
LLN0 class				
LLN0	WW_LLN0MEA	Logical Node device		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL2	Name plate	M	

2.13 WW_LLN0PRO

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
LLN0 class				
LLN0	WW_LLN0PRO	Logical Node device		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL2	Name plate	M	

2.14 WW_LLN0REC

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
LLN0 class				
LLN0	WW_LLN0REC	Logical Node device		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL2	Name plate	M	

2.15 WW_LLN0SYS

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
LLN0 class				
LLN0	WW_LLN0SYS	Logical Node device		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL2	Name plate	M	

2.16 WW_LPHDCON

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
LPHD class				
LPHD	WW_LPHDCON	Physical device information		
Data				
<i>Common Logical Node Information</i>				
PhyNam	WW_DPL1	Physical device name plate	M	
PhyHealth	WW_INS3	Physical Device Health	M	
Proxy	WW_SPS1	Indicates if this LN is a proxy	M	

2.17 WW_LPHDMEA

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
LPHD class				
LPHD	WW_LPHDMEA	Physical device information		
Data				
<i>Common Logical Node Information</i>				
PhyNam	WW_DPL1	Physical device name plate	M	
PhyHealth	WW_INS3	Physical Device Health	M	
Proxy	WW_SPS1	Indicates if this LN is a proxy	M	

2.18 WW_LPHDPRO

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
LPHD class				
LPHD	WW_LPHDPRO	Physical device information		
Data				
<i>Common Logical Node Information</i>				
PhyNam	WW_DPL1	Physical device name plate	M	
PhyHealth	WW_INS3	Physical Device Health	M	
Proxy	WW_SPS1	Indicates if this LN is a proxy	M	

2.19 WW_LPHDREC

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
LPHD class				
LPHD	WW_LPHDREC	Physical device information		
Data				
<i>Common Logical Node Information</i>				
PhyNam	WW_DPL1	Physical device name plate	M	
PhyHealth	WW_INS3	Physical Device Health	M	
Proxy	WW_SPS1	Indicates if this LN is a proxy	M	

2.20 WW_LPHDSYS

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
LPHD class				
LPHD	WW_LPHDSYS	Physical device information		
Data				
<i>Common Logical Node Information</i>				
PhyNam	WW_DPL1	Physical device name plate	M	
PhyHealth	WW_INS3	Physical Device Health	M	
Proxy	WW_SPS1	Indicates if this LN is a proxy	M	

2.21 WW_MMTR1

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
MSTA class				
MMTR1	WW_MMTR1	Metering		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Metered values</i>				
TotVAh	WW_BCR1	Absolute Apparent Power Hours	O	
TotWh	WW_BCR1	Absolute Active Power Hours	O	
TotVArh	WW_BCR1	Absolute Reactive Power Hours	O	
SupWh	WW_BCR1	Consumed Active Energy	O	
SupVArh	WW_BCR1	Consumed Reactive Energy	O	
DmdWh	WW_BCR1	Fed Active Energy	O	
DmdVArh	WW_BCR1	Fed Reactive Energy	O	

2.22 WW_MMXU3

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
MMXU class				

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
MMXU	WW_MMXU3	Measurement		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Measured values</i>				
TotW	WW_MV1	Total Active Power (Total P)	O	
TotVAr	WW_MV1	Total Reactive Power (Total Q)	O	
TotVA	WW_MV1	Total Apparent Power (Total S)	O	
TotPF	WW_MV1	Total Power factor (Total PF)	O	

2.23 WW_MMXU6

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
MMXU class				
MMXU	WW_MMXU6	Measurement		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Measured values</i>				
PPV	WW_DEL2	Phase to phase voltages (VL12, VL23, VL31)	O	
PhV	WW_WYE2	Phase to ground voltages (VL1, VL2, VL3)	O	
Hz	WW_MV1	Frequency	O	

2.24 WW_MMXU7

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
MMXU class				
<i>Common Logical Node Information</i>				
MMXU	WW_MMXU7	Measurement		

2 Logical Nodes

2.25 WW_MSTA1

Attribute	Attribute	Explanation	M/O/E	Remarks			
Name	Type						
Data							
<i>Common Logical Node Information</i>							
Mod	WW_INC1	Mode	M	Status-only			
Beh	WW_INS1	Behaviour	M				
Health	WW_INS3	Health	M				
NamPlt	WW_LPL1	Name plate	M				
<i>Measured values</i>							
A	WW_WYE2	Phase currents (IL1, IL2, IL3)	O				

2.25 WW_MSTA1

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
MSTA class				
MSTA	WW_MSTA1	Metering Statistics		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Metered values</i>				
AvAPhA	WW_MV1	Average current IL1	E	
AvAPhB	WW_MV1	Average current IL2	E	
AvAPhC	WW_MV1	Average current IL3	E	
MaxAPhA	WW_MV1	Maximum current IL1	E	
MaxAPhB	WW_MV1	Maximum current IL2	E	
MaxAPhC	WW_MV1	Maximum current IL3	E	
MinAPhA	WW_MV1	Minimum current IL1	E	
MinAPhB	WW_MV1	Minimum current IL2	E	
MinAPhC	WW_MV1	Minimum current IL3	E	

2.26 WW_MSTA2

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
MSTA class				
MSTA	WW_MSTA2	Metering Statistics		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Metered values</i>				
AvVPhAB	WW_MV1	Average voltage VL12	E	
AvVPhBC	WW_MV1	Average voltage VL23	E	
AvVPhCA	WW_MV1	Average voltage VL31	E	
MaxVPhAB	WW_MV1	Maximum voltage VL12	E	
MaxVPhBC	WW_MV1	Maximum voltage VL23	E	
MaxVPhCA	WW_MV1	Maximum voltage VL31	E	
MinVPhAB	WW_MV1	Minimum voltage VL12	E	
MinVPhBC	WW_MV1	Minimum voltage VL23	E	
MinVPhCA	WW_MV1	Minimum voltage VL31	E	
AvVPhA	WW_MV1	Average voltage VL1	E	
AvVPhB	WW_MV1	Average voltage VL2	E	
AvVPhC	WW_MV1	Average voltage VL3	E	
MaxVPhA	WW_MV1	Maximum voltage VL1	E	
MaxVPhB	WW_MV1	Maximum voltage VL2	E	
MaxVPhC	WW_MV1	Maximum voltage VL3	E	
MinVPhA	WW_MV1	Minimum voltage VL1	E	
MinVPhB	WW_MV1	Minimum voltage VL2	E	
MinVPhB	WW_MV1	Minimum voltage VL3	E	

2.27 WW_MSTA3

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
MSTA class				
MSTA	WW_MSTA3	Metering Statistics		

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Metered values</i>				
AvVA	WW_MV1	Average apparent power	O	
MaxVA	WW_MV1	Maximum apparent power	O	
MinVA	WW_MV1	Minimum apparent power	O	
Avw	WW_MV1	Average real power	O	
MaxW	WW_MV1	Maximum real power	O	
MinW	WW_MV1	Minimum real power	O	
AvVAr	WW_MV1	Average reactive power	O	
MaxVAr	WW_MV1	Maximum reactive power	O	
MinVAr	WW_MV1	Minimum reactive power	O	

2.28 WW_PDOP1

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
PDOP class				
PDOP	WW_PDOP1	Directional overpower		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

2.29 WW_PDUP1

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
PDUP class				
PDUP	WW_PDUP1	Directional underpower		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

2.30 WW_PFRC1

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
PFRC class				
PFRC	WW_PFRC1	Rate of change of frequency		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

2.31 WW_PIOC1

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
PIOC class				
PIOC	WW_PIOC1	Instantaneous overcurrent		

2 Logical Nodes

2.32 WW_PMRI1

Attribute	Attribute	Explanation	M/O/E	Remarks			
Name	Type						
Data							
<i>Common Logical Node Information</i>							
Mod	WW_INC1	Mode	M	Status-only			
Beh	WW_INS1	Behaviour	M				
Health	WW_INS3	Health	M				
NamPlt	WW_LPL1	Name plate	M				
<i>Status Information</i>							
Str	WW_ACD1	Start	M				
Op	WW_ACT1	Operate	M				

2.32 WW_PMRI1

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
PMRI class				
PMRI	WW_PMRI1	Motor restart inhibition		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Op	WW_ACT1	Operate	O	

2.33 WW_PMSS1

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
PMSS class				
PMSS	WW_PMSS1	Motor starting time supervision		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Op	WW_ACT1	Operate	O	
MotCyc	WW_INS6	Motor Cycle	E	

2.34 WW_PPAM1

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
PPAM class				
PPAM	WW_PPAM1	Phase angle measuring		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

2.35 WW_PTOC1

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
PTOC class				
PTOC	WW_PTOC1	Time overcurrent		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
Op	WW_ACT1	Operate	M	

2.36 WW_PTOC3

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
PTOC class				
PTOC	WW_PTOC3	Time overcurrent		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

2.37 WW_PTOC4

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
PTOC class				
PTOC	WW_PTOC4	Time overcurrent		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

2.38 WW_PTOF1

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
PTOF class				
PTOF	WW_PTOF1	Overfrequency		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

2.39 WW_PTOV1

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
PTOV class				
PTOV	WW_PTOV1	Overvoltage		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

2.40 WW_PTOV2

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
PTOV class				
PTOV	WW_PTOV2	Overvoltage		

2 Logical Nodes

2.41 WW_PTOV3

Attribute	Attribute	Explanation	M/O/E	Remarks			
Name	Type						
Data							
<i>Common Logical Node Information</i>							
Mod	WW_INC1	Mode	M	Status-only			
Beh	WW_INS1	Behaviour	M				
Health	WW_INS3	Health	M				
NamPlt	WW_LPL1	Name plate	M				
<i>Status Information</i>							
Str	WW_ACD1	Start	M				
Op	WW_ACT1	Operate	M				

2.41 WW_PTOV3

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
PTOV class				
PTOV	WW_PTOV3	Overvoltage		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

2.42 WW_PTTR2

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
PTTR class				
PTTR	WW_PTTR2	Thermal overload		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Op	WW_ACT1	Operate	M	

2.43 WW_PTTR4

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
PTTR class				
PTTR	WW_PTTR4	Thermal overload		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Op	WW_ACT1	Operate	M	

2.44 WW_PTUC1

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
PTUC class				
PTUC	WW_PTUC1	Undercurrent		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	

2 Logical Nodes

2.45 WW_PTUF1

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
Op	WW_ACT1	Operate	M	

2.45 WW_PTUF1

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
PTUF class				
PTUF	WW_PTUF1	Underfrequency		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

2.46 WW_PTUV1

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
PTUV class				
PTUV	WW_PTUV1	Undervoltage		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

2.47 WW_PTUV2

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
PTUV class				
PTUV	WW_PTUV2	Undervoltage		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

2.48 WW_PTUV3

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
PTUV class				
PTUV	WW_PTUV3	Undervoltage		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

2.49 WW_PUPF1

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
PUPF class				
PUPF	WW_PUPF1	Underpower factor		

2 Logical Nodes

2.50 WW_RBRF1

Attribute	Attribute	Explanation	M/O/E	Remarks			
Name	Type						
Data							
<i>Common Logical Node Information</i>							
Mod	WW_INC1	Mode	M	Status-only			
Beh	WW_INS1	Behaviour	M				
Health	WW_INS3	Health	M				
NamPlt	WW_LPL1	Name plate	M				
<i>Status Information</i>							
Str	WW_ACD1	Start	M				
Op	WW_ACT1	Operate	M				

2.50 WW_RBRF1

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
RBRF class				
RBRF	WW_RBRF1	Breaker failure		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
Str	WW_ACD1	Start	M	
OpEx	WW_ACT1	Breaker failure trip	M	

2.51 WW_RDRE1

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
RDRE class				
RDRE	WW_RDRE1	Disturbance recorder function		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
RcdMade	WW_SPS1	Recording made	M	
FltNum	WW_INS2	Fault Number	M	
GriFltNum	WW_INS2	Grid Fault Number	O	
RcdStr	WW_SPS1	Recording started	O	

2.52 WW_SCBR1

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
RBRF class				
SCBR	WW_SCBR1	Circuit breaker monitoring		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<i>Status Information</i>				
TrCctAlm	WW_ACD1	Alarm signal	E	

2.53 WW_XCBR2

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
XCBR class				
XCBR	WW_XCBR2	Circuit Breaker		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
Loc	WW_SPS1	Local operation	M	

2 Logical Nodes

2.54 WW_XSWI1

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
OpCnt	WW_INS2	Operation counter	M	
<i>Status Information</i>				
CBOpCap	WW_INS5	Circuit breaker operating capability	M	
<i>Controls</i>				
Pos	WW_DPC1	Switch position	M	
BlkOpen	WW_SPC1	Block opening	M	
BlkClose	WW_SPC1	Block closing	M	

2.54 WW_XSWI1

Attribute	Attribute	Explanation	M/O/E	Remarks
Name	Type			
XSWI class				
XSWI	WW_XSWI1	Circuit switch		
Data				
<i>Common Logical Node Information</i>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
Loc	WW_SPS1	Local operation	M	
OpCnt	WW_INS2	Operation counter	M	
<i>Status Information</i>				
SwTyp	WW_INS5	Switch type	M	
SwOpCap	WW_INS5	Switch operating capability	M	
<i>Controls</i>				
Pos	WW_DPC1	Switch position	M	
BlkOpen	WW_SPC1	Block opening	M	
BlkClose	WW_SPC1	Block closing	M	

3 Common Data Class

3.1 Common Data Class Definitions

The following table contains the list of Common Data Classes implemented in the device:

CDC Type	CDC Class	Description
WW_ACD1	ACD	Directional Protection activation information
WW_ACT1	ACT	Protection Activation Information
WW_analogValue1	analogValue	Analogue value
WW_BCR1	BCR	Binary Counter Reading
WW_Cancel1	Cancel	Cancel operating
WW_CMV2	CMV	Complex measured value
WW_DEL2	DEL	Delta
WW_DPC1	DPC	Controllable Double Point
WW_DPC2	DPC	Controllable Double Point
WW_DPL1	DPL	Device name plate
WW_INC1	INC	Controllable Integer Status
WW_INS1	INS	Integer Status
WW_INS2	INS	Integer Status
WW_INS3	INS	Integer Status
WW_INS5	INS	Integer Status
WW_INS6	INS	Integer Status
WW_LPL1	LPL	Logical node name plate
WW_LPL2	LPL	Logical node name plate
WW_MV1	MV	Measured Value
WW_Oper1	Oper	Start>Select operating
WW_origin1	origin	Originator
WW_SPC1	SPC	Controllable Single Point
WW_SPC2	SPC	Controllable Single Point
WW_SPS1	SPS	Single Point Status
WW_units1	units	Unit definition
WW_vector1	vector	Vector definition
WW_WYE2	WYE	Phase to ground related measured values of a three phase system

3 Common Data Class

3.1.1 WW_ACD1

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
ACD class						
General	BOOLEAN	ST	dchg		M	
dirGeneral	Enum	ST	dchg	ACDdir	M	
q	Quality	ST	qchg		M	
t	Timestamp	ST			M	

3.1.2 WW_ACT1

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
ACT class						
General	BOOLEAN	ST	dchg		M	
q	Quality	ST	qchg		M	
t	Timestamp	ST			M	

3.1.3 WW_BCR1

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
BCR class						
actVal	INT32	ST	dchg		M	
q	Quality	ST	qchg		M	
t	Timestamp	ST			M	
pulsQty	FLOAT32	CF			M	
units	Struct	CF			O	

3.1.4 WW_CMV2

Attribute Name	Attribute Type	FC	TrgOp	Value / Value Range	M/O/E	Remarks
CMV class						
cVal	Struct	MX		WW_vector1	M	
q	Quality	ST	qchg		M	
t	Timestamp	ST			M	

Attribute	Attribute	FC	TrgOp	Value / Value Range	M/O/E	Remarks
Name	Type					
instCVal	Struct	MX		WW_vector1	O	
units	Struct	CF		WW_units1	O	
db	INT32U	CF			O	
dbAng	INT32U	CF			E	

3.1.5 WW_DEL2

Attribute	Attribute	FC	TrgOp	Value / Value Range	M/O/E	Remarks
Name	Type					
DEL class						
phsAB	WW_CMV2					
phsBC	WW_CMV2					
phsCA	WW_CMV2					

3.1.6 WW_DPC1

Attribute	Attribute	FC	TrgOp	Value / Value Range	M/O/E	Remarks
Name	Type					
DPC class						
stVal	Dbpos	ST	dchg	Dbpos	M	
q	Quality	ST	qchg		M	
t	Timestamp	ST			M	
ctlModel	Enum	CF		ctlModel	M	

3.1.7 WW_DPC2

Attribute	Attribute	FC	TrgOp	Value / Value Range	M/O/E	Remarks
Name	Type					
DPC class						
origin	Struct	ST		WW_origin1	O	
ctlNum	INT8U	ST			O	
stVal	Dbpos	ST	dchg	Dbpos	M	
q	Quality	ST	qchg		M	
t	Timestamp	ST			M	
stSeld	BOOLEAN	ST	dchg		O	

3 Common Data Class

3.1.8 WW_DPL1

Attribute	Attribute	FC	TrgOp	Value / Value Range	M/O/E	Remarks
Name	Type					
ctlModel	Enum	CF		ctlModel	M	
sboTimeout	INT32U	CF			O	
sboClass	Enum	CF		sboClass	O	
cdcNs	VisString255	EX			O	
Oper	Struct	CO		WW_Oper1		
SBOw	Struct	CO		WW_Oper1		
Cancel	Struct	CO		WW_Cancel1		

3.1.8 WW_DPL1

Attribute	Attribute	FC	TrgOp	Value / Value Range	M/O/E	Remarks
Name	Type					
DPL class						
vendor	VisString255	DC			M	

3.1.9 WW_INC1

Attribute	Attribute	FC	TrgOp	Value / Value Range	M/O/E	Remarks
Name	Type					
INC class						
stVal	Enum	ST	dchg	Mode	M	
q	Quality	ST	qchg		M	
t	Timestamp	ST			M	
ctlModel	Enum	CF		ctlModel	M	

3.1.10 WW_INS1

Attribute	Attribute	FC	TrgOp	Value / Value Range	M/O/E	Remarks
Name	Type					
INS class						
stVal	Enum	ST	dchg	Behaviour	M	
q	Quality	ST	qchg		M	
t	Timestamp	ST			M	

3.1.11 WW_INS2

Attribute	Attribute	FC	TrgOp	Value / Value Range	M/O/E	Remarks
Name	Type					
INS class						
stVal	INT32	ST	dchg		M	
q	Quality	ST	qchg		M	
t	Timestamp	ST			M	

3.1.12 WW_INS3

Attribute	Attribute	FC	TrgOp	Value / Value Range	M/O/E	Remarks
Name	Type					
INS class						
stVal	Enum	ST	dchg	AutoRecSt	M	
q	Quality	ST	qchg		M	
t	Timestamp	ST			M	

3.1.13 WW_INS5

Attribute	Attribute	FC	TrgOp	Value / Value Range	M/O/E	Remarks
Name	Type					
INS class						
stVal	Enum	ST	dchg	CBOpCap	M	
q	Quality	ST	qchg		M	
t	Timestamp	ST			M	

3.1.14 WW_INS6

Attribute	Attribute	FC	TrgOp	Value / Value Range	M/O/E	Remarks
Name	Type					
INS class						
stVal	Enum	ST	dchg	MotorCycle	M	
q	Quality	ST	qchg		M	
t	Timestamp	ST			M	

3 Common Data Class

3.1.15 WW_LPL1

Attribute	Attribute	FC	TrgOp	Value / Value Range	M/O/E	Remarks
Name	Type					
LPL class						
vendor	visString255	DC			M	
swRev	visString255	DC			M	
d	visString255	DC			M	

3.1.16 WW_LPL2

Attribute	Attribute	FC	TrgOp	Value / Value Range	M/O/E	Remarks
Name	Type					
LPL class						
vendor	visString255	DC			M	
swRev	visString255	DC			M	
d	visString255	DC			M	
ldNs	visString255	EX				

3.1.17 WW_MV1

Attribute	Attribute	FC	TrgOp	Value / Value Range	M/O/E	Remarks
Name	Type					
MV class						
mag	Struct	MX		WW_analogValue1	M	
q	Quality	ST	qchg		M	
t	Timestamp	ST			M	
units	Struct	CF		WW_units1	O	
db	INT32U	CF			O	
d	visString255	DC			O	
dataNs	visString255	DC			O	

3.1.18 WW_SPC1

Attribute	Attribute	FC	TrgOp	Value / Value Range	M/O/E	Remarks
Name	Type					
SPC class						
stVal	BOOLEAN	ST	dchg		M	

Attribute	Attribute	FC	TrgOp	Value / Value Range	M/O/E	Remarks
Name	Type					
q	Quality	ST	dchg		M	
t	Timestamp	ST			M	
ctlModel	Enum	CF		ctlModel	M	

3.1.19 WW_SPC2

Attribute	Attribute	FC	TrgOp	Value / Value Range	M/O/E	Remarks
Name	Type					
SPC class						
Oper	Struct	CO		WW_Oper1		
stVal	BOOLEAN	ST	dchg		M	
q	Quality	ST	dchg		M	
t	Timestamp	ST			M	
ctlModel	Enum	CF		ctlModel	M	

3.1.20 WW_SPS1

Attribute	Attribute	FC	TrgOp	Value / Value Range	M/O/E	Remarks
Name	Type					
SPS class						
stVal	BOOLEAN	ST	dchg		M	
q	Quality	ST	qchg		M	
t	Timestamp	ST			M	

3.1.21 WW_WYE2

Attribute	Attribute	FC	TrgOp	Value / Value Range	M/O/E	Remarks
Name	Type					
WYE class						
phsAB	WW_CMV2					
phsBC	WW_CMV2					
phsCA	WW_CMV2					
neut	WW_CMV2					

3.2 Common Data Attributes Type Definitions

3.2.1 WW_analogValue1

Attribute	Attribute	FC	TrgOp	Value / Value Range	M/O/E	Remarks
Name	Type					
analogValue class						
f	FLOAT32	MX			M	

3.2.2 WW_Cancel1

Attribute	Attribute	FC	TrgOp	Value / Value Range	M/O/E	Remarks
Name	Type					
Cancel class						
ctlval	BOOLEAN	CO			M	
origin	Struct	ST		WW_origin1	O	
ctlNum	INT8U	ST			O	
T	Timestamp	CO			O	
Test	BOOLEAN	CO			O	

3.2.3 WW_Oper1

Attribute	Attribute	FC	TrgOp	Value / Value Range	M/O/E	Remarks
Name	Type					
Oper class						
ctlval	BOOLEAN	CO			M	
origin	Struct	ST		WW_origin1	O	
ctlNum	INT8U	ST			O	
T	Timestamp	CO			O	
Test	BOOLEAN	CO			O	
Check	Check	CO			O	

3.2.4 WW_origin1

Attribute	Attribute	FC	TrgOp	Value / Value Range	M/O/E	Remarks
Name	Type					
origin class						
orCat	Enum	ST		orCategory	M	

Attribute	Attribute	FC	TrgOp	Value / Value Range	M/O/E	Remarks
Name	Type					
orldent	Octet64	ST			M	

3.2.5 WW_units1

Attribute	Attribute	FC	TrgOp	Value / Value Range	M/O/E	Remarks
Name	Type					
unit class						
SIUnit	Enum			SIUnit	M	
multiplier	Enum			multiplier	O	

3.2.6 WW_vector1

Attribute	Attribute	FC	TrgOp	Value / Value Range	M/O/E	Remarks
Name	Type					
vector class						
mag	Struct			WW_analogValue1	M	
ang	Struct			WW_analogValue1	O	

3.3 Enumerated type definitions

3.3.1 AutoRecSt

Ordinal	Semantic
1	Ready
2	InProgress
3	Successful

3.3.2 Beh

Ordinal	Semantic
1	on
2	blocked
3	test
4	test/blocked
5	off

3.3.3 CBOpCap

Ordinal	Semantic
1	None
2	Open
3	Close-Open
4	Open-Close-Open
5	Close-Open-Close-Open

3.3.4 ctlModel

Ordinal	Semantic
1	status-only
2	direct-with-normal-security
3	sbo-with-normal-security
4	direct-with-enhanced-security

Ordinal	Semantic
5	sbo-with-enhanced-security

3.3.5 Dbpos

Ordinal	Semantic
1	intermediate
2	off
3	on
4	bad

3.3.6 ACDdir

Ordinal	Semantic
0	unknown
1	forward
2	backward
3	both

3.3.7 Health

Ordinal	Semantic
1	Ok
2	Warning
3	Alarm

3.3.8 Mod

Ordinal	Semantic
1	on
2	blocked
3	test
4	test/block

Ordinal	Semantic
5	off

3.3.9 MotorCycle

Ordinal	Semantic
0	Trip/Off
1	Stop
2	Start
3	Run

3.3.10 multiplier

Ordinal	Semantic
-24	y
-21	z
-18	a
-15	f
-12	p
-9	n
-6	μ
-3	m
-2	c
-1	d
0	
1	da
2	h
3	k
6	M
9	G
12	T
15	P
18	E

Ordinal	Semantic
21	Z
24	Y

3.3.11 orCategory

Ordinal	Semantic
0	not-supported
1	bay-control
2	station-control
3	remote-control
4	automatic-bay
5	automatic-station
6	automatic-remote
7	maintenance
8	process

3.3.12 sboClass

Ordinal	Semantic
0	operate-once
1	operate-many

3.3.13 SIUnit

Ordinal	Semantic
1	none
2	m
3	kg
4	s
5	A
6	K
7	mol
8	cd

Ordinal	Semantic
9	deg
10	rad
11	sr
21	Gy
22	q
23	°C
24	Sv
25	F
26	C
27	S
28	H
29	V
30	ohm
31	J
32	N
33	Hz
34	Ix
35	Lm
36	Wb
37	T
38	W
39	Pa
41	m ²
42	m ³
43	m/s
44	m/s ²
45	m ³ /s
46	m/m ³
47	M
48	kg/m ³
49	m ² /s
50	W/m K

Ordinal	Semantic
51	J/K
52	ppm
53	1/s
54	rad/s
61	VA
62	Watts
63	VAr
64	phi
65	cos(phi)
66	Vs
67	V ²
68	As
69	A ²
70	A ² t
71	VAh
72	Wh
73	VArh
74	V/Hz

4 Appendix

4.1 Register Maps

Legend: * The Logical Node is dependent on the settings in the “Device planning”. (See  “4.2 Device Planning Dependencies”).

LDevice::CTRL

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
CILO1* (WW_CILO1)		
	Mod	
	Beh	
	Health	
	NamPlt	
	EnaOpn	SG[1] . Interl OFF
	EnaCls	SG[1] . Interl ON

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
CSWI1* (WW_CSWI1)		
	Mod	
	Beh	
	Health	
	NamPlt	
	Loc	
	Pos	SG[1] . Pos

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
LLNO (WW_LLNOCON)		
	Mod	
	Beh	
	Health	
	NamPlt	

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
LPHD1 (WW_LPHDCON)		
	PhyNam	
	PhyHealth	
	Proxy	

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
TCSSCBR1 (WW_SCBR1)		
	Mod	TCS - 74TC . active
	Beh	
	Health	
	NamPlt	
	TrCctAlm	TCS - 74TC . Alarm

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
XCBR1* (WW_XCBR2)		
	Mod	
	Beh	
	Health	
	NamPlt	
	Loc	
	OpCnt	
	Pos	SG[1] . Pos
	BlkOpn	
	BlkClis	
	CBOpCap	

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
XSWI1* (WW_XSWI1)		
	Mod	
	Beh	
	Health	
	NamPlt	
	Loc	
	OpCnt	
	Pos	SG[1] . Pos
	BlkOpn	
	BlkClis	
	SwTyp	
	SwOpCap	

LDevice::DR

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
LLN0 (WW_LLNOREC)		
	Mod	

4 Appendix

4.1 Register Maps

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
LLNO (WW_LLNOREC)		
	Beh	
	Health	
	NamPlt	

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
LPHD1 (WW_LPHDREC)		
	PhyNam	
	PhyHealth	
	Proxy	

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
RDRE1 (WW_RDRE1)		
	Mod	
	Beh	
	Health	
	NamPlt	
	RcdMade	Disturb rec . recording
	FltNum	
	GriFltNum	
	RcdStr	Disturb rec . recording

LDevice::EXT

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
COUTGGIO1 (WW_GGIO4)		
	Mod	
	Beh	
	Health	
	NamPlt	
	Ind1	IEC 61850 . COUTGGIO1.Ind1.stVal-I
	Ind2	IEC 61850 . COUTGGIO1.Ind2.stVal-I
	Ind3	IEC 61850 . COUTGGIO1.Ind3.stVal-I
	Ind4	IEC 61850 . COUTGGIO1.Ind4.stVal-I
	Ind5	IEC 61850 . COUTGGIO1.Ind5.stVal-I
	Ind6	IEC 61850 . COUTGGIO1.Ind6.stVal-I
	Ind7	IEC 61850 . COUTGGIO1.Ind7.stVal-I
	Ind8	IEC 61850 . COUTGGIO1.Ind8.stVal-I
	Ind9	IEC 61850 . COUTGGIO1.Ind9.stVal-I

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
COUTGGIO1 (WW_GGIO4)		
	Ind10	IEC 61850 . COUTGGIO1.Ind10.stVal-I
	Ind11	IEC 61850 . COUTGGIO1.Ind11.stVal-I
	Ind12	IEC 61850 . COUTGGIO1.Ind12.stVal-I
	Ind13	IEC 61850 . COUTGGIO1.Ind13.stVal-I
	Ind14	IEC 61850 . COUTGGIO1.Ind14.stVal-I
	Ind15	IEC 61850 . COUTGGIO1.Ind15.stVal-I
	Ind16	IEC 61850 . COUTGGIO1.Ind16.stVal-I
	Ind17	IEC 61850 . COUTGGIO1.Ind17.stVal-I
	Ind18	IEC 61850 . COUTGGIO1.Ind18.stVal-I
	Ind19	IEC 61850 . COUTGGIO1.Ind19.stVal-I
	Ind20	IEC 61850 . COUTGGIO1.Ind20.stVal-I
	Ind21	IEC 61850 . COUTGGIO1.Ind21.stVal-I
	Ind22	IEC 61850 . COUTGGIO1.Ind22.stVal-I
	Ind23	IEC 61850 . COUTGGIO1.Ind23.stVal-I
	Ind24	IEC 61850 . COUTGGIO1.Ind24.stVal-I
	Ind25	IEC 61850 . COUTGGIO1.Ind25.stVal-I
	Ind26	IEC 61850 . COUTGGIO1.Ind26.stVal-I
	Ind27	IEC 61850 . COUTGGIO1.Ind27.stVal-I
	Ind28	IEC 61850 . COUTGGIO1.Ind28.stVal-I
	Ind29	IEC 61850 . COUTGGIO1.Ind29.stVal-I
	Ind30	IEC 61850 . COUTGGIO1.Ind30.stVal-I
	Ind31	IEC 61850 . COUTGGIO1.Ind31.stVal-I
	Ind32	IEC 61850 . COUTGGIO1.Ind32.stVal-I

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
COUTGGIO2 (WW_GGIO4)		
	Mod	
	Beh	
	Health	
	NamPlt	
	Ind1	IEC 61850 . COUTGGIO2.Ind1.stVal-I
	Ind2	IEC 61850 . COUTGGIO2.Ind2.stVal-I
	Ind3	IEC 61850 . COUTGGIO2.Ind3.stVal-I
	Ind4	IEC 61850 . COUTGGIO2.Ind4.stVal-I
	Ind5	IEC 61850 . COUTGGIO2.Ind5.stVal-I
	Ind6	IEC 61850 . COUTGGIO2.Ind6.stVal-I
	Ind7	IEC 61850 . COUTGGIO2.Ind7.stVal-I

4 Appendix

4.1 Register Maps

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
COUTGGIO2 (WW_GGIO4)		
	Ind8	IEC 61850 . COUTGGIO2.Ind8.stVal-I
	Ind9	IEC 61850 . COUTGGIO2.Ind9.stVal-I
	Ind10	IEC 61850 . COUTGGIO2.Ind10.stVal-I
	Ind11	IEC 61850 . COUTGGIO2.Ind11.stVal-I
	Ind12	IEC 61850 . COUTGGIO2.Ind12.stVal-I
	Ind13	IEC 61850 . COUTGGIO2.Ind13.stVal-I
	Ind14	IEC 61850 . COUTGGIO2.Ind14.stVal-I
	Ind15	IEC 61850 . COUTGGIO2.Ind15.stVal-I
	Ind16	IEC 61850 . COUTGGIO2.Ind16.stVal-I
	Ind17	IEC 61850 . COUTGGIO2.Ind17.stVal-I
	Ind18	IEC 61850 . COUTGGIO2.Ind18.stVal-I
	Ind19	IEC 61850 . COUTGGIO2.Ind19.stVal-I
	Ind20	IEC 61850 . COUTGGIO2.Ind20.stVal-I
	Ind21	IEC 61850 . COUTGGIO2.Ind21.stVal-I
	Ind22	IEC 61850 . COUTGGIO2.Ind22.stVal-I
	Ind23	IEC 61850 . COUTGGIO2.Ind23.stVal-I
	Ind24	IEC 61850 . COUTGGIO2.Ind24.stVal-I
	Ind25	IEC 61850 . COUTGGIO2.Ind25.stVal-I
	Ind26	IEC 61850 . COUTGGIO2.Ind26.stVal-I
	Ind27	IEC 61850 . COUTGGIO2.Ind27.stVal-I
	Ind28	IEC 61850 . COUTGGIO2.Ind28.stVal-I
	Ind29	IEC 61850 . COUTGGIO2.Ind29.stVal-I
	Ind30	IEC 61850 . COUTGGIO2.Ind30.stVal-I
	Ind31	IEC 61850 . COUTGGIO2.Ind31.stVal-I
	Ind32	IEC 61850 . COUTGGIO2.Ind32.stVal-I

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
CTLGGIO1 (WW_GGIO14)		
	Mod	
	Beh	
	Health	
	NamPlt	
	SPCSO1	
	SPCSO2	
	SPCSO3	
	SPCSO4	
	SPCSO5	

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
CTLGGIO1 (WW_GGIO14)		
	SPCSO6	
	SPCSO7	
	SPCSO8	
	SPCSO9	
	SPCSO10	
	SPCSO11	
	SPCSO12	
	SPCSO13	
	SPCSO14	
	SPCSO15	
	SPCSO16	
	SPCSO17	
	SPCSO18	
	SPCSO19	
	SPCSO20	
	SPCSO21	
	SPCSO22	
	SPCSO23	
	SPCSO24	
	SPCSO25	
	SPCSO26	
	SPCSO27	
	SPCSO28	
	SPCSO29	
	SPCSO30	
	SPCSO31	
	SPCSO32	

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
EPGAPC1 (WW_GAPC1)		
	Mod	ExP[1] . active ExP[1] . Blo TripCmd ExP[1] . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	ExP[1] . Alarm
	Op	ExP[1] . Trip

4 Appendix

4.1 Register Maps

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
EPGAPC2 (WW_GAPC1)		
	Mod	ExP[2] . active ExP[2] . Blo TripCmd ExP[2] . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	ExP[2] . Alarm
	Op	ExP[2] . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
EPGAPC3 (WW_GAPC1)		
	Mod	ExP[3] . active ExP[3] . Blo TripCmd ExP[3] . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	ExP[3] . Alarm
	Op	ExP[3] . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
EPGAPC4 (WW_GAPC1)		
	Mod	ExP[4] . active ExP[4] . Blo TripCmd ExP[4] . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	ExP[4] . Alarm
	Op	ExP[4] . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
GOSINGGIO1 (WW_GGIO11)		
	Mod	
	Beh	
	Health	
	NamPlt	
	Ind1	
	Ind2	
	Ind3	
	Ind4	
	Ind5	
	Ind6	

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
GOSINGGIO1 (WW_GGIO11)		
	Ind7	
	Ind8	
	Ind9	
	Ind10	
	Ind11	
	Ind12	
	Ind13	
	Ind14	
	Ind15	
	Ind16	
	Ind17	
	Ind18	
	Ind19	
	Ind20	
	Ind21	
	Ind22	
	Ind23	
	Ind24	
	Ind25	
	Ind26	
	Ind27	
	Ind28	
	Ind29	
	Ind30	
	Ind31	
	Ind32	

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
GOSINGGIO2 (WW_GGIO10)		
	Mod	
	Beh	
	Health	
	NamPlt	
	Ind1	
	Ind2	
	Ind3	
	Ind4	

4 Appendix

4.1 Register Maps

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
GOSINGGIO2 (WW_GGPIO10)		
	Ind5	
	Ind6	
	Ind7	
	Ind8	
	Ind9	
	Ind10	
	Ind11	
	Ind12	
	Ind13	
	Ind14	
	Ind15	
	Ind16	
	Ind17	
	Ind18	
	Ind19	
	Ind20	
	Ind21	
	Ind22	
	Ind23	
	Ind24	
	Ind25	
	Ind26	
	Ind27	
	Ind28	
	Ind29	
	Ind30	
	Ind31	
	Ind32	

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
LLN0 (WW_LLNO0SYS)		
	Mod	
	Beh	
	Health	
	NamPlt	

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
LPHD1 (WW_LPHDSYS)		
	PhyNam	
	PhyHealth	
	Proxy	

LDevice::MEAS

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
CMMXU1 (WW_MMXU7)		
	Mod	
	Beh	
	Health	
	NamPlt	
	A	CT . IL1 RMS CT . phi IL1 CT . IL2 RMS CT . phi IL2 CT . IL3 RMS CT . phi IL3 CT . IG meas RMS CT . phi IG meas CT . IG calc RMS CT . phi IG calc

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
CMSTA1 (WW_MSTA1)		
	Mod	
	Beh	
	Health	
	NamPlt	
	AvAPhsA	CT . IL1 avg
	AvAPhsB	CT . IL2 avg
	AvAPhsC	CT . IL3 avg
	MaxAPhsA	CT . IL1 max
	MaxAPhsB	CT . IL2 max
	MaxAPhsC	CT . IL3 max
	MinAPhsA	CT . IL1 min
	MinAPhsB	CT . IL2 min
	MinAPhsC	CT . IL3 min

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
ECMMTR1 (WW_MMTR1)		
	Mod	
	Beh	
	Health	
	NamPlt	
	SupWh	PQSCr . Wp+

4 Appendix

4.1 Register Maps

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
ECMMTR1 (WW_MMTR1)		
	DmdWh	PQSCr . Wp-
	SupVArh	PQSCr . Wq+
	DmdVArh	PQSCr . Wq-
	TotWh	PQSCr . Wp Net
	TotVArh	PQSCr . Wq Net
	TotVAh	PQSCr . Ws Net

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
LLN0 (WW_LLNAMEA)		
	Mod	
	Beh	
	Health	
	NamPlt	

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
LPHD1 (WW_LPHDMEA)		
	PhyNam	
	PhyHealth	
	Proxy	

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PMMXU1 (WW_MMXU3)		
	Mod	
	Beh	
	Health	
	NamPlt	
	TotW	PQSCr . P RMS
	TotVAr	PQSCr . Q
	TotVA	PQSCr . S RMS
	TotPF	PQSCr . cos phi RMS

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PMSTA1 (WW_MSTA3)		
	Mod	
	Beh	
	Health	
	NamPlt	

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PMSTA1 (WW_MSTA3)		
	AvVA	PQSCr . S avg (Demand)
	MaxVA	PQSCr . S max
	MinVA	PQSCr . S min
	AvW	PQSCr . P avg
	MaxW	PQSCr . P max
	MinW	PQSCr . P min
	AvVAr	PQSCr . Q avg (Demand)
	MaxVAr	PQSCr . Q max
	MinVAr	PQSCr . Q min

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
VMMXU1 (WW_MMXU6)		
	Mod	
	Beh	
	Health	
	NamPlt	
	PPV	VT . VL12 RMS VT . phi VL12 VT . VL23 RMS VT . phi VL23 VT . VL31 RMS VT . phi VL31
	PhV	VT . VL1 RMS VT . phi VL1 VT . VL2 RMS VT . phi VL2 VT . VL3 RMS VT . phi VL3 VT . VX meas RMS VT . phi VX meas VT . VG calc RMS VT . phi VG calc
	Hz	VT . f

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
VMSTA1 (WW_MSTA2)		
	Mod	
	Beh	
	Health	
	NamPlt	
	AvVPhsAB	VT . VL12 avg
	AvVPhsBC	VT . VL23 avg
	AvVPhsCA	VT . VL31 avg
	MaxVPhsAB	VT . VL12 max
	MaxVPhsBC	VT . VL23 max
	MaxVPhsCA	VT . VL31 max
	MinVPhsAB	VT . VL12 min
	MinVPhsBC	VT . VL23 min
	MinVPhsCA	VT . VL31 min
	AvVPhsA	VT . VL1 avg

4 Appendix

4.1 Register Maps

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
VMSTA1 (WW_MSTA2)		
	AvVPhsB	VT . VL2 avg
	AvVPhsC	VT . VL3 avg
	MaxVPhsA	VT . VL1 max
	MaxVPhsB	VT . VL2 max
	MaxVPhsC	VT . VL3 max
	MinVPhsA	VT . VL1 min
	MinVPhsB	VT . VL2 min
	MinVPhsC	VT . VL3 min

LDevice::PROT

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
GFPTOC1 (WW_PTOC3)		
	Mod	IG[1] - 50N, 51N . active IG[1] - 50N, 51N . Blo TripCmd IG[1] - 50N, 51N . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	IG[1] - 50N, 51N . Alarm
	Op	IG[1] - 50N, 51N . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
GFPTOC2 (WW_PTOC3)		
	Mod	IG[2] - 50N, 51N . active IG[2] - 50N, 51N . Blo TripCmd IG[2] - 50N, 51N . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	IG[2] - 50N, 51N . Alarm
	Op	IG[2] - 50N, 51N . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
GFPTOC3 (WW_PTOC3)		
	Mod	IG[3] - 50N, 51N . active IG[3] - 50N, 51N . Blo TripCmd IG[3] - 50N, 51N . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	IG[3] - 50N, 51N . Alarm

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
GFPTOC3 (WW_PTOC3)		
	Op	IG[3] - 50N, 51N . Trip
Logical Node		
GFPTOC4 (WW_PTOC3)		
	Mod	IG[4] - 50N, 51N . active IG[4] - 50N, 51N . Blo TripCmd IG[4] - 50N, 51N . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	IG[4] - 50N, 51N . Alarm
	Op	IG[4] - 50N, 51N . Trip
Logical Node		
IHMI1 (WW_IHMI1)		
	Mod	
	Beh	
	Health	
	NamPlt	
Logical Node		
JAMPIOC1 (WW_PIOC1)		
	Mod	Jam[1] - 51LR . active Jam[1] - 51LR . Blo TripCmd Jam[1] - 51LR . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	Jam[1] - 51LR . Alarm
	Op	Jam[1] - 51LR . Trip
Logical Node		
JAMPIOC2 (WW_PIOC1)		
	Mod	Jam[2] - 51LR . active Jam[2] - 51LR . Blo TripCmd Jam[2] - 51LR . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	Jam[2] - 51LR . Alarm
	Op	Jam[2] - 51LR . Trip

4 Appendix

4.1 Register Maps

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
LLNO (WW_LLNO PRO)		
	Mod	
	Beh	
	Health	
	NamPlt	
LPHD1 (WW_LPHD PRO)		
	PhyNam	
	PhyHealth	
	Proxy	
PDOP1* (WW_PDOP1)		
	Mod	PQS[1] - 32, 37 . active PQS[1] - 32, 37 . Blo TripCmd PQS[1] - 32, 37 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	PQS[1] - 32, 37 . Alarm
	Op	PQS[1] - 32, 37 . Trip
PDOP2* (WW_PDOP1)		
	Mod	PQS[2] - 32, 37 . active PQS[2] - 32, 37 . Blo TripCmd PQS[2] - 32, 37 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	PQS[2] - 32, 37 . Alarm
	Op	PQS[2] - 32, 37 . Trip
PDOP3* (WW_PDOP1)		
	Mod	PQS[3] - 32, 37 . active PQS[3] - 32, 37 . Blo TripCmd PQS[3] - 32, 37 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	PQS[3] - 32, 37 . Alarm

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PDOP3* (WW_PDOP1)		
	Op	PQS[3] - 32, 37 . Trip
Logical Node		
PDOP4* (WW_PDOP1)		
	Mod	PQS[4] - 32, 37 . active PQS[4] - 32, 37 . Blo TripCmd PQS[4] - 32, 37 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	PQS[4] - 32, 37 . Alarm
	Op	PQS[4] - 32, 37 . Trip
Logical Node		
PDOP5* (WW_PDOP1)		
	Mod	PQS[5] - 32, 37 . active PQS[5] - 32, 37 . Blo TripCmd PQS[5] - 32, 37 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	PQS[5] - 32, 37 . Alarm
	Op	PQS[5] - 32, 37 . Trip
Logical Node		
PDOP6* (WW_PDOP1)		
	Mod	PQS[6] - 32, 37 . active PQS[6] - 32, 37 . Blo TripCmd PQS[6] - 32, 37 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	PQS[6] - 32, 37 . Alarm
	Op	PQS[6] - 32, 37 . Trip
Logical Node		
PDUP1* (WW_PDUP1)		
	Mod	PQS[1] - 32, 37 . active PQS[1] - 32, 37 . Blo TripCmd PQS[1] - 32, 37 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	

4 Appendix

4.1 Register Maps

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PDUP1* (WW_PDUP1)		
	Str	PQS[1] - 32, 37 . Alarm
	Op	PQS[1] - 32, 37 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PDUP2* (WW_PDUP1)		
	Mod	PQS[2] - 32, 37 . active PQS[2] - 32, 37 . Blo TripCmd PQS[2] - 32, 37 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	PQS[2] - 32, 37 . Alarm
	Op	PQS[2] - 32, 37 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PDUP3* (WW_PDUP1)		
	Mod	PQS[3] - 32, 37 . active PQS[3] - 32, 37 . Blo TripCmd PQS[3] - 32, 37 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	PQS[3] - 32, 37 . Alarm
	Op	PQS[3] - 32, 37 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PDUP4* (WW_PDUP1)		
	Mod	PQS[4] - 32, 37 . active PQS[4] - 32, 37 . Blo TripCmd PQS[4] - 32, 37 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	PQS[4] - 32, 37 . Alarm
	Op	PQS[4] - 32, 37 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PDUP5* (WW_PDUP1)		
	Mod	PQS[5] - 32, 37 . active PQS[5] - 32, 37 . Blo TripCmd PQS[5] - 32, 37 . ExBlo TripCmd
	Beh	
	Health	

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PDUP5* (WW_PDUP1)		
	NamPlt	
	Str	PQS[5] - 32, 37 . Alarm
	Op	PQS[5] - 32, 37 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PDUP6* (WW_PDUP1)		
	Mod	PQS[6] - 32, 37 . active PQS[6] - 32, 37 . Blo TripCmd PQS[6] - 32, 37 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	PQS[6] - 32, 37 . Alarm
	Op	PQS[6] - 32, 37 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PFRC1* (WW_PFRC1)		
	Mod	f[1] - 81 . active f[1] - 81 . Blo TripCmd f[1] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[1] - 81 . Alarm
	Op	f[1] - 81 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PFRC2* (WW_PFRC1)		
	Mod	f[2] - 81 . active f[2] - 81 . Blo TripCmd f[2] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[2] - 81 . Alarm
	Op	f[2] - 81 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PFRC3* (WW_PFRC1)		
	Mod	f[3] - 81 . active f[3] - 81 . Blo TripCmd f[3] - 81 . ExBlo TripCmd
	Beh	

4 Appendix

4.1 Register Maps

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PFRC3* (WW_PFRC1)		
	Health	
	NamPlt	
	Str	f[3] - 81 . Alarm
	Op	f[3] - 81 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PFRC4* (WW_PFRC1)		
	Mod	f[4] - 81 . active f[4] - 81 . Blo TripCmd f[4] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[4] - 81 . Alarm
	Op	f[4] - 81 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PFRC5* (WW_PFRC1)		
	Mod	f[5] - 81 . active f[5] - 81 . Blo TripCmd f[5] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[5] - 81 . Alarm
	Op	f[5] - 81 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PFRC6* (WW_PFRC1)		
	Mod	f[6] - 81 . active f[6] - 81 . Blo TripCmd f[6] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[6] - 81 . Alarm
	Op	f[6] - 81 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PMRI1 (WW_PMRI1)		
	Mod	MStart . active MStart . Blo TripCmd MStart . ExBlo TripCmd
	Beh	

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PMRI1 (WW_PMRI1)		
	Health	
	NamPlt	
	Op	MStart . Blo

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PMSS1 (WW_PMSS1)		
	Mod	MStart . active MStart . Blo TripCmd MStart . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Op	MStart . Trip
	MotCyc	MStart . MotorCyc Enum

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PPAM1* (WW_PPAM1)		
	Mod	f[1] - 81 . active f[1] - 81 . Blo TripCmd f[1] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[1] - 81 . Alarm
	Op	f[1] - 81 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PPAM2* (WW_PPAM1)		
	Mod	f[2] - 81 . active f[2] - 81 . Blo TripCmd f[2] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[2] - 81 . Alarm
	Op	f[2] - 81 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PPAM3* (WW_PPAM1)		
	Mod	f[3] - 81 . active f[3] - 81 . Blo TripCmd f[3] - 81 . ExBlo TripCmd
	Beh	
	Health	

4 Appendix

4.1 Register Maps

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PPAM3* (WW_PPAM1)		
	NamPlt	
	Str	f[3] - 81 . Alarm
	Op	f[3] - 81 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PPAM4* (WW_PPAM1)		
	Mod	f[4] - 81 . active f[4] - 81 . Blo TripCmd f[4] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[4] - 81 . Alarm
	Op	f[4] - 81 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PPAM5* (WW_PPAM1)		
	Mod	f[5] - 81 . active f[5] - 81 . Blo TripCmd f[5] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[5] - 81 . Alarm
	Op	f[5] - 81 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PPAM6* (WW_PPAM1)		
	Mod	f[6] - 81 . active f[6] - 81 . Blo TripCmd f[6] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[6] - 81 . Alarm
	Op	f[6] - 81 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTOC1 (WW_PTOC1)		
	Mod	I[1] - 50, 51 . active I[1] - 50, 51 . Blo TripCmd I[1] - 50, 51 . ExBlo TripCmd
	Beh	

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTOC1 (WW_PTOC1)		
	Health	
	NamPlt	
	Str	I[1] - 50, 51 . Alarm
	Op	I[1] - 50, 51 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTOC2 (WW_PTOC1)		
	Mod	I[2] - 50, 51 . active I[2] - 50, 51 . Blo TripCmd I[2] - 50, 51 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	I[2] - 50, 51 . Alarm
	Op	I[2] - 50, 51 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTOC3 (WW_PTOC1)		
	Mod	I[3] - 50, 51 . active I[3] - 50, 51 . Blo TripCmd I[3] - 50, 51 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	I[3] - 50, 51 . Alarm
	Op	I[3] - 50, 51 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTOC4 (WW_PTOC1)		
	Mod	I[4] - 50, 51 . active I[4] - 50, 51 . Blo TripCmd I[4] - 50, 51 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	I[4] - 50, 51 . Alarm
	Op	I[4] - 50, 51 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTOC5 (WW_PTOC1)		
	Mod	I[5] - 50, 51 . active I[5] - 50, 51 . Blo TripCmd I[5] - 50, 51 . ExBlo TripCmd

4 Appendix

4.1 Register Maps

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTOC5 (WW_PTOC1)		
	Beh	
	Health	
	NamPlt	
	Str	I[5] - 50, 51 . Alarm
	Op	I[5] - 50, 51 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTOC6 (WW_PTOC1)		
	Mod	I[6] - 50, 51 . active I[6] - 50, 51 . Blo TripCmd I[6] - 50, 51 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	I[6] - 50, 51 . Alarm
	Op	I[6] - 50, 51 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTOF1* (WW_PTOF1)		
	Mod	f[1] - 81 . active f[1] - 81 . Blo TripCmd f[1] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[1] - 81 . Alarm
	Op	f[1] - 81 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTOF2* (WW_PTOF1)		
	Mod	f[2] - 81 . active f[2] - 81 . Blo TripCmd f[2] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[2] - 81 . Alarm
	Op	f[2] - 81 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTOF3* (WW_PTOF1)		
	Mod	f[3] - 81 . active f[3] - 81 . Blo TripCmd f[3] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[3] - 81 . Alarm
	Op	f[3] - 81 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTOF4* (WW_PTOF1)		
	Mod	f[4] - 81 . active f[4] - 81 . Blo TripCmd f[4] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[4] - 81 . Alarm
	Op	f[4] - 81 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTOF5* (WW_PTOF1)		
	Mod	f[5] - 81 . active f[5] - 81 . Blo TripCmd f[5] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[5] - 81 . Alarm
	Op	f[5] - 81 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTOF6* (WW_PTOF1)		
	Mod	f[6] - 81 . active f[6] - 81 . Blo TripCmd f[6] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[6] - 81 . Alarm
	Op	f[6] - 81 . Trip

4 Appendix

4.1 Register Maps

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTOV1* (WW_PTOV2)		
	Mod	V[1] - 27, 59 . active V[1] - 27, 59 . Blo TripCmd V[1] - 27, 59 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V[1] - 27, 59 . Alarm
	Op	V[1] - 27, 59 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTOV2* (WW_PTOV2)		
	Mod	V[2] - 27, 59 . active V[2] - 27, 59 . Blo TripCmd V[2] - 27, 59 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V[2] - 27, 59 . Alarm
	Op	V[2] - 27, 59 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTOV3* (WW_PTOV2)		
	Mod	V[3] - 27, 59 . active V[3] - 27, 59 . Blo TripCmd V[3] - 27, 59 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V[3] - 27, 59 . Alarm
	Op	V[3] - 27, 59 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTOV4* (WW_PTOV2)		
	Mod	V[4] - 27, 59 . active V[4] - 27, 59 . Blo TripCmd V[4] - 27, 59 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V[4] - 27, 59 . Alarm
	Op	V[4] - 27, 59 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTOV5* (WW_PTOV2)		
	Mod	V[5] - 27, 59 . active V[5] - 27, 59 . Blo TripCmd V[5] - 27, 59 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V[5] - 27, 59 . Alarm
	Op	V[5] - 27, 59 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTOV6* (WW_PTOV2)		
	Mod	V[6] - 27, 59 . active V[6] - 27, 59 . Blo TripCmd V[6] - 27, 59 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V[6] - 27, 59 . Alarm
	Op	V[6] - 27, 59 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTUF1* (WW_PTUF1)		
	Mod	f[1] - 81 . active f[1] - 81 . Blo TripCmd f[1] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[1] - 81 . Alarm
	Op	f[1] - 81 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTUF2* (WW_PTUF1)		
	Mod	f[2] - 81 . active f[2] - 81 . Blo TripCmd f[2] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[2] - 81 . Alarm
	Op	f[2] - 81 . Trip

4 Appendix

4.1 Register Maps

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTUF3* (WW_PTUF1)		
	Mod	f[3] - 81 . active f[3] - 81 . Blo TripCmd f[3] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[3] - 81 . Alarm
	Op	f[3] - 81 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTUF4* (WW_PTUF1)		
	Mod	f[4] - 81 . active f[4] - 81 . Blo TripCmd f[4] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[4] - 81 . Alarm
	Op	f[4] - 81 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTUF5* (WW_PTUF1)		
	Mod	f[5] - 81 . active f[5] - 81 . Blo TripCmd f[5] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[5] - 81 . Alarm
	Op	f[5] - 81 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTUF6* (WW_PTUF1)		
	Mod	f[6] - 81 . active f[6] - 81 . Blo TripCmd f[6] - 81 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[6] - 81 . Alarm
	Op	f[6] - 81 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTUV1* (WW_PTUV2)		
	Mod	V[1] - 27, 59 . active V[1] - 27, 59 . Blo TripCmd V[1] - 27, 59 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V[1] - 27, 59 . Alarm
	Op	V[1] - 27, 59 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTUV2* (WW_PTUV2)		
	Mod	V[2] - 27, 59 . active V[2] - 27, 59 . Blo TripCmd V[2] - 27, 59 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V[2] - 27, 59 . Alarm
	Op	V[2] - 27, 59 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTUV3* (WW_PTUV2)		
	Mod	V[3] - 27, 59 . active V[3] - 27, 59 . Blo TripCmd V[3] - 27, 59 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V[3] - 27, 59 . Alarm
	Op	V[3] - 27, 59 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTUV4* (WW_PTUV2)		
	Mod	V[4] - 27, 59 . active V[4] - 27, 59 . Blo TripCmd V[4] - 27, 59 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V[4] - 27, 59 . Alarm
	Op	V[4] - 27, 59 . Trip

4 Appendix

4.1 Register Maps

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTUV5* (WW_PTUV2)		
	Mod	V[5] - 27, 59 . active V[5] - 27, 59 . Blo TripCmd V[5] - 27, 59 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V[5] - 27, 59 . Alarm
	Op	V[5] - 27, 59 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PTUV6* (WW_PTUV2)		
	Mod	V[6] - 27, 59 . active V[6] - 27, 59 . Blo TripCmd V[6] - 27, 59 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V[6] - 27, 59 . Alarm
	Op	V[6] - 27, 59 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PUPF1 (WW_PUPF1)		
	Mod	PF[1] - 55 . active PF[1] - 55 . Blo TripCmd PF[1] - 55 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	PF[1] - 55 . Alarm
	Op	PF[1] - 55 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
PUPF2 (WW_PUPF1)		
	Mod	PF[2] - 55 . active PF[2] - 55 . Blo TripCmd PF[2] - 55 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	PF[2] - 55 . Alarm
	Op	PF[2] - 55 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
RBRF1 (WW_RBRF1)		
	Mod	CBF - 50BF, 62BF . active CBF - 50BF, 62BF . ExBlo CBF - 50BF, 62BF . ExBlo
	Beh	
	Health	
	NamPlt	
	Str	CBF - 50BF, 62BF . running
	OpEx	CBF - 50BF, 62BF . Alarm

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
RTDPTTR1 (WW_PTTR4)		
	Mod	RTD . active RTD . Blo TripCmd RTD . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Op	RTD . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
TMPTTR1 (WW_PTTR2)		
	Mod	ThR . active ThR . Blo TripCmd ThR . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	ThR . Alarm
	Op	ThR . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
ULPTOC1 (WW_PTOC4)		
	Mod	I2>[1] - 46 . active I2>[1] - 46 . Blo TripCmd I2>[1] - 46 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	I2>[1] - 46 . Alarm
	Op	I2>[1] - 46 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
ULPTOC2 (WW_PTOC4)		
	Mod	I2>[2] - 46 . active I2>[2] - 46 . Blo TripCmd I2>[2] - 46 . ExBlo TripCmd

4 Appendix

4.1 Register Maps

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
ULPTOC2 (WW_PTOC4)		
	Beh	
	Health	
	NamPlt	
	Str	I2>[2] - 46 . Alarm
	Op	I2>[2] - 46 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
ULPTUC1 (WW_PTUC1)		
	Mod	I<[1] - 37 . active I<[1] - 37 . Blo TripCmd I<[1] - 37 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	I<[1] - 37 . Alarm
	Op	I<[1] - 37 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
ULPTUC2 (WW_PTUC1)		
	Mod	I<[2] - 37 . active I<[2] - 37 . Blo TripCmd I<[2] - 37 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	I<[2] - 37 . Alarm
	Op	I<[2] - 37 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
ULPTUC3 (WW_PTUC1)		
	Mod	I<[3] - 37 . active I<[3] - 37 . Blo TripCmd I<[3] - 37 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	I<[3] - 37 . Alarm
	Op	I<[3] - 37 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
VAPTOV1* (WW_PTOV3)		
	Mod	V012[1] - 47 . active V012[1] - 47 . Blo TripCmd V012[1] - 47 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V012[1] - 47 . Alarm
	Op	V012[1] - 47 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
VAPTOV2* (WW_PTOV3)		
	Mod	V012[2] - 47 . active V012[2] - 47 . Blo TripCmd V012[2] - 47 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V012[2] - 47 . Alarm
	Op	V012[2] - 47 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
VAPTOV3* (WW_PTOV3)		
	Mod	V012[3] - 47 . active V012[3] - 47 . Blo TripCmd V012[3] - 47 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V012[3] - 47 . Alarm
	Op	V012[3] - 47 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
VAPTOV4* (WW_PTOV3)		
	Mod	V012[4] - 47 . active V012[4] - 47 . Blo TripCmd V012[4] - 47 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V012[4] - 47 . Alarm
	Op	V012[4] - 47 . Trip

4 Appendix

4.1 Register Maps

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
VAPTOV5* (WW_PTOV3)		
	Mod	V012[5] - 47 . active V012[5] - 47 . Blo TripCmd V012[5] - 47 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V012[5] - 47 . Alarm
	Op	V012[5] - 47 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
VAPTOV6* (WW_PTOV3)		
	Mod	V012[6] - 47 . active V012[6] - 47 . Blo TripCmd V012[6] - 47 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V012[6] - 47 . Alarm
	Op	V012[6] - 47 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
VAPTUV1* (WW_PTUV3)		
	Mod	V012[1] - 47 . active V012[1] - 47 . Blo TripCmd V012[1] - 47 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V012[1] - 47 . Alarm
	Op	V012[1] - 47 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
VAPTUV2* (WW_PTUV3)		
	Mod	V012[2] - 47 . active V012[2] - 47 . Blo TripCmd V012[2] - 47 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V012[2] - 47 . Alarm
	Op	V012[2] - 47 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
VAPTVU3* (WW_PTUV3)		
	Mod	V012[3] - 47 . active V012[3] - 47 . Blo TripCmd V012[3] - 47 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V012[3] - 47 . Alarm
	Op	V012[3] - 47 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
VAPTVU4* (WW_PTUV3)		
	Mod	V012[4] - 47 . active V012[4] - 47 . Blo TripCmd V012[4] - 47 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V012[4] - 47 . Alarm
	Op	V012[4] - 47 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
VAPTVU5* (WW_PTUV3)		
	Mod	V012[5] - 47 . active V012[5] - 47 . Blo TripCmd V012[5] - 47 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V012[5] - 47 . Alarm
	Op	V012[5] - 47 . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
VAPTVU6* (WW_PTUV3)		
	Mod	V012[6] - 47 . active V012[6] - 47 . Blo TripCmd V012[6] - 47 . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V012[6] - 47 . Alarm
	Op	V012[6] - 47 . Trip

4 Appendix

4.1 Register Maps

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
VSPTOV1* (WW_PTOV1)		
	Mod	VG[1] - 27A, 59N,A . active VG[1] - 27A, 59N,A . Blo TripCmd VG[1] - 27A, 59N,A . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	VG[1] - 27A, 59N,A . Alarm
	Op	VG[1] - 27A, 59N,A . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
VSPTOV2* (WW_PTOV1)		
	Mod	VG[2] - 27A, 59N,A . active VG[2] - 27A, 59N,A . Blo TripCmd VG[2] - 27A, 59N,A . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	VG[2] - 27A, 59N,A . Alarm
	Op	VG[2] - 27A, 59N,A . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
VSPTUV1* (WW_PTUV1)		
	Mod	VG[1] - 27A, 59N,A . active VG[1] - 27A, 59N,A . Blo TripCmd VG[1] - 27A, 59N,A . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	VG[1] - 27A, 59N,A . Alarm
	Op	VG[1] - 27A, 59N,A . Trip

Logical Node	Data Object	Module (- ANSI/IEEE Device Number) . Name
VSPTUV2* (WW_PTUV1)		
	Mod	VG[2] - 27A, 59N,A . active VG[2] - 27A, 59N,A . Blo TripCmd VG[2] - 27A, 59N,A . ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	VG[2] - 27A, 59N,A . Alarm
	Op	VG[2] - 27A, 59N,A . Trip

4.2 Device Planning Dependencies

The availability of Logical Node instances in the generated ICD file depends on the settings in the “Device planning” menu.

The following list gives an overview about those settings for every module that have an effect on the availability of a Logical Node.

Module (- ANSI/IEEE Device Number) . Name	Value
CILO1	
SG[1] . SwitchgearType	Controlled SG
SG[1] . SwitchgearType	Controlled Make Break SG
CSWI1	
SG[1] . SwitchgearType	Controlled SG
SG[1] . SwitchgearType	Controlled Make Break SG
XCBR1	
SG[1] . SwitchgearType	Monitored Make Break SG
SG[1] . SwitchgearType	Controlled Make Break SG
XSWI1	
SG[1] . SwitchgearType	Monitored SG
SG[1] . SwitchgearType	Controlled SG
PDOP1	
PQS[1] - 32, 37 . Mode	P>
PQS[1] - 32, 37 . Mode	Pr>
PQS[1] - 32, 37 . Mode	Q>
PQS[1] - 32, 37 . Mode	Qr>
PQS[1] - 32, 37 . Mode	S>
PDOP2	
PQS[2] - 32, 37 . Mode	P>
PQS[2] - 32, 37 . Mode	Pr>
PQS[2] - 32, 37 . Mode	Q>
PQS[2] - 32, 37 . Mode	Qr>
PQS[2] - 32, 37 . Mode	S>
PDOP3	
PQS[3] - 32, 37 . Mode	P>
PQS[3] - 32, 37 . Mode	Pr>
PQS[3] - 32, 37 . Mode	Q>
PQS[3] - 32, 37 . Mode	Qr>
PQS[3] - 32, 37 . Mode	S>
PDOP4	

4 Appendix

4.2 Device Planning Dependencies

Module (- ANSI/IEEE Device Number) . Name	Value
PQS[4] - 32, 37 . Mode	P>
PQS[4] - 32, 37 . Mode	Pr>
PQS[4] - 32, 37 . Mode	Q>
PQS[4] - 32, 37 . Mode	Qr>
PQS[4] - 32, 37 . Mode	S>
PDOP5	
PQS[5] - 32, 37 . Mode	P>
PQS[5] - 32, 37 . Mode	Pr>
PQS[5] - 32, 37 . Mode	Q>
PQS[5] - 32, 37 . Mode	Qr>
PQS[5] - 32, 37 . Mode	S>
PDOP6	
PQS[6] - 32, 37 . Mode	P>
PQS[6] - 32, 37 . Mode	Pr>
PQS[6] - 32, 37 . Mode	Q>
PQS[6] - 32, 37 . Mode	Qr>
PQS[6] - 32, 37 . Mode	S>
PDUP1	
PQS[1] - 32, 37 . Mode	P<
PQS[1] - 32, 37 . Mode	Pr<
PQS[1] - 32, 37 . Mode	Q<
PQS[1] - 32, 37 . Mode	Qr<
PQS[1] - 32, 37 . Mode	S<
PDUP2	
PQS[2] - 32, 37 . Mode	P<
PQS[2] - 32, 37 . Mode	Pr<
PQS[2] - 32, 37 . Mode	Q<
PQS[2] - 32, 37 . Mode	Qr<
PQS[2] - 32, 37 . Mode	S<
PDUP3	
PQS[3] - 32, 37 . Mode	P<
PQS[3] - 32, 37 . Mode	Pr<
PQS[3] - 32, 37 . Mode	Q<
PQS[3] - 32, 37 . Mode	Qr<
PQS[3] - 32, 37 . Mode	S<
PDUP4	
PQS[4] - 32, 37 . Mode	P<

Module (- ANSI/IEEE Device Number) . Name	Value
PQS[4] - 32, 37 . Mode	Pr<
PQS[4] - 32, 37 . Mode	Q<
PQS[4] - 32, 37 . Mode	Qr<
PQS[4] - 32, 37 . Mode	S<
PDUP5	
PQS[5] - 32, 37 . Mode	P<
PQS[5] - 32, 37 . Mode	Pr<
PQS[5] - 32, 37 . Mode	Q<
PQS[5] - 32, 37 . Mode	Qr<
PQS[5] - 32, 37 . Mode	S<
PDUP6	
PQS[6] - 32, 37 . Mode	P<
PQS[6] - 32, 37 . Mode	Pr<
PQS[6] - 32, 37 . Mode	Q<
PQS[6] - 32, 37 . Mode	Qr<
PQS[6] - 32, 37 . Mode	S<
PFRC1	
f[1] - 81 . Mode	f< and df/dt
f[1] - 81 . Mode	f> and df/dt
f[1] - 81 . Mode	f< and DF/DT
f[1] - 81 . Mode	f> and DF/DT
f[1] - 81 . Mode	df/dt
PFRC2	
f[2] - 81 . Mode	f< and df/dt
f[2] - 81 . Mode	f> and df/dt
f[2] - 81 . Mode	f< and DF/DT
f[2] - 81 . Mode	f> and DF/DT
f[2] - 81 . Mode	df/dt
PFRC3	
f[3] - 81 . Mode	f< and df/dt
f[3] - 81 . Mode	f> and df/dt
f[3] - 81 . Mode	f< and DF/DT
f[3] - 81 . Mode	f> and DF/DT
f[3] - 81 . Mode	df/dt
PFRC4	
f[4] - 81 . Mode	f< and df/dt
f[4] - 81 . Mode	f> and df/dt

4 Appendix

4.2 Device Planning Dependencies

Module (- ANSI/IEEE Device Number) . Name	Value
f[4] - 81 . Mode	f< and DF/DT
f[4] - 81 . Mode	f> and DF/DT
f[4] - 81 . Mode	df/dt
PFRC5	
f[5] - 81 . Mode	f< and df/dt
f[5] - 81 . Mode	f> and df/dt
f[5] - 81 . Mode	f< and DF/DT
f[5] - 81 . Mode	f> and DF/DT
f[5] - 81 . Mode	df/dt
PFRC6	
f[6] - 81 . Mode	f< and df/dt
f[6] - 81 . Mode	f> and df/dt
f[6] - 81 . Mode	f< and DF/DT
f[6] - 81 . Mode	f> and DF/DT
f[6] - 81 . Mode	df/dt
PPAM1	
f[1] - 81 . Mode	delta phi
PPAM2	
f[2] - 81 . Mode	delta phi
PPAM3	
f[3] - 81 . Mode	delta phi
PPAM4	
f[4] - 81 . Mode	delta phi
PPAM5	
f[5] - 81 . Mode	delta phi
PPAM6	
f[6] - 81 . Mode	delta phi
PTOF1	
f[1] - 81 . Mode	f>
PTOF2	
f[2] - 81 . Mode	f>
PTOF3	
f[3] - 81 . Mode	f>
PTOF4	
f[4] - 81 . Mode	f>
PTOF5	
f[5] - 81 . Mode	f>

Module (- ANSI/IEEE Device Number) . Name	Value
PTOF6	
f[6] - 81 . Mode	f>
PTOV1	
V[1] - 27, 59 . Mode	V>
PTOV2	
V[2] - 27, 59 . Mode	V>
PTOV3	
V[3] - 27, 59 . Mode	V>
PTOV4	
V[4] - 27, 59 . Mode	V>
PTOV5	
V[5] - 27, 59 . Mode	V>
PTOV6	
V[6] - 27, 59 . Mode	V>
PTUF1	
f[1] - 81 . Mode	f<
PTUF2	
f[2] - 81 . Mode	f<
PTUF3	
f[3] - 81 . Mode	f<
PTUF4	
f[4] - 81 . Mode	f<
PTUF5	
f[5] - 81 . Mode	f<
PTUF6	
f[6] - 81 . Mode	f<
PTUV1	
V[1] - 27, 59 . Mode	V<
PTUV2	
V[2] - 27, 59 . Mode	V<
PTUV3	
V[3] - 27, 59 . Mode	V<
PTUV4	
V[4] - 27, 59 . Mode	V<
PTUV5	
V[5] - 27, 59 . Mode	V<
PTUV6	

4 Appendix


4.2 Device Planning Dependencies

Module (- ANSI/IEEE Device Number) . Name	Value
V[6] - 27, 59 . Mode	V<
VAPTOV1	
V012[1] - 47 . Mode	V1>
V012[1] - 47 . Mode	V2>
VAPTOV2	
V012[2] - 47 . Mode	V1>
V012[2] - 47 . Mode	V2>
VAPTOV3	
V012[3] - 47 . Mode	V1>
V012[3] - 47 . Mode	V2>
VAPTOV4	
V012[4] - 47 . Mode	V1>
V012[4] - 47 . Mode	V2>
VAPTOV5	
V012[5] - 47 . Mode	V1>
V012[5] - 47 . Mode	V2>
VAPTOV6	
V012[6] - 47 . Mode	V1>
V012[6] - 47 . Mode	V2>
VAPTUV1	
V012[1] - 47 . Mode	V1<
VAPTUV2	
V012[2] - 47 . Mode	V1<
VAPTUV3	
V012[3] - 47 . Mode	V1<
VAPTUV4	
V012[4] - 47 . Mode	V1<
VAPTUV5	
V012[5] - 47 . Mode	V1<
VAPTUV6	
V012[6] - 47 . Mode	V1<
VSPTOV1	
VG[1] - 27A, 59N,A . Mode	V>
VSPTOV2	
VG[2] - 27A, 59N,A . Mode	V>
VSPTUV1	
VG[1] - 27A, 59N,A . Mode	V<

Module (- ANSI/IEEE Device Number) . Name	Value
VSPTUV2	
VG[2] - 27A, 59N,A . Mode	V<

High PRO TEC

docs.SEGelectronics.de/HighPROTEC



SEG Electronics GmbH reserves the right to update any portion of this publication at any time.
Information provided by SEG Electronics GmbH is believed to be correct and reliable. However, SEG
Electronics GmbH assumes no responsibility unless otherwise expressly undertaken.

SEG
electronics

SEG Electronics GmbH
Krefelder Weg 47 • D-47906 Kempen (Germany)
Postfach 10 07 55 (P.O.Box) • D-47884 Kempen (Germany)
Telephone: +49 (0) 21 52 145 1

Internet: www.SEGelectronics.de

Sales
Telephone: +49 (0) 21 52 145 331
Fax: +49 (0) 21 52 145 354

Service
Telephone: +49 (0) 21 52 145 614
Fax: +49 (0) 21 52 145 354

SEG Electronics has company-owned plants, subsidiaries, and branches, as well
as authorized distributors and other authorized service and sales facilities
throughout the world.

Complete address / phone / fax / email information for all locations is
available on our website.