



High**PROTEC**

IEC 61850 | MICS

**MCDGV4**

Software-Version: 2.4.a

Model Implementation Conformance Statement (MICS)

UCA International Users Group Testing Sub Committee

English

---

# INDEX

1.	Introduction.....	5
2.	Logical Nodes.....	6
2.1.	Logical Nodes List.....	6
2.2.	Logical Node definitions.....	7
2.2.1	WW CILO1.....	10
2.2.2	WW CSW1.....	10
2.2.3	WW GGIO3.....	11
2.2.4	WW GGIO4.....	11
2.2.5	WW GGIO5.....	12
2.2.6	WW IHMI1.....	13
2.2.7	WW LLN0CON.....	13
2.2.8	WW LLN0MEA.....	14
2.2.9	WW LLN0PRO.....	14
2.2.10	WW LLN0REC.....	14
2.2.11	WW LLN0SYS.....	14
2.2.12	WW LPHDCON.....	15
2.2.13	WW LPHDMEA.....	15
2.2.14	WW LPHDPRO.....	15
2.2.15	WW LPHDREC.....	15
2.2.16	WW LPHDSYS.....	16
2.2.17	WW MMXU1.....	16
2.2.18	WW MMXU2.....	16
2.2.19	WW MMXU3.....	17
2.2.20	WW MSTA1.....	17
2.2.21	WW MSTA2.....	17
2.2.22	WW MSTA3.....	18
2.2.23	WW PDIF1.....	18
2.2.24	WW PDIF2.....	19
2.2.25	WW PDIF3.....	19
2.2.26	WW PDIF4.....	19
2.2.27	WW PDOP1.....	20
2.2.28	WW PDUP1.....	20
2.2.29	WW PDUP2.....	20

---

2.2.30	WW PFRC1.....	21
2.2.31	WW PHAR1.....	21
2.2.32	WW PIOC1.....	21
2.2.33	WW PPAM1.....	22
2.2.34	WW PSOF1.....	22
2.2.35	WW PTOC1.....	22
2.2.36	WW PTOC3.....	22
2.2.37	WW PTOC4.....	23
2.2.38	WW PTOF1.....	23
2.2.39	WW PTOV1.....	23
2.2.40	WW PTOV2.....	24
2.2.41	WW PTOV3.....	24
2.2.42	WW PTTR1.....	24
2.2.43	WW PTTR3.....	25
2.2.44	WW PTUF1.....	25
2.2.45	WW PTUV1.....	25
2.2.46	WW PTUV2.....	26
2.2.47	WW PUPF1.....	26
2.2.48	WW PVPH1.....	26
2.2.49	WW RBRF1.....	26
2.2.50	WW RDRE1.....	27
2.2.51	WW RSYN2.....	27
2.2.52	WW XCBR2.....	28
2.2.53	WW XSWI1.....	28
3.	Common Data Class.....	29
3.1.	Common Data Class definitions.....	29
3.1.1	WW ACD1.....	29
3.1.2	WW ACT1.....	30
3.1.3	WW CMV1.....	30
3.1.4	WW DEL1.....	30
3.1.5	WW DPC1.....	30
3.1.6	WW DPC2.....	30
3.1.7	WW DPL1.....	31
3.1.8	WW INC1.....	31
3.1.9	WW INS1.....	31

---

---

3.1.10	WW INS2.....	31
3.1.11	WW INS3.....	32
3.1.12	WW INS5.....	32
3.1.13	WW LPL1.....	32
3.1.14	WW LPL2.....	32
3.1.15	WW LPL3.....	32
3.1.16	WW MV1.....	32
3.1.17	WW SPC1.....	33
3.1.18	WW SPC2.....	33
3.1.19	WW SPS1.....	33
3.1.20	WW WYE1.....	33
3.2.	Common Data Attributes type definitions.....	34
3.2.1	WW analogValue1.....	34
3.2.2	WW Cancel1.....	34
3.2.3	WW Oper1.....	34
3.2.4	WW origin1.....	34
3.2.5	WW units1.....	34
3.2.6	WW vector1.....	34
3.3.	Enumerated type definitions.....	35
3.3.1	Beh.....	35
3.3.2	CBOPcap.....	35
3.3.3	ctlModel.....	35
3.3.4	Dbpos.....	35
3.3.5	dir.....	35
3.3.6	Health.....	36
3.3.7	Mod.....	36
3.3.8	multiplier.....	36
3.3.9	orCategory.....	36
3.3.10	sboClass.....	37
3.3.11	SIUnit.....	37
4.	Appendix – Register Maps.....	39
4.1.	Device Planing Dependencies.....	77

# 1. Introduction

This model implementation conformance statement is applicable to the device MCDGV4, Version 2.4.a (Firmware-Build 24038).

This MICS document specifies the modelling extensions compared to IEC 61850 edition 1.

Clause 2 contains the list of implemented logical nodes.

Clause 3 describes the new and extended logical nodes.

Clause 4 describes the existing common data classes.

Clause 5 describes the existing enum types.

## 2. Logical Nodes

### 2.1. Logical Nodes List

The following table contains the list of logical nodes implemented in the device:

<b>L : System Logical Nodes</b>
LLN0 (Logical Node device)
LPHD (Physical device)
<b>P : Logical Nodes for protection functions</b>
PDIF (Differential)
PDOP (Directional overpower)
PDUP (Directional underpower)
PFRC (Rate of change of frequency)
PHAR (Harmonic restraint)
PIOC (Instantaneous overcurrent)
PPAM (Phase angle or out-of-step protection)
PSOF (Switch Onto Fault)
PTOC (Time overcurrent)
PTOF (Overfrequency)
PTOV (Overvoltage)
PTTR (Thermal overload protection)
PTUF (Underfrequency)
PTUV (Undervoltage)
PUPF (Underpower factor)
PVPH (Volts per Hz)

<b>R : Logical Nodes for protection related functions</b>
RBRF (Breaker failure)
RDRE (Disturbance recorder function)
RSYN (Synchronism-check or synchronising)
<b>G : Logical Nodes for generic references</b>
GGIO (Generic process I/O)
<b>M : Logical Nodes for metering and measurement</b>
MMXU (Measurement)
MSTA (Metering Statistics)
<b>X : Logical Nodes for switchgear</b>
XCBR (Circuit Breaker)
XSWI (Circuit Switch)
<b>C : Logical Nodes for control</b>
CILO (Interlocking)
CSWI (Switch controller)
<b>I : Logical Nodes for interfacing and archiving</b>
IHMI (Human machine interface)

## 2.2. Logical Node definitions

The following table use

- M: Data is mandatory in the IEC-61850-7-4.
- O: Data is optional in the IEC-61850-7-4 and is used in the device.
- E: Data is an extension to the IEC-61850-7-4.

LN Type	LN Class	Description
WW_CILO1	CILO	Interlocking

LN Type	LN Class	Description
WW_CSWI1	CSWI	Switch controller
WW_GGIO3	GGIO	Generic process I/O
WW_GGIO4	GGIO	Generic process I/O
WW_GGIO5	GGIO	Generic process I/O
WW_IHMI1	IHMI	Human machine interface
WW_LLNOCON	LLNO	Logical Node device
WW_LLNOMEA	LLNO	Logical Node device
WW_LLNOPRO	LLNO	Logical Node device
WW_LLNOREC	LLNO	Logical Node device
WW_LLNOSYS	LLNO	Logical Node device
WW_LPHDCON	LPHD	Physical device
WW_LPHDMEA	LPHD	Physical device
WW_LPHDPRO	LPHD	Physical device
WW_LPHDREC	LPHD	Physical device
WW_LPHDSYS	LPHD	Physical device
WW_MMXU1	MMXU	Measurement
WW_MMXU2	MMXU	Measurement
WW_MMXU3	MMXU	Measurement
WW_MSTA1	MSTA	Metering Statistics
WW_MSTA2	MSTA	Metering Statistics
WW_MSTA3	MSTA	Metering Statistics
WW_PDIF1	PDIF	Differential



LN Type	LN Class	Description
WW_PDIF2	PDIF	Differential
WW_PDIF3	PDIF	Differential
WW_PDIF4	PDIF	Differential
WW_PDOP1	PDOP	Directional overpower
WW_PDUP1	PDUP	Directional underpower
WW_PDUP2	PDUP	Directional underpower
WW_PFRC1	PFRC	Rate of change of frequency
WW_PHAR1	PHAR	Harmonic restraint
WW_PIOC1	PIOC	Instantaneous overcurrent
WW_PPAM1	PPAM	Phase angle or out-of-step protection
WW_PSOFF1	PSOF	Switch Onto Fault
WW_PTOC1	PTOC	Time overcurrent
WW_PTOC3	PTOC	Time overcurrent
WW_PTOC4	PTOC	Time overcurrent
WW_PTOF1	PTOF	Overfrequency
WW_PTOV1	PTOV	Overvoltage
WW_PTOV2	PTOV	Overvoltage
WW_PTOV3	PTOV	Overvoltage
WW_PTTR1	PTTR	Thermal overload protection
WW_PTTR3	PTTR	Thermal overload protection
WW_PTUF1	PTUF	Underfrequency
WW_PTUV1	PTUV	Undervoltage

LN Type	LN Class	Description
WW_PTUV2	PTUV	Undervoltage
WW_PUPF1	PUPF	Underpower factor
WW_PVPH1	PVPH	Volts per Hz
WW_RBRF1	RBRF	Breaker failure
WW_RDRE1	RDRE	Disturbance recorder function
WW_RSYN2	RSYN	Synchroncheck
WW_XCBR2	XCBR	Circuit Breaker
WW_XSWI1	XSWI	Circuit Switch

### 2.2.1 WW\_CILO1

CILO class				
Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
CILO	WW_CILO1	Interlocking		
Data				
Common Logical Node Information				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behavior	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
Status Information				
EnaOpn	WW_SPS1	Enable Open	M	
EnaCls	WW_SPS1	Enable Close	M	

### 2.2.2 WW\_CSWI1

CSWI class				
Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
CSWI	WW_CSWI1	Switch Controller		
Data				
Common Logical Node Information				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
Loc	WW_SPS1	Local operation	O	
Controls				
Pos	WW_DPC2	Switch position	M	

2.2.3 WW\_GGIO3

GGIO class				
Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
GGIO		Generic process I/O		
Data				
Common Logical Node Information				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
Status information				
Ind1	WW_SPS1	General indication (binary input)	O	
Ind2	WW_SPS1	General indication (binary input)	O	
Ind3	WW_SPS1	General indication (binary input)	O	
Ind4	WW_SPS1	General indication (binary input)	O	
Ind5	WW_SPS1	General indication (binary input)	O	
Ind6	WW_SPS1	General indication (binary input)	O	
Ind7	WW_SPS1	General indication (binary input)	O	
Ind8	WW_SPS1	General indication (binary input)	O	
Ind9	WW_SPS1	General indication (binary input)	O	
Ind10	WW_SPS1	General indication (binary input)	O	
Ind11	WW_SPS1	General indication (binary input)	O	
Ind12	WW_SPS1	General indication (binary input)	O	
Ind13	WW_SPS1	General indication (binary input)	O	
Ind14	WW_SPS1	General indication (binary input)	O	
Ind15	WW_SPS1	General indication (binary input)	O	
Ind16	WW_SPS1	General indication (binary input)	O	
Ind17	WW_SPS1	General indication (binary input)	O	
Ind18	WW_SPS1	General indication (binary input)	O	
Ind19	WW_SPS1	General indication (binary input)	O	
Ind20	WW_SPS1	General indication (binary input)	O	
Ind21	WW_SPS1	General indication (binary input)	O	
Ind22	WW_SPS1	General indication (binary input)	O	
Ind23	WW_SPS1	General indication (binary input)	O	
Ind24	WW_SPS1	General indication (binary input)	O	
Ind25	WW_SPS1	General indication (binary input)	O	
Ind26	WW_SPS1	General indication (binary input)	O	
Ind27	WW_SPS1	General indication (binary input)	O	
Ind28	WW_SPS1	General indication (binary input)	O	
Ind29	WW_SPS1	General indication (binary input)	O	
Ind30	WW_SPS1	General indication (binary input)	O	
Ind31	WW_SPS1	General indication (binary input)	O	
Ind32	WW_SPS1	General indication (binary input)	O	

2.2.4 WW\_GGIO4

GGIO class				
Attribute Name	Attribute Type	Explanation	M/O/E	Remarks

GGIO		Generic process I/O		
<b>Data</b>				
<b>Common Logical Node Information</b>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<b>Status information</b>				
Ind1	WW_SPS1	General indication (binary input)	O	
Ind2	WW_SPS1	General indication (binary input)	O	
Ind3	WW_SPS1	General indication (binary input)	O	
Ind4	WW_SPS1	General indication (binary input)	O	
Ind5	WW_SPS1	General indication (binary input)	O	
Ind6	WW_SPS1	General indication (binary input)	O	
Ind7	WW_SPS1	General indication (binary input)	O	
Ind8	WW_SPS1	General indication (binary input)	O	
Ind9	WW_SPS1	General indication (binary input)	O	
Ind10	WW_SPS1	General indication (binary input)	O	
Ind11	WW_SPS1	General indication (binary input)	O	
Ind12	WW_SPS1	General indication (binary input)	O	
Ind13	WW_SPS1	General indication (binary input)	O	
Ind14	WW_SPS1	General indication (binary input)	O	
Ind15	WW_SPS1	General indication (binary input)	O	
Ind16	WW_SPS1	General indication (binary input)	O	
Ind17	WW_SPS1	General indication (binary input)	O	
Ind18	WW_SPS1	General indication (binary input)	O	
Ind19	WW_SPS1	General indication (binary input)	O	
Ind20	WW_SPS1	General indication (binary input)	O	
Ind21	WW_SPS1	General indication (binary input)	O	
Ind22	WW_SPS1	General indication (binary input)	O	
Ind23	WW_SPS1	General indication (binary input)	O	
Ind24	WW_SPS1	General indication (binary input)	O	
Ind25	WW_SPS1	General indication (binary input)	O	
Ind26	WW_SPS1	General indication (binary input)	O	
Ind27	WW_SPS1	General indication (binary input)	O	
Ind28	WW_SPS1	General indication (binary input)	O	
Ind29	WW_SPS1	General indication (binary input)	O	
Ind30	WW_SPS1	General indication (binary input)	O	
Ind31	WW_SPS1	General indication (binary input)	O	
Ind32	WW_SPS1	General indication (binary input)	O	

### 2.2.5 WW\_GGIO5

<b>GGIO class</b>				
<b>Attribute Name</b>	<b>Attribute Type</b>	<b>Explanation</b>	<b>M/O/E</b>	<b>Remarks</b>
GGIO		Generic process I/O		
<b>Data</b>				
<b>Common Logical Node Information</b>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	

NamPlt	WW_LPL1	Name plate	M	
<b>Status information</b>				
SPCSO1	WW_SPC2	Single point controllable status output	O	
SPCSO2	WW_SPC2	Single point controllable status output	O	
SPCSO3	WW_SPC2	Single point controllable status output	O	
SPCSO4	WW_SPC2	Single point controllable status output	O	
SPCSO5	WW_SPC2	Single point controllable status output	O	
SPCSO6	WW_SPC2	Single point controllable status output	O	
SPCSO7	WW_SPC2	Single point controllable status output	O	
SPCSO8	WW_SPC2	Single point controllable status output	O	
SPCSO9	WW_SPC2	Single point controllable status output	O	
SPCSO10	WW_SPC2	Single point controllable status output	O	
SPCSO11	WW_SPC2	Single point controllable status output	O	
SPCSO12	WW_SPC2	Single point controllable status output	O	
SPCSO13	WW_SPC2	Single point controllable status output	O	
SPCSO14	WW_SPC2	Single point controllable status output	O	
SPCSO15	WW_SPC2	Single point controllable status output	O	
SPCSO16	WW_SPC2	Single point controllable status output	O	
SPCSO17	WW_SPC2	Single point controllable status output	O	
SPCSO18	WW_SPC2	Single point controllable status output	O	
SPCSO19	WW_SPC2	Single point controllable status output	O	
SPCSO20	WW_SPC2	Single point controllable status output	O	
SPCSO21	WW_SPC2	Single point controllable status output	O	
SPCSO22	WW_SPC2	Single point controllable status output	O	
SPCSO23	WW_SPC2	Single point controllable status output	O	
SPCSO24	WW_SPC2	Single point controllable status output	O	
SPCSO25	WW_SPC2	Single point controllable status output	O	
SPCSO26	WW_SPC2	Single point controllable status output	O	
SPCSO27	WW_SPC2	Single point controllable status output	O	
SPCSO28	WW_SPC2	Single point controllable status output	O	
SPCSO29	WW_SPC2	Single point controllable status output	O	
SPCSO30	WW_SPC2	Single point controllable status output	O	
SPCSO31	WW_SPC2	Single point controllable status output	O	
SPCSO32	WW_SPC2	Single point controllable status output	O	

### 2.2.6 WW\_IHMI1

<b>IHMI class</b>				
<b>Attribute Name</b>	<b>Attribute Type</b>	<b>Explanation</b>	<b>M/O/E</b>	<b>Remarks</b>
IHMI	WW_IHMI1	Human machine interface		
<b>Data</b>				
<b>Common Logical Node Information</b>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	

### 2.2.7 WW\_LLNOCON

<b>LLNO class</b>				
<b>Attribute</b>	<b>Attribute</b>	<b>Explanation</b>	<b>M/O/E</b>	<b>Remarks</b>

Name	Type			
LLN0	WW_LLNOCON	Logical Node device		
<b>Data</b>				
<b>Common Logical Node Information</b>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL2	Name plate	M	

### 2.2.8 WW\_LLNOMEA

LLN0 class				
Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
LLN0	WW_LLNOMEA	Logical Node device		
<b>Data</b>				
<b>Common Logical Node Information</b>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL2	Name plate	M	

### 2.2.9 WW\_LLNOPRO

LLN0 class				
Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
LLN0	WW_LLNOPRO	Logical Node device		
<b>Data</b>				
<b>Common Logical Node Information</b>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL2	Name plate	M	

### 2.2.10 WW\_LLNOREC

LLN0 class				
Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
LLN0	WW_LLNOREC	Logical Node device		
<b>Data</b>				
<b>Common Logical Node Information</b>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL2	Name plate	M	

### 2.2.11 WW\_LLNOSYS

LLN0 class				
------------	--	--	--	--

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
LLNO	WW_LLNO SYS	Logical Node device		
<b>Data</b>				
<b>Common Logical Node Information</b>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL2	Name plate	M	

### 2.2.12 WW\_LPHDCON

<b>LPHD class</b>				
Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
LPHD	WW_LPHDCON	Physical device information		
<b>Data</b>				
<b>Common Logical Node Information</b>				
PhyNam	WW_DPL1	Physical device name plate	M	
PhyHealth	WW_INS3	Physical Device Health	M	
Proxy	WW_SPS1	Indicates if this LN is a proxy	M	

### 2.2.13 WW\_LPHDMEA

<b>LPHD class</b>				
Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
LPHD	WW_LPHDMEA	Physical device information		
<b>Data</b>				
<b>Common Logical Node Information</b>				
PhyNam	WW_DPL1	Physical device name plate	M	
PhyHealth	WW_INS3	Physical Device Health	M	
Proxy	WW_SPS1	Indicates if this LN is a proxy	M	

### 2.2.14 WW\_LPHDPRO

<b>LPHD class</b>				
Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
LPHD	WW_LPHDPRO	Physical device information		
<b>Data</b>				
<b>Common Logical Node Information</b>				
PhyNam	WW_DPL1	Physical device name plate	M	
PhyHealth	WW_INS3	Physical Device Health	M	
Proxy	WW_SPS1	Indicates if this LN is a proxy	M	

### 2.2.15 WW\_LPHDREC

<b>LPHD class</b>				
Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
LPHD	WW_LPHDREC	Physical device information		

Data				
Common Logical Node Information				
PhyNam	WW_DPL1	Physical device name plate	M	
PhyHealth	WW_INS3	Physical Device Health	M	
Proxy	WW_SPS1	Indicates if this LN is a proxy	M	

### 2.2.16 WW\_LPHDSYS

LPHD class				
Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
LPHD	WW_LPHDSYS	Physical device information		
Data				
Common Logical Node Information				
PhyNam	WW_DPL1	Physical device name plate	M	
PhyHealth	WW_INS3	Physical Device Health	M	
Proxy	WW_SPS1	Indicates if this LN is a proxy	M	

### 2.2.17 WW\_MMXU1

MMXU class				
Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
MMXU	WW_MMXU1	Measurement		
Data				
Common Logical Node Information				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
Measured values				
A	WW_WYE1	Phase currents (IL1, IL2, IL3)	O	

### 2.2.18 WW\_MMXU2

MMXU class				
Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
MMXU	WW_MMXU2	Measurement		
Data				
Common Logical Node Information				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
Measured values				
PPV	WW_DEL1	Phase to phase voltages (UL12, UL23, UL31)	O	
PhV	WW_WYE1	Phase to ground voltages (UL1, UL2, UL3)	O	



2.2.19 WW\_MMXU3

MMXU class				
Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
MMXU	WW_MMXU3	Measurement		
Data				
Common Logical Node Information				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
Measured values				
TotW	WW_MV1	Total Active Power (Total P)	O	
TotVAr	WW_MV1	Total Reactive Power (Total Q)	O	
TotVA	WW_MV1	Total Apparent Power (Total S)	O	
TotPF	WW_MV1	Total Power factor (Total PF)	O	

2.2.20 WW\_MSTA1

MSTA class				
Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
MSTA	WW_MSTA1	Metering Statistics		
Data				
Common Logical Node Information				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
Metered values				
AvAPhA	WW_MV1	Average current IL1	E	
AvAPhB	WW_MV1	Average current IL2	E	
AvAPhC	WW_MV1	Average current IL3	E	
MaxAPhA	WW_MV1	Maximum current IL1	E	
MaxAPhB	WW_MV1	Maximum current IL2	E	
MaxAPhC	WW_MV1	Maximum current IL3	E	
MinAPhA	WW_MV1	Minimum current IL1	E	
MinAPhB	WW_MV1	Minimum current IL2	E	
MinAPhC	WW_MV1	Minimum current IL3	E	

2.2.21 WW\_MSTA2

MSTA class				
Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
MSTA	WW_MSTA2	Metering Statistics		
Data				
Common Logical Node Information				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	

Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<b>Metered values</b>				
AvVPhAB	WW_MV1	Average voltage UL12	E	
AvVPhBC	WW_MV1	Average voltage UL23	E	
AvVPhCA	WW_MV1	Average voltage UL31	E	
MaxVPhAB	WW_MV1	Maximum voltage UL12	E	
MaxVPhBC	WW_MV1	Maximum voltage UL23	E	
MaxVPhCA	WW_MV1	Maximum voltage UL31	E	
MinVPhAB	WW_MV1	Minimum voltage UL12	E	
MinVPhBC	WW_MV1	Minimum voltage UL23	E	
MinVPhCA	WW_MV1	Minimum voltage UL31	E	
AvVPhA	WW_MV1	Average voltage UL1	E	
AvVPhB	WW_MV1	Average voltage UL2	E	
AvVPhC	WW_MV1	Average voltage UL3	E	
MaxVPhA	WW_MV1	Maximum voltage UL1	E	
MaxVPhB	WW_MV1	Maximum voltage UL2	E	
MaxVPhC	WW_MV1	Maximum voltage UL3	E	
MinVPhA	WW_MV1	Minimum voltage UL1	E	
MinVPhB	WW_MV1	Minimum voltage UL2	E	
MinVPhB	WW_MV1	Minimum voltage UL3	E	

### 2.2.22 WW\_MSTA3

<b>MSTA class</b>				
Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
MSTA	WW_MSTA3	Metering Statistics		
<b>Data</b>				
<b>Common Logical Node Information</b>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<b>Metered values</b>				
AvVA	WW_MV1	Average apparent power	O	
MaxVA	WW_MV1	Maximum apparent power	O	
MinVA	WW_MV1	Minimum apparent power	O	
Avw	WW_MV1	Average real power	O	
MaxW	WW_MV1	Maximum real power	O	
MinW	WW_MV1	Minimum real power	O	
AvVAr	WW_MV1	Average reactive power	O	
MaxVAr	WW_MV1	Maximum reactive power	O	
MinVAr	WW_MV1	Minimum reactive power	O	

### 2.2.23 WW\_PDIF1

<b>PDIF class</b>				
Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PDIF	WW_PDIF1	Differential		

Data				
Common Logical Node Information				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
Status Information				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

### 2.2.24 WW\_PDIF2

PDIF class				
Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PDIF	WW_PDIF2	Differential		
Data				
Common Logical Node Information				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
Status Information				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

### 2.2.25 WW\_PDIF3

PDIF class				
Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PDIF	WW_PDIF3	Differential		
Data				
Common Logical Node Information				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
Status Information				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

### 2.2.26 WW\_PDIF4

PDIF class				
Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PDIF	WW_PDIF4	Differential		
Data				
Common Logical Node Information				
Mod	WW_INC1	Mode	M	Status-only

Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<b>Status Information</b>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

2.2.27 WW\_PDOP1

<b>PDOP class</b>				
Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PDOP	WW_PDOP1	Directional overpower		
<b>Data</b>				
<b>Common Logical Node Information</b>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<b>Status Information</b>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

2.2.28 WW\_PDUP1

<b>PDUP class</b>				
Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PDUP	WW_PDUP1	Directional underpower		
<b>Data</b>				
<b>Common Logical Node Information</b>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<b>Status Information</b>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

2.2.29 WW\_PDUP2

<b>PDUP class</b>				
Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PDUP	WW_PDUP2	Directional underpower		
<b>Data</b>				
<b>Common Logical Node Information</b>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	

Status Information				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

### 2.2.30 WW\_PFRC1

PFRC class				
Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PFRC	WW_PFRC1	Rate of change of frequency		
Data				
Common Logical Node Information				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
Status Information				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

### 2.2.31 WW\_PHAR1

PHAR class				
Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PHAR	WW_PHAR1	Harmonic restraint		
Data				
Common Logical Node Information				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
Status Information				
Str	WW_ACD1	Start	M	

### 2.2.32 WW\_PIOC1

PIOC class				
Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PIOC	WW_PIOC1	Instantaneous overcurrent		
Data				
Common Logical Node Information				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
Status Information				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

### 2.2.33 WW\_PPAM1

PPAM class				
Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PPAM	WW_PPAM1	Phase angle measuring		
Data				
Common Logical Node Information				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
Status Information				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

### 2.2.34 WW\_PSO1

PSOF class				
Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PSOF	WW_PSO1	Protection Switch Onto fault		
Data				
Common Logical Node Information				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL3	Name plate	M	
Status Information				
Str	WW_ACD1	Start	M	

This is new logical node.

### 2.2.35 WW\_PTOC1

PTOC class				
Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PTOC	WW_PTOC1	Time overcurrent		
Data				
Common Logical Node Information				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
Status Information				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

### 2.2.36 WW\_PTOC3

PTOC class				
------------	--	--	--	--

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PTOC	WW_PTOC3	Time overcurrent		
<b>Data</b>				
<b>Common Logical Node Information</b>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<b>Status Information</b>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

2.2.37 WW\_PTOC4

PTOC class				
Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PTOC	WW_PTOC4	Time overcurrent		
<b>Data</b>				
<b>Common Logical Node Information</b>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<b>Status Information</b>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

2.2.38 WW\_PTOF1

PTOF class				
Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PTOF	WW_PTOF1	Overfrequency		
<b>Data</b>				
<b>Common Logical Node Information</b>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<b>Status Information</b>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

2.2.39 WW\_PTOV1

PTOV class				
Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PTOV	WW_PTOV1	Overvoltage		
<b>Data</b>				

Common Logical Node Information				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
Status Information				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

### 2.2.40 WW\_PTOV2

PTOV class				
Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PTOV	WW_PTOV2	Overvoltage		
Data				
Common Logical Node Information				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
Status Information				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

### 2.2.41 WW\_PTOV3

PTOV class				
Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PTOV	WW_PTOV3	Overvoltage		
Data				
Common Logical Node Information				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
Status Information				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

### 2.2.42 WW\_PTTR1

PTTR class				
Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PTTR	WW_PTTR1	Thermal overload		
Data				
Common Logical Node Information				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	



Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<b>Status Information</b>				
Op	WW_ACT1	Operate	M	

### 2.2.43 WW\_PTTR3

PTTR class				
Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PTTR	WW_PTTR3	Thermal overload		
<b>Data</b>				
<b>Common Logical Node Information</b>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<b>Status Information</b>				
Op	WW_ACT1	Operate	M	

### 2.2.44 WW\_PTUF1

PTUF class				
Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PTUF	WW_PTUF1	Underfrequency		
<b>Data</b>				
<b>Common Logical Node Information</b>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<b>Status Information</b>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

### 2.2.45 WW\_PTUV1

PTUV class				
Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PTUV	WW_PTUV1	Undervoltage		
<b>Data</b>				
<b>Common Logical Node Information</b>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<b>Status Information</b>				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

2.2.46 WW\_PTUV2

PTUV class				
Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PTUV	WW_PTUV2	Undervoltage		
Data				
Common Logical Node Information				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
Status Information				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

2.2.47 WW\_PUPF1

PUPF class				
Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PUPF	WW_PUPF1	Underpower factor		
Data				
Common Logical Node Information				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
Status Information				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

2.2.48 WW\_PVPH1

PVPH class				
Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
PVPH	WW_PVPH1	Volts per Hz		
Data				
Common Logical Node Information				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
Status Information				
Str	WW_ACD1	Start	M	
Op	WW_ACT1	Operate	M	

2.2.49 WW\_RBRF1

RBRF class				
------------	--	--	--	--

Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
RBRF	WW_RBRF1	Breaker failure		
<b>Data</b>				
<b>Common Logical Node Information</b>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<b>Status Information</b>				
Str	WW_ACD1	Start	M	
OpEx	WW_ACT1	Breaker failure trip	M	

### 2.2.50 WW\_RDRE1

RDRE class				
Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
RDRE	WW_RDRE1	Disturbance recorder function		
<b>Data</b>				
<b>Common Logical Node Information</b>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<b>Status Information</b>				
RcdMade	WW_SPS1	Recording made	M	
FltNum	WW_INS2	Fault Number	M	
GriFltNum	WW_INS2	Grid Fault Number	O	
RcdStr	WW_SPS1	Recording startet	O	

### 2.2.51 WW\_RSYN2

RSYN class				
Attribute Name	Attribute Type	Explanation	M/O/E	Remarks
RSYN	WW_RSYN2	Synchronism-check or synchronising		
<b>Data</b>				
<b>Common Logical Node Information</b>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
<b>Status Information</b>				
Rel	WW_SPS1	Release	M	
AngInd	WW_SPS1	Phase Angle difference to high	E	
HzInd	WW_SPS1	Frequency difference to high	E	
VInd	WW_SPS1	Voltage difference to high	E	
<b>Measured Values</b>				
DifAngClc	WW_MV1	Phase Angle difference value	E	
DifHzClc	WW_MV1	Frequency difference value	E	
DifVClc	WW_MV1	Voltage difference value	E	

2.2.52 WW\_XCBR2

<b>XCBR class</b>				
<b>Attribute Name</b>	<b>Attribute Type</b>	<b>Explanation</b>	<b>M/O/E</b>	<b>Remarks</b>
XCBR	WW_XCBR2	Circuit Breaker		
<b>Data</b>				
<b>Common Logical Node Information</b>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
Loc	WW_SPS1	Local operation	M	
OpCnt	WW_INS2	Operation counter	M	
<b>Status Information</b>				
CBOpCap	WW_INS5	Circuit breaker operating capability	M	
<b>Controls</b>				
Pos	WW_DPC1	Switch position	M	
BlkOpn	WW_SPC1	Block opening	M	
BlkCls	WW_SPC1	Block closing	M	

2.2.53 WW\_XSWI1

<b>XSWI class</b>				
<b>Attribute Name</b>	<b>Attribute Type</b>	<b>Explanation</b>	<b>M/O/E</b>	<b>Remarks</b>
XSWI	WW_XSWI1	Circuit switch		
<b>Data</b>				
<b>Common Logical Node Information</b>				
Mod	WW_INC1	Mode	M	Status-only
Beh	WW_INS1	Behaviour	M	
Health	WW_INS3	Health	M	
NamPlt	WW_LPL1	Name plate	M	
Loc	WW_SPS1	Local operation	M	
OpCnt	WW_INS2	Operation counter	M	
<b>Status Information</b>				
SwTyp	WW_INS5	Switch type	M	
SwOpCap	WW_INS5	Switch operating capability	M	
<b>Controls</b>				
Pos	WW_DPC1	Switch position	M	
BlkOpn	WW_SPC1	Block opening	M	
BlkCls	WW_SPC1	Block closing	M	

### 3. Common Data Class

#### 3.1. Common Data Class definitions

The following table contains the list of Common Data Class implemented in the device:

CDC Type	CDC Class	Description
WW_ACD1	ACD	Directional Protection activation information
WW_ACT1	ACT	Protection Activation Information
WW_analogValue1	analogValue	Analogue value
WW_Cancel1	Cancel	Cancel operating
WW_CMV1	CMV	Complex measured value
WW_DEL1	DEL	Delta
WW_DPC1	DPC	Controllable Double Point
WW_DPC2	DPC	Controllable Double Point
WW_DPL1	DPL	Device name plate
WW_INC1	INC	Controllable Integer Status
WW_INS1	INS	Integer Status
WW_INS2	INS	Integer Status
WW_INS3	INS	Integer Status
WW_INS5	INS	Integer Status
WW_LPL1	LPL	Logical node name plate
WW_LPL2	LPL	Logical node name plate
WW_LPL3	LPL	Logical node name plate
WW_MV1	MV	Measured Value
WW_Oper1	Oper	Start/Select operating
WW_origin1	origin	Originator
WW_SPC1	SPC	Controllable Single Point
WW_SPC2	SPC	Controllable Single Point
WW_SPS1	SPS	Single Point Status
WW_units1	units	Unit definition
WW_vector1	vector	Vector definition
WW_WYE1	WYE	Phase to ground related measured values of a three phase system

##### 3.1.1 WW\_ACD1

<b>ACD class</b>
------------------

Attribute Name	Attribute Type	FC	TrgOp	Value/Value range	M/O/E	Remarks
General	BOOLEAN	ST	dchg		M	
dirGeneral	Enum	ST	dchg	ACDdir	M	
q	Quality	ST	qchg		M	
t	Timestamp	ST			M	

### 3.1.2 WW\_ACT1

ACT class						
Attribute Name	Attribute Type	FC	TrgOp	Value/Value range	M/O/E	Remarks
General	BOOLEAN	ST	dchg		M	
q	Quality	ST	qchg		M	
t	Timestamp	ST			M	

### 3.1.3 WW\_CMV1

CMV class						
Attribute Name	Attribute Type	FC	TrgOp	Value/Value range	M/O/E	Remarks
cVal	Struct	MX		WW_vector1	M	
q	Quality	ST	qchg		M	
t	Timestamp	ST			M	
instCVal	Struct	MX		WW_vector1	O	
units	Struct	CF		WW_units1	O	
db	INT32U	CF			O	

### 3.1.4 WW\_DEL1

DEL class						
Attribute Name	Attribute Type	FC	TrgOp	Value/Value range	M/O/E	Remarks
phsAB	WW_CMV1					
phsBC	WW_CMV1					
phsCA	WW_CMV1					

### 3.1.5 WW\_DPC1

DPC class						
Attribute Name	Attribute Type	FC	TrgOp	Value/Value range	M/O/E	Remarks
stVal	Dbpos	ST	dchg	Dbpos	M	
q	Quality	ST	qchg		M	
t	Timestamp	ST			M	
ctlModel	Enum	CF		ctlmodel	M	

### 3.1.6 WW\_DPC2

DPC class						
Attribute Name	Attribute Type	FC	TrgOp	Value/Value range	M/O/E	Remarks

origin	Struct	ST		WW_origin1	O	
ctlNum	INT8U	ST			O	
stVal	Dbpos	ST	dchg	Dbpos	M	
q	Quality	ST	qchg		M	
t	Timestamp	ST			M	
stSeld	BOOLEAN	ST	dchg		O	
ctlModel	Enum	CF		ctlmodel	M	
sboTimeout	INT32U	CF			O	
sboClass	Enum	CF		sboClass	O	
cdcNs	VisString255	EX			O	
Oper	Struct	CO		WW_Oper1		
SBOw	Struct	CO		WW_Oper1		
Cancel	Struct	CO		WW_Cancel1		

### 3.1.7 WW\_DPL1

DPL class						
Attribute Name	Attribute Type	FC	TrgOp	Value/Value range	M/O/E	Remarks
vendor	VisString255	DC			M	

### 3.1.8 WW\_INC1

INC class						
Attribute Name	Attribute Type	FC	TrgOp	Value/Value range	M/O/E	Remarks
stVal	Enum	ST	dchg	Mode	M	
q	Quality	ST	qchg		M	
t	Timestamp	ST			M	
ctlModel	Enum	CF		ctlModel	M	

### 3.1.9 WW\_INS1

INS class						
Attribute Name	Attribute Type	FC	TrgOp	Value/Value range	M/O/E	Remarks
stVal	Enum	ST	dchg	Behaviour	M	
q	Quality	ST	qchg		M	
t	Timestamp	ST			M	

### 3.1.10 WW\_INS2

INS class						
Attribute Name	Attribute Type	FC	TrgOp	Value/Value range	M/O/E	Remarks
stVal	INT32	ST	dchg		M	
q	Quality	ST	qchg		M	
t	Timestamp	ST			M	

3.1.11 WW\_INS3

INS class						
Attribute Name	Attribute Type	FC	TrgOp	Value/Value range	M/O/E	Remarks
stVal	Enum	ST	dchg	AutoRecSt	M	
q	Quality	ST	qchg		M	
t	Timestamp	ST			M	

3.1.12 WW\_INS5

INS class						
Attribute Name	Attribute Type	FC	TrgOp	Value/Value range	M/O/E	Remarks
stVal	Enum	ST	dchg	CBOpCap	M	
q	Quality	ST	qchg		M	
t	Timestamp	ST			M	

3.1.13 WW\_LPL1

LPL class						
Attribute Name	Attribute Type	FC	TrgOp	Value/Value range	M/O/E	Remarks
vendor	visString255	DC			M	
swRev	visString255	DC			M	
d	visString255	DC			M	

3.1.14 WW\_LPL2

LPL class						
Attribute Name	Attribute Type	FC	TrgOp	Value/Value range	M/O/E	Remarks
vendor	visString255	DC			M	
swRev	visString255	DC			M	
d	visString255	DC			M	
ldNs	visString255	EX				

3.1.15 WW\_LPL3

LPL class						
Attribute Name	Attribute Type	FC	TrgOp	Value/Value range	M/O/E	Remarks
vendor	visString255	DC			M	
swRev	visString255	DC			M	
d	visString255	DC			M	
LnNS	visString255	EX				

3.1.16 WW\_MV1

MV class						
Attribute	Attribute	FC	TrgOp	Value/Value range	M/O/E	Remarks



Name	Type					
mag	Struct	MX		WW_analogValue1	M	
q	Quality	ST	qchg		M	
t	Timestamp	ST			M	
units	Struct	CF		WW_units1	O	
db	INT32U	CF			O	
d	visString255	DC			O	
dataNs	visString255	DC			O	

### 3.1.17 WW\_SPC1

SPC class						
Attribute Name	Attribute Type	FC	TrgOp	Value/Value range	M/O/E	Remarks
stVal	BOOLEAN	ST	dchg		M	
q	Quality	ST	dchg		M	
t	Timestamp	ST			M	
ctlModel	Enum	CF		ctlModel	M	

### 3.1.18 WW\_SPC2

SPC class						
Attribute Name	Attribute Type	FC	TrgOp	Value/Value range	M/O/E	Remarks
Oper	Struct	CO		WW_Oper1		
stVal	BOOLEAN	ST	dchg		M	
q	Quality	ST	dchg		M	
t	Timestamp	ST			M	
ctlModel	Enum	CF		ctlModel	M	

### 3.1.19 WW\_SPS1

SPS class						
Attribute Name	Attribute Type	FC	TrgOp	Value/Value range	M/O/E	Remarks
stVal	BOOLEAN	ST	dchg		M	
q	Quality	ST	qchg		M	
t	Timestamp	ST			M	

### 3.1.20 WW\_WYE1

WYE class						
Attribute Name	Attribute Type	FC	TrgOp	Value/Value range	M/O/E	Remarks
phsAB	WW_CMV1					
phsBC	WW_CMV1					
phsCA	WW_CMV1					
neut	WW_CMV1					

### 3.2. Common Data Attributes type definitions

#### 3.2.1 WW\_analogValue1

analogValue class						
Attribute Name	Attribute Type	FC	TrgOp	Value/Value range	M/O/E	Remarks
f	FLOAT32	MX			M	

#### 3.2.2 WW\_Cancel1

Cancel class						
Attribute Name	Attribute Type	FC	TrgOp	Value/Value range	M/O/E	Remarks
ctlval	BOOLEAN	CO			M	
origin	Struct	ST		WW_origin1	O	
ctlNum	INT8U	ST			O	
T	Timestamp	CO			O	
Test	BOOLEAN	CO			O	

#### 3.2.3 WW\_Oper1

Oper class						
Attribute Name	Attribute Type	FC	TrgOp	Value/Value range	M/O/E	Remarks
ctlval	BOOLEAN	CO			M	
origin	Struct	ST		WW_origin1	O	
ctlNum	INT8U	ST			O	
T	Timestamp	CO			O	
Test	BOOLEAN	CO			O	
Check	Check	CO			O	

#### 3.2.4 WW\_origin1

origin class						
Attribute Name	Attribute Type	FC	TrgOp	Value/Value range	M/O/E	Remarks
orCat	Enum	ST		orCategory	M	
orIdent	Octet64	ST			M	

#### 3.2.5 WW\_units1

unit class						
Attribute Name	Attribute Type	FC	TrgOp	Value/Value range	M/O/E	Remarks
SIUnit	Enum			SIUnit	M	
multiplier	Enum			multiplier	O	

#### 3.2.6 WW\_vector1

vector class						
--------------	--	--	--	--	--	--

Attribute Name	Attribute Type	FC	TrgOp	Value/Value range	M/O/E	Remarks
mag	Struct			WW_analogValue1	M	
ang	Struct			WW_analogValue1	O	

### 3.3. Enumerated type definitions

#### 3.3.1 Beh

Ordinal	Semantic
1	on
2	blocked
3	test
4	test/blocked
5	off

#### 3.3.2 CBOpCap

Ordinal	Semantic
1	None
2	Open
3	Close-Open
4	Open-Close-Open
5	Close-Open-Close-Open

#### 3.3.3 ctlModel

Ordinal	Semantic
1	status-only
2	direct-with-normal-security
3	sbo-with-normal-security
4	direct-with-enhanced-security
5	sbo-with-enhanced-security

#### 3.3.4 Dbpos

Ordinal	Semantic
1	intermediate
2	off
3	on
4	bad

#### 3.3.5 dir

Ordinal	Semantic
1	unknown
2	forward
3	backward
4	both

### 3.3.6 Health

Ordinal	Semantic
1	Ok
2	Warning
3	Alarm

### 3.3.7 Mod

Ordinal	Semantic
1	on
2	blocked
3	test
4	test/block
5	off

### 3.3.8 multiplier

Ordinal	Semantic
-24	y
-21	z
-18	a
-15	f
-12	p
-9	n
-6	$\mu$
-3	m
-2	c
-1	d
0	
1	da
2	h
3	k
6	M
9	G
12	T
15	P
18	E
21	Z
24	Y

### 3.3.9 orCategory

Ordinal	Semantic
0	not-supported
1	bay-control
2	station-control
3	remote-control
4	automatic-bay
5	automatic-station
6	automatic-remote
7	maintenance

8	process
---	---------

### 3.3.10 sboClass

Ordinal	Semantic
0	operate-once
1	operate-many

### 3.3.11 SIUnit

Ordinal	Semantic
1	none
2	m
3	kg
4	s
5	A
6	K
7	mol
8	cd
9	deg
10	rad
11	sr
21	Gy
22	q
23	°C
24	Sv
25	F
26	C
27	S
28	H
29	V
30	ohm
31	J
32	N
33	Hz
34	lx
35	Lm
36	Wb
37	T
38	W
39	Pa
41	m <sup>2</sup>
42	m <sup>3</sup>
43	m/s
44	m/s <sup>2</sup>
45	m <sup>3</sup> /s
46	m/m <sup>3</sup>
47	M
48	kg/m <sup>3</sup>
49	m <sup>2</sup> /s
50	W/m K
51	J/K
52	ppm

## Common Data Class

---

53	1/s
54	rad/s
61	VA
62	Watts
63	VAr
64	phi
65	cos(phi)
66	Vs
67	V <sup>2</sup>
68	As
69	A <sup>2</sup>
70	A <sup>2</sup> t
71	VAh
72	Wh
73	VArh
74	V/Hz

## 4. Appendix – Register Maps

LDevice::CTRL

Logical Node	Data Object	Module.Name
CILO1* (WW_CILO1 )		
	Mod	
	Beh	
	Health	
	NamPlt	
	EnaOpn	SG[1].Interl OFF
	EnaCls	SG[1].Interl ON
CILO2* (WW_CILO1 )		
	Mod	
	Beh	
	Health	
	NamPlt	
	EnaOpn	SG[2].Interl OFF
	EnaCls	SG[2].Interl ON
CILO3* (WW_CILO1 )		
	Mod	
	Beh	
	Health	
	NamPlt	
	EnaOpn	SG[3].Interl OFF
	EnaCls	SG[3].Interl ON
CILO4* (WW_CILO1 )		
	Mod	
	Beh	
	Health	
	NamPlt	
	EnaOpn	SG[4].Interl OFF
	EnaCls	SG[4].Interl ON
CILO5* (WW_CILO1 )		
	Mod	
	Beh	

LDevice::CTRL

	Health	
	NamPlt	
	EnaOpn	SG[5].Interl OFF
	EnaCls	SG[5].Interl ON
CILO6* (WW_CILO1 )		
	Mod	
	Beh	
	Health	
	NamPlt	
	EnaOpn	SG[6].Interl OFF
	EnaCls	SG[6].Interl ON
CSWI1* (WW_CSWI1 )		
	Mod	
	Beh	
	Health	
	NamPlt	
	Loc	
	Pos	SG[1].Pos
CSWI2* (WW_CSWI1 )		
	Mod	
	Beh	
	Health	
	NamPlt	
	Loc	
	Pos	SG[2].Pos
CSWI3* (WW_CSWI1 )		
	Mod	
	Beh	
	Health	
	NamPlt	
	Loc	
	Pos	SG[3].Pos
CSWI4* (WW_CSWI1 )		
	Mod	
	Beh	
	Health	



LDevice::CTRL

	NamPlt	
	Loc	
	Pos	SG[4].Pos
CSWI5* (WW_CSWI1 )		
	Mod	
	Beh	
	Health	
	NamPlt	
	Loc	
	Pos	SG[5].Pos
CSWI6* (WW_CSWI1 )		
	Mod	
	Beh	
	Health	
	NamPlt	
	Loc	
	Pos	SG[6].Pos
LLN0 (WW_LLNOCON )		
	Mod	
	Beh	
	Health	
	NamPlt	
LPHD1 (WW_LPHDCON )		
	PhyNam	
	PhyHealth	
	Proxy	
XCBR1* (WW_XCBR2 )		
	Mod	
	Beh	
	Health	
	NamPlt	
	Loc	
	OpCnt	
	Pos	SG[1].Pos
	BlkOpn	
	BlkCls	

LDevice::CTRL

	CBOpCap	
XCBR2* (WW_XCBR2 )		
	Mod	
	Beh	
	Health	
	NamPlt	
	Loc	
	OpCnt	
	Pos	SG[2].Pos
	BlkOpn	
	BlkCls	
	CBOpCap	
XCBR3* (WW_XCBR2 )		
	Mod	
	Beh	
	Health	
	NamPlt	
	Loc	
	OpCnt	
	Pos	SG[3].Pos
	BlkOpn	
	BlkCls	
	CBOpCap	
XCBR4* (WW_XCBR2 )		
	Mod	
	Beh	
	Health	
	NamPlt	
	Loc	
	OpCnt	
	Pos	SG[4].Pos
	BlkOpn	
	BlkCls	
	CBOpCap	
XCBR5* (WW_XCBR2 )		
	Mod	

LDevice::CTRL

	Beh	
	Health	
	NamPlt	
	Loc	
	OpCnt	
	Pos	SG[5].Pos
	BlkOpn	
	BlkCls	
	CBOpCap	
XCBR6* (WW_XCBR2 )		
	Mod	
	Beh	
	Health	
	NamPlt	
	Loc	
	OpCnt	
	Pos	SG[6].Pos
	BlkOpn	
	BlkCls	
	CBOpCap	
XSWI1* (WW_XSWI1 )		
	Mod	
	Beh	
	Health	
	NamPlt	
	Loc	
	OpCnt	
	Pos	SG[1].Pos
	BlkOpn	
	BlkCls	
	SwTyp	
	SwOpCap	
XSWI2* (WW_XSWI1 )		
	Mod	
	Beh	
	Health	

LDevice::CTRL

	NamPlt	
	Loc	
	OpCnt	
	Pos	SG[2].Pos
	BlkOpn	
	BlkCls	
	SwTyp	
	SwOpCap	
XSWI3* (WW_XSWI1 )		
	Mod	
	Beh	
	Health	
	NamPlt	
	Loc	
	OpCnt	
	Pos	SG[3].Pos
	BlkOpn	
	BlkCls	
	SwTyp	
	SwOpCap	
XSWI4* (WW_XSWI1 )		
	Mod	
	Beh	
	Health	
	NamPlt	
	Loc	
	OpCnt	
	Pos	SG[4].Pos
	BlkOpn	
	BlkCls	
	SwTyp	
	SwOpCap	
XSWI5* (WW_XSWI1 )		
	Mod	
	Beh	
	Health	

LDevice::CTRL

	NamPlt	
	Loc	
	OpCnt	
	Pos	SG[5].Pos
	BlkOpn	
	BlkCls	
	SwTyp	
	SwOpCap	
<b>XSWI6* (WW_XSWI1 )</b>		
	Mod	
	Beh	
	Health	
	NamPlt	
	Loc	
	OpCnt	
	Pos	SG[6].Pos
	BlkOpn	
	BlkCls	
	SwTyp	
	SwOpCap	

LDevice::DR

Logical Node	Data Object	Module.Name
<b>LLN0 (WW_LLNOREC )</b>		
	Mod	
	Beh	
	Health	
	NamPlt	
<b>LPHD1 (WW_LPHDREC )</b>		
	PhyNam	
	PhyHealth	
	Proxy	
<b>RDRE1 (WW_RDRE1 )</b>		
	Mod	
	Beh	
	Health	
	NamPlt	

LDevice::CTRL

	RcdMade	Disturb rec.recording
	FltNum	
	GriFltNum	
	RcdStr	Disturb rec.recording

LDevice::EXT

Logical Node	Data Object	Module.Name
CoGGIO1 (WW_GGIO5 )		
	Mod	
	Beh	
	Health	
	NamPlt	
	SPCSO1	
	SPCSO2	
	SPCSO3	
	SPCSO4	
	SPCSO5	
	SPCSO6	
	SPCSO7	
	SPCSO8	
	SPCSO9	
	SPCSO10	
	SPCSO11	
	SPCSO12	
	SPCSO13	
	SPCSO14	
	SPCSO15	
	SPCSO16	
	SPCSO17	
	SPCSO18	
	SPCSO19	
	SPCSO20	
	SPCSO21	
	SPCSO22	
	SPCSO23	
	SPCSO24	
	SPCSO25	

LDevice::CTRL

	SPCSO26	
	SPCSO27	
	SPCSO28	
	SPCSO29	
	SPCSO30	
	SPCSO31	
	SPCSO32	
InGGIO1 (WW_GGIO3 )		
	Mod	
	Beh	
	Health	
	NamPlt	
	Ind1	
	Ind2	
	Ind3	
	Ind4	
	Ind5	
	Ind6	
	Ind7	
	Ind8	
	Ind9	
	Ind10	
	Ind11	
	Ind12	
	Ind13	
	Ind14	
	Ind15	
	Ind16	
	Ind17	
	Ind18	
	Ind19	
	Ind20	
	Ind21	
	Ind22	
	Ind23	
	Ind24	

LDevice::CTRL

	Ind25	
	Ind26	
	Ind27	
	Ind28	
	Ind29	
	Ind30	
	Ind31	
	Ind32	
LLN0 (WW_LLN0SYS )		
	Mod	
	Beh	
	Health	
	NamPlt	
LPHD1 (WW_LPHDSYS )		
	PhyNam	
	PhyHealth	
	Proxy	
OutGGIO1 (WW_GGIO4 )		
	Mod	
	Beh	
	Health	
	NamPlt	
	Ind1	IEC61850.VirtOut1-I
	Ind2	IEC61850.VirtOut2-I
	Ind3	IEC61850.VirtOut3-I
	Ind4	IEC61850.VirtOut4-I
	Ind5	IEC61850.VirtOut5-I
	Ind6	IEC61850.VirtOut6-I
	Ind7	IEC61850.VirtOut7-I
	Ind8	IEC61850.VirtOut8-I
	Ind9	IEC61850.VirtOut9-I
	Ind10	IEC61850.VirtOut10-I
	Ind11	IEC61850.VirtOut11-I
	Ind12	IEC61850.VirtOut12-I
	Ind13	IEC61850.VirtOut13-I
	Ind14	IEC61850.VirtOut14-I



LDevice::CTRL

	Ind15	IEC61850.VirtOut15-I
	Ind16	IEC61850.VirtOut16-I
	Ind17	IEC61850.VirtOut17-I
	Ind18	IEC61850.VirtOut18-I
	Ind19	IEC61850.VirtOut19-I
	Ind20	IEC61850.VirtOut20-I
	Ind21	IEC61850.VirtOut21-I
	Ind22	IEC61850.VirtOut22-I
	Ind23	IEC61850.VirtOut23-I
	Ind24	IEC61850.VirtOut24-I
	Ind25	IEC61850.VirtOut25-I
	Ind26	IEC61850.VirtOut26-I
	Ind27	IEC61850.VirtOut27-I
	Ind28	IEC61850.VirtOut28-I
	Ind29	IEC61850.VirtOut29-I
	Ind30	IEC61850.VirtOut30-I
	Ind31	IEC61850.VirtOut31-I
	Ind32	IEC61850.VirtOut32-I

LDevice::MEAS

Logical Node	Data Object	Module.Name
LLNO (WW_LLNO MEA )		
	Mod	
	Beh	
	Health	
	NamPlt	
LPHD1 (WW_LPHD MEA )		
	PhyNam	
	PhyHealth	
	Proxy	
MMXU1 (WW_MMXU2 )		
	Mod	
	Beh	
	Health	
	NamPlt	

LDevice::CTRL

	PPV	Voltage.VL12 RMS Voltage.phi VL12 Voltage.VL23 RMS Voltage.phi VL23 Voltage.VL31 RMS Voltage.phi VL31
	PhV	Voltage.VL1 RMS Voltage.phi VL1 Voltage.VL2 RMS Voltage.phi VL2 Voltage.VL3 RMS Voltage.phi VL3 Voltage.VX meas RMS Voltage.phi VX meas Voltage.VG calc RMS Voltage.phi VG calc
MMXU2 (WW_MMXU1 )		
	Mod	
	Beh	
	Health	
	NamPlt	
	A	CT Ntrl.IL1 RMS CT Ntrl.phi IL1 CT Ntrl.IL2 RMS CT Ntrl.phi IL2 CT Ntrl.IL3 RMS CT Ntrl.phi IL3 CT Ntrl.IG meas RMS CT Ntrl.phi IG meas CT Ntrl.IG calc RMS CT Ntrl.phi IG calc
MMXU3 (WW_MMXU1 )		
	Mod	
	Beh	
	Health	
	NamPlt	
	A	CT Mains.IL1 RMS CT Mains.phi IL1 CT Mains.IL2 RMS CT Mains.phi IL2 CT Mains.IL3 RMS CT Mains.phi IL3 CT Mains.IG meas RMS CT Mains.phi IG meas CT Mains.IG calc RMS CT Mains.phi IG calc
MMXU4 (WW_MMXU3 )		

LDevice::CTRL

	Mod	
	Beh	
	Health	
	NamPlt	
	TotW	PQSCr.P RMS
	TotVAr	PQSCr.Q RMS
	TotVA	PQSCr.S RMS
	TotPF	PQSCr.cos phi RMS
MSTA1 (WW_MSTA2 )		
	Mod	
	Beh	
	Health	
	NamPlt	
	MaxVPhsAB	Voltage.VL12 max
	MaxVPhsBC	Voltage.VL23 max
	MaxVPhsCA	Voltage.VL31 max
	MinVPhsAB	Voltage.VL12 min
	MinVPhsBC	Voltage.VL23 min
	MinVPhsCA	Voltage.VL31 min
	MaxVPhsA	Voltage.VL1 max
	MaxVPhsB	Voltage.VL2 max
	MaxVPhsC	Voltage.VL3 max
	MinVPhsA	Voltage.VL1 min
	MinVPhsB	Voltage.VL2 min
	MinVPhsC	Voltage.VL3 min
MSTA2 (WW_MSTA1 )		
	Mod	
	Beh	
	Health	
	NamPlt	
	AvAPhsA	CT Ntrl.IL1 avg
	AvAPhsB	CT Ntrl.IL2 avg
	AvAPhsC	CT Ntrl.IL3 avg
	MaxAPhsA	CT Ntrl.IL1 max
	MaxAPhsB	CT Ntrl.IL2 max
	MaxAPhsC	CT Ntrl.IL3 max

LDevice::CTRL

	MinAPhsA	CT Ntrl.IL1 min
	MinAPhsB	CT Ntrl.IL2 min
	MinAPhsC	CT Ntrl.IL3 min
MSTA3 (WW_MSTA1 )		
	Mod	
	Beh	
	Health	
	NamPlt	
	AvAPhsA	CT Mains.IL1 avg
	AvAPhsB	CT Mains.IL2 avg
	AvAPhsC	CT Mains.IL3 avg
	MaxAPhsA	CT Mains.IL1 max
	MaxAPhsB	CT Mains.IL2 max
	MaxAPhsC	CT Mains.IL3 max
	MinAPhsA	CT Mains.IL1 min
	MinAPhsB	CT Mains.IL2 min
	MinAPhsC	CT Mains.IL3 min
MSTA4 (WW_MSTA3 )		
	Mod	
	Beh	
	Health	
	NamPlt	
	AvVA	PQSCr.S avg
	MaxVA	PQSCr.S max
	MinVA	PQSCr.S min
	AvW	PQSCr.P avg
	MaxW	PQSCr.P max
	MinW	PQSCr.P min
	AvVAr	PQSCr.Q avg
	MaxVAr	PQSCr.Q max
	MinVAr	PQSCr.Q min

LDevice::PROT

Logical Node	Data Object	Module.Name
IE5027PIOC1 (WW_PIOC1 )		

LDevice::CTRL

	Mod	InEn.active InEn.Blo TripCmd InEn.ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	InEn.Alarm
	Op	InEn.Trip
IHMI1 (WW_IHMI1 )		
	Mod	
	Beh	
	Health	
	NamPlt	
LLN0 (WW_LLNOPRO )		
	Mod	
	Beh	
	Health	
	NamPlt	
LPHD1 (WW_LPHDPRO )		
	PhyNam	
	PhyHealth	
	Proxy	
LoEPDUP1* (WW_PDUP2 )		
	Mod	LoE-Z1[1].active LoE-Z1[1].Blo TripCmd LoE-Z1[1].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	LoE-Z1[1].Alarm
	Op	LoE-Z1[1].Trip
LoEPDUP2* (WW_PDUP2 )		
	Mod	LoE-Z2[1].active LoE-Z2[1].Blo TripCmd LoE-Z2[1].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	

LDevice::CTRL

	Str	LoE-Z2[1].Alarm
	Op	LoE-Z2[1].Trip
LoEPDUP3* (WW_PDUP2 )		
	Mod	LoE-Z1[2].active LoE-Z1[2].Blo TripCmd LoE-Z1[2].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	LoE-Z1[2].Alarm
	Op	LoE-Z1[2].Trip
LoEPDUP4* (WW_PDUP2 )		
	Mod	LoE-Z2[2].active LoE-Z2[2].Blo TripCmd LoE-Z2[2].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	LoE-Z2[2].Alarm
	Op	LoE-Z2[2].Trip
PDIF1 (WW_PDIF1 )		
	Mod	Id.active Id.Blo TripCmd Id.ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	Id.Alarm
	Op	Id.TripCmd
PDIF2 (WW_PDIF4 )		
	Mod	IdH.active IdH.Blo TripCmd IdH.ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	IdH.Alarm
	Op	IdH.TripCmd
PDIF3 (WW_PDIF2 )		

LDevice::CTRL

	Mod	IdG[1].active IdG[1].Blo TripCmd IdG[1].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	IdG[1].Alarm
	Op	IdG[1].Trip
PDIF4 (WW_PDIF3 )		
	Mod	IdGH[1].active IdGH[1].Blo TripCmd IdGH[1].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	IdGH[1].Alarm
	Op	IdGH[1].TripCmd
PDIF5 (WW_PDIF2 )		
	Mod	IdG[2].active IdG[2].Blo TripCmd IdG[2].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	IdG[2].Alarm
	Op	IdG[2].Trip
PDIF6 (WW_PDIF3 )		
	Mod	IdGH[2].active IdGH[2].Blo TripCmd IdGH[2].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	IdGH[2].Alarm
	Op	IdGH[2].TripCmd
PDOP1* (WW_PDOP1 )		
	Mod	P.active P.Blo TripCmd P.ExBlo TripCmd
	Beh	

LDevice::CTRL

	Health	
	NamPlt	
	Str	P.Alarm
	Op	P.Trip
PDOP2* (WW_PDOP1 )		
	Mod	Q.active Q.Blo TripCmd Q.ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	Q.Alarm
	Op	Q.Trip
PDOP3* (WW_PDOP1 )		
	Mod	PQS[1].active PQS[1].Blo TripCmd PQS[1].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	PQS[1].Alarm
	Op	PQS[1].Trip
PDOP4* (WW_PDOP1 )		
	Mod	PQS[2].active PQS[2].Blo TripCmd PQS[2].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	PQS[2].Alarm
	Op	PQS[2].Trip
PDOP5* (WW_PDOP1 )		
	Mod	PQS[3].active PQS[3].Blo TripCmd PQS[3].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	



LDevice::CTRL

	Str	PQS[3].Alarm
	Op	PQS[3].Trip
PDOP6* (WW_PDOP1 )		
	Mod	PQS[4].active PQS[4].Blo TripCmd PQS[4].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	PQS[4].Alarm
	Op	PQS[4].Trip
PDOP7* (WW_PDOP1 )		
	Mod	PQS[5].active PQS[5].Blo TripCmd PQS[5].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	PQS[5].Alarm
	Op	PQS[5].Trip
PDOP8* (WW_PDOP1 )		
	Mod	PQS[6].active PQS[6].Blo TripCmd PQS[6].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	PQS[6].Alarm
	Op	PQS[6].Trip
PDUP1* (WW_PDUP1 )		
	Mod	P.active P.Blo TripCmd P.ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	P.Alarm
	Op	P.Trip

LDevice::CTRL

PDUP2* (WW_PDUP1 )		
	Mod	Q.active Q.Blo TripCmd Q.ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	Q.Alarm
	Op	Q.Trip
PDUP3* (WW_PDUP1 )		
	Mod	PQS[1].active PQS[1].Blo TripCmd PQS[1].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	PQS[1].Alarm
	Op	PQS[1].Trip
PDUP4* (WW_PDUP1 )		
	Mod	PQS[2].active PQS[2].Blo TripCmd PQS[2].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	PQS[2].Alarm
	Op	PQS[2].Trip
PDUP5* (WW_PDUP1 )		
	Mod	PQS[3].active PQS[3].Blo TripCmd PQS[3].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	PQS[3].Alarm
	Op	PQS[3].Trip
PDUP6* (WW_PDUP1 )		

LDevice::CTRL

	Mod	PQS[4].active PQS[4].Blo TripCmd PQS[4].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	PQS[4].Alarm
	Op	PQS[4].Trip
PDUP7* (WW_PDUP1 )		
	Mod	PQS[5].active PQS[5].Blo TripCmd PQS[5].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	PQS[5].Alarm
	Op	PQS[5].Trip
PDUP8* (WW_PDUP1 )		
	Mod	PQS[6].active PQS[6].Blo TripCmd PQS[6].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	PQS[6].Alarm
	Op	PQS[6].Trip
PFRC1* (WW_PFRC1 )		
	Mod	df/dt.active df/dt.Blo TripCmd df/dt.ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	df/dt.Alarm
	Op	df/dt.Trip
PFRC2* (WW_PFRC1 )		
	Mod	delta phi.active delta phi.Blo TripCmd delta phi.ExBlo TripCmd

LDevice::CTRL

	Beh	
	Health	
	NamPlt	
	Str	delta phi.Alarm
	Op	delta phi.Trip
PFRC3* (WW_PFRC1 )		
	Mod	f[1].active f[1].Blo TripCmd f[1].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[1].Alarm
	Op	f[1].Trip
PFRC4* (WW_PFRC1 )		
	Mod	f[2].active f[2].Blo TripCmd f[2].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[2].Alarm
	Op	f[2].Trip
PFRC5* (WW_PFRC1 )		
	Mod	f[3].active f[3].Blo TripCmd f[3].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[3].Alarm
	Op	f[3].Trip
PFRC6* (WW_PFRC1 )		
	Mod	f[4].active f[4].Blo TripCmd f[4].ExBlo TripCmd
	Beh	
	Health	

LDevice::CTRL

	NamPlt	
	Str	f[4].Alarm
	Op	f[4].Trip
PFRC7* (WW_PFRC1 )		
	Mod	f[5].active f[5].Blo TripCmd f[5].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[5].Alarm
	Op	f[5].Trip
PFRC8* (WW_PFRC1 )		
	Mod	f[6].active f[6].Blo TripCmd f[6].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[6].Alarm
	Op	f[6].Trip
PHAR1 (WW_PHAR1 )		
	Mod	IH2.active
	Beh	
	Health	
	NamPlt	
	Str	IH2.3-ph Blo
PPAM1* (WW_PPAM1 )		
	Mod	df/dt.active df/dt.Blo TripCmd df/dt.ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	df/dt.Alarm
	Op	df/dt.Trip
PPAM2* (WW_PPAM1 )		

LDevice::CTRL

	Mod	delta phi.active delta phi.Blo TripCmd delta phi.ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	delta phi.Alarm
	Op	delta phi.Trip
PPAM3* (WW_PPAM1 )		
	Mod	f[1].active f[1].Blo TripCmd f[1].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[1].Alarm
	Op	f[1].Trip
PPAM4* (WW_PPAM1 )		
	Mod	f[2].active f[2].Blo TripCmd f[2].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[2].Alarm
	Op	f[2].Trip
PPAM5* (WW_PPAM1 )		
	Mod	f[3].active f[3].Blo TripCmd f[3].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[3].Alarm
	Op	f[3].Trip
PPAM6* (WW_PPAM1 )		
	Mod	f[4].active f[4].Blo TripCmd f[4].ExBlo TripCmd

LDevice::CTRL

	Beh	
	Health	
	NamPlt	
	Str	f[4].Alarm
	Op	f[4].Trip
PPAM7* (WW_PPAM1 )		
	Mod	f[5].active f[5].Blo TripCmd f[5].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[5].Alarm
	Op	f[5].Trip
PPAM8* (WW_PPAM1 )		
	Mod	f[6].active f[6].Blo TripCmd f[6].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[6].Alarm
	Op	f[6].Trip
PSOF1 (WW_PSOF1 )		
	Mod	SOTF.active SOTF.ExBlo SOTF.Ex rev Interl
	Beh	
	Health	
	NamPlt	
	Str	SOTF.enabled
PTOC1 (WW_PTOC1 )		
	Mod	I[1].active I[1].Blo TripCmd I[1].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	I[1].Alarm

LDevice::CTRL

	Op	I[1].Trip
PTOC10 (WW_PTOC3 )		
	Mod	IG[4].active IG[4].Blo TripCmd IG[4].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	IG[4].Alarm
	Op	IG[4].Trip
PTOC11 (WW_PTOC4 )		
	Mod	I2>[1].active I2>[1].Blo TripCmd I2>[1].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	I2>[1].Alarm
	Op	I2>[1].Trip
PTOC12 (WW_PTOC4 )		
	Mod	I2>[2].active I2>[2].Blo TripCmd I2>[2].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	I2>[2].Alarm
	Op	I2>[2].Trip
PTOC13 (WW_PTOC4 )		
	Mod	I2>G.active I2>G.Blo TripCmd I2>G.ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	I2>G.Alarm
	Op	I2>G.Trip
PTOC2 (WW_PTOC1 )		



LDevice::CTRL

	Mod	I[2].active I[2].Blo TripCmd I[2].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	I[2].Alarm
	Op	I[2].Trip
PTOC3 (WW_PTOC1 )		
	Mod	I[3].active I[3].Blo TripCmd I[3].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	I[3].Alarm
	Op	I[3].Trip
PTOC4 (WW_PTOC1 )		
	Mod	I[4].active I[4].Blo TripCmd I[4].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	I[4].Alarm
	Op	I[4].Trip
PTOC5 (WW_PTOC1 )		
	Mod	I[5].active I[5].Blo TripCmd I[5].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	I[5].Alarm
	Op	I[5].Trip
PTOC6 (WW_PTOC1 )		
	Mod	I[6].active I[6].Blo TripCmd I[6].ExBlo TripCmd
	Beh	

LDevice::CTRL

	Health	
	NamPlt	
	Str	I[6].Alarm
	Op	I[6].Trip
PTOC7 (WW_PTOC3 )		
	Mod	IG[1].active IG[1].Blo TripCmd IG[1].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	IG[1].Alarm
	Op	IG[1].Trip
PTOC8 (WW_PTOC3 )		
	Mod	IG[2].active IG[2].Blo TripCmd IG[2].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	IG[2].Alarm
	Op	IG[2].Trip
PTOC9 (WW_PTOC3 )		
	Mod	IG[3].active IG[3].Blo TripCmd IG[3].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	IG[3].Alarm
	Op	IG[3].Trip
PTOF1* (WW_PTOF1 )		
	Mod	df/dt.active df/dt.Blo TripCmd df/dt.ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	df/dt.Alarm

LDevice::CTRL

	Op	df/dt.Trip
PTOF2* (WW_PTOF1 )		
	Mod	delta phi.active delta phi.Blo TripCmd delta phi.ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	delta phi.Alarm
	Op	delta phi.Trip
PTOF3* (WW_PTOF1 )		
	Mod	f[1].active f[1].Blo TripCmd f[1].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[1].Alarm
	Op	f[1].Trip
PTOF4* (WW_PTOF1 )		
	Mod	f[2].active f[2].Blo TripCmd f[2].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[2].Alarm
	Op	f[2].Trip
PTOF5* (WW_PTOF1 )		
	Mod	f[3].active f[3].Blo TripCmd f[3].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[3].Alarm
	Op	f[3].Trip
PTOF6* (WW_PTOF1 )		

LDevice::CTRL

	Mod	f[4].active f[4].Blo TripCmd f[4].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[4].Alarm
	Op	f[4].Trip
PTOF7* (WW_PTOF1 )		
	Mod	f[5].active f[5].Blo TripCmd f[5].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[5].Alarm
	Op	f[5].Trip
PTOF8* (WW_PTOF1 )		
	Mod	f[6].active f[6].Blo TripCmd f[6].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[6].Alarm
	Op	f[6].Trip
PTOV1* (WW_PTOV2 )		
	Mod	V[1].active V[1].Blo TripCmd V[1].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V[1].Alarm
	Op	V[1].Trip
PTOV10 (WW_PTOV3 )		
	Mod	V012[4].active V012[4].Blo TripCmd V012[4].ExBlo TripCmd

LDevice::CTRL

	Beh	
	Health	
	NamPlt	
	Str	V012[4].Alarm
	Op	V012[4].Trip
PTOV11 (WW_PTOV3 )		
	Mod	V012[5].active V012[5].Blo TripCmd V012[5].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V012[5].Alarm
	Op	V012[5].Trip
PTOV12 (WW_PTOV3 )		
	Mod	V012[6].active V012[6].Blo TripCmd V012[6].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V012[6].Alarm
	Op	V012[6].Trip
PTOV2* (WW_PTOV2 )		
	Mod	V[2].active V[2].Blo TripCmd V[2].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V[2].Alarm
	Op	V[2].Trip
PTOV3* (WW_PTOV2 )		
	Mod	V[3].active V[3].Blo TripCmd V[3].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	

LDevice::CTRL

	Str	V[3].Alarm
	Op	V[3].Trip
PTOV4* (WW_PTOV2 )		
	Mod	V[4].active V[4].Blo TripCmd V[4].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V[4].Alarm
	Op	V[4].Trip
PTOV5* (WW_PTOV2 )		
	Mod	V[5].active V[5].Blo TripCmd V[5].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V[5].Alarm
	Op	V[5].Trip
PTOV6* (WW_PTOV2 )		
	Mod	V[6].active V[6].Blo TripCmd V[6].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V[6].Alarm
	Op	V[6].Trip
PTOV7 (WW_PTOV3 )		
	Mod	V012[1].active V012[1].Blo TripCmd V012[1].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V012[1].Alarm
	Op	V012[1].Trip
PTOV8 (WW_PTOV3 )		

LDevice::CTRL

	Mod	V012[2].active V012[2].Blo TripCmd V012[2].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V012[2].Alarm
	Op	V012[2].Trip
PTOV9 (WW_PTOV3 )		
	Mod	V012[3].active V012[3].Blo TripCmd V012[3].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V012[3].Alarm
	Op	V012[3].Trip
PTTR1 (WW_PTTR3 )		
	Mod	ThR.active ThR.Blo TripCmd ThR.ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Op	ThR.Trip
PTTR2 (WW_PTTR1 )		
	Mod	RTD.active RTD.Blo TripCmd RTD.ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Op	RTD.Trip
PTUF1* (WW_PTUF1 )		
	Mod	df/dt.active df/dt.Blo TripCmd df/dt.ExBlo TripCmd
	Beh	
	Health	
	NamPlt	

LDevice::CTRL

	Str	df/dt.Alarm
	Op	df/dt.Trip
PTUF2* (WW_PTUF1 )		
	Mod	delta phi.active delta phi.Blo TripCmd delta phi.ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	delta phi.Alarm
	Op	delta phi.Trip
PTUF3* (WW_PTUF1 )		
	Mod	f[1].active f[1].Blo TripCmd f[1].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[1].Alarm
	Op	f[1].Trip
PTUF4* (WW_PTUF1 )		
	Mod	f[2].active f[2].Blo TripCmd f[2].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[2].Alarm
	Op	f[2].Trip
PTUF5* (WW_PTUF1 )		
	Mod	f[3].active f[3].Blo TripCmd f[3].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[3].Alarm
	Op	f[3].Trip



LDevice::CTRL

PTUF6* (WW_PTUF1 )		
	Mod	f[4].active f[4].Blo TripCmd f[4].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[4].Alarm
	Op	f[4].Trip
PTUF7* (WW_PTUF1 )		
	Mod	f[5].active f[5].Blo TripCmd f[5].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[5].Alarm
	Op	f[5].Trip
PTUF8* (WW_PTUF1 )		
	Mod	f[6].active f[6].Blo TripCmd f[6].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	f[6].Alarm
	Op	f[6].Trip
PTUV1* (WW_PTUV2 )		
	Mod	V[1].active V[1].Blo TripCmd V[1].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V[1].Alarm
	Op	V[1].Trip
PTUV2* (WW_PTUV2 )		

LDevice::CTRL

	Mod	V[2].active V[2].Blo TripCmd V[2].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V[2].Alarm
	Op	V[2].Trip
PTUV3* (WW_PTUV2 )		
	Mod	V[3].active V[3].Blo TripCmd V[3].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V[3].Alarm
	Op	V[3].Trip
PTUV4* (WW_PTUV2 )		
	Mod	V[4].active V[4].Blo TripCmd V[4].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V[4].Alarm
	Op	V[4].Trip
PTUV5* (WW_PTUV2 )		
	Mod	V[5].active V[5].Blo TripCmd V[5].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V[5].Alarm
	Op	V[5].Trip
PTUV6* (WW_PTUV2 )		
	Mod	V[6].active V[6].Blo TripCmd V[6].ExBlo TripCmd

LDevice::CTRL

	Beh	
	Health	
	NamPlt	
	Str	V[6].Alarm
	Op	V[6].Trip
PUPF1 (WW_PUPF1 )		
	Mod	PF[1].active PF[1].Blo TripCmd PF[1].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	PF[1].Alarm
	Op	PF[1].Trip
PUPF2 (WW_PUPF1 )		
	Mod	PF[2].active PF[2].Blo TripCmd PF[2].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	PF[2].Alarm
	Op	PF[2].Trip
PVPH1* (WW_PVPH1 )		
	Mod	V/f>[1].active V/f>[1].Blo TripCmd V/f>[1].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	V/f>[1].Alarm
	Op	V/f>[1].Trip
PVPH2* (WW_PVPH1 )		
	Mod	V/f>[2].active V/f>[2].Blo TripCmd V/f>[2].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	

LDevice::CTRL

	Str	V/f>[2].Alarm
	Op	V/f>[2].Trip
<b>RBRF1 (WW_RBRF1 )</b>		
	Mod	CBF.active CBF.ExBlo CBF.ExBlo
	Beh	
	Health	
	NamPlt	
	Str	CBF.running
	OpEx	CBF.Alarm
<b>RSYN1 (WW_RSYN2 )</b>		
	Mod	Sync.active Sync.ExBlo Sync.ExBlo
	Beh	
	Health	
	NamPlt	
	Rel	Sync.Ready to Close
	AngInd	Sync.AngleDiffTooHigh
	HzInd	Sync.SlipTooHigh
	VInd	Sync.VDiffTooHigh
	DifAngClc	Sync.Angle Diff
	DifHzClc	Sync.Slip Freq
	DifVClc	Sync.Volt Diff
<b>VePTOV1* (WW_PTOV1 )</b>		
	Mod	VG[1].active VG[1].Blo TripCmd VG[1].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	VG[1].Alarm
	Op	VG[1].Trip
<b>VePTOV2* (WW_PTOV1 )</b>		
	Mod	VG[2].active VG[2].Blo TripCmd VG[2].ExBlo TripCmd
	Beh	

LDevice::CTRL

	Health	
	NamPlt	
	Str	VG[2].Alarm
	Op	VG[2].Trip
<b>VePTUV1* (WW_PTUV1 )</b>		
	Mod	VG[1].active VG[1].Blo TripCmd VG[1].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	VG[1].Alarm
	Op	VG[1].Trip
<b>VePTUV2* (WW_PTUV1 )</b>		
	Mod	VG[2].active VG[2].Blo TripCmd VG[2].ExBlo TripCmd
	Beh	
	Health	
	NamPlt	
	Str	VG[2].Alarm
	Op	VG[2].Trip

\* Logical Node is dependent from settings in the “Device Planing”. (See 4.1 Device Planing Dependencies)

### 4.1. Device Planing Dependencies

Depending on the settings in the Device Planing section Logical Node instances will be available in the generated ICD file. The following list will give you an overview about the different selections for each Module which have an effect on the existence of a Logical Node.

Module.Name	Value
<b>CILO1</b>	
SG[1].SwitchgearType	Controlled SG
	Controlled Make Break SG
<b>CILO2</b>	
SG[2].SwitchgearType	Controlled SG
	Controlled Make Break SG
<b>CILO3</b>	

<b>Module.Name</b>	<b>Value</b>
SG[3].SwitchgearType	Controlled SG
	Controlled Make Break SG
CILO4	
SG[4].SwitchgearType	Controlled SG
	Controlled Make Break SG
CILO5	
SG[5].SwitchgearType	Controlled SG
	Controlled Make Break SG
CILO6	
SG[6].SwitchgearType	Controlled SG
	Controlled Make Break SG
CSWI1	
SG[1].SwitchgearType	Controlled SG
	Controlled Make Break SG
CSWI2	
SG[2].SwitchgearType	Controlled SG
	Controlled Make Break SG
CSWI3	
SG[3].SwitchgearType	Controlled SG
	Controlled Make Break SG
CSWI4	
SG[4].SwitchgearType	Controlled SG
	Controlled Make Break SG
CSWI5	
SG[5].SwitchgearType	Controlled SG
	Controlled Make Break SG
CSWI6	
SG[6].SwitchgearType	Controlled SG
	Controlled Make Break SG
XCBR1	
SG[1].SwitchgearType	Monitored Make Break SG
	Controlled Make Break SG
XCBR2	
SG[2].SwitchgearType	Monitored Make Break SG
	Controlled Make Break SG
XCBR3	
SG[3].SwitchgearType	Monitored Make Break SG

Module.Name	Value
	Controlled Make Break SG
XCBR4	
SG[4].SwitchgearType	Monitored Make Break SG
	Controlled Make Break SG
XCBR5	
SG[5].SwitchgearType	Monitored Make Break SG
	Controlled Make Break SG
XCBR6	
SG[6].SwitchgearType	Monitored Make Break SG
	Controlled Make Break SG
XSWI1	
SG[1].SwitchgearType	Monitored SG
	Controlled SG
XSWI2	
SG[2].SwitchgearType	Monitored SG
	Controlled SG
XSWI3	
SG[3].SwitchgearType	Monitored SG
	Controlled SG
XSWI4	
SG[4].SwitchgearType	Monitored SG
	Controlled SG
XSWI5	
SG[5].SwitchgearType	Monitored SG
	Controlled SG
XSWI6	
SG[6].SwitchgearType	Monitored SG
	Controlled SG
LoEPDUP1	
LoE-Z1[1].Mode	use
LoEPDUP2	
LoE-Z2[1].Mode	use
LoEPDUP3	
LoE-Z1[2].Mode	use
LoEPDUP4	
LoE-Z2[2].Mode	use
PDOP1	

Module.Name	Value
P.Mode	P>
	Pr>
PDOP2	
Q.Mode	Q>
	Qr>
PDOP3	
PQS[1].Mode	P>
	Pr>
	Q>
	Qr>
	S>
PDOP4	
PQS[2].Mode	P>
	Pr>
	Q>
	Qr>
	S>
PDOP5	
PQS[3].Mode	P>
	Pr>
	Q>
	Qr>
	S>
PDOP6	
PQS[4].Mode	P>
	Pr>
	Q>
	Qr>
	S>
PDOP7	
PQS[5].Mode	P>
	Pr>
	Q>
	Qr>
	S>
PDOP8	
PQS[6].Mode	P>



Module.Name	Value
	Pr>
	Q>
	Qr>
	S>
PDUP3	
PQS[1].Mode	P<
	Pr<
	Q<
	Qr<
	S<
PDUP4	
PQS[2].Mode	P<
	Pr<
	Q<
	Qr<
	S<
PDUP5	
PQS[3].Mode	P<
	Pr<
	Q<
	Qr<
	S<
PDUP6	
PQS[4].Mode	P<
	Pr<
	Q<
	Qr<
	S<
PDUP7	
PQS[5].Mode	P<
	Pr<
	Q<
	Qr<
	S<
PDUP8	
PQS[6].Mode	P<
	Pr<

Module.Name	Value
	Q<
	Qr<
	S<
PFRC1	
df/dt.Mode	use
PFRC3	
f[1].Mode	f< and df/dt
	f> and df/dt
	f< and DF/DT
	f> and DF/DT
	df/dt
PFRC4	
f[2].Mode	f< and df/dt
	f> and df/dt
	f< and DF/DT
	f> and DF/DT
	df/dt
PFRC5	
f[3].Mode	f< and df/dt
	f> and df/dt
	f< and DF/DT
	f> and DF/DT
	df/dt
PFRC6	
f[4].Mode	f< and df/dt
	f> and df/dt
	f< and DF/DT
	f> and DF/DT
	df/dt
PFRC7	
f[5].Mode	f< and df/dt
	f> and df/dt
	f< and DF/DT
	f> and DF/DT
	df/dt
PFRC8	
f[6].Mode	f< and df/dt

Module.Name	Value
	f> and df/dt
	f< and DF/DT
	f> and DF/DT
	df/dt
PPAM2	
delta phi.Mode	use
PPAM3	
f[1].Mode	delta phi
PPAM4	
f[2].Mode	delta phi
PPAM5	
f[3].Mode	delta phi
PPAM6	
f[4].Mode	delta phi
PPAM7	
f[5].Mode	delta phi
PPAM8	
f[6].Mode	delta phi
PTOF3	
f[1].Mode	f>
PTOF4	
f[2].Mode	f>
PTOF5	
f[3].Mode	f>
PTOF6	
f[4].Mode	f>
PTOF7	
f[5].Mode	f>
PTOF8	
f[6].Mode	f>
PTOV1	
V[1].Mode	V>
PTOV2	
V[2].Mode	V>
PTOV3	
V[3].Mode	V>
PTOV4	

Module.Name	Value
V[4].Mode	V>
PTOV5	
V[5].Mode	V>
PTOV6	
V[6].Mode	V>
PTUF3	
f[1].Mode	f<
PTUF4	
f[2].Mode	f<
PTUF5	
f[3].Mode	f<
PTUF6	
f[4].Mode	f<
PTUF7	
f[5].Mode	f<
PTUF8	
f[6].Mode	f<
PTUV1	
V[1].Mode	V<
	V(t)<
PTUV2	
V[2].Mode	V<
	V(t)<
PTUV3	
V[3].Mode	V<
	V(t)<
PTUV4	
V[4].Mode	V<
	V(t)<
PTUV5	
V[5].Mode	V<
	V(t)<
PTUV6	
V[6].Mode	V<
	V(t)<
PVPH1	
V/f>[1].Mode	use

Module.Name	Value
PVPH2	
V/f>[2].Mode	use
VePTOV1	
VG[1].Mode	V>
VePTOV2	
VG[2].Mode	V>
VePTUV1	
VG[1].Mode	V<
VePTUV2	
VG[2].Mode	V<